PACKING LIST

Name	Quantity	Notes
Main Machine	1	
Power Cord	1	
lampshade	1	
Carrying Case	1	
User Manual	1	

GVM Official website | Facebook | Download APP IOS | Download APP Android

Web: www.gvmled.com
Sale Email:sale@gvmled.com
Only Email: support@gvmled.com
Amazon Email: gvmstore-us@gvmled.com
Amazon Email: gvmstore-uk@gvmled.com

CONTENTS

Product Introduction ..... Page 1
Product parameter ..... Page 2
Disclaimers ..... Page 3
Precautions ..... Page 3
Product structure icon ..... Page 4
Installation method ..... Page 5,6,7
Description of product control keys ..... Page 8
Function introduction and instruction for use ..... Page 9
APP control and APP on-line control ..... Page 10,11
Simple faults and troubleshooting ..... Page 12
Use and preservation ..... Page 13
Packing list ..... Page 13

PRODUCT INTRODUCTION

Welcome to use "GVM-G100W", this product is specially designed for the senior photography enthusiasts. Product usage scenarios are available for live broadcast / video photography, etc., and can also be used for YouTube video capture. The main features of the product are:

① Dual color temperature: flexible with stepless adjustment, color range 3200K-5600K, with 1 cob lamp bead, helping to restore and enrich the color of the object, and providing you with natural and vivid shooting effect.

② APP intelligent control system, which can be controlled by your smart mobile device.

③ With OLED screen display and stable system, supporting 180 ° rotation, it can effectively control the light. It is also equipped with the standard cover, which can avoid redundant light and make the light more concentrated. Custom control fill light, allowing you to easily shoot the desired results.

We believe that once using our product correctly, you can make huge progress when shooting. Before using the product, you are strongly recommended to read the instructions below carefully.

PRODUCT PARAMETER

- Brand : GVM
- Product model : GVM-G100W
- Product Type : Photography Fill Light
- Product Name : 360W double color temperature spotlight
- Function Feature : APP control , remote control , high display , Stepless light control
- Color rendering index : ≥97
- Lamp beads quantity : COB*1
- Color temperature : 3200K-5600K
- Brightness : Bare light:11000lux/0.5m ; 3500lux/1m
  Plus standard cover:32000lux/0.5m ; 7200lux/1m
- Light adjustment method : Stepless adjustment
- Product Weight : 1.7KG
- Product Size(mm) : 295x225x124
- Cooling : Heat sink+fan
- Power : 360W
- Input : AC-100-240V
- Product material : Aluminum alloy + ABS plastic
- Commodity origin : China: Huizhou

DISCLAIMERS

1. Before using this product, please read the instructions carefully and make sure you understand the content. If you do not understand the instructions, please receive learn to discard it and not use it. Any people around, or even damage the product and other things around.
2. Once you use the product, you are assumed to have read the disclaimer and warning carefully, understand and acknowledge all the terms and contents of this statement, and promise to take full responsibility for the use of this product and possible consequences.

PRECAUTIONS

1. The product is not waterproof, please use it in rainproof environment.
2. The product is not anti-corrosion, therefore do not let the product touch any corrosive liquid.
3. When using the product, make sure the product is put firmly and prevent from falling and damage.
4. If the product will not be used for a long time, please switch off the power to reduce energy loss.

PRODUCT STRUCTURE ICON

INSTALLATION METHOD

① The lamp can be installed and fixed on the bracket by rotating the knob clockwise, and unloaded by rotating in the counterclockwise direction.

② Insert the protective bayonet of the lampshade into the protective bayonet of the lamp, and then turn it slightly clockwise.

③ Push the bearing: disassembly buckle back, and turn the lamp cover anticlockwise at the same time. Then the lamp cover can be removed.

④ Loosen the angle fixing handle, adjust the angle of spotlight you need, and then turn the angle fixing handle tight.

⑤ Connect the power cord for power supply.

DESCRIPTION OF PRODUCT CONTROL KEYS

FUNCTION INSTRUCTION & INSTRUCTION FOR USE

① Mode selection :

There are two kinds of more which are master mode and slave mode, respectively. Long press the mode button (automatically in master mode when switch on the machine). In master mode, it is able adjust brightness, color temperature and channel value, and it is also able to connect APP, and control the parameters through APP. While in the slave mode, it is only able to set channel value, rather than lightness and color temperature.

② Channel adjustment (Only range 0-11)

Set channel value using channel addition and subtraction key, ranging from 0 to 11.

③ Adjust brightness (Only range 0%-100%)

In the master mode, adjust lightness through the knob on APP, ranging from 10% to 99%.

④ Adjust color temperature (CCT) range 3200K-5600K

In the master mode, adjust color temperature through the knob on APP, ranging from 3200K to 5600K.

⑤ On-line control (between photography lights) :

Prepare two or more photography lights, set as master mode and the other slave mode, and set a same channel value, in this way, it is able to control the lightness and color temperature of slave machine through adjusting the knob of the master machine. Moreover, it is also able to connect the master machine and APP, and then use the APP to control the slave machine.

APP CONNECTION AND APP CONTROL

Download APP: Search "GVM" in App Store or Google Play to download the APP.

Set master mode for the photography light (automatically as a master mode when switching on the machine), open "GVM Easy" APP on the mobile phone (compatible turn on WIFI on the phone), click "Add Equipment" account (as long as the email format is correct, the email account password can be entered at will, because the next time you open the APP, you will automatically login), in the main menu, in the APP—>switch the devices—select "SingleDouble color temperature light", then in the main menu in APP—>add—select "switch WIFI", and connect photography light (WIFI initial username: GVM_LED, password: gvm_admin), more it shows "Device connection GVM_LED", return back to the main interface, after it shows "Connected" in the main interface, it means the connection is successful, then you can adjust the parameters of switch on and off through the control key in APP, and also the slave machine.

If there is a slave, the slave and the master are controlled by the APP at the same time. The master/slave connection mode is the same as "Example 2: online control (link control between lamps and lamps)".

WIFI username and password resetting

It is able to reset the WIFI username and password if plug press the WIFI reset button for over 5 seconds. After resetting, the username and the password will return to the initial: WIFI username: GVM_LED; WIFI password: gvm_admin.

USE AND PRESERVATION

Do not put the product in a highly humid, strong electromagnetic field, high temperature and dust environment. Moreover, if not use the product for a long time, disconnect the power.

Clean : Before clean, disconnect the power plug. And use wet cloth rather than any detergent or volatile liquid, avoiding damaging the surface layer.

Power : Make sure the power is in the demanded range, not too high or too low.

Repairing : If there is fault in performance deposition, do not unpack the shell by yourself, avoiding damage the machine and lose the right of maintenance. When there is a fault, do not hesitate to contact us, and we will do our best to deal with the problem.

Accessories : Please use the accessories provided by manufacturer and approved ones, in order to maximize the performance.

Guarantee : Do does not modify the product, or you will lose the right of maintenance.

SIMPIE FAULTS AND TROUBLESHOOTING

Phenomenon	Check the product	Troubleshooting
The switch button pressed no response	Check the matching power adapter voltage is right or not.	Make sure the adapter is well connected with the power plug.
The brightness and color temperature cannot be adjusted	Check if the mode switch set as slave mode, lightness and color temperature of the products cannot be controlled in slave mode.	Provide MODE button for once, switch the mode from slave mode to master mode.
The product is in the light mode, but the light does not shine	Check if the product is "OFF" or "Dimmer" in the APP.	Press the "ON/OFF" button once more.
APP can't connect with the product	Check whether the WIFI is connected, and check whether the WIFI is successfully connected, and "Connected" is displayed in the APP.	Normal steps: 1. Open the APP inside after boot. 2. Successfully connected to WIFI. 3. Open the APP, and the connection will be successful.
WIFI is successfully connected, but the device cannot be controlled	Check if the "Device Device" type in the APP is the same as switched to "SingleDouble color temperature light"	Click APP main menu—>Switch devices—> SingleDouble color temperature light