

MX910 Series

User's Guide

September 2022

www.lexmark.com

Machine type(s):

7421

Model(s):

036, 236, 436

Contents ______2

Contents

Safety information	
Learning about the printer	9
Finding information about the printer	
Connecting the printer to an outlet	
Selecting a location for the printer	
Printer configurations	
Understanding the basic functions of the scanner	13
Using the ADF and scanner glass	14
Understanding the printer control panel	15
Using the control panel	15
Understanding the colors of the Sleep button and indicator lights	15
Understanding the home screen	16
Using the touch-screen buttons	18
Setting up and using the home screen applications	20
Finding the IP address of the printer	20
Finding the IP address of the computer	20
Accessing the Embedded Web Server	20
Customizing the home screen	21
Understanding the different applications	21
Activating the home screen applications	22
Setting up Remote Operator Panel	25
Exporting and importing a configuration	26
Additional printer setup	27
Installing internal options	27
Installing hardware options	38
Attaching cables	44
Setting up the printer software	45
Networking	46
Verifying printer setup	50

Loading paper and specialty media	51
Setting the paper size and type	51
Configuring Universal paper settings	51
Loading trays	51
Loading the multipurpose feeder	53
Linking and unlinking trays	56
Paper and specialty media guide	58
Using specialty media	58
Paper guidelines	60
Supported paper sizes, types, and weights	63
Printing	70
Printing forms and a document	70
Printing from a flash drive or mobile device	71
Printing confidential and other held jobs	73
Printing information pages	74
Canceling a print job	75
Copying	76
Making copies	76
Creating a copy shortcut	77
Customizing copy settings	78
Placing a header or footer on pages	81
Canceling a copy job while pages are being printed	81
Understanding the copy options	81
E-mailing	84
Setting up the printer to e-mail	84
Creating an e-mail shortcut	85
E-mailing a document	85
Customizing e-mail settings	86
Canceling an e-mail	86
Understanding the e-mail options	
Faxing	89
Setting up the printer to fax	89

Sending a fax	104
Sending a fax at a scheduled time	105
Creating shortcuts	105
Customizing fax settings	106
Canceling a fax job	108
Holding and forwarding faxes	108
Understanding the fax options	109
Scanning	111
Using Scan to Network	111
Scanning to an FTP address	111
Scanning to a computer or flash drive	113
Understanding the scan options	114
Understanding the printer menus	116
Menus list	116
Paper menu	117
Reports menu	127
Network/Ports menu	128
Security menu	141
Settings menu	148
Saving money and the environment	197
Saving paper and toner	197
Saving energy	198
Recycling	199
Securing the printer	201
Using the security lock feature	201
Statement of Volatility	201
Erasing volatile memory	202
Erasing non-volatile memory	202
Erasing printer hard disk memory	202
Configuring printer hard disk encryption	203
Finding the printer security information	203
Maintaining the printer	204
Cleaning printer parts	204

	Checking the status of parts and supplies	209
	Estimated number of remaining pages	209
	Ordering supplies	
	Ordering a 300K maintenance kit	211
	Storing parts and supplies	211
	Replacing supplies	212
	Replacing the 300K maintenance kit	224
	Replacing the ADF scan pad	234
	Moving the printer	236
٧	lanaging the printer	238
	Checking the virtual display	238
	Setting up e-mail alerts	238
	Viewing reports	238
	Copying printer settings to other printers	239
	Configuring supply notifications from the Embedded Web Server	239
	Restoring factory default settings	240
C	learing jams	.241
	Avoiding jams	241
	Understanding jam messages and locations	242
	[x]-page jam, clear jammed paper from multipurpose feeder. [200.xx]	244
	[x]-page jam, open door C and clear all jammed paper. [2yy.xx]	244
	[x]-page jam, slide the 3000-sheet tray and open door C. [2yy.xx]	246
	[x]-page jam, open door D and clear all jammed paper. [24y.xx]	249
	[x]-page jam, slide the 3000-sheet tray and open door D. [24y.xx]	250
	[x]-page jam, slide the 3000-sheet tray and open door F. [24y.xx]	251
	[x]-page jam, open doors G, H, and J and clear jammed paper. Leave paper in bin. [4yy.xx].	254
	[x]-page jam, press latch to access area G. Leave paper in bin. [40y.xx]	257
	[x]-page jam, press latch to access area G and clear jammed staples. Leave paper in bin. [402.93]	260
	[x]-page jam, open door H and rotate knob H6 clockwise. Leave paper in bin. [426.xx–428.xx]	263
	[x]-page jam, press latch at area E to open ADF's top cover. [28y.xx]	
Γ	roubleshooting	270
	Understanding the printer messages	
	Solving printer problems	

Solving print problems	293
Solving copy problems	
Solving fax problems	322
Solving scanner problems	
Solving home screen application problems	33 ²
Embedded Web Server does not open	332
Contacting customer support	333
Notices	334
Product information	334
Edition notice	334
Power consumption	340
ndex	353

Safety information 7

Safety information

Connect the power cord directly to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.



CAUTION—POTENTIAL INJURY: Do not use this product with extension cords, multioutlet power strips, multioutlet extenders, or other types of surge or UPS devices. The power rating capacity of these types of accessories can be easily overloaded by a laser printer and may result in poor printer performance, property damage, or potential fire.

Do not place or use this product near water or wet locations.



CAUTION—POTENTIAL INJURY: This product uses a laser. Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure.

This product uses a printing process that heats the print media, and the heat may cause the media to release emissions. You must understand the section in your operating instructions that discusses the guidelines for selecting print media to avoid the possibility of harmful emissions.



CAUTION—POTENTIAL INJURY: The lithium battery in this product is not intended to be replaced. There is a danger of explosion if a lithium battery is incorrectly replaced. Do not recharge, disassemble, or incinerate a lithium battery. Discard used lithium batteries according to the manufacturer's instructions and local regulations.



CAUTION—HOT SURFACE: The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.



CAUTION—POTENTIAL INJURY: The printer weight is greater than 18 kg (40 lb) and requires two or more trained personnel to lift it safely.



CAUTION—POTENTIAL INJURY: Before moving the printer, follow these guidelines to avoid personal injury or printer damage:

- Turn off the printer, and then unplug the power cord from the electrical outlet.
- Disconnect all cords and cables from the printer.
- If the printer does not have a caster base but is configured with optional trays, then remove the trays.
- Use the handholds located on both sides of the printer to lift it.
- Make sure your fingers are not under the printer when you set it down.
- Make sure there is adequate clearance around the printer.
- Use only the power cord provided with this product or the manufacturer's authorized replacement.



CAUTION—POTENTIAL INJURY: To reduce risk of fire, use only the telecommunications (RJ-11) cord provided with this product or a UL Listed 26 AWG or larger replacement when connecting this product to the public switched telephone network.



CAUTION—SHOCK HAZARD: If you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.



CAUTION—SHOCK HAZARD: Make sure that all external connections (such as Ethernet and telephone system connections) are properly installed in their marked plug-in ports.

Safety information 8

This product is designed, tested, and approved to meet strict global safety standards with the use of specific manufacturer's components. The safety features of some parts may not always be obvious. The manufacturer is not responsible for the use of other replacement parts.

This product produces ozone during normal operation, and is equipped with a filter designed to limit ozone concentrations to levels well below the recommended exposure limits. To avoid high ozone concentration levels during extensive usage, install this product in a well-ventilated area and replace the ozone and exhaust filters as indicated in the product maintenance instructions.



CAUTION—POTENTIAL INJURY: Do not cut, twist, bind, crush, or place heavy objects on the power cord. Do not subject the power cord to abrasion or stress. Do not pinch the power cord between objects such as furniture and walls. If any of these things happen, a risk of fire or electrical shock results. Inspect the power cord regularly for signs of such problems. Remove the power cord from the electrical outlet before inspecting it.

Refer service or repairs, other than those described in the user documentation, to a service representative.



CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock when cleaning the exterior of the printer, unplug the power cord from the electrical outlet and disconnect all cables from the printer before proceeding.



CAUTION—SHOCK HAZARD: Do not use the fax feature during a lightning storm. Do not set up this product or make any electrical or cabling connections, such as the fax feature, power cord, or telephone, during a lightning storm.



CAUTION—TIPPING HAZARD: Floor-mounted configurations require additional furniture for stability. You must use either a printer stand or printer base if you are using multiple input options. If you purchased a multifunction printer (MFP) that scans, copies, and faxes, then you may need additional furniture. For more information, see **www.lexmark.com/multifunctionprinters**.



CAUTION—POTENTIAL INJURY: To reduce the risk of equipment instability, load each tray separately. Keep all other trays closed until needed.

SAVE THESE INSTRUCTIONS.

Learning about the printer

Finding information about the printer

What are you looking for?	Find it here
Initial setup instructions: Connecting the printer Installing the printer software	Setup documentation—The setup documentation came with the printer and is also available at http://support.lexmark.com .
Additional setup and instructions for using the printer: • Selecting and storing paper and specialty media • Loading paper • Configuring printer settings • Viewing and printing documents and photos • Setting up and using the printer software • Configuring the printer on a network • Caring for and maintaining the printer • Troubleshooting and solving problems	User's Guide and Quick Reference Guide—The guides are available at http://support.lexmark.com . Note: These guides are also available in other languages.
Information on setting up and configuring the accessibility features of your printer	Lexmark Accessibility Guide—This guide is available at http://support.lexmark.com .
Help using the printer software	Windows or Mac Help—Open a printer software program or application, and then click Help . Click to view context-sensitive information. Notes: Help is automatically installed with the printer software. The printer software is located in the printer program folder or on the desktop, depending on your operating system.

What are you looking for?	Find it here
The latest supplemental information, updates, and customer support:	Lexmark support Web site— http://support.lexmark.com
DocumentationDriver downloads	Note: Select your country or region, and then select your product to view the appropriate support site.
Live chat supportE-mail supportVoice support	Support telephone numbers and hours of operation for your country or region can be found on the support Web site or on the printed warranty that came with your printer.
	Record the following information (located on the store receipt and at the back of the printer), and have it ready when you contact customer support so that they may serve you faster:
	Machine Type number Serial number
	Serial numberDate purchasedStore where purchased
Warranty information	Warranty information varies by country or region:
	In the U.S.—See the Statement of Limited Warranty included with this printer, or go to http://support.lexmark.com .
	• In other countries and regions—See the printed warranty that came with this printer.

Connecting the printer to an outlet

Connect the power cord to the printer and then to a properly grounded and easily accessible electrical outlet.

Note: The electrical outlet may look different depending on your country or region.

Selecting a location for the printer



CAUTION—POTENTIAL INJURY: The printer weight is greater than 18 kg (40 lb) and requires two or more trained personnel to lift it safely.

When selecting a location for the printer, leave enough room to open trays, covers, and doors. If you plan to install any options, then leave enough room for them also. It is important to:

- Set up the printer near a properly grounded and easily accessible electrical outlet.
- Make sure that airflow in the room meets the latest revision of the ASHRAE 62 standard or the CEN Technical Committee 156 standard.
- Provide a flat, sturdy, and stable surface.
- · Keep the printer:
 - Clean, dry, and free of dust.
 - Away from stray staples and paper clips.
 - Away from the direct airflow of air conditioners, heaters, or ventilators.
 - Free from direct sunlight and humidity extremes.

• Observe the recommended temperatures and avoid fluctuations:

Ambient temperature	10 to 30°C (50 to 86°F)
Storage temperature	-10 to 40°C (14 to 104°F)

• Allow the following recommended amount of space around the printer for proper ventilation:



1	Rear	120 mm (4.80 in.)
2 Right side 400 mm (15.70 i		400 mm (15.70 in.)
3	Front	444.5 mm (17.50 in.)
4 Left side 120 mm (4.80 in.)		120 mm (4.80 in.)
5	Тор	400 mm (15.70 in.)

Printer configurations

Note: Make sure to configure the printer on a flat, sturdy, and stable surface.

Basic model




1	Automatic document feeder (ADF)	
2	ADF tray	
3	ADF bin	
4	Control panel	
5	Multipurpose feeder	
6	6 Standard 2 x 500-sheet tray	
7	7 Standard bin	

Configured model



CAUTION—TIPPING HAZARD: Floor-mounted configurations require additional furniture for stability. You must use either a printer stand or printer base if you are using multiple input options. If you purchased a multifunction printer (MFP) that scans, copies, and faxes, then you may need additional furniture. For more information, see www.lexmark.com/multifunctionprinters.



	Hardware option	Alternative hardware option	
1	Staple finisher None		
	Note: This is supported only in select printer models.		
2	3000-sheet tray	None	
3	2 x 500-sheet tray	2500-sheet tray	
4	2500-sheet tray	2 x 500-sheet tray	
5	Finisher	None	
	Staple, hole punch finisher		
	Booklet finisher		

When using optional trays:

- The 3000-sheet tray is supported only if another optional tray is installed.
- The staple finisher is not supported if another finisher is installed.

Understanding the basic functions of the scanner

- Make quick copies or set the printer to perform specific copy jobs.
- Send a fax using the printer control panel.
- Send a fax to multiple fax destinations at the same time.
- Scan documents and send them to your computer, an e-mail address, a flash drive, or an FTP destination.
- Scan documents and send them to another printer (PDF through an FTP).

Using the ADF and scanner glass

Use the ADF for multiple-page or two-sided documents. Load an original document faceup. Use the scanner glass for single-page documents, book pages, small items (such as postcards or photos), transparencies, photo paper, or thin media (such as magazine clippings). Place the document facedown in the corner with the arrow.

Understanding the printer control panel

Using the control panel



Use the		То	
1	Display	View the printer status and messages.	
		Set up and operate the printer.	
2	Home button	Go to the home screen.	
3	3 Sleep button Enable Sleep mode or Hibernate mode.		
		The following actions wake the printer from Sleep mode:	
		Touching the control panel home screen	
		Opening the scanner cover	
		The following actions wake the printer from Hibernate mode:	
		Pressing the Sleep button until the printer wakes	
		Performing a power-on reset using the main power switch	
4	Keypad	Enter numbers, letters, or symbols.	
5	Start button	Start a job, depending on which mode is selected.	
6	Clear all / Reset button	Reset the default settings of a function, such as copying, faxing, or scanning.	
7	Stop or Cancel button	Stop all printer activity.	
8	Indicator light	Check the status of the printer.	

Understanding the colors of the Sleep button and indicator lights

The colors of the Sleep button and indicator lights on the printer control panel signify a certain printer status or condition.


Indicator light	Printer status
Off	The printer is off or in Hibernate mode.
Blinking green	The printer is warming up, processing data, or printing.
Solid green	The printer is on, but idle.
Blinking red	The printer requires user intervention.

Sleep button light	Printer status
Off	The printer is off, idle or in Ready state.
Solid amber	The printer is in Sleep mode.
Blinking amber	The printer is entering or waking from Hibernate mode.
Blinking amber for 0.1 second, then goes completely off for 1.9 seconds in a slow, pulsing pattern	The printer is in Hibernate mode.

Understanding the home screen

When the printer is turned on, the display shows a basic screen, referred to as the home screen. Touch the home screen buttons and icons to initiate an action such as copying, faxing, or scanning; to open the menu screen; or to respond to messages.

Note: Your home screen may vary depending on your home screen customization settings, administrative setup, and active embedded solutions.



Touch		То
1	Change Language	Launch the Change Language pop-up window that lets you change the primary language of the printer.
2	Сору	Access the Copy menus and make copies.
3	Fax	Access the Fax menus and send fax.
4	E-mail	Access the E-mail menus and send e-mails.
5	FTP	Access the File Transfer Protocol (FTP) menus and scan documents directly to an FTP server.

Touch		То
6	Arrows	Scroll up or down.
7	Forms and Favorites	Quickly find and print frequently used online forms.
8	Menu icon	Access the printer menus.
		Note: The menus are available only when the printer is in Ready state.
9	Bookmarks	Create, organize, and save a set of bookmarks (URL) into a tree view of folders and file links.
		Note: The tree view supports only bookmarks created from this function, and not from any other application.
10	USB Drive	View, select, print, scan, or e-mail photos and documents from a flash drive.
		Note: This icon appears only when you return to the home screen while a memory card or flash drive is connected to the printer.
11	Held Jobs	Display all current held jobs.
12	Status/Supplies	 Show a warning or error message whenever the printer requires intervention to continue processing.
		 Access the messages screen for more information on the message, and how to clear it.
13	Tips	Open a context-sensitive Help dialog.
14	Search Held Jobs	Search for one or more of the following items:
		User name for held or confidential print jobs
		Job names for held jobs, excluding confidential print jobs
		Profile names
		Bookmark container or print job names
		USB container or print job names for supported file types


Features

Feature	Description
Menu trail line	A menu trail line is located at the top of each menu screen. This feature shows the path taken to arrive at the current menu.
Example: Menus > Settings > Copy Settings >	Touch any of the underlined words to return to that menu.
Number of Copies	Number of Copies is not underlined because it is the current screen. If you touch an underlined word on the "Number of Copies" screen before the number of copies is set and saved, then the selection is not saved, and it does not become the default setting.
Attendance message alert	If an attendance message affects a function, then this icon appears and the red indicator light blinks.

Feature	Description
Warning	If an error condition occurs, then this icon appears.
1	
Status message bar	Show the current printer status such as Ready or Busy .
	Show printer conditions such as Toner Low or Cartridge Low .
	Show intervention messages so the printer can continue processing.
Printer IP address	The IP address of your network printer is located at the upper left corner of
Example:	the home screen and appears as four sets of numbers separated by periods.
1124 124 124 124	You can use the IP address when accessing the Embedded Web Server so you can view and remotely configure printer settings even when you are not physically near the printer.

Using the touch-screen buttons

Note: Your home screen, icons, and buttons may vary, depending on your home screen customization settings, administrative setup, and active embedded solutions.



	Touch	То
1	Arrows	View a list of options.
2	Copy It	Print a copy.
3	Advanced Options	Select a copy option.
4	Home	Go to the home screen.
5	Increase	Select a higher value.
6	Decrease	Select a lower value.
7	Tips	Open a context-sensitive Help dialog.

Other touch-screen buttons

Touch	То
Accept	Save a setting.
Cancel	Cancel an action or a selection.
	Exit a screen and return to the previous screen without saving changes.
Reset	Reset values on the screen.
C	

Setting up and using the home screen applications

Notes:

- Your home screen may vary depending on your home screen customization settings, administrative setup, and active embedded applications.
- There may be additional solutions and applications available for purchase. For more information, go to www.lexmark.com or contact the place where you purchased the printer.
- The shortcuts that you created using MyShortcut can only be edited or deleted using the application. For more information, see <u>"Using MyShortcut" on page 24</u>.

Finding the IP address of the printer

Note: Make sure your printer is connected to a network or to a print server.

You can find the printer IP address:

- From the top left corner of the printer home screen.
- From the TCP/IP section in the Network/Ports menu.
- By printing a network setup page or menu settings page, and then finding the TCP/IP section.

Note: An IP address appears as four sets of numbers separated by periods, such as 123.123.123.

Finding the IP address of the computer

For Windows users

- **1** Run the command prompt.
- **2** Type **ipconfig**, and then look for the IP address.

For Macintosh users

- **1** From System Preferences in the Apple menu, select **Network**.
- **2** Select your connection type, and then click **Advanced** > **TCP/IP**.
- **3** Look for the IP address.

Accessing the Embedded Web Server

The Embedded Web Server is the printer Web page that lets you view and remotely configure printer settings even when you are not physically near the printer.

- 1 Obtain the printer IP address:
 - From the printer control panel home screen
 - From the TCP/IP section in the Network/Ports menu

• By printing a network setup page or menu settings page, and then finding the TCP/IP section

Note: An IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.

- 2 Open a Web browser, and then type the printer IP address in the address field.
- 3 Press Enter.

Note: If you are using a proxy server, then temporarily disable it to load the Web page correctly.

Customizing the home screen

1 Open a Web browser, and then type the printer IP address in the address field.

Note: View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

- **2** Do one or more of the following:
 - Show or hide the icons of basic printer functions.
 - a Click Settings > General Settings > Home screen customization.
 - **b** Select the check boxes to specify which icons appear on the home screen.

Note: If you clear a check box beside an icon, then the icon does not appear on the home screen.

- c Click Submit.
- Customize the icon for an application. For more information, see <u>"Finding information about the home screen applications" on page 22</u> or see the documentation that came with the application.

Understanding the different applications

Use	То
Card Copy	Scan and print both sides of a card on a single page. For more information, see <u>"Setting up Card Copy"</u> on page 23.
Fax	Scan a document, and then send it to a fax number. For more information, see <u>"Faxing" on page 89</u> .
Forms and Favorites	Quickly find and print frequently used online forms directly from the printer home screen. For more information, see <u>"Setting up Forms and Favorites"</u> on page 22.
Multi Send	Scan a document, and then send it to multiple destinations. For more information, see "Setting up Multi Send" on page 24.
MyShortcut	Create shortcuts directly on the printer home screen. For more information, see <u>"Using MyShortcut"</u> on page 24.
Scan to E-mail	Scan a document, and then send it to an e-mail address. For more information, see <u>"E-mailing"</u> on page 84.
Scan to Computer	Scan a document, and then save it to a predefined folder on a host computer. For more information, see <u>"Setting up Scan to Computer"</u> on page 113.
Scan to FTP	Scan documents directly to a File Transfer Protocol (FTP) server. For more information, see "Scanning to an FTP address" on page 112.

Use	То
Scan to Network	Scan a document, and then send it to a network shared folder. For more information, see "Setting up Scan to Network" on page 25.

Activating the home screen applications

Finding information about the home screen applications


Your printer comes with preinstalled home screen applications. Before you can use these applications, you must first activate and set up these applications using the Embedded Web Server. For more information on accessing the Embedded Web Server, see "Accessing the Embedded Web Server" on page 20.

For more information on configuring and using the home screen applications, do the following:

- 1 Go to http://support.lexmark.com.
- 2 Click **Software Solutions**, and then select either of the following:
 - Scan to Network—This lets you find information about the Scan to Network application.
 - Other Applications—This lets you find information about the other applications.
- 3 Click the Manuals tab, and then select the document for the home screen application.

Setting up Forms and Favorites

Note: A later version of this *User's Guide* may contain a direct link to the *Administrator's Guide* of this application. To check for updates of this *User's Guide*, go to http://support.lexmark.com.



1 Open a Web browser, and then type the printer IP address in the address field.

Note: View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

- 2 Click Settings > Apps > Apps Management > Forms and Favorites.
- **3** Click **Add**, and then customize the settings.

Notes:

- See the mouse-over help beside each field for a description of the setting.
- To make sure the location settings of the bookmark are correct, type the correct IP address of the host computer where the bookmark is located. For more information on obtaining the IP address of the host computer, see "Finding the IP address of the computer" on page 20.


Make sure the printer has access rights to the folder where the bookmark is located.

4 Click Apply.

To use the application, touch **Forms and Favorites** on the printer home screen, and then navigate through form categories, or search for forms based on a form number, name, or description.

Setting up Card Copy

Note: A later version of this *User's Guide* may contain a direct link to the *Administrator's Guide* of this application. To check for updates of this *User's Guide*, go to http://support.lexmark.com.



1 Open a Web browser, and then type the printer IP address in the address field.

Note: View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

- 2 Click Settings > Apps > Apps Management > Card Copy.
- **3** Change the default scanning options, if necessary.
 - **Default tray**—Select the default tray to be used for printing scan images.
 - **Default number of copies**—Specify the number of copies that should automatically print when the application is used.
 - **Default contrast setting**—Specify a setting to increase or decrease the level of contrast when a copy of the scanned card is printed. Select **Best for Content** if you want the printer to adjust the contrast automatically.
 - **Default scale setting**—Set the size of the scanned card when printed. The default setting is 100% (full size).
 - **Resolution setting**—Adjust the quality of the scanned card.

Notes:


- When scanning a card, make sure the scan resolution is not more than 200 dpi for color, and 400 dpi for black and white.
- When scanning multiple cards, make sure the scan resolution is not more than 150 dpi for color, and 300 dpi for black and white.
- Print Borders—Select the check box to print the scan image with a border around it.

4 Click Apply.

To use the application, touch **Card Copy** on the printer home screen, and then follow the instructions.

Using MyShortcut


Note: A later version of this *User's Guide* may contain a direct link to the *Administrator's Guide* of this application. To check for updates of this *User's Guide*, go to http://support.lexmark.com.



To use the application, touch **MyShortcut**, and then follow the instructions on the printer display.

Setting up Multi Send

Note: A later version of this *User's Guide* may contain a direct link to the *Administrator's Guide* of this application. To check for updates of this *User's Guide*, go to http://support.lexmark.com.



1 Open a Web browser, and then type the printer IP address in the address field.

Note: View the printer IP address on the printer home screen. The printer IP address appears as four sets of numbers separated by periods, such as 123.123.123.

- 2 Click Settings > Apps > Apps Management > Multi Send.
- **3** From the Profiles section, click **Add**, and then customize the settings.

Notes:

- See the mouse-over help beside each field for a description of the setting.
- If you select FTP or Share Folder as a destination, then make sure the location settings of the
 destination are correct. Type the correct IP address of the host computer where the specified
 destination is located. For more information on obtaining the IP address of the host computer, see
 "Finding the IP address of the computer" on page 20.

4 Click Apply.

To use the application, touch **Multi Send** on the printer home screen, and then follow the instructions on the printer display.

Setting up Scan to Network

Note: A later version of this *User's Guide* may contain a direct link to the *Administrator's Guide* of this application. To check for updates of this *User's Guide*, go to http://support.lexmark.com.

Scan a document and send it to a shared network folder. You can define up to 30 unique folder destinations.

Notes:

The printer must have permission to write to the destinations. From the computer where the destination is specified, use sharing, security, and firewall settings to allow the printer at least a write access. For help, see the documentation that came with your operating system.

The Scan to Network icon appears only when one or more destinations are defined.

1 Open a Web browser, and then type the printer IP address in the address field.

Note: View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

- **2** Do either of the following:
 - Click Set up Scan to Network > Click here.
 - Click Settings > Apps > Apps Management > Scan to Network.
- **3** Specify the destinations, and then customize the settings.

Notes:

- See the mouse-over help beside some of the fields for a description of the setting.
- To make sure the location settings of the destination are correct, type the correct IP address of the host computer where the specified destination is located. For more information on obtaining the IP address of the host computer, see <u>"Finding the IP address of the computer" on page 20</u>.
- Make sure the printer has access rights to the folder where the specified destination is located.

4 Click Apply.

To use the application, touch **Scan to Network** on the printer home screen, and then follow the instructions on the printer display.

Setting up Remote Operator Panel

This application enables you to interact with the printer control panel even when you are not physically near the network printer. From your computer, you can view the printer status, release held print jobs, create bookmarks, and do other print-related tasks.

1 Open a Web browser, and then type the printer IP address in the address field.

Note: View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

2 Click Settings > Remote Operator Panel Settings.

- **3** Select the **Enable** check box, and then customize the settings.
- 4 Click Submit.

To use the application, click Remote Operator Panel > Launch VNC Applet.

Exporting and importing a configuration

You can export configuration settings into a text file, and then import the file to apply the settings to other printers.

1 Open a Web browser, and then type the printer IP address in the address field.

Note: View the IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

2 Export or import a configuration file for one or multiple applications.

For one application

a Navigate to:

Settings > **Apps** > **Apps Management** > select an application > **Configure**

b Export or import the configuration file.

Notes:

- If a JVM Out of Memory error occurs, then repeat the export process until the configuration file is saved.
- If a timeout occurs and a blank screen appears, then refresh the Web browser, and then click Apply.

For multiple applications

- a Click Settings > Import/Export.
- **b** Export or import a configuration file.

Note: When importing a configuration file, click Submit to complete the process.

Additional printer setup

Installing internal options



CAUTION—SHOCK HAZARD: If you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.

Available internal options

- · Memory card
 - DDR2 DIMM
 - Flash memory
 - Fonts
 - Firmware cards
 - Forms and Bar Code
 - PRESCRIBE
 - IPDS
- LexmarkTM Internal Solutions Ports (ISP)
 - Standard 10/100/1000 Ethernet
 - MarkNet[™] N8350 802.11 b/g/n wireless print server
 - MarkNet N8352 802.11 b/g/n wireless print server


Accessing the controller board

Note: Use the screwdriver located inside the bottom front door of the printer.




CAUTION—SHOCK HAZARD: If you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.


Remove the connector cover.



Remove the screws from the controller board access cover.




Remove the access cover.




Use the following illustration to locate the appropriate connector:

Warning—Potential Damage: Controller board electronic components are easily damaged by static electricity. Touch a metal surface on the printer before touching any controller board electronic components or connectors.



1	Option card connector
2	Memory card connector
3	Lexmark Internal Solutions Port or printer hard disk connector

5 Align the base of the access cover to the printer.



6 Reattach the access cover.



- **7** Tighten the screws on the access cover.
- 8 Reattach the connector cover.

Installing a memory card


4

CAUTION—SHOCK HAZARD: If you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.


- 1 Access the controller board.
 For more information, see "Accessing the controller board" on page 27.
- **2** Unpack the memory card.

Warning—Potential Damage: Do not touch the connection points along the edge of the card. Doing so may cause damage.

3 Align the notch (1) on the memory card with the ridge (2) on the connector.



4 Push the memory card straight into the connector, and then push the card toward the controller board wall until it *clicks* into place.




Installing an optional card

4


CAUTION—SHOCK HAZARD: If you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.

Warning—Potential Damage: Controller board electronic components are easily damaged by static electricity. Touch a metal surface on the printer before touching any controller board electronic components or connectors.

- 1 Access the controller board.
 For more information, see <u>"Accessing the controller board" on page 27.</u>
- **2** Unpack the optional card.
 - **Warning—Potential Damage:** Avoid touching the connection points along the edge of the card. Doing so may cause damage.
- **3** Holding the card by its sides, align the plastic pins (1) on the card with the holes (2) on the controller board.



4 Push the card firmly into place.



Warning—Potential Damage: Improper installation of the card may cause damage to the card and the controller board.

Note: The entire length of the connector on the card must touch and be flush with the controller board.

Installing an Internal Solutions Port

The controller board supports one optional Lexmark Internal Solutions Port (ISP). Install an ISP for additional connectivity options.

Note: Use the screwdriver located inside the bottom front door of the printer.




4

CAUTION—SHOCK HAZARD: If you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.

Warning—Potential Damage: Controller board electronic components are easily damaged by static electricity. Touch a metal surface on the printer before touching any controller board electronic components or connectors.

1 Unpack the ISP kit.



1	ISP
2	Plastic mounting bracket
3	Thumbscrews


- 2 Access the controller board. For more information, see "Accessing the controller board" on page 27.
- **3** Remove the printer hard disk.

Note: The hard disk must be removed before installing an ISP.


a Unplug the hard disk interface cable from the controller board.



b Remove the screws that secure the hard disk.



c Remove the hard disk.




- **4** Install the ISP in the same location where the hard disk was located on the controller board.
 - **a** Align the posts of the plastic mounting bracket with the holes on the controller board cage, and then press the bracket on the cage until it *clicks* into place.






b Install the ISP on the bracket.




c Use the provided thumbscrew for the ISP to attach the ISP to the bracket.




5 Secure the ISP mounting bracket to the controller board cage using the screws.




6 Remove the thumbscrews that attach the hard disk mounting bracket to the hard disk, and then remove the bracket.



7 Align the standoffs of the hard disk with the holes on the ISP, and then press the hard disk down until the standoffs *click* into place.



8 Insert the plug of the hard disk interface cable into the connector on the ISP, and then connect the ISP solution interface cable into the receptacle of the controller board.



Removing a printer hard disk

Note: Use the screwdriver located inside the bottom front door of the printer.





CAUTION—SHOCK HAZARD: If you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.


Warning—Potential Damage: Controller board electronic components are easily damaged by static electricity. Touch a metal surface on the printer before touching any controller board electronic components or connectors.

- **1** Access the controller board.


 For more information, see "Accessing the controller board" on page 27.
- 2 Unplug the hard disk interface cable from the controller board, leaving the cable attached to the hard disk. To unplug the cable, squeeze the paddle at the plug of the interface cable to disengage the latch before pulling out the cable.



3 Remove the screws holding the hard disk in place.



4 Remove the hard disk.



Installing hardware options

Order of installation



CAUTION—POTENTIAL INJURY: The printer weight is greater than 18 kg (40 lb) and requires two or more trained personnel to lift it safely.



CAUTION—TIPPING HAZARD: Floor-mounted configurations require additional furniture for stability. You must use either a printer stand or printer base if you are using multiple input options. If you purchased a multifunction printer (MFP) that scans, copies, and faxes, then you may need additional furniture. For more information, see www.lexmark.com/multifunctionprinters.



CAUTION—SHOCK HAZARD: If you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.

Install the printer and any options you have purchased in the following order:

- Optional 2 x 500- or 2500-sheet tray
- Printer
- Staple finisher

Note: This option is supported only in select printer models.

- Staple, hole punch finisher or booklet finisher
- Optional 3000-sheet tray

Note: The staple finisher is not supported if another finisher is installed. For more information on installing the finishers and optional trays, see the instruction sheet that came with the option.

Installing optional trays

Notes:

- For information on installing the optional 3000-sheet tray, see the instruction sheet that came with the option.
- Use the screwdriver located inside the bottom front door of the printer.





CAUTION—POTENTIAL INJURY: The printer weight is greater than 18 kg (40 lb) and requires two or more trained personnel to lift it safely.



CAUTION—SHOCK HAZARD: If you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.




CAUTION—TIPPING HAZARD: Floor-mounted configurations require additional furniture for stability. You must use either a printer stand or printer base if you are using multiple input options. If you purchased a multifunction printer (MFP) that scans, copies, and faxes, then you may need additional furniture. For more information, see www.lexmark.com/multifunctionprinters.

The optional trays come with the following accessories:


Accessory name	Quantity
Stabilizing feet	2
Locking clip	3
Metal bracket	1

Accessory name	Quantity
Screw	5

1 Turn off the printer.




- **2** Unplug the power cord from the electrical outlet and then from the printer.
- **3** Unpack the optional tray, and then remove all packing material.




4 Attach the stabilizing feet to the optional tray.


Note: Make sure the feet *click* into place.



Remove the connector cover from the printer.



Lift the printer using the handles at the sides.






7 Align the printer with the tray, and then lower the printer into place.



8 Remove the tape from the connectors, and then plug the connectors into the receptacles of the printer.




9 Open Tray 2 and Tray 3.





10 Secure the tray to the printer using the locking clips and the metal bracket.

Back




• Front





11 Reinstall the connector cover.



12 Connect the power cord to the printer and electrical outlet.

- **13** Turn on the printer.
- 14 Set the printer software to recognize the optional tray. For more information, see "Adding available options in the print driver" on page 45.

Attaching cables




CAUTION—POTENTIAL INJURY: Do not use the fax feature during a lightning storm. Do not set up this product or make any electrical or cabling connections, such as the fax feature, power cord, or telephone, during a lightning storm.

Connect the printer to the computer using a USB cable, or to the network using an Ethernet cable.

Make sure to match the following:

- The USB symbol on the cable with the USB symbol on the printer
- The appropriate Ethernet cable to the Ethernet port



	Use the	То
1	EXT port	Connect additional devices (telephone or answering machine) to the printer and the telephone line. Use this port if you do not have a dedicated fax line for the printer and if this connection method is supported in your country or region.
		Note: Remove the plug to access the port.
2	LINE port	Connect the printer to an active telephone line through a standard wall jack (RJ-11), DSL filter, or VoIP adapter, or any other adapter that allows you to access the telephone line to send and receive faxes.

	Use the	То
3	Printer power cord socket	Connect the printer to a properly grounded electrical outlet.
4	Internal Solutions Port (ISP) or printer hard disk slot	Attach an ISP or a printer hard disk.
	Note: If the printer has support for wireless connection, then the wireless antenna is attached here.	
5	Ethernet port	Connect the printer to a network.
6	USB ports	Attach a keyboard.
7	USB printer port	Connect the printer to a computer.

Warning—Potential Damage: Do not touch the USB cable, any wireless network adapter, or the printer in the area shown while actively printing. Loss of data or a malfunction can occur.

Setting up the printer software

Installing the printer

- **1** Obtain a copy of the software installer package.
- **2** Run the installer, and then follow the instructions on the computer screen.
- **3** For Macintosh users, add the printer.

Note: Obtain the printer IP address from the TCP/IP section in the Network/Ports menu.

Adding available options in the print driver

For Windows users

- 1 Open the printers folder.
- **2** Select the printer you want to update, and then do the following:
 - For Windows 7 or later, select **Printer properties**.
 - For earlier versions, select **Properties**.
- 3 Navigate to the Configuration tab, and then select **Update Now Ask Printer**.
- **4** Apply the changes.

For Macintosh users

- 1 From System Preferences in the Apple menu, navigate to your printer, and then select Options & Supplies.
- **2** Navigate to the list of hardware options, and then add any installed options.
- **3** Apply the changes.

Networking

Notes:

• Purchase a MarkNet N8350 wireless network adapter before setting up the printer on a wireless network. For information on installing the wireless network adapter, see the setup sheet that came with the adapter.

• A Service Set Identifier (SSID) is a name assigned to a wireless network. Wired Equivalent Privacy (WEP), Wi-Fi Protected Access (WPA), and WPA2 are types of security used on a network.

Preparing to set up the printer on an Ethernet network

To configure your printer to connect to an Ethernet network, organize the following information before you begin:

Note: If your network automatically assigns IP addresses to computers and printers, continue on to installing the printer.

- A valid, unique IP address for the printer to use on the network
- The network gateway
- The network mask
- A nickname for the printer (optional)

Note: A printer nickname can make it easier for you to identify your printer on the network. You can choose to use the default printer nickname, or assign a name that is easier for you to remember.

You will need an Ethernet cable to connect the printer to the network and an available port where the printer can physically connect to the network. Use a new network cable when possible to avoid potential problems caused by a damaged cable.

Preparing to set up the printer on a wireless network

Notes:

- Make sure your wireless network adapter is installed in your printer and working properly. For more
 information, see the instruction sheet that came with the wireless network adapter.
- Make sure your access point (wireless router) is turned on and is working properly.

Make sure you have the following information before setting up the printer on a wireless network:

- **SSID**—The SSID is also referred to as the network name.
- Wireless Mode (or Network Mode)—The mode is either infrastructure or ad hoc.
- Channel (for ad hoc networks)—The channel defaults to automatic for infrastructure networks.

Some ad hoc networks will also require the automatic setting. Check with your system support person if you are not sure which channel to select.

- Security Method—There are four basic options for Security Method:
 - WEP key

If your network uses more than one WEP key, then enter up to four in the provided spaces. Select the key currently in use on the network by selecting the default WEP transmit key.

- WPA or WPA2 preshared key or passphrase

WPA includes encryption as an additional layer of security. The choices are AES or TKIP. Encryption must be set for the same type on the router and on the printer, or the printer will not be able to communicate on the network.

- 802.1X-RADIUS

If you are installing the printer on an 802.1X network, then you may need the following:

- Authentication type
- Inner authentication type
- 802.1X user name and password
- Certificates
- No security

If your wireless network does not use any type of security, then you will not have any security information.

Note: We do not recommend using an unsecured wireless network.

Notes:

- If you do not know the SSID of the network that your computer is connected to, then launch the wireless
 utility of the computer network adapter, and then look for the network name. If you cannot find the SSID
 or the security information for your network, then see the documentation that came with the access
 point, or contact your system support person.
- To find the WPA/WPA2 preshared key or passphrase for the wireless network, see the documentation
 that came with the access point, see the Embedded Web Server associated with the access point, or
 consult your system support person.

Connecting the printer using the Wireless Setup Wizard

Before you begin, make sure that:

- A wireless network adapter is installed in the printer and is working properly. For more information, see the instruction sheet that came with the wireless network adapter.
- An Ethernet cable is disconnected from the printer.
- Active NIC is set to Auto. To set this to Auto, navigate to:



Note: Make sure to turn off the printer, then wait for at least five seconds, and then turn the printer back on.

1 From the printer control panel, navigate to:

> Network/Ports > Network [x] > Network [x] Setup > Wireless > Wireless Connection Setup

2 Select a wireless connection setup.

Use	То
Search for networks	Show available wireless connections.
	Note: This menu item shows all broadcast secured or unsecured SSIDs.
Enter a network name	Manually type the SSID.
	Note: Make sure to type the correct SSID.
Wi-Fi Protected Setup	Connect the printer to a wireless network using Wi-Fi Protected Setup.

3 Follow the instructions on the printer display.

Connecting the printer to a wireless network using Wi-Fi Protected Setup

Before you begin, make sure that:

- The access point (wireless router) is Wi-Fi Protected Setup (WPS) certified or WPS-compatible. For more information, see the documentation that came with your access point.
- A wireless network adapter installed in your printer is attached and working properly. For more information, see the instruction sheet that came with the wireless network adapter.

Using the Push Button Configuration method

- **1** From the printer control panel, navigate to:
 - > Network/Ports > Network [x] > Network [x] Setup > Wireless > Wireless Connection Setup > Wi-Fi Protected Setup > Start Push Button Method
- **2** Follow the instructions on the printer display.

Using the Personal Identification Number (PIN) method

- **1** From the printer control panel, navigate to:
 - > Network/Ports > Network [x] > Network [x] Setup > Wireless > Wireless Connection Setup > Wi-Fi Protected Setup > Start PIN Method
- 2 Copy the eight-digit WPS PIN.
- 3 Open a Web browser, and then type the IP address of your access point in the address field.

Notes:

- The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- **4** Access the WPS settings. For more information, see the documentation that came with your access point.
- **5** Enter the eight-digit PIN, and then save the setting.

Connecting the printer to a wireless network using the Embedded Web Server

Before you begin, make sure that:

- Your printer is connected temporarily to an Ethernet network.
- A wireless network adapter is installed in your printer and working properly. For more information, see the instruction sheet that came with the wireless network adapter.
- 1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer control panel. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Network/Ports > Wireless.
- 3 Modify the settings to match the settings of your access point (wireless router).

Note: Make sure to enter the correct SSID, security method, preshared key or passphrase, network mode, and channel.

- 4 Click Submit.
- **5** Turn off the printer, and then disconnect the Ethernet cable. Then wait for at least five seconds, and then turn the printer back on.
- **6** To verify if your printer is connected to the network, print a network setup page. Then in the Network Card [x] section, see if the status is Connected.

Changing port settings after installing an internal solutions port

Notes:

- If the printer has a static IP address, then do not change the configuration.
- If the computers are configured to use the network name instead of an IP address, then do not change the configuration.
- If you are adding a wireless internal solutions port (ISP) to a printer previously configured for an Ethernet connection, then disconnect the printer from the Ethernet network.

For Windows users

- **1** Open the printers folder.
- 2 From the shortcut menu of the printer with the new ISP, open the printer properties.
- **3** Configure the port from the list.
- 4 Update the IP address.
- **5** Apply the changes.

For Macintosh users

- 1 From System Preferences in the Apple menu, navigate to the list of printers, and then select + > IP.
- 2 Type the IP address in the address field.
- **3** Apply the changes.

Setting up serial printing (Windows only)

- **1** Set the parameters in the printer.
 - **a** From the control panel, navigate to the menu for the port settings.
 - **b** Locate the menu for the serial port settings, and then adjust the settings, if necessary.
 - c Apply the changes.
- **2** From your computer, open the printers folder, and then select your printer.
- **3** Open the printer properties, and then select the COM port from the list.
- **4** Set the COM port parameters in Device Manager.

Notes:

- Serial printing reduces printing speed.
- Make sure that the serial cable is connected to the serial port on your printer.

Verifying printer setup

Printing a menu settings page

From the home screen, navigate to:



> Reports > Menu Settings Page

Printing a network setup page

If the printer is attached to a network, then print a network setup page to verify the network connection. This page also provides important information that aids network printing configuration.

1 From the home screen, navigate to:



2 Check the first section of the network setup page, and confirm that the status is **Connected**.

If the status is **Not Connected**, then the LAN drop may not be active, or the network cable may be malfunctioning. Consult a system support person for a solution, and then print another network setup page.

Loading paper and specialty media

The selection and handling of paper and specialty media can affect how reliably documents print. For more information, see "Avoiding jams" on page 241 and "Storing paper" on page 63.

Setting the paper size and type

From the home screen navigate to:



> Paper Menu > Paper Size/Type > select a tray > select the paper size or type > Submit

Configuring Universal paper settings

The Universal paper size setting is a user-defined setting that lets you print on paper sizes that are not preset in the printer menus.

1 From the home screen, navigate to:



> Paper Menu > Universal Setup

- 2 Select a unit of measure, and then set the portrait width and height.
- **3** Apply the changes.

Loading trays




CAUTION—POTENTIAL INJURY: To reduce the risk of equipment instability, load each tray separately. Keep all other trays closed until needed.

1 Pull out the tray.

Note: Do not remove trays while a job prints or while Busy appears on the printer display. Doing so may cause a jam.



2 Squeeze and slide the paper guides to the correct position for the size of the paper you are loading.



Note: Use the indicators on the bottom of the tray to position the guides.



3 Flex the sheets back and forth to loosen them, and then fan them. Do not fold or crease the paper. Straighten the edges on a level surface.



4 Load the paper stack with the printable side faceup.



Notes:

- Load printable side facedown for duplex printing.
- Load pre-punched paper with the holes toward the front or the left side of the tray.
- Load letterhead with the header on the left side of the tray.
- Make sure that the paper is below the maximum fill line on the edge of the paper tray. Overfilling may cause paper jams.



- **5** Insert the tray.
- **6** From the control panel, set the paper size and paper type in the Paper menu to match the paper loaded in the tray.

Loading the multipurpose feeder

1 Open the multipurpose feeder.



2 Adjust the guide to match the size of the paper you are loading.



3 Flex the sheets of paper back and forth to loosen them, and then fan them. Do not fold or crease the paper. Straighten the edges on a level surface.




- 4 Load the paper.
 - Load only one size and type of paper.

Loading letterhead

Without an optional finisher	With an optional finisher
One-sided printing	One-sided printing
Note: For long-edge orientation, load letterhead facedown with the header on the left side of the	Note: For long-edge orientation, load letterhead facedown with the header on the right side of the
feeder.	feeder.

Without an optional finisher Two-sided printing Two-sided printing Note: For long-edge orientation, load letterhead faceup with the header on the right side of the feeder. With an optional finisher Two-sided printing Note: For long-edge orientation, load letterhead faceup with the header on the left side of the feeder.

Loading prepunched paper




• Load envelopes with the flap side up.



Warning—Potential Damage: Never use envelopes with stamps, clasps, snaps, windows, coated linings, or self-stick adhesives. These envelopes may severely damage the printer.

• Make sure that the paper is below the maximum fill line. Overfilling may cause paper jams.



5 From the control panel, set the paper size and paper type in the Paper menu to match the paper loaded in the feeder.

Linking and unlinking trays

Linking and unlinking trays

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Paper Menu.
- **3** Change the paper size and type settings for the trays you are linking.
 - To link trays, make sure the paper size and type for the tray match that of the other tray.
 - To unlink trays, make sure the paper size or type for the tray does *not* match that of the other tray.
- 4 Click Submit.

Note: You can also change the paper size and type settings using the printer control panel. For more information, see "Setting the paper size and type" on page 51.

Warning—Potential Damage: Paper loaded in the tray should match the paper type name assigned in the printer. The temperature of the fuser varies according to the specified paper type. Printing issues may occur if settings are not properly configured.

Creating a custom name for a paper type

1 From the home screen, navigate to:



- **2** Type a custom paper type name, and then apply the changes.
- 3 Touch Custom Types, and then verify if the new custom paper type name has replaced the custom name.

Assigning a custom paper type

Using the Embedded Web Server

Assign a custom paper type name to a tray when linking or unlinking trays.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Paper Menu > Custom Types.
- **3** Select a custom paper type name, and then select a paper type.

Note: Paper is the factory default paper type for all user-defined custom names.

4 Click Submit.

Using the printer control panel

1 From the home screen, navigate to:



2 Select a custom paper type name, and then select a paper type.

Note: Paper is the factory default paper type for all user-defined custom names.

3 Touch Submit.

Paper and specialty media guide

Notes:

- Make sure that the paper size, type, and weight are set correctly on the computer or control panel.
- Flex, fan, and straighten specialty media before loading them.
- The printer may print at a reduced speed to prevent damage to the fuser.
- For more information on card stock and labels, see the *Card Stock & Label Guide* on the Lexmark support Web site at http://support.lexmark.com.

Using specialty media

Tips on using card stock

Card stock is heavy, single-ply specialty media. Many of its variable characteristics, such as moisture content, thickness, and texture, can significantly affect print quality.

- From the printer control panel, set the paper size, type, texture, and weight in the Paper menu to match the card stock loaded in the tray.
- Print samples on the card stock being considered for use before buying large quantities.
- Specify the paper texture and weight from the tray settings to match the paper loaded in the tray.
- Preprinting, perforation, and creasing may significantly affect the print quality and cause jams or other paper feed problems.
- Before loading the card stock on the tray, flex and fan the card stock to loosen them. Straighten the edges
 on a level surface.

Tips on using envelopes

- From the printer control panel, set the paper size, type, texture, and weight in the Paper menu to match the envelopes loaded in the tray.
- Print samples on the envelopes being considered for use before buying large quantities.
- Use envelopes designed specifically for laser printers.
- For best performance, use envelopes made from 90-g/m² (24-lb) paper or 25% cotton.
- Use only new envelopes from undamaged packages.
- To optimize performance and minimize jams, do not use envelopes that:
 - Have excessive curl or twist.
 - Are stuck together or damaged in any way.
 - Have windows, holes, perforations, cutouts, or embossing.
 - Have metal clasps, string ties, or folding bars.
 - Have an interlocking design.
 - Have postage stamps attached.
 - Have any exposed adhesive when the flap is in the sealed or closed position.

- Have bent corners.
- Have rough, cockle, or laid finishes.
- Adjust the width guides to fit the width of the envelopes.
- Before loading the envelopes on the tray, flex the stack of envelopes back and forth to loosen them, and then fan them. Straighten the edges on a level surface.

Note: A combination of high humidity (over 60%) and high printing temperature may wrinkle or seal envelopes.

Tips on using labels

- From the printer control panel, set the paper size, type, texture, and weight in the Paper menu to match the labels loaded in the tray.
- Print samples on labels being considered for use before buying large quantities.
- For more information on label printing, characteristics, and design, see the *Card Stock & Label Guide* on the Lexmark Web site at http://support.lexmark.com.
- Use labels designed specifically for laser printers.
- Do not use labels with slick backing material.
- Do not use labels with exposed adhesive.
- Use full label sheets. Partial sheets may cause labels to peel off during printing, resulting in a jam. Partial sheets also contaminate the printer and the cartridge with adhesive, and could void the printer and toner cartridge warranties.
- Before loading labels on the tray, flex and fan labels to loosen them. Straighten the edges on a level surface.

Tips on using letterhead

- Use letterhead specifically for laser printers.
- Print samples before buying large quantities.
- Before loading letterhead, flex and fan the sheets.
- When printing on letterhead, take note of the page orientation.

Source	Printing	Side with the letterhead	Paper orientation
Trays	One-sided	Faceup	Load the sheet with the top edge toward the back of the tray.
	Two-sided	Facedown	Load the sheet with the top edge toward the front of the tray.
Multipurpose feeder	One-sided	Facedown	Load the sheet with the top edge on the left side.
	Two-sided	Faceup	Load the sheet with the top edge on the right side.

Tips on using transparencies

- From the printer control panel, set the paper size, type, texture, and weight in the Paper menu to match the transparencies loaded in the tray.
- Print a test page on the transparencies being considered for use before buying large quantities.
- Use transparencies designed specifically for laser printers.
- Avoid getting fingerprints on the transparencies to prevent print quality problems.
- Before loading transparencies, flex and fan the sheets to prevent them from sticking together.
- When printing on large volumes of transparencies, make sure to print by batches of only up to 20 with an interval of at least three minutes between batches, to prevent the transparencies from sticking together in the bin. You can also remove transparencies from the bin by batches of 20.

Paper guidelines

Paper characteristics

The following paper characteristics affect print quality and reliability. Consider these factors before printing on them:

Weight

The printer trays can feed paper weights between $60-256 \text{ g/m}^2$ (16-68-lb) grain long paper. The multipurpose feeder can feed paper weights between $60-256 \text{ g/m}^2$ (16-68-lb) grain long paper. Paper lighter than 60 g/m^2 (16 lb) might not be stiff enough to feed properly, and may cause jams.

Note: Two-sided printing is supported for 60–169 g/m² (16–45-lb) paper.

Curl

Curl is the tendency for paper to curl at its edges. Excessive curl can cause paper feeding problems. Curl can occur after the paper passes through the printer, where it is exposed to high temperatures. Storing paper unwrapped in hot, humid, cold, or dry conditions, even in the trays, can contribute to paper curling prior to printing and can cause feeding problems.

Smoothness

Paper smoothness directly affects print quality. If paper is too rough, toner cannot fuse to it properly. If paper is too smooth, it can cause paper feeding or print quality issues. Always use paper between 100 and 200 Sheffield points.

Moisture content

The amount of moisture in paper affects both print quality and the ability of the printer to feed the paper correctly. Leave paper in its original wrapper until it is time to use it. This limits the exposure of paper to moisture changes that can degrade its performance.

Store paper in its original wrapper in the same environment as the printer for 24 to 48 hours before printing. Extend the time several days if the storage or transportation environment is very different from the printer environment. Thick paper may also require a longer conditioning period.

Grain direction

Grain refers to the alignment of the paper fibers in a sheet of paper. Grain is either *grain long*, running the length of the paper, or *grain short*, running the width of the paper.

For 60-256 g/m² (16-68-lb) paper, grain long paper is recommended.

Fiber content

Most high-quality xerographic paper is made from 100% chemically treated pulped wood. This content provides the paper with a high degree of stability, resulting in fewer paper feeding problems and better print quality. Paper containing fibers such as cotton can negatively affect paper handling.

Selecting paper

Using the appropriate paper prevents jams and helps ensure trouble-free printing.

To help avoid paper jams and poor print quality:

- Always use new, undamaged paper.
- Before loading paper, know the recommended printable side of the paper. This information is usually indicated on the paper package.
- Do not use paper that has been cut or trimmed by hand.
- Do not mix paper sizes, types, or weights in the same tray; mixing results in jams.
- Do not use coated papers unless they are specifically designed for electrophotographic printing.

Selecting preprinted forms and letterhead

- Use grain long for 60–256-g/m² (16–68-lb) paper.
- Use only forms and letterhead printed using an offset lithographic or engraved printing process.
- Avoid paper with rough or heavily textured surfaces.
- Use inks that are not affected by the resin in toner. Inks that are oxidation-set or oil-based generally meet these requirements; latex inks might not.
- Print samples on preprinted forms and letterheads considered for use before buying large quantities. This determines whether or not the ink in the preprinted form or letterhead will affect print quality.
- When in doubt, contact your paper supplier.

Using recycled paper and other office papers

As an environmentally conscientious company, Lexmark supports the use of recycled paper produced specifically for use in laser (electrophotographic) printers.

While no blanket statement can be made that all recycled paper will feed well, Lexmark consistently tests papers that represent recycled cut size copier papers available on the global market. This scientific testing is conducted with rigor and discipline. Many factors are taken into consideration both separately and as a whole, including the following:

- Amount of post-consumer waste (Lexmark tests up to 100% post-consumer waste content.)
- Temperature and humidity conditions (Testing chambers simulate climates from all over the world.)
- Moisture content (Business papers should have low moisture: 4–5%.)
- Bending resistance and proper stiffness means optimum feeding through the printer.

- Thickness (impacts how much can be loaded into a tray)
- Surface roughness (measured in Sheffield units, impacts print clarity and how well toner fuses to the paper)
- Surface friction (determines how easily sheets can be separated)
- Grain and formation (impacts curling, which also influences the mechanics of how the paper behaves as it moves through the printer)
- Brightness and texture (look and feel)

Recycled papers are better than ever; however, the amount of recycled content in a paper affects the degree of control over foreign matter. And while recycled papers are one good path to printing in an environmentally responsible manner, they are not perfect. The energy required to de-ink and deal with additives such as colorants and "glue" often generates more carbon emissions than does normal paper production. However, using recycled papers enables better resource management overall.

Lexmark concerns itself with the responsible use of paper in general based on life cycle assessments of its products. To gain a better understanding of the impact of printers on the environment, the company commissioned a number of life cycle assessments and found that paper was identified as the primary contributor (up to 80%) of carbon emissions caused throughout the entire life of a device (from design to end-of-life). This is due to the energy-intensive manufacturing processes required to make paper.

Thus, Lexmark seeks to educate customers and partners on minimizing the impact of paper. Using recycled paper is one way. Eliminating excessive and unnecessary paper consumption is another. Lexmark is well-equipped to help customers minimize printing and copying waste. In addition, the company encourages purchasing paper from suppliers who demonstrate their commitment to sustainable forestry practices.

Lexmark does not endorse specific suppliers, although a converter's product list for special applications is maintained. However, the following paper choice guidelines will help alleviate the environmental impact of printing:

- **1** Minimize paper consumption.
- **2** Be selective about the origin of wood fiber. Buy from suppliers who carry certifications such as the Forestry Stewardship Council (FSC) or the Program for the Endorsement of Forest Certification (PEFC). These certifications guarantee that the paper manufacturer uses wood pulp from forestry operators that employ environmentally and socially responsible forest management and restoration practices.
- **3** Choose the most appropriate paper for printing needs: normal 75 or 80 g/m² certified paper, lower weight paper, or recycled paper.

Unacceptable paper examples

Test results indicate that the following paper types are at risk for use with laser printers:

- Chemically treated papers used to make copies without carbon paper, also known as carbonless papers
- Preprinted papers with chemicals that may contaminate the printer
- Preprinted papers that can be affected by the temperature in the printer fuser
- Preprinted papers that require a registration (the precise location on the page) greater than ± 2.3 mm (± 0.9 in.), such as optical character recognition (OCR) forms. In some cases, registration can be adjusted with a software application to successfully print on these forms.)
- Coated papers (erasable bond), synthetic papers, thermal papers
- Rough-edged, rough or heavily textured surface papers or curled papers
- Recycled papers that fail EN12281:2002 (European testing)
- Paper weighing less than 60 g/m² (16 lb)
- Multiple part forms or documents

For more information about Lexmark, visit <u>www.lexmark.com</u>. General sustainability-related information can be found at the **Environmental Sustainability** link.

Storing paper

Use these paper storage guidelines to help avoid jams and uneven print quality:

- For best results, store paper where the temperature is 21°C (70°F) and the relative humidity is 40 percent. Most label manufacturers recommend printing in a temperature range of 18–24°C (65–75°F) with relative humidity between 40 and 60 percent.
- Store paper in cartons, on a pallet or shelf, rather than on the floor.
- Store individual packages on a flat surface.
- Do not store anything on top of individual paper packages.
- Take paper out of the carton or wrapper only when you are ready to load it in the printer. The carton and wrapper help keep the paper clean, dry, and flat.

Supported paper sizes, types, and weights

Paper sizes supported by the printer

Paper sizes supported by the trays and multipurpose feeder

Paper size	Dimensions	Standard 500-she et tray (Tray 1)	Standard 500-she et tray (Tray 2)	2 x 500- sheet tray	2500-she et tray	3000-she et tray	Multipurpos e feeder ³	Two-sided printing
A4	210 x 297 mm (8.3 x 11.7 in.)	✓	✓	✓	\ 2	\ 2	√ 2	✓
A5	148 x 210 mm (5.8 x 8.3 in.)	√ 1	√ 1	√ 1	X	X	✓	\
A6	105 x 148 mm (4.1 x 5.8 in.)	х	х	х	х	х	√ 1	✓
JIS B5	182 x 257 mm (7.2 x 10.1 in.)	✓	✓	✓	х	х	✓	✓
Letter	216 x 279 mm (8.5 x 11 in.)	✓	✓	✓	\ 2	\ 2	✓	✓

¹ Supported only in short-edge orientation.

Note: Banner is supported in the multipurpose feeder only if the width is up to 296.9 mm (11.69 in.), and the length is up to 1219.2 mm (48 in.). Set the paper size to Universal.

² Supported only in long-edge orientation.

³ Supports paper size without size sensing.

 $^{^4}$ Supported only if the width is from 139.7 mm (5.5 in.) to 320 mm (12.6 in.), and the length is from 148 mm (5.83 in.) to 458 mm (18 in.).

Paper size	Dimensions	Standard 500-she et tray (Tray 1)	Standard 500-she et tray (Tray 2)	2 x 500- sheet tray	2500-she et tray	3000-she et tray	Multipurpos e feeder ³	Two-sided printing
Legal	216 x 356 mm (8.5 x 14 in.)	✓	✓	✓	X	X	✓	✓
Executive	184 x 267 mm (7.3 x 10.5 in.)	✓	✓	✓	х	х	✓	✓
JIS B4	257 x 364 mm (10.12 x 14.33 in.)	✓	✓	✓	х	х	✓	✓
SRA3	320 x 450 mm (12.6 x 17.7 in.)	х	√ 1	х	х	х	√ 1	√
АЗ	297 x 420 mm (11.69 x 16.54 in.)	✓	✓	✓	х	х	✓	✓
12 x 18	305 x 457 mm (12 x 18 in.)	х	√ 1	х	х	х	√ 1	✓
11 x 17	279.4 x 431.8 mm (11 x 17 in.)	√	√	√	х	х	✓	√
Oficio	216 x 340 mm (8.5 x 13.4 in.)	✓	√	✓	х	х	✓	✓
Folio	216 x 330 mm (8.5 x 13 in.)	✓	✓	✓	х	х	✓	✓
Statement	140 x 216 mm (5.5 x 8.5 in.)	√ 1	√ 1	√ 1	х	Х	✓	✓
Universal	76.2 x 76.2 mm (3 x 3 in.) to 320 x 1219.2 mm (12.6 x 48 in.)	✓	✓	✓	х	х	√	\ 4
7 3/4 Envelope	98 x 191 mm (3.9 x 7.5 in.)	х	х	х	х	х	✓	х
9 Envelope	98 x 225 mm (3.9 x 8.9 in.)	x	x	х	х	х	✓	х
10 Envelope	105 x 241 mm (4.1 x 9.5 in.)	x	x	х	х	х	✓	х
DL Envelope	110 x 220 mm (4.3 x 8.7 in.)	x	x	х	х	х	✓	х

¹ Supported only in short-edge orientation.

Note: Banner is supported in the multipurpose feeder only if the width is up to 296.9 mm (11.69 in.), and the length is up to 1219.2 mm (48 in.). Set the paper size to Universal.

² Supported only in long-edge orientation.

³ Supports paper size without *size sensing*.

 $^{^4}$ Supported only if the width is from 139.7 mm (5.5 in.) to 320 mm (12.6 in.), and the length is from 148 mm (5.83 in.) to 458 mm (18 in.).

Paper size	Dimensions	Standard 500-she et tray (Tray 1)	Standard 500-she et tray (Tray 2)	2 x 500- sheet tray	2500-she et tray	3000-she et tray	Multipurpos e feeder ³	Two-sided printing
C5 Envelope	162 x 229 mm (6.4 x 9 in.)	x	x	X	X	X	✓	x
B5 Envelope	176 x 250 mm (6.9 x 9.8 in.)	x	x	X	X	X	✓	x
Other Envelope	98 x 162 mm (3.9 x 6.3 in.) to 176 x 250 mm (6.9 x 9.8 in.)		х	X	Х	Х	✓	x

¹ Supported only in short-edge orientation.

Note: Banner is supported in the multipurpose feeder only if the width is up to 296.9 mm (11.69 in.), and the length is up to 1219.2 mm (48 in.). Set the paper size to Universal.

Paper sizes supported by the ADF and scanner glass

Paper size	Dimensions	ADF	Scanner glass
Business card		x	√ 1,2
3 x 5	76.2 x 127 mm (3 x 5 in.)	x	√ 1,2
4 x 6	101.6 x 152.4 mm (4 x 6 in.)	✓2	√ 1,2
A4	210 x 297 mm (8.3 x 11.7 in.)	✓	✓
A5	148 x 210 mm (5.8 x 8.3 in.)	✓	√2
A6	105 x 148 mm (4.1 x 5.8 in.)	√ 1,2	√ 1,2
JIS B5	182 x 257 mm (7.2 x 10.1 in.)	✓	✓
Letter	216 x 279 mm (8.5 x 11 in.)	✓	✓
Legal	216 x 356 mm (8.5 x 14 in.)	✓	✓
Executive	184 x 267 mm (7.3 x 10.5 in.)	✓	✓
JIS B4	257 x 364 mm (10.12 x 14.33 in.)	✓	✓
SRA3	320 x 450 mm (12.6 x 17.7 in.)	х	х
А3	297 x 420 mm (11.69 x 16.54 in.)	✓	✓

¹ Supported only in short-edge orientation.

² Supported only in long-edge orientation.

³ Supports paper size without *size sensing*.

 $^{^4}$ Supported only if the width is from 139.7 mm (5.5 in.) to 320 mm (12.6 in.), and the length is from 148 mm (5.83 in.) to 458 mm (18 in.).

² Supports paper size without *size sensing*.

Paper size	Dimensions	ADF	Scanner glass	
12 x 18	305 x 457 mm (12 x 18 in.)	X	х	
11 x 17	279.4 x 431.8 mm (11 x 17 in.)	✓	✓	
Oficio	216 x 340 mm (8.5 x 13.4 in.)	√ 2	\ 2	
Folio	216 x 330 mm (8.5 x 13 in.)	✓	✓	
Statement	140 x 216 mm (5.5 x 8.5 in.)	✓	√	
Universal	89 x 98.4 mm (3.50 x 3.87 in.) to 297 x 431.8 mm (11.69 x 17.00 in.)	√ 2	√ 2	
7 3/4 Envelope	98 x 191 mm (3.9 x 7.5 in.)	X	x	
9 Envelope	98 x 225 mm (3.9 x 8.9 in.)	X	x	
10 Envelope	105 x 241 mm (4.1 x 9.5 in.)	X	х	
DL Envelope	110 x 220 mm (4.3 x 8.7 in.)	X	х	
C5 Envelope	162 x 229 mm (6.4 x 9 in.)	х	х	
B5 Envelope	176 x 250 mm (6.9 x 9.8 in.)	х	х	
Other Envelope	98 x 162 mm (3.9 x 6.3 in.) to 176 x 250 mm (6.9 x 9.8 in.)	х	х	
Custom Scan Size [x]		√2	√ 2	

¹ Supported only in short-edge orientation.

Paper types and weights supported by the printer

The printer engine supports 60–256-g/m² (16–68-lb) paper weights.

Note: Labels, transparencies, envelopes, and card stock always print at reduced speed.

Paper type		Standard 500-sheet tray (Tray 2)	2 x 500- sheet tray		3000-shee t tray	Multipurpose feeder	ADF	Scanne r
Plain Paper ¹	✓	✓	✓	✓	✓	✓	>	✓
Card Stock ¹	✓	✓	✓	✓	✓	√	✓	✓
Transparencie s ²	x	x	x	x	x	√	>	✓
Recycled ¹	✓	✓	✓	✓	✓	√	✓	✓

¹ Paper is supported for two-sided printing.

² Supports paper size without *size sensing*.

² Print transparencies in batches of only up to 20 to prevent them from sticking together. For more information, see <u>"Tips on using transparencies" on page 60.</u>

Paper type	Standard 500-sheet tray (Tray 1)	Standard 500-sheet tray (Tray 2)	2 x 500- sheet tray	2500-she et tray	3000-shee t tray	Multipurpose feeder	ADF	Scanne r
Glossy ¹	✓	✓	✓	✓	✓	✓	✓	✓
Heavy Glossy ¹	√	√	√	√	√	√	√	✓
Labels	х	х	х	х	х	√	√	✓
Vinyl Labels	x	х	х	х	х	x	√	✓
Bond ¹	✓	✓	√	✓	✓	√	√	✓
Envelope	x	х	х	х	x	√	√	√
Rough Envelope	х	x	х	х	x	√	✓	✓
Letterhead ¹	√	√	√	√	√	√	√	✓
Preprinted ¹	√	√	√	√	√	√	√	✓
Colored Paper ¹	√	√	√	√	√	√	√	✓
Light Paper ¹	√	√	√	√	√	√	√	✓
Heavy Paper ¹	√	√	√	√	√	√	√	✓
Rough Cotton ¹	√	✓	√	✓	√	√	√	✓
Custom Type ¹	✓	✓	√	✓	✓	√	√	✓

¹ Paper is supported for two-sided printing.

Paper sizes, types, and weights supported by the finishers

The printer engine supports $60-256 \text{ g/m}^2$ (16-68-lb) paper weights.

Note: When a finisher is installed, the standard finisher bin becomes the default bin even for print jobs that do not require finishing.

² Print transparencies in batches of only up to 20 to prevent them from sticking together. For more information, see <u>"Tips on using transparencies" on page 60.</u>

Supported paper sizes

Paper size	Staple finisher	Staple, hole punch finisher bin 1	Staple, hole punch finisher bin 2	Booklet finisher
A6	√ 3	√ 3	x	х
A5	√ 3	√ 3	√ 2	х
JIS B5	✓	✓	✓	x
JIS B4	✓	✓	✓	✓
Executive	✓	✓	✓	х
Letter	✓	✓	✓	√
A4	✓	✓	✓	√
Legal	✓	√ 4	✓	√
12 x 18	√ 1	√ 3	√ 1	√
11 x 17	✓	✓	✓	√
SRA3	√ 1	√ 3	√ 1	✓
АЗ	✓	✓	✓	√
Oficio	√ 1	√ 3	√ 3	x
Folio	√ 1	√ 3	√ 3	x
Statement	√ 1	√ 3	√ 3	x
Universal	✓	√3	√ 1	√ 5

¹ Paper is supported only if the finisher stacks the paper but does not staple or punch holes in it.

 $^{^2}$ Paper is supported only if the finisher stacks or staples the paper but does not punch holes in it.

³ Paper is supported but the finisher does not stack, staple, or punch holes in it.

⁴ Paper is supported only for 2-hole punch.

 $^{^{5}}$ Paper is supported only if the paper size is between 210 x 279.4 mm (8.27 x 11 in.) and 320 x 457.2 mm (12.6 x 18 in.).

Supported paper types

Paper type	Staple finisher	Staple, hole punch finisher	Booklet finisher
Plain Paper	✓	✓	√ 5
Card Stock	\ 2	✓	x
Transparency ¹	√ 2	√3	х
Recycled	√ 2	✓	√ 5
Glossy	√ 2	✓	√ 5
Heavy Glossy	√ 2	√ 4	x
Labels	√ 2	√ 3	х
Bond	✓	✓	√ 5
Envelope	√ 2	√ 3	x
Rough Envelope	√ 2	√ 3	x
Letterhead	✓	✓	√ 5
Preprinted	✓	✓	√ 5
Colored Paper	✓	✓	√ 5
Light Paper	✓	✓	√ 5
Heavy Paper	√ 2	√ 4	х
Rough Cotton	√ 2	✓	х
Custom Type	✓	✓	√ 5

¹ Print on transparencies by batches of only up to 20 to prevent them from sticking together. For more information, see "Tips on using transparencies" on page 60.

² Paper is supported only if the finisher stacks the paper but does not staple it.

³ Paper is supported only if the finisher stacks the paper but does not staple or punch holes in it.

⁴ Paper is supported only if the finisher punches holes or stacks the paper but does not staple it.

⁵ Paper is supported only if the finisher staples or folds the paper.

Printing 70

Printing

Printing forms and a document

Printing forms

Use Forms and Favorites to quickly and easily access frequently used forms or other information that is regularly printed. Before you can use this application, first set it up on the printer. For more information, see <u>"Setting up Forms and Favorites" on page 22</u>.

- **1** From the home screen, navigate to:
 - Forms and Favorites > select the form from the list > enter the number of copies > adjust other settings
- 2 Apply the changes.

Printing from a computer

Note: For specialty media such as labels, card stock, and envelopes, set the paper size and type in the printer before sending the print job.

- 1 With a document open, click File > Print.
- **2** If necessary, adjust the settings.
- **3** Send the print job.

Adjusting toner darkness

1 From the home screen, navigate to:



2 Adjust the toner darkness setting, and then save the changes.


Printing 71

Printing from a flash drive or mobile device

Printing from a flash drive

Notes:

- Before printing an encrypted PDF file, you are prompted to type the file password from the control panel.
- You cannot print files for which you do not have printing permissions.
- 1 Insert a flash drive into the USB port.



Notes:

- A flash drive icon appears on the printer home screen when a flash drive is inserted.
- If you insert the flash drive when the printer requires attention, such as when a jam has occurred, then the printer ignores the flash drive.
- If you insert the flash drive while the printer is processing other print jobs, then **Busy** appears on the printer display. After these print jobs are processed, you may need to view the held jobs list to print documents from the flash drive.

Warning—Potential Damage: Do not touch the printer or the flash drive in the area shown while actively printing, reading, or writing from the memory device. Loss of data or a malfunction can occur.

Printing 72



- **2** From the control panel, touch the document you want to print.
- **3** Specify the number of copies to be printed, and then send the job for printing.

Notes:

- Do not remove the flash drive from the USB port until the document has finished printing.
- If you leave the flash drive in the printer after leaving the initial USB menu screen, then touch **Held**Jobs on the home screen to print files from the flash drive.

Supported flash drives and file types

Notes:

- High-speed USB flash drives must support the full-speed standard. Low-speed USB devices are not supported.
- USB flash drives must support the File Allocation Table (FAT) system. Devices formatted with New Technology File System (NTFS) or any other file system are not supported.

Recommended flash drives	File type
Lexar FireFly (512MB and 1GB)	Documents:
SanDisk Cruzer Micro (512MB and 1GB)	• .pdf
Sony (512MB and 1GB)	• .xps
	Images:
	• .dcx
	• .gif
	• .jpeg or .jpg
	• .bmp
	• .pcx
	• .tiff or .tif
	• .png

Printing 73

Printing from a mobile device

To download a compatible mobile printing application, visit www.lexmark.com/mobile.

Note: Mobile printing applications may also be available from your mobile device manufacturer.

Printing confidential and other held jobs

Storing print jobs in the printer

1 From the printer control panel, navigate to:



> Security > Confidential Print > select the print job type

Use	То
Max Invalid PIN	Limit the number of times an invalid PIN can be entered.
	Note: When the limit is reached, the print jobs for that user name and PIN are deleted.
Confidential Job Expiration	Hold print jobs in the computer until you enter the PIN from the printer control panel.
	Note: The PIN is set from the computer. It must be four digits, using the numbers 1–9.
Repeat Job Expiration	Print and store print jobs in the printer memory.
Verify Job Expiration	Print one copy of a print job and hold the remaining copies. It allows you to examine if the first copy is satisfactory. The print job is automatically deleted from the printer memory when all copies are printed.
Reserve Job Expiration	Store print jobs for printing at a later time.
	Note: The print jobs are held until deleted from the Held Jobs menu.

Notes:

- Confidential, Verify, Reserve, and Repeat print jobs may be deleted if the printer requires extra memory to process additional held jobs.
- You can set the printer to store print jobs in the printer memory until you start the print job from the printer control panel.
- All print jobs that can be initiated by the user at the printer are called *held jobs*.
- 2 Touch Submit.

Printing held jobs

- 1 With a document open, select File > Print.
- 2 Select the printer, and then do the following:
 - For Windows users, click Properties or Preferences, and then click Print and Hold.
 - For Macintosh users, select **Print and Hold**.
- **3** Select the print job type.

Printing 74

- 4 If necessary, assign a user name.
- **5** Send the print job.
- **6** From the printer home screen, touch **Held Jobs**.
- **7** Send the print job.

Modifying confidential print settings

Note: This feature is available only in network printers or printers connected to print servers.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address in the TCP/IP section in the Network/Ports menu. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings tab > Security > Confidential Print Setup.
- **3** Modify the settings:
 - Set a maximum number of PIN entry attempts. When a user exceeds a specific number of PIN entry attempts, all of the jobs for that user are deleted.
 - Set an expiration time for confidential print jobs. When a user has not printed the jobs within the specified time, all of the jobs for that user are deleted.
- **4** Save the modified settings.

Printing information pages

Printing a font sample list

1 From the home screen, navigate to:



2 Touch PCL Fonts or PostScript Fonts.

Printing a directory list

A directory list shows the resources stored in a flash memory or in the printer hard disk.

From the home screen, navigate to:



Printing 75

Canceling a print job

Canceling a print job from the printer control panel

- **1** From the printer control panel, touch **Cancel Job** or press on the keypad.
- 2 Touch the print job you want to cancel, and then touch **Delete Selected Jobs**.

Note: If you press on the keypad, then touch **Resume** to return to the home screen.

Canceling a print job from the computer

- **1** Depending on the operating system, do either of the following:
 - Open the printers folder, and then select your printer.
 - From the System Preferences in the Apple menu, navigate to your printer.
- **2** Select the print job to cancel.

Copying

Use the ADF for multiple-page or two-sided documents. Load the original document faceup. Use the scanner glass for single-page documents, book pages, small items (such as postcards or photos), transparencies, photo paper, or thin media (such as magazine clippings). Place the document facedown in the corner with the arrow.

Making copies

Copying using the ADF or scanner glass

1 Load an original document into the ADF tray or on the scanner glass.

Note: To avoid a cropped image, make sure the size of the original document and the size of the copy paper are the same.

2 From the home screen, navigate to:

Copy > specify the copy settings > Copy It

Note: To make a quick copy, from the control panel, press



Copying photos

- **1** Place a photo on the scanner glass.
- **2** From the home screen, navigate to:

Copy > Content > Photo >

- **3** From the Content Source menu, select the setting that best matches the original photo.
- 4 Touch ✓ > Copy It.

Copying on transparencies or letterhead

- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

Copy > Copy from > select the size of the original document >

3 Touch **Copy to**, and then select the tray that contains the specialty media.

If you are loading the specialty media into the multipurpose feeder, then navigate to:

Multipurpose Feeder > > select the size of the specialty media > > Transparency or Letterhead

4 Touch ✓ > Copy It.

Creating a copy shortcut

Notes:

- Make sure that Copy Shortcuts is set to Display. From the home screen, touch > Settings > General Settings > Home screen customization > Copy Shortcuts > Display > Submit.
- To delete a copy shortcut, touch > Manage Shortcuts > Copy Shortcuts > the shortcut to delete > Delete now.

Creating a copy shortcut using the printer control panel

- **1** From the home screen, touch **Copy**.
- 2 Adjust the copy settings, and then touch Save as Shortcut.

Note: If you change the settings after the copy shortcut has been created, then the settings are not saved.

- **3** Type a unique name for the shortcut, and then touch **Done**.
- **4** Verify that the shortcut name is correct, and then touch **OK**. If the shortcut name is incorrect, then touch **Cancel**, and then reenter the information.

Notes:

- The shortcut name appears in the Copy Shortcuts icon on the printer home screen.
- You can use the shortcut when copying another document using the same settings.

Customizing copy settings

Copying to a different size

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, navigate to:

Copy > Copy from > select the size of the original document >

- 3 Touch Copy to, and then select a new size for the copy.
- 4 Touch ✓ > Copy It.

Making copies using paper from a selected tray

- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

Copy > Copy from > select the size of the original document >

- **3** Touch **Copy to**, and then select the tray containing the paper type you want to use.
- 4 Touch ✓ > Copy It.

Copying different paper sizes

Copying onto mixed paper sizes

- 1 Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

Copy > Copy from > Mixed Sizes >

3 Touch Copy to > Auto Size Match > > Copy It.

Copying onto a single paper size

- **1** Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, navigate to:

Copy > Copy from > Mixed Sizes >

3 Touch Copy to > Letter > ✓ > Copy It.

The scanner identifies the different paper sizes as they are scanned, and then scales the mixed paper sizes to fit on the paper size selected.

Copying on both sides of the paper (two-sided)

- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

Copy > Sides (Duplex) > select the preferred two-sided method

Note: For the preferred method, the first number represents sides of the original documents while the second number represents sides of the copy. For example, select "2 sided to 2 sided" if you have two-sided original documents and you want two-sided copies.

3 Touch ✓ > Copy It.

Reducing or enlarging copies

Copies can be scaled from 25% to 400% of the original document size.

- 1 Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, touch **Copy**.
- **3** From the Scale area, touch or to decrease or increase the value by 1%.

 Touching "Copy to" or "Copy from" after setting Scale manually changes the scale value back to Auto.

Note: Auto is the factory default setting. This automatically adjusts the scan image of the original document to fit the size of the paper onto which you are copying.

4 Touch Copy It.

Adjusting copy quality


- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

Copy > Content > specify the content type of the document >

3 Specify the content source of the document, and then touch **≤** > **Copy It**.

Collating copies

If you print multiple copies of a document, then you can choose to print the copies as a set (collated) or to print the copies as groups of pages (not collated).



- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

Copy > enter the number of copies > Collate > select the preferred order of pages > ✓ > Copy It

Placing separator sheets between copies

- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

Copy > Advanced Options > Separator Sheets > select where you want to place the separator sheets

Note: Set Collate to (1,2,3) (1,2,3) to place separator sheets between copies. If Collate is set to (1,1,1) (2,2,2), then the separator sheets are added to the end of the copy job. For more information, see "Collating copies" on page 79.

3 Touch ✓ > Copy It.

Copying multiple pages onto a single sheet

In order to save paper, you can copy either two or four consecutive pages of a multiple-page document onto a single sheet of paper.

Notes:

- Make sure to set the paper size to letter, legal, A4, or JIS B5.
- Make sure to set the copy size to 100%.
- 1 Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

Copy > Advanced Options > Paper Saver > select the output you want > > Copy It

Note: If Paper Saver is set to Off, then the Print Page Borders option is unavailable.

Creating a custom copy job

The custom copy job is used to combine one or more sets of original documents into a single copy job.

The definition of a set depends on the scan source:

- If you scan a document on the scanner glass, then a set consists of one page.
- If you scan multiple pages using the ADF, then a set consists of all scanned pages until the ADF tray becomes empty.
- If you scan one page using the ADF, then a set consists of one page.
- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

Copy > Advanced Options > Custom Job > On > > Copy It

Note: When the end of a set is reached, the scan screen appears.

3 Load the next document into the ADF tray or on the scanner glass, and then touch **Scan from automatic** feeder or **Scan from flatbed**.

Note: Change the scan job settings, if necessary.

4 If you have another document to scan, then repeat the previous step. Otherwise, touch Finish the job.

Placing a header or footer on pages

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, navigate to:

Copy > **Advanced Options** > **Header/Footer** > select where you want to place the header or footer > select the type of header or footer you want

- **3** Enter the required information depending on the header or footer you selected, and then touch **Done**.
- **4** Touch

 ✓, and then press .

Canceling a copy job while pages are being printed

- **1** From the printer control panel, touch **Cancel Job** or press on the keypad.
- 2 Touch the job you want to cancel, and then touch **Delete Selected Jobs**.

Note: If you press on the keypad, then touch **Resume** to return to the home screen.

Understanding the copy options

Copy from

This option opens a screen where you can select the paper size of the original document.

- Touch the paper size that matches the original document.
- To copy an original document that contains mixed paper sizes with the same width, touch Mixed Sizes.
- To set the printer to automatically detect the size of the original document, touch Auto Size Sense.

Copy to

This option opens a screen where you can enter the paper size and type on which your copies will be printed.

- Touch the paper size and type that matches the paper loaded.
- If the paper size setting for "Copy from" and "Copy to" are different, then the printer automatically adjusts the Scale setting to accommodate the difference.

Scale

This option lets you scale the document from 25% to 400% of the original document size. You can also set automatic scaling.

When copying to a different paper size, such as from legal-size to letter-size paper, set the "Copy from" and
"Copy to" paper sizes automatically to scale the scan image to fit the size of the paper onto which you are
copying.

• To decrease or increase the value by 1%, touch or the printer control panel. To make a continuous decrease or increase in value, hold the button for two seconds or more.

Darkness

This option lets you adjust how light or dark the copies are in relation to the original document.

Sides (Duplex)

This option lets you make one- or two-sided copies from one- or two-sided original documents.

Collate

This option keeps the pages of a print job stacked in sequence when printing multiple copies of the document.

Copies

This option lets you set the number of copies to be printed.

Content

This option lets you specify the content type and source of the original document.

Save As Shortcut

This option lets you save the current settings by assigning a shortcut name.

Note: Selecting this option automatically assigns the next available shortcut number.

Punch

This setting specifies whether copy jobs will have holes punched in them.

Staple

This setting specifies whether copy jobs that contain multiple pages will be stapled.

Using the advanced options

 Advanced Duplex—This specifies the document orientation, one-sided or two-sided printing, and type of binding.

- Advanced Imaging—This adjusts the Auto Center, Background Removal, Color Balance, Color Dropout,
 Contrast, Mirror Image, Negative Image, Scan Edge to Edge, Shadow Detail, and Sharpness settings before
 you copy the document.
- Create Booklet—This creates a one-sided or two-sided booklet.

Note: This option appears only when a printer hard disk is installed.

- Cover Page Setup—This sets up the cover page of copies and booklets.
- Custom Job—This combines multiple scanning jobs into a single job.

Note: This option appears only when a printer hard disk is installed.

- **Edge Erase**—This removes smudges or marks around the edges of a document. You can choose to remove an equal area around all four sides of the paper, or pick a particular edge. Edge Erase removes whatever is within the area selected.
- Fold—This folds the paper in two (bifold) or three (trifold).

Note: This option appears only if a booklet finisher is installed.

- Header/Footer—This inserts Date/Time, Page number, Bates number, or Custom text in the specified header or footer location.
- Margin Shift—This increases or decreases the page margin by shifting the scanned image. Touch to set the margin you want. If the additional margin is too large, then the copy is cropped.
- Offset Pages—This offsets pages between copies or between jobs.
- Overlay—This creates a watermark or message that overlays each page of your copy. You can choose from preset messages or enter a custom message.
- **Paper Saver**—This prints two or more pages of an original document on the same page. Paper Saver is also called *N-up* printing, where *N* stands for the number of pages. For example, 2-up would print two pages on a single page, and 4-up would print four pages on a single page.
- Separator Sheets—This places a blank sheet of paper between copies, pages, or print jobs. The separator sheets can be drawn from a tray that contains a type or color of paper that is different from the paper your copies are printed on.

E-mailing

Use the ADF for multiple-page or two-sided documents. Load the original document faceup. Use the scanner glass for single-page documents, book pages, small items (such as postcards or photos), transparencies, photo paper, or thin media (such as magazine clippings). Place the document facedown in the corner with the arrow.

Setting up the printer to e-mail

Configuring e-mail settings

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > E-mail/FTP Settings > E-mail Settings.
- **3** Enter the appropriate information, and then click **Submit**.

Creating an e-mail shortcut

Notes:

• Make sure that E-mail Shortcuts is set to Display. From the home screen, touch > Settings > General Settings > Home screen customization > E-mail Shortcuts > Display > Submit.

• To delete an e-mail shortcut, touch | > Manage Shortcuts > E-mail Shortcuts > the shortcut to delete > Delete Entry > Delete now.

Creating an e-mail shortcut using the Embedded Web Server

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings.
- **3** From the Other Settings column, click **Manage Shortcuts** > **E-mail Shortcut Setup**.
- **4** Type a unique name for the e-mail recipient, and then type the e-mail address. If you are entering multiple addresses, then separate each address with a comma.
- 5 Click Add.

Creating an e-mail shortcut using the control panel

1 From the home screen, navigate to:

MyShortcut > Create > E-mail

- **2** Type a unique shortcut name, and then touch **Done**.
- **3** Configure the e-mail settings, and then touch **Done**.
- **4** Touch **E-mail Shortcuts** on the home screen to verify the shortcut.

E-mailing a document

Sending an e-mail using the control panel

- **1** Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch E-mail, and then enter the information needed.
- **3** Configure and then save the output file type settings.
- 4 Touch Send It.

Sending an e-mail using a shortcut number

- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** Press #, and then enter the shortcut number using the keypad.
- 3 Touch Send It.

Sending an e-mail using the address book

- 1 Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:
 - E-mail > Recipient(s) > 2 > type the name of the recipient > Search
- **3** Select the recipient's name, and then touch **Done**.

Customizing e-mail settings

Changing the output file type

- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:
 - E-mail > Recipient(s) > type the e-mail address > Done > Send as
- **3** Select the file type you want to send.
 - Note: If you select Secure PDF, then you will be prompted to enter your password twice.
- 4 Touch > Send It

Canceling an e-mail

- When using the ADF, touch Cancel Job while Scanning appears.
- When using the scanner glass, touch Cancel Job while Scanning appears, or while Scan the Next Page / Finish the Job appears.

Understanding the e-mail options

Recipient(s)

This option lets you enter the recipient of your e-mail. You may enter multiple e-mail addresses.

Subject

This option lets you type a subject line for your e-mail.

Message

This option lets you type a message that will be sent with your scanned attachment.

File Name

This option lets you customize the attachment file name.

Original Size

This option lets you set the paper size of the documents you are going to e-mail. When Original Size is set to Mixed Sizes, you can scan an original document that contains mixed paper sizes (letter- and legal-size pages).

Resolution

This option lets you adjust the output quality of your e-mail. Increasing the image resolution increases the e-mail file size and the time needed to scan your original document. Decreasing the image resolution reduces the file size.

Content

This option lets you specify the content type and source of the original document.

Save As Shortcut

This option lets you save the current settings as a shortcut by assigning a shortcut name.

Note: Selecting this option automatically assigns the next available shortcut number.

Darkness

This option lets you adjust how light or dark your scanned documents are in relation to the original document.

Send As

This option lets you set the output type for the scan image.

Select one of the following:

- PDF—Use this to create a single file with multiple pages. This can be sent as a secured or compressed file.
- **TIFF**—Use this to create multiple files or a single file. If Multi-page TIFF is turned off in the Settings menu of the Embedded Web Server, then TIFF saves one page in each file. The file size is usually larger than an equivalent JPEG.
- JPEG—Use this to create and attach a separate file for each page of your original document.
- **XPS**—Use this to create a single XPS file with multiple pages.

Page Setup

This option lets you change the following settings:

• **Sides (Duplex)**—This specifies if the original document is printed on only one side or on both sides of the paper. This also identifies what needs to be scanned for inclusion in the e-mail.

- **Orientation**—This specifies the orientation of the original document, and then changes the Sides (Duplex) and Binding settings to match the orientation.
- Binding—This specifies if the original document is bound on the long-edge or short-edge side.

Scan Preview

This option lets you view the first page of the image before it is included in the e-mail. When the first page is scanned, the scanning is paused and a preview image appears.

Note: This option appears only when a working printer hard disk is installed.

Using the advanced options

Select from the following settings:

- Advanced Imaging—This adjusts the Background Removal, Color Balance, Color Dropout, Contrast, JPEG
 Quality, Mirror Image, Negative Image, Scan Edge to Edge, Shadow Detail, Sharpness, and Temperature
 settings before you e-mail the document.
- Custom Job—This combines multiple scanning jobs into a single job.

Note: This option appears only when a formatted, working printer hard disk is installed.

- **Edge Erase**—This removes smudges or marks around the edges of a document. You can choose to remove an equal area around all four sides of the paper, or pick a particular edge. Edge Erase will erase whatever is within the area selected, leaving nothing on that portion of the scan.
- Transmission Log—This prints the transmission log or transmission error log.

Faxing

Use the ADF for multiple-page or two-sided documents. Load the original document faceup. Use the scanner glass for single-page documents, book pages, small items (such as postcards or photos), transparencies, photo paper, or thin media (such as magazine clippings). Place the document facedown in the corner with the arrow.

Setting up the printer to fax



CAUTION—SHOCK HAZARD: Do not use the fax feature during a lightning storm. Do not set up this product or make any electrical or cabling connections, such as the fax feature, power cord, or telephone, during a lightning storm.

Notes:

- The following connection methods are applicable only in some countries or regions.
- During the initial printer setup, clear the fax function check box and any other function you plan to set up later, and then touch **Continue**.
- The indicator light may blink red if the fax function is enabled and not fully set up.

Warning—Potential Damage: Do not touch cables or the printer in the area shown while actively sending or receiving a fax.



Initial fax setup

Many countries and regions require outgoing faxes to contain the following information in a margin at the top or bottom of each transmitted page, or on the first page of the transmission: fax name (identification of the business, other entity, or individual sending the message) and fax number (telephone number of the sending fax machine, business, other entity, or individual). For more information, see <u>"Regulatory notices for telecommunication terminal equipment"</u> on page 343.

To enter your fax setup information, use the printer control panel, or use your browser to access the Embedded Web Server and then enter the Settings menu.

Note: If you do not have a TCP/IP environment, then you must use the printer control panel to enter your fax setup information.

Using the printer control panel for fax setup

When the printer is turned on for the first time, a series of start-up screens appear. If the printer has fax capabilities, then the Fax Name and Fax Number screens appear.

- **1** When the Fax Name screen appears, do the following:
 - a Enter the name to be printed on all outgoing faxes.
 - **b** Enter the fax name, and then touch **Submit**.
- 2 When the Fax Number screen appears, enter the fax number, and then touch Submit.

Using the Embedded Web Server for fax setup

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Fax Settings > Analog Fax Setup.
- 3 In the Fax Name field, type the name to be printed on all outgoing faxes.
- **4** In the Fax Number field, enter the printer fax number.
- 5 Click Submit.

Choosing a fax connection

Setting up fax using a standard telephone line




CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.



CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.

CAUTION—POTENTIAL INJURY: To reduce the risk of fire, use only a 26 AWG or larger telecommunications (RJ-11) cord when connecting this product to the public switched telephone network. For users in Australia, the cord must be approved by the Australian Communications and Media Authority.

Setup 1: Printer is connected to a dedicated fax line



- **1** Connect one end of the telephone cable to the line port of the printer.
- **2** Connect the other end of the cable to an active analog wall jack.


Notes:

- You can set the printer to receive faxes automatically (Auto Answer On) or manually (Auto Answer Off).
- If you want to receive faxes automatically, then set the printer to pick up on a specified number of rings.

Setup 2: Printer is sharing the line with an answering machine


Note: If you subscribe to a distinctive ring service, then make sure that you set the correct ring pattern for the printer. Otherwise, the printer does not receive faxes even if you have set it to receive faxes automatically.

Connected to the same telephone wall jack



- **1** Connect one end of the telephone cable to the line port of the printer.
- **2** Connect the other end of the cable to an active analog wall jack.
- **3** Connect the answering machine to the telephone port of the printer.

Connected to different wall jacks




- **1** Connect one end of the telephone cable to the line port of the printer.
- **2** Connect the other end of the cable to an active analog wall jack.

Notes:

- If you have only one telephone number on your line, then set the printer to receive faxes automatically.
- Set the printer to pick up calls two rings after the answering machine. For example, if the answering machine picks up calls after four rings, then set the printer Rings to Answer setting to six.

Setup 3: Printer is sharing the line with a telephone subscribed to voice mail service



- **1** Connect one end of the telephone cable to the line port of the printer.
- **2** Connect the other end of the cable to an active analog wall jack.
- **3** Connect the telephone to the telephone port of the printer.

Notes:

- This setup works best if you are using voice mail more often than fax, and if you subscribe to a distinctive ring service.
- When you answer the telephone and you hear fax tones, press *9* or the manual answer code on the telephone to receive the fax.
- You can also set the printer to receive faxes automatically, but turn off the voice mail service when you are expecting a fax.

Setting up fax using digital subscriber line




CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.



CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.



CAUTION—POTENTIAL INJURY: To reduce the risk of fire, use only a 26 AWG or larger telecommunications (RJ-11) cord when connecting this product to the public switched telephone network. For users in Australia, the cord must be approved by the Australian Communications and Media Authority.



Digital subscriber line (DSL) splits your regular telephone line into two channels: voice and Internet. Telephone and fax signals travel through the voice channel, and Internet signals pass through the other channel.

To minimize interference between the two channels, ask for a DSL filter from your DSL provider.

- **1** Connect the line port of the DSL filter to the wall jack.
- **2** Connect one end of the telephone cable to the line port of the printer.
- **3** Connect the other end of the cable to the telephone port on the DSL filter.

Note: To connect a telephone to the printer, remove any installed adapter plug from the telephone port of the printer, and then connect the telephone.

Setting up fax using VoIP telephone service




CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.



CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.



CAUTION—POTENTIAL INJURY: To reduce the risk of fire, use only a 26 AWG or larger telecommunications (RJ-11) cord when connecting this product to the public switched telephone network. For users in Australia, the cord must be approved by the Australian Communications and Media Authority.



- **1** Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the cable to the port labeled **Phone Line 1** or **Phone Port** on the VoIP adapter.

Note: The port labeled **Phone Line 2** or **Fax Port** is not always active. VoIP providers may charge extra cost for the activation of the second telephone port.

3 Connect the telephone to the telephone port of the printer.

Notes:

- To check if the telephone port on the VoIP adapter is active, plug an analog telephone into the port, and then listen for a dial tone.
- If you need two telephone ports for your devices, but do not want to pay extra cost, then use a phone splitter. Plug the phone splitter into the port labeled **Phone Line 1** or **Phone Port**, and then plug the printer and telephone into the splitter.
- To check the splitter, plug an analog telephone into the splitter, and then listen for a dial tone.

Setting up fax using cable modem connection



CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.




CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.



CAUTION—POTENTIAL INJURY: To reduce the risk of fire, use only a 26 AWG or larger telecommunications (RJ-11) cord when connecting this product to the public switched telephone network. For users in Australia, the cord must be approved by the Australian Communications and Media Authority.


Setup 1: Printer is connected directly to a cable modem



- **1** Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the cable to the port labeled **Phone Line 1** or **Phone Port** on the cable modem.
- **3** Connect your analog telephone to the telephone port of the printer.

Note: To check if the telephone port on the cable modem is active, connect an analog telephone, and then listen for a dial tone.

Setup 2: Printer is connected to a wall jack; cable modem is installed elsewhere in the facility



- **1** Connect one end of the telephone cable to the line port of the printer.
- **2** Connect the other end of the cable to an active analog telephone wall jack.
- **3** Connect your analog telephone to the telephone port of the printer.

Setting up fax in countries or regions with different telephone wall jacks and plugs



CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.




CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.



CAUTION—POTENTIAL INJURY: To reduce the risk of fire, use only a 26 AWG or larger telecommunications (RJ-11) cord when connecting this product to the public switched telephone network. For users in Australia, the cord must be approved by the Australian Communications and Media Authority.


The standard wall jack adopted by most countries or regions is RJ11. If the wall jack or equipment in your facility is not compatible with this type of connection, then use a telephone adapter. An adapter for your country or region may not come with your printer, and you may need to purchase it separately.

There may be an adapter plug installed in the telephone port of the printer. Do not remove the adapter plug from the telephone port of the printer if you are connecting to a serial or cascaded telephone system.



Part name	Part number
Lexmark adapter plug	40X8519


Connecting the printer to a non-RJ11 wall jack



- **1** Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the cable to the RJ11 adapter, and then connect the adapter to the wall jack.
- **3** If you want to connect another device with a non-RJ11 connector to the same wall jack, then connect it directly to the telephone adapter.

Connecting the printer to a wall jack in Germany

The German wall jack has two kinds of ports. The N ports are for fax machines, modems, and answering machines. The F port is for telephones. Connect the printer to any of the N ports.




- **1** Connect one end of the telephone cable to the line port of the printer.
- **2** Connect the other end of the cable to the RJ11 adapter, and then connect the adapter to an N port.
- **3** If you want to connect a telephone and answering machine to the same wall jack, then connect the devices as shown.

Connecting to a distinctive ring service

A distinctive ring service may be available from your telephone company. This service lets you have multiple telephone numbers on one telephone line, with each telephone number having a different ring pattern. This may be useful for distinguishing between fax and voice calls. If you subscribe to a distinctive ring service, then follow these steps to connect the equipment:

- 1 Connect one end of the telephone cable that came with the printer to the printer LINE port |
- 2 Connect the other end of the telephone cable to an active analog telephone wall jack.



3 Change the distinctive rings setting to match the setting you want for the printer to answer.

Note: The factory default setting for distinctive rings is On. This sets the printer to answer single, double, and triple ring patterns.

- **a** From the home screen, navigate to:
 - > Settings > Fax Settings > Analog Fax Setup > Answer On
- **b** Select the pattern setting you want to change, and then touch **Submit**.

Setting the outgoing fax name and number

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Fax Settings > Analog Fax Setup.
- **3** In the Fax Name field, type the name to be printed on all outgoing faxes.
- 4 In the Fax Number field, enter the printer fax number.
- 5 Click Submit.

Setting the date and time

You can set the date and time so that they are printed on every fax you send.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

 View the IP address on the home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Security > Set Date and Time.
- **3** In the Manually Set Date & Time field, enter the current date and time.

Note: The use of network time is recommended.

4 Click Submit.

Configuring the printer to observe daylight saving time

The printer can be set to automatically adjust for daylight saving time.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Security > Set Date and Time.
- **3** Click the **Automatically Observe DST** check box.
- **4** In the Custom Time Zone Setup section, set the DST start and end dates.
- 5 Click Submit.

Sending a fax

Using the control panel

- 1 Load the original document into the ADF tray or on the scanner glass.
- **2** From the home screen, touch **Fax**, and then enter the needed information.
- **3** If necessary, configure other fax settings.
- **4** Send the fax job.

Using the computer

For Windows users

- 1 With a document open, click File > Print.
- 2 Select the printer, and then click Properties, Preferences, Options, or Setup.
- **3** Click **Fax** > **Enable fax**, and then enter the recipient number.

- 4 If necessary, configure other fax settings.
- **5** Send the fax job.

For Macintosh users

- 1 With a document open, choose File > Print.
- **2** Select the printer and enter the recipient number.
- **3** If necessary, configure other fax settings.
- **4** Send the fax job.

Sending a fax at a scheduled time

1 Load an original document faceup, short edge first into the ADF tray or facedown on the scanner glass.

Notes:

- Do not load postcards, photos, small items, transparencies, photo paper, or thin media (such as magazine clippings) into the ADF tray. Place these items on the scanner glass.
- The ADF indicator light comes on when the paper is loaded properly.
- 2 If you are loading a document into the ADF tray, then adjust the paper guides.
- **3** From the home screen, navigate to:

Fax > enter the fax number > Options > Delayed Send

Note: If Fax Mode is set to Fax Server, then the Delayed Send button does not appear. Faxes waiting for transmission are listed in the fax queue.

4 Specify the time the fax will be transmitted, and then touch



5 Touch Fax It.

Note: The document is scanned, and then faxed at the scheduled time.

Creating shortcuts

Notes:

- Make sure that Fax Shortcuts is set to Display. From the home screen, touch => Settings > General Settings > Home screen customization > Fax Shortcuts > Display > Submit.
- To delete a fax shortcut, touch | > Manage Shortcuts > Fax Shortcuts > the shortcut to delete > Delete now.

Creating a fax destination shortcut using the Embedded Web Server

Assign a shortcut number to a single fax number or a group of fax numbers.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

 View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Manage Shortcuts > Fax Shortcut Setup.

Note: A password may be required. If you do not have an ID and password, then contact your system support person.

3 Type a name for the shortcut, and then enter the fax number.

Notes:

- To create a multiple-number shortcut, enter the fax numbers for the group.
- Separate each fax number in the group with a semicolon (;).
- 4 Assign a shortcut number.

Note: If you enter a number that is already in use, then you are prompted to select another number.

5 Click Add.

Creating a fax destination shortcut using the printer control panel

1 From the home screen, touch Fax, and then enter the fax number.

Note: To create a group of fax numbers, touch Next number, and then enter the next fax number.

- 2 Touch
- **3** Type a unique name for the shortcut, and then touch **Done**.
- **4** Verify that the shortcut name and number are correct, and then touch **OK**.

Note: If the name or number is incorrect, then touch Cancel, and then reenter the information.

Customizing fax settings

Changing the fax resolution

1 Load an original document faceup, short edge first into the ADF tray or facedown on the scanner glass.

Notes:

- Do not load postcards, photos, small items, transparencies, photo paper, or thin media (such as magazine clippings) into the ADF tray. Place these items on the scanner glass.
- The ADF indicator light comes on when the paper is loaded properly.
- 2 If you are loading a document into the ADF tray, then adjust the paper guides.
- **3** From the home screen, navigate to:

Fax > enter the fax number > Options

4 From the Resolution area, touch the arrows to select the resolution you want.

Note: Select a resolution from Standard (fastest speed) to Ultra Fine (best quality at a reduced speed).

5 Touch Fax It.

Making a fax lighter or darker

1 Load an original document faceup, short edge first into the ADF tray or facedown on the scanner glass.

Notes:

- Do not load postcards, photos, small items, transparencies, photo paper, or thin media (such as magazine clippings) into the ADF tray. Place these items on the scanner glass.
- The ADF indicator light comes on when the paper is loaded properly.
- 2 If you are loading a document into the ADF tray, then adjust the paper guides.
- **3** From the home screen, navigate to:
 - Fax > enter the fax number > Options
- 4 Adjust the fax darkness, and then touch Fax It.

Viewing a fax log

1 Type the printer IP address into the address field of your Web browser.

Note: If you do not know the IP address of the printer, then print a network setup page and locate the IP address in the TCP/IP section.

- 2 Click Reports.
- 3 Click Fax Job Log or Fax Call Log.

Blocking junk faxes

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Fax Settings > Analog Fax Setup > Block No Name Fax.

Notes:

- This option blocks all incoming faxes that have a private caller ID or have no fax name.
- In the Banned Fax List field, enter the phone numbers or type the fax names of specific fax callers you want to block.

Canceling a fax job

1 From the control panel, touch **Cancel Job** or press **a** on the keypad.

2 Touch the job you want to cancel, and then touch **Delete Selected Jobs**.

Note: If you press on the keypad, then touch **Resume** to return to the home screen.

Holding and forwarding faxes

Holding faxes

This option lets you hold received faxes from printing until they are released. Held faxes can be released manually or at a scheduled day or time.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Fax Settings > Analog Fax Setup > Holding Faxes.
- **3** From the Held Fax Mode menu, select one of the following:
 - Off
 - Always On
 - Manual
 - Scheduled
- **4** If you selected Scheduled, then continue with the following steps:
 - a Click Fax Holding Schedule.
 - **b** From the Action menu, select **Hold faxes**.
 - **c** From the Time menu, select the time you want the held faxes released.
 - **d** From the Day(s) menu, select the day you want the held faxes released.
- 5 Click Add.

Forwarding a fax

This option lets you print and forward received faxes to a fax number, e-mail address, FTP site, or LDSS.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

• View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

Faxing 109

- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > Fax Settings.
- **3** From the Fax Forwarding menu, select **Print**, **Print and Forward**, or **Forward**.
- 4 From the "Forward to" menu, select Fax, E-mail, FTP, LDSS, or eSF.
- **5** In the "Forward to Shortcut" field, enter the shortcut number where you want the fax forwarded.

Note: The shortcut number must be valid for the setting selected in the "Forward to" menu.

6 Click Submit.

Understanding the fax options

Resolution

This option lets you adjust the quality of the fax output. Increasing the image resolution increases the file size and the time needed to scan your original document. Decreasing the image resolution reduces the file size.

Select one of the following:

- **Standard**—Use this when faxing most documents.
- Fine 200 dpi—Use this when faxing documents with small prints.
- **Super fine 300 dpi**—Use this when faxing documents with fine details.
- Ultra fine 600 dpi—Use this when faxing documents with pictures or photos.

Darkness

This option lets you adjust how light or dark the faxes are in relation to the original document.

Page Setup

This option lets you change the following settings:

- **Sides (Duplex)**—This specifies if the original document is printed on one side or on both sides of the page (duplex). This also identifies what needs to be scanned for inclusion in the fax.
- **Orientation**—This specifies the orientation of the original document, and then changes the Sides (Duplex) and Binding settings to match the orientation.
- Binding—This specifies if the original document is bound on the long-edge or short-edge side.

Content

This option lets you specify the content type and source of the original document.

Delayed Send

This option lets you send a fax at a later time or date.

Faxing 110

Color

This option lets you set the output to either color or monochrome for the scanned image.

Scan Preview

This option lets you view the first page of the image before it is included in the fax. When the first page is scanned, the scanning is paused and a preview image appears.

Note: This option appears only when a working printer hard disk is installed.

Using the advanced options

Select from the following settings:

- Advanced Imaging—This adjusts the Background Removal, Color Balance, Color Dropout, Contrast, Mirror Image, Negative Image, Scan Edge to Edge, Shadow Detail, Sharpness, and Temperature settings before you fax the document.
- Custom Job—This combines multiple scanning jobs into a single job.

Note: This option appears only when a formatted, working printer hard disk is installed.


- **Edge Erase**—This removes smudges or marks around the edges of a document. You can choose to remove an equal area around all four sides of the paper, or pick a particular edge. Edge Erase erases whatever is within the area selected, leaving nothing on that portion of the scan.
- Transmission Log—This prints the transmission log or transmission error log.

Scanning

Using Scan to Network

Scan to Network lets you scan your documents to network destinations specified by your system support person. After the destinations (shared network folders) have been established on the network, the setup process for the application involves installing and configuring the application on the appropriate printer using its Embedded Web Server. For more information, see <u>"Setting up Scan to Network" on page 25</u>.

Scanning to an FTP address



Creating shortcuts

Notes:

- Make sure that FTP Shortcuts is set to Display. From the home screen, touch
 Settings > General
 Settings > Home screen customization > FTP Shortcuts > Display > Submit.
- To delete an FTP shortcut, touch > Manage Shortcuts > FTP Shortcuts > the shortcut to delete > Delete now.

Creating an FTP shortcut using the Embedded Web Server

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

 View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.

- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Navigate to:

Settings > Other Settings area > Manage Shortcuts > FTP Shortcut Setup

3 Enter the appropriate information.

Note: A password may be required. If you do not have an ID and password, then contact your system support person.

4 Enter a shortcut number.

Note: If you enter a number that is already in use, then you are prompted to select another number.

5 Click Add.

Creating an FTP shortcut using the printer control panel

1 From the home screen, navigate to:

FTP > FTP > type the FTP address > > type a name for the shortcut > Done

2 Verify that the shortcut name and number are correct, and then touch **OK**.

Notes:

- If the name or number is incorrect, then touch Cancel, and then reenter the information.
- If you enter a number that is already in use, then you are prompted to select another number.

Scanning to an FTP address

Scanning to an FTP address using the control panel

- **1** Load an original document into the ADF tray or on the scanner glass.
- **2** From the home screen, navigate to:

FTP > FTP > type the FTP address > Done > Send It

Notes:

- You can also enter the recipient using the shortcut number or address book.
- To add recipients, touch Next Number.

Scanning to a computer or flash drive

Use the ADF for multiple-page or two-sided documents. Load the original document faceup. Use the scanner glass for single-page documents, book pages, small items (such as postcards or photos), transparencies, photo paper, or thin media (such as magazine clippings). Place the document facedown in the corner with the arrow.

Setting up Scan to Computer

Notes:

- This feature is supported only in Windows Vista or later.
- Make sure your computer and printer are connected to the same network.
- **1** Open the printers folder, and then select your printer.

Note: If your printer is not in the list, then add your printer.

- **2** Open the printer properties, and then adjust the settings as necessary.
- 3 From the control panel, touch Scan to Computer > select the appropriate scan setting > Send It.

Scanning to a flash drive

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 Insert the flash drive into the USB port.
- **3** Select the destination folder, and then touch **Scan to USB drive**.
- 4 Adjust the scan settings, and then touch Scan It.

Understanding the scan options

FTP

This option lets you enter the IP address for the FTP destination.

Note: An IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.

File Name

This option lets you type a file name for the scan image.

Save As Shortcut

This option lets you save the current settings as a shortcut by assigning a shortcut name.

Note: Selecting this option automatically assigns the next available shortcut number.

Original Size

This option lets you set the paper size of the documents you are going to scan. When Original Size is set to Mixed Sizes, you can scan an original document that contains mixed paper sizes (letter- and legal-size pages).

Darkness

This option lets you adjust how light or dark the scanned documents are in relation to the original document.

Resolution

This option lets you adjust the output quality of your file. Increasing the image resolution increases the file size and the time needed to scan your original document. Decreasing the image resolution reduces the file size.

Send As

This option lets you set the output type for the scan image.

Select one of the following:

- PDF—Use to create a single file with multiple pages. The PDF can be sent as a secured or compressed file.
- **TIFF**—Use to create multiple files or a single file. If Multi-page TIFF is turned off in the Settings menu, then TIFF saves one page in each file. The file size is usually larger than an equivalent JPEG.
- JPEG—Use to create and attach a separate file for each page of the original document.
- **XPS**—Use to create a single XPS file with multiple pages.

Content

This option lets you specify the content type and source of the original document.

Page Setup

This option lets you change the following settings:

• **Sides (Duplex)**—This specifies if the original document is printed on only one side or on both sides of the paper.

- **Orientation**—This specifies the orientation of the original document, and then changes the Sides (Duplex) and Binding settings to match the orientation.
- Binding—This specifies if the original document is bound on the long-edge or short-edge side.

Scan Preview

This option lets you view the first page of the image before it is included in the file. When the first page is scanned, the scanning is paused and a preview image appears.

Note: This option appears only when a formatted, working printer hard disk is installed.

Using the advanced options

Select from the following settings:

- Advanced Imaging—This adjusts the Background Removal, Color Balance, Color Dropout, Contrast, JPEG
 Quality, Mirror Image, Negative Image, Scan Edge to Edge, Shadow Detail, Sharpness, and Temperature
 settings before you scan the document.
- Custom Job—This combines multiple scanning jobs into a single job.

Note: This option appears only when a formatted, working printer hard disk is installed.

- **Edge Erase**—This removes smudges or marks around the edges of a document. You can choose to remove an equal area around all four sides of the paper, or pick a particular edge. Edge Erase erases whatever is within the area selected, leaving nothing on that portion of the scan.
- Transmission Log—This prints the transmission log or transmission error log.

Understanding the printer menus

Menus list

Paper Menu	Reports	Network/Ports	Security
Default Source	Menu Settings Page	Active NIC	Edit Security Setups
Paper Size/Type	Device Statistics	Standard Network ¹	Miscellaneous Security Settings
Configure MP	Stapler Test	Standard USB	Confidential Print
Substitute Size	Network Setup Page	Parallel [x]	Erase Temporary Data Files
Paper Texture	Network [x] Setup Page	Serial [x]	Security Audit Log
Paper Loading	Shortcut List	SMTP Setup	Set Date and Time
Custom Types	Fax Job Log		
Custom Names	Fax Call Log		
Custom Scan Sizes	Copy Shortcuts		
Custom Bin Names	E-mail Shortcuts		
Universal Setup	Fax Shortcuts		
Bin Setup	FTP Shortcuts		
	Profiles List		
	Print Fonts		
	Print Directory		
	Print Demo		
	Asset Report		
	Event Log Summary		
Settings	Help	Manage Shortcuts	Option Card Menu ²
General Settings	Print All Guides	Fax Shortcuts	A list of installed DLEs (Download
Copy Settings	Copy Guide	E-mail Shortcuts	Emulators) appears.
Fax Settings	E-mail Guide	FTP Shortcuts	
E-mail Settings	Fax Guide	Copy Shortcuts	
FTP Settings	FTP Guide	Profile Shortcuts	
Flash Drive Menu	Print Defects Guide		
Print Settings	Information Guide		
	Supplies Guide		

¹ Depending on the printer setup, this menu appears as Standard Network or Network [x].

 $^{^{\}rm 2}$ This menu appears only when one or more DLEs are installed.

Paper menu

Default Source menu

Use	То
Default Source Tray [x] Multipurpose Feeder Manual Paper Manual Envelope	Set a default paper source for all print jobs. Notes: Tray 1 (standard tray) is the factory default setting. From the Paper menu, set Configure MP to "Cassette" for Multipurpose Feeder to appear as a menu setting. If two trays contain paper of the same size and type, and the trays have the same settings, then the trays are automatically linked.
	When one tray is empty, the print job continues using the linked tray.

Paper Size/Type menu

Use	То
Tray [x] Size	Specify the paper size loaded in each tray.
A4	Notes:
A5	
A6	 Letter is the U.S. factory default setting. A4 is the international factory default setting.
JIS-B5	
JIS-B4	 If two trays contain paper of the same size and type, and the trays have the same settings, then the trays are automatically linked. The
Letter	multipurpose feeder may also be linked. When one tray is empty,
Legal	the print job continues using the linked tray.
12 x 18	
11 x 17	
SRA3	
A3	
Executive	
Oficio (Mexico)	
Folio	
Statement	
Universal	

Note: Only installed trays and feeders are listed in this menu.

Use	То
Tray [x] Type Plain Paper Card Stock Transparency Recycled Glossy Heavy Glossy Labels Bond Envelope Rough Envelope Letterhead Preprinted Colored Paper Light Paper Heavy Paper Rough/Cotton Custom Type [x]	 Specify the type of paper loaded in each tray. Notes: Plain Paper is the factory default setting for Tray 1. Custom Type [x] is the factory default setting for all other trays. If available, a user-defined name appears instead of Custom Type [x]. Use this menu to configure automatic tray linking.
MP Feeder Size	Specify the paper size loaded in the multipurpose feeder.
A4 A5 A6 JIS-B5 JIS-B4 Letter Legal 12 x 18 11 x 17 SRA3 A3 Executive Oficio (Mexico) Folio Statement Universal	 Notes: Letter is the U.S. factory default setting. A4 is the international factory default setting. From the Paper menu, set Configure MP to "Cassette" for MP Feeder Size to appear as a menu. The multipurpose feeder does not automatically detect paper size. The paper size value must be set.

Note: Only installed trays and feeders are listed in this menu.

Use	То
MP Feeder Type	Specify the paper type loaded in the multipurpose feeder.
Plain Paper	Notes:
Card Stock	
Transparency	Plain Paper is the factory default setting.
Recycled	• From the Paper menu, set Configure to "Cassette" for MP Feeder
Glossy	Type to appear as a menu.
Heavy Glossy	
Labels	
Bond	
Envelope	
Rough Envelope	
Letterhead	
Preprinted	
Colored Paper	
Light Paper	
Heavy Paper	
Rough/Cotton	
Custom Type [x]	
Manual Paper Size	Specify the size of the paper being manually loaded.
A4	Note: Letter is the U.S. factory default setting. A4 is the international
A5	factory default setting.
A6	
JIS B5	
Letter	
Legal	
Executive	
Oficio (Mexico)	
JIS B4	
A3	
11 × 17	
Folio	
Statement	
Universal	
SRA3	
12 x 18	

Note: Only installed trays and feeders are listed in this menu.

Use	То
Manual Paper Type Plain Paper Card Stock Transparency Recycled Labels Bond Letterhead Preprinted Colored Paper Light Paper Heavy Paper Rough/Cotton Custom Type [x]	Specify the paper type being manually loaded. Notes: Plain Paper is the factory default setting. From the Paper menu, set Configure MP to "Manual" for Manual Paper Type to appear as a menu.
Manual Envelope Size 7 3/4 Envelope 9 Envelope 10 Envelope DL Envelope C5 Envelope B5 Envelope Other Envelope	Specify the envelope size being manually loaded. Note: 10 Envelope is the U.S. factory default setting. DL Envelope is the international factory default setting.
Manual Envelope Type Envelope Rough Envelope Custom Type [x] Note: Only installed trays and feeders ar	Specify the envelope type being manually loaded. Note: Envelope is the factory default setting.

Configure MP menu

Use	То
Configure MP	Determine when the printer selects paper from the multipurpose feeder.
Cassette	Notes:
Manual	Cassette is the factory default setting. Cassette configures the
First	multipurpose feeder as the automatic paper source.
	Manual sets the multipurpose feeder only for manual-feed print jobs.
	 First configures the multipurpose feeder as the primary paper source.

Substitute Size menu

Use	То
Substitute Size Off	Substitute a specified paper size if the requested paper size is not available.
Statement/A5 Letter/A4 11 x 17/A3	Notes: • All Listed is the factory default setting. All available substitutions
allowed.	Setting a size substitution lets the print job continue without Change

Paper Texture menu

Use	То
Plain Texture Smooth Normal Rough	Specify the relative texture of the plain paper loaded. Note: Normal is the factory default setting.
Card Stock Texture Smooth Normal Rough	Specify the relative texture of the card stock loaded. Notes: Normal is the factory default setting. The options appear only if card stock is supported.
Transparency Texture Smooth Normal Rough	Specify the relative texture of the transparencies loaded. Note: Normal is the factory default setting.
Recycled Texture Smooth Normal Rough	Specify the relative texture of the recycled paper loaded. Note: Normal is the factory default setting.
Labels Texture Smooth Normal Rough	Specify the relative texture of the labels loaded. Note: Normal is the factory default setting.
Bond Texture Smooth Normal Rough	Specify the relative texture of the bond paper loaded. Note: Rough is the factory default setting.
Envelope Texture Smooth Normal Rough	Specify the relative texture of the envelopes loaded. Note: Normal is the factory default setting.

Use	То
Rough Envelope Texture Rough	Specify the relative texture of the rough envelopes loaded.
Letterhead Texture Smooth Normal Rough	Specify the relative texture of the letterhead loaded. Note: Normal is the factory default setting.
Preprinted Texture Smooth Normal Rough	Specify the relative texture of the preprinted paper loaded. Note: Normal is the factory default setting.
Colored Texture Smooth Normal Rough	Specify the relative texture of the colored paper loaded. Note: Normal is the factory default setting.
Light Texture Smooth Normal Rough	Specify the relative texture of the paper loaded. Note: Normal is the factory default setting.
Heavy Texture Smooth Normal Rough	Specify the relative texture of the paper loaded. Note: Normal is the factory default setting.
Rough/Cotton Texture Rough	Specify the relative texture of the cotton paper loaded.
Custom [x] Texture Smooth Normal Rough	Specify the relative texture of the custom paper loaded. Notes: Normal is the factory default setting. The options appear only if the custom type is supported.

Paper Loading menu

Use	То
Card Stock Loading Duplex Off	Determine and set two-sided printing for all print jobs with Card Stock as the paper type.

Notes:

- Off is the factory default setting for all Paper Loading menu selections.
- Duplex sets the printer default to two-sided printing for every print job unless one-sided printing is selected from Print Properties or the print dialog, depending on your operating system.

Use	То
Recycled Loading Duplex Off	Determine and set two-sided printing for all print jobs with Recycled as the paper type.
Glossy Loading Duplex Off	Determine and set two-sided printing for all print jobs with Glossy as the paper type.
Heavy Glossy Loading Duplex Off	Determine and set two-sided printing for all print jobs with Heavy Glossy as the paper type.
Labels Loading Duplex Off	Determine and set two-sided printing for all print jobs with Labels as the paper type.
Bond Loading Duplex Off	Determine and set two-sided printing for all print jobs with Bond as the paper type.
Letterhead Loading Duplex Off	Determine and set two-sided printing for all print jobs with Letterhead as the paper type.
Preprinted Loading Duplex Off	Determine and set two-sided printing for all print jobs with Preprinted as the paper type.
Colored Loading Duplex Off	Determine and set two-sided printing for all print jobs with Colored as the paper type.
Light Loading Duplex Off	Determine and set two-sided printing for all print jobs with Light as the paper type.
Heavy Loading Duplex Off	Determine and set two-sided printing for all print jobs with Heavy as the paper type.
Rough/Cotton Loading Duplex Off	Determine and set two-sided printing for all print jobs with Rough or Cotton as the paper type.
Custom [x] Loading Duplex Off	Determine and set two-sided printing for all print jobs with Custom [x] as the paper type. Note: Custom [x] Loading is available only when the custom
	type is supported.

Notes:

- Off is the factory default setting for all Paper Loading menu selections.
- Duplex sets the printer default to two-sided printing for every print job unless one-sided printing is selected from Print Properties or the print dialog, depending on your operating system.

Custom Types menu

Use	То
Custom Type [x] Paper Card Stock	Associate a paper or specialty media type with a factory default custom type name or a user-defined custom name created from the Embedded Web Server or from MarkVision TM Professional.
Transparency Rough/Cotton Labels Envelope	 Notes: Paper is the factory default setting. The custom media type must be supported by the selected tray or multipurpose feeder in order to print from that source.
Recycled Paper Card Stock Transparency Rough/Cotton Labels Envelope	 Specify a paper type when Recycled is selected in other menus. Notes: Paper is the factory default setting. The custom media type must be supported by the selected tray or multipurpose feeder in order to print from that source.

Custom Names menu

Use	То
Custom Name [x]	Specify a custom name for a paper type. This name replaces Custom Type [x] in the printer menus.

Custom Scan Sizes menu

Use	То
Custom Scan Size [x]	Specify a custom scan size name, scan sizes, and options. The custom
Scan Size Name	scan size name replaces Custom Scan Size [x] in the printer menus.
Width	
1–11.69 inches (25–297 mm)	
Height	
1–17 inches (22–432 mm)	
Orientation	
Portrait	
Landscape	
2 scans per side	
Off	
On	

Custom Bin Names menu

Use	То
Standard Bin	Specify a custom name for the standard bin.

Use	То
Bin [x]	Specify a custom name for Bin [x].

Universal Setup menu

Use	То
Units of Measure	Identify the units of measure.
Inches	Notes:
Millimeters	Inches is the U.S. factory default setting.
	Millimeters is the international factory default setting.
Portrait Width	Set the portrait width.
3.54–48 inches	Notes:
89.9–1219 mm	 If the width exceeds the maximum, then the printer uses the maximum width allowed.
	• 12 inches is the U.S. factory default setting. You can increase the width in 0.01-inch increments.
	 305 mm is the international factory default setting. You can increase the width in 1-mm increments.
Portrait Height	Set the portrait height.
5.5–48 inches	Notes:
139.7–1219 mm	 If the height exceeds the maximum, then the printer uses the maximum height allowed.
	• 17 inches is the U.S. factory default setting. You can increase the height in 0.01-inch increments.
	 432 mm is the international factory default setting. You can increase the height in 1-mm increments.
Feed Direction Short Edge	Specify the feed direction if the paper can be loaded in either direction.
Long Edge	Notes:
	Short Edge is the factory default setting.
	Long Edge appears only when the longest edge is shorter than the maximum width supported in the tray.

Bin Setup menu

Use	То
Output Bin	Specify the default bin.
Standard Bin	Note: Standard Bin is the factory default setting.
Bin [x]*	,
*5.7	

^{* [}x] can be any number from 1 to 4 if the appropriate optional bins are installed. If multiple bins are assigned the same name, then the name appears only once in the bin list.

Use	То
Configure Bins	Specify configuration options for bins.
Mailbox	Notes:
Link Link Optional Type Assignment	Mailbox is the factory default setting. This treats each bin as a separate mailbox.
Type Assignment	Link configures all available bins as one large bin.
	 Link Optional links together all available bins except the standard bin and only appears when at least two optional bins are installed.
	 Type Assignment assigns each paper type to a bin or linked bin set.
Overflow Bin	Specify an alternative bin when a designated bin is full.
Standard Bin	Notes:
Bin [x]*	This menu appears only when optional bins are installed.
	Standard Bin is the factory default setting.
Assign Type/Bin	Select a bin for each supported paper type.
Plain Paper Bin	For each type, select from the following options:
Card Stock Bin	Disabled
Transparency Bin	Standard Bin
Recycled Bin	Bin [x]*
Glossy Bin	Note: Disabled is the factory default setting.
Heavy Glossy Bin	
Labels Bin	
Bond Bin	
Envelope Bin	
Rough Envelope Bin	
Letterhead Bin	
Preprinted Bin	
Colored Bin	
Light Paper Bin	
Heavy Paper Bin	
Rough/Cotton Bin	
Custom [x] Bin	

^{*} [x] can be any number from 1 to 4 if the appropriate optional bins are installed. If multiple bins are assigned the same name, then the name appears only once in the bin list.

Reports menu

Reports menu

Use	То
Menu Settings Page	Print a report containing information about the paper loaded in trays, installed memory, total page count, alarm settings, timeouts, control panel language, TCP/IP address, status of supplies, status of the network connection, and other information.
Device Statistics	Print a report containing printer statistics such as supply information and number of printed pages.
Stapler Test	Print a report that confirms that the staple finisher is functioning properly.
	Note: This menu item appears only when a supported staple finisher is installed.
Network Setup Page	Print a report containing information about the network printer settings, such as the TCP/IP address information.
	Note: This menu item appears only in network printers or printers connected to print servers.
Network [x] Setup Page	Print a report containing information about the network printer settings, such as the TCP/IP address information.
	Note: This menu item appears only in network printers or in printers connected to print servers, and when there is more than one network option installed.
Shortcut List	Print a report containing information about configured shortcuts.
Fax Job Log	Print a report containing information about the last 200 completed faxes.
	Note: This menu item appears only when Enable Job Log in the Fax Settings menu is set to On.
Fax Call Log	Print a report containing information about the last 100 attempted, received, and blocked calls.
	Note: This menu item appears only when Enable Job Log in the Fax Settings menu is set to On.
Copy Shortcuts	Print a report containing information about copy shortcuts.
E-mail Shortcuts	Print a report containing information about e-mail shortcuts.
Fax Shortcuts	Print a report containing information about fax shortcuts.
FTP Shortcuts	Print a report containing information about FTP shortcuts.
Profiles List	Print a list of profiles stored in the printer.
Print Fonts	Print a report of all the fonts available for the printer language currently set in the printer.

Use	То
Print Directory	Print a list of all the resources stored in an optional flash memory card or printer hard disk.
	Notes:
	Job Buffer Size must be set to 100%.
	 Make sure that the flash memory or hard disk is working and installed correctly.
Asset Report	Print a report containing asset information including the printer serial number and model name.

Network/Ports menu

Active NIC menu

Use	То
Active NIC	Allow the printer to connect to a network.
Auto [list of available network cards]	Notes:
[list of available fietwork edias]	Auto is the factory default setting.
	This menu item appears only if an optional network adapter is installed.

Standard Network or Network [x] menu

Note: Only active ports appear in this menu.

Use	То
Energy Efficient Ethernet Enable	Reduce power consumption when the printer receives no data from the Ethernet network.
Disable	Note: Enable is the factory default setting.
PCL SmartSwitch On	Set the printer to automatically switch to PCL emulation when a print job requires it, regardless of the default printer language.
Off	Notes:
	On is the factory default setting.
	If PCL SmartSwitch is disabled, then the printer does not examine incoming data and it uses the default printer language specified in the Setup menu.

Use	То
PS SmartSwitch On	Set the printer to automatically switch to PS emulation when a print job requires it, regardless of the default printer language.
Off	Notes:
	 On is the factory default setting. If PS SmartSwitch is disabled, then the printer does not examine incoming data and it uses the default printer language specified in the Setup menu.
NPA Mode Off	Set the printer to perform the special processing required for bidirectional communication following the conventions defined by the NPA protocol.
Auto	Notes:
	 Auto is the factory default setting. The printer automatically restarts when the setting is changed from the control panel.
Network Buffer	Set the size of the network input buffer.
Auto	Notes:
3KB to [maximum size allowed]	Auto is the factory default setting.
	The maximum size allowed depends on the amount of memory in the printer, the size of the other link buffers, and whether Resource Save is set to On or Off.
	To increase the maximum size range for the Network Buffer, disable or reduce the size of the parallel, serial, and USB buffers.
	The printer automatically restarts when the setting is changed from the control panel.
Job Buffering Off	Temporarily store print jobs in the printer hard disk before printing. This menu only appears when a formatted disk is installed.
On	Notes:
Auto	 Off is the factory default setting. The printer automatically restarts when the setting is changed from the control panel. The menu selection is then updated.
Mac Binary PS	Set the printer to process Macintosh binary PostScript print jobs.
On	Note: Auto is the factory default setting.
Off	
Auto	
Standard Network Setup OR Network [x] Setup	Show and set the printer network settings.
Reports	Note: The Wireless menu appears only when the printer is connected to a wireless network.
Network Card	Wile 1635 He Work.
TCP/IP	
IPv6	
Wireless	
AppleTalk	

Reports menu

To access the menu, navigate to either of the following:

- Network/Ports > Standard Network > Standard Network Setup > Reports
- Network/Ports > Network [x] > Network [x] Setup > Reports

Use	То
Print Setup Page	Print a report containing information about the network printer settings, such as the TCP/IP address.

Network Card menu

To access the menu, navigate to either of the following:

- Network/Ports > Standard Network > Standard Network Setup > Network Card
- Network/Ports > Network [x] > Network [x] Setup > Network Card

Use	То
View Card Status Connected Disconnected	View the connection status of the wireless network adapter.
View Card Speed	View the speed of an active wireless network adapter.
Network Address UAA LAA	View the network addresses.
Job Timeout 0, 10–225 seconds	Set the amount of time it takes for a network print job to be canceled. Notes:
	 "90 seconds" is the factory default setting. A setting value of 0 disables the timeout. If a value between 1 and 9 is selected, then Invalid appears on the display, and the value is not saved.
Banner Page Off On	Allow the printer to print a banner page. Note: Off is the factory default setting.

TCP/IP menu

To access the menu, navigate to either of the following:

- Network/Ports > Standard Network > Standard Network Setup > TCP/IP
- Network/Ports > Network [x] > Network [x] Setup > TCP/IP

Note: This menu is available only in network printers or printers attached to print servers.

Use	То
Set Hostname	Set the current TCP/IP host name.
	Note: This can be changed only from the Embedded Web Server.
IP Address	View or change the current TCP/IP address.
	Note: Manually setting the IP address sets the Enable DHCP and Enable Auto IP settings to Off. It also sets Enable BOOTP and Enable RARP to Off on systems that support BOOTP and RARP.
Netmask	View or change the current TCP/IP netmask.
Gateway	View or change the current TCP/IP gateway.
Enable DHCP	Specify the DHCP address and parameter assignment.
On Off	Note: On is the factory default setting.
Enable RARP	Specify the RARP address assignment setting.
On Off	Note: Off is the factory default setting.
Enable BOOTP	Specify the BOOTP address assignment setting.
On Off	Note: On is the factory default setting.
Enable AutoIP	Specify the Zero Configuration Networking setting.
Yes No	Note: Yes is the factory default setting.
Enable FTP/TFTP Yes	Enable the built-in FTP server, which lets you send files to the printer using File Transfer Protocol.
No	Note: Yes is the factory default setting.
Enable HTTP Server Yes	Enable the built-in Web server (Embedded Web Server). When enabled, the printer can be monitored and managed remotely using a Web browser.
No	Note: Yes is the factory default setting.
WINS Server Address	View or change the current WINS server address.
Enable DDNS	View or change the current DDNS setting.
Yes No	Note: Yes is the factory default setting.
Enable mDNS	View or change the current mDNS setting.
Yes No	Note: Yes is the factory default setting.
DNS Server Address	View or change the current DNS server address.
Backup DNS Server Address	View or change the backup DNS server addresses.
Backup DNS Server Address 2	
Backup DNS Server Address 3	

Use	То
Enable HTTPS	View or change the current HTTPS setting.
Yes	Note: Yes is the factory default setting.
No	

IPv6 menu

To access the menu, navigate to any of the following:

- Network/Ports menu > Standard Network > Standard Network Setup > IPv6
- Network/Ports menu > Network [x] > Network [x] Setup > IPv6

Note: This menu is available only in network printers or printers that are attached to print servers.

Use	То
Enable IPv6	Enable IPv6 in the printer.
On	Note: On is the factory default setting.
Off	
Auto Configuration	Specify whether or not the network adapter accepts the automatic
On	IPv6 address configuration entries provided by a router.
Off	Note: On is the factory default setting.
Set Hostname	Set the host name.
View Address	Note: These settings can be changed only from the Embedded
View Router Address	Web Server.
Enable DHCPv6	Enable DHCPv6 in the printer.
On	Note: On is the factory default setting.
Off	

Wireless menu

Note: This menu is available only in printers connected to a wireless network or printer models that have a wireless network adapter.

To access the menu, navigate to:

Network/Ports > Network [x] > Network [x] Setup > Wireless

Use	То
Wi-Fi Protected Setup	Establish a wireless network and enable network security.
Start Push Button Method	Notes:
Start PIN Method	Start Push Button Method connects the printer to a wireless network when buttons on both the printer and the access point (wireless router) are pressed within a given period of time.
	 Start PIN Method connects the printer to a wireless network when a PIN on the printer is entered into the wireless settings of the access point.

Use	То
Enable/Disable WPS Auto-detection Enable	Automatically detect the connection method that an access point with WPS uses—Start Push Button Method or Start PIN Method.
Disable	Note: Disable is the factory default setting.
Network Mode	Specify the network mode.
BSS Type	Notes:
Infrastructure Ad hoc	 Infrastructure is the factory default setting. This lets the printer access a network using an access point.
	 Ad hoc configures wireless connection directly between the printer and a computer.
Compatibility	Specify the wireless standard for the wireless network.
802.11b/g 802.11b/g/n	Note: 802.11b/g/n is the factory default setting.
Choose Network	Select an available network for the printer to use.
View Signal Quality	View the quality of the wireless connection.
View Security Mode	View the encryption method for the wireless network.

AppleTalk menu

To access the menu, navigate to either of the following:

- Network/Ports > Standard Network > Standard Network Setup > AppleTalk
- Network/Ports > Network [x] > Network [x] Setup > AppleTalk

Use	То
Activate	Enable or disable AppleTalk support.
Yes	Note: No is the factory default setting.
No	
View Name	Show the assigned AppleTalk name.
	Note: The AppleTalk name can be changed only from the Embedded Web Server.
View Address	Show the assigned AppleTalk address.
	Note: The AppleTalk address can be changed only from the Embedded Web Server.
Set Zone	Provide a list of AppleTalk zones available on the network.
[list of zones available on the network]	Note: The default zone for the network is the factory default setting.

Standard USB menu

Use	То
PCL SmartSwitch On Off	Set the printer to automatically switch to PCL emulation when a print job received through a USB port requires it, regardless of the default printer language.
	Notes:
	On is the factory default setting.
	When set to Off, the printer does not examine incoming data. The printer uses PostScript emulation if the PS SmartSwitch is set to On. It uses the default printer language specified in the Setup menu if the PS SmartSwitch is set to Off.
PS SmartSwitch On	Set the printer to automatically switch to PS emulation when a print job received through a USB port requires it, regardless of the default printer language.
Off	Notes:
	On is the factory default setting.
	When set to Off, the printer does not examine incoming data. The printer uses PCL emulation if the PCL SmartSwitch is set to On. It uses the default printer language specified in the Setup menu if the PCL SmartSwitch is set to Off.
NPA Mode	Set the printer to perform the special processing required for bidirectional communication following the conventions defined by the NPA protocol.
On Off	Notes:
Auto	Auto is the factory default setting. Auto sets the printer to examine data, determine the format, and then process it appropriately.
	The printer automatically restarts when changing the setting from the printer control panel. The menu selection is then updated.
USB Buffer	Set the size of the USB input buffer.
Disabled	Notes:
Auto 3K to [maximum size allowed]	Auto is the factory default setting.
	Disabled turns off job buffering. Any jobs already buffered on the printer hard disk are printed before normal processing resumes.
	The USB buffer size value can be changed in 1-K increments.
	The maximum size allowed depends on the amount of memory in the printer, the size of the other link buffers, and whether Resource Save is set to On or Off.
	To increase the maximum size range for the USB Buffer, disable or reduce the size of the parallel, serial, and network buffers.
	The printer automatically restarts when the setting is changed from the printer control panel. The menu selection is then updated.

Use	То
Job Buffering	Temporarily store print jobs in the printer hard disk before printing.
Off On	Notes:
Auto	Off is the factory default setting.
	On buffers jobs on the printer hard disk.
	 Auto buffers print jobs only if the printer is busy processing data from another input port.
	 Changing this setting from the printer control panel and then exiting the menus causes the printer to restart. The menu selection is then updated.
Mac Binary PS	Set the printer to process Macintosh binary PostScript print jobs.
On Off	Notes:
Auto	Auto is the factory default setting.
	 On processes raw binary PostScript print jobs.
	 Off filters print jobs using the standard protocol.
ENA Address	Set the network address information for an external print server.
ууу.ууу.ууу.	Note: This menu is available only when the printer is attached to an external print server through the USB port.
ENA Netmask	Set the netmask information for an external print server.
ууу.ууу.ууу.	Note: This menu is available only when the printer is attached to an external print server through the USB port.
ENA Gateway	Set the gateway information for an external print server.
ууу.ууу.ууу	Note: This menu is available only when the printer is attached to an external print server through the USB port.

Parallel [x] menu

Note: This menu appears only when an optional parallel card is installed.

Use	То
PCL SmartSwitch On Off	Set the printer to automatically switch to PCL emulation when a print job received through a serial port requires it, regardless of the default printer language.
	Notes:
	On is the factory default setting.
	 When set to Off, the printer does not examine incoming data. The printer uses PostScript emulation if PS SmartSwitch is set to On. It uses the default printer language specified in the Setup menu if PS SmartSwitch is set to Off.

Use	То
PS SmartSwitch On	Set the printer to automatically switch to PS emulation when a print job received through a serial port requires it, regardless of the default printer language.
Off	Notes:
	 On is the factory default setting. When set to Off, the printer does not examine incoming data. The printer
	uses PCL emulation if PCL SmartSwitch is set to On. It uses the default printer language specified in the Setup menu if PCL SmartSwitch is set to Off.
NPA Mode On	Set the printer to perform the special processing required for bidirectional communication following the conventions defined by the NPA protocol.
Off	Notes:
Auto	Auto is the factory default setting.
	Changing this setting from the printer control panel and then exiting the menus causes the printer to restart. The menu selection is then updated.
Parallel Buffer	Set the size of the parallel input buffer.
Disabled	Notes:
Auto 3K to [maximum size allowed]	Auto is the factory default setting.
SK to [maximum size allowed]	Disabled turns off job buffering. Any print jobs already buffered on the printer hard disk are printed before normal processing resumes.
	The parallel buffer size setting can be changed in 1-KB increments.
	 The maximum size allowed depends on the amount of memory in the printer, the size of the other link buffers, and whether Resource Save is set to On or Off.
	 To increase the maximum size range for the Parallel Buffer, disable or reduce the size of the USB, serial, and network buffers.
	Changing this setting from the printer control panel and then exiting the menus causes the printer to restart. The menu selection is then updated.
Job Buffering	Temporarily store print jobs on the printer hard disk before printing.
Off	Notes:
On Auto	Off is the factory default setting.
Auto	On buffers print jobs on the printer hard disk.
	 Auto buffers print jobs only if the printer is busy processing data from another input port.
	Changing this setting from the printer control panel and then exiting the menus causes the printer to restart. The menu selection is then updated.
Advanced Status	Enable bidirectional communication through the parallel port.
On Off	Notes:
Off	On is the factory default setting.
	Off disables parallel port negotiation.

Use	То
Protocol	Specify the parallel port protocol.
Standard Fastbytes	Notes:
	Fastbytes is the factory default setting. It provides compatibility with most existing parallel ports and is the recommended setting.
	Standard tries to resolve parallel port communication problems.
Honor Init On	Determine if the printer honors printer hardware initialization requests from the computer.
Off	Notes:
	Off is the factory default setting.
	 The computer requests initialization by activating the Init signal from the parallel port. Many personal computers activate the Init signal each time the computer is turned on.
Parallel Mode 2	Determine if the parallel port data is sampled on the leading or trailing edge of a strobe.
Off	Note: On is the factory default setting.
Mac Binary PS	Set the printer to process Macintosh binary PostScript print jobs.
On	Notes:
Off Auto	Auto is the factory default setting.
Auto	Off filters print jobs using the standard protocol.
	On processes raw binary PostScript print jobs.
ENA Address	Set the network address information for an external print server.
ууу.ууу.ууу	Note: This menu item is available only if the printer is attached to an external print server through the USB port.
ENA Netmask	Set the netmask information for an external print server.
ууу.ууу.ууу	Note: This menu item is available only if the printer is attached to an external print server through the USB port.
ENA Gateway	Set the gateway information for an external print server.
ууу.ууу.ууу.	Note: This menu item is available only if the printer is attached to an external print server through the USB port.

Serial [x] menu

Note: This menu appears only when an optional serial card is installed.

Use	То
PCL SmartSwitch On Off	Set the printer to automatically switch to PCL emulation when a print job received through a serial port requires it, regardless of the default printer language.
	Notes:
	On is the factory default setting.
	 When set to Off, the printer does not examine incoming data. The printer uses PostScript emulation if PS SmartSwitch is set to On. It uses the default printer language specified in the Setup menu if PS SmartSwitch is set to Off.
PS SmartSwitch On	Set the printer to automatically switch to PS emulation when a print job received through a serial port requires it, regardless of the default printer language.
Off	Notes:
	On is the factory default setting.
	When set to Off, the printer does not examine incoming data. The printer uses PCL emulation if PCL SmartSwitch is set to On. It uses the default printer language specified in the Setup menu if PCL SmartSwitch is set to Off.
NPA Mode On	Set the printer to perform the special processing required for bidirectional communication following the conventions defined by the NPA protocol.
Off	Notes:
Auto	Auto is the factory default setting. Auto sets the printer to examine data, determine the format, and then processes it appropriately.
	When set to On, the printer performs NPA processing. If the data is not in NPA format, it is rejected as bad data.
	When set to Off, the printer does not perform NPA processing.
	Changing this setting from the printer control panel and then exiting the menus causes the printer to restart. The menu selection is then updated.
Serial Buffer	Set the size of the serial input buffer.
Disabled Auto	Notes:
3K to [maximum size allowed]	Auto is the factory default setting.
	Disabled turns off job buffering. Any jobs already buffered on the disk are printed before normal processing is resumed.
	The serial buffer size setting can be changed in 1-KB increments.
	 The maximum size allowed depends on the amount of memory in the printer, the size of the other link buffers, and whether Resource Save is set to On or Off.
	To increase the maximum size range for the Serial Buffer, disable or reduce the size of the parallel, serial, and network buffers.
	Changing this setting from the printer control panel and then exiting the menus causes the printer to restart. The menu selection is then updated.

Use	То
Job Buffering	Temporarily store print jobs on the printer hard disk before printing.
Off	Notes:
On Auto	 Off is the factory default setting. The printer does not buffer print jobs on the printer hard disk. On buffers print jobs on the printer hard disk. Auto buffers print jobs only if the printer is busy processing data from another input port. Changing this setting from the printer control panel and then exiting the menus causes the printer to restart. The menu selection is then updated.
Protocol DTR DTR/DSR XON/XOFF XON/XOFF/DTR XONXOFF/DTRDSR	Select the hardware and software handshaking settings for the serial port. Notes: DTR is the factory default setting. DTR/DSR is a hardware handshaking setting. XON/XOFF is a software handshaking setting. XON/XOFF/DTR and XON/XOFF/DTR/DSR are combined hardware and software handshaking settings.
Robust XON On Off	 Determine whether the printer communicates availability to the computer. Notes: Off is the factory default setting. This menu item applies only to the serial port if Serial Protocol is set to XON/XOFF.
Baud 1200 2400 4800 9600 19200 38400 57600 115200 138200 172800 230400 345600	 Specify the rate at which data can be received through the serial port. Notes: 9600 is the factory default setting. 138200, 172800, 230400, and 345600 baud rates are only displayed in the Standard Serial menu. These settings do not appear in the Serial Option 1, Serial Option 2, or Serial Option 3 menus.
Data Bits	Specify the number of data bits sent in each transmission frame.
7 8	Note: 8 is the factory default setting.
Parity	Set the parity for serial input and output data frames.
Even Odd None Ignore	Note: None is the factory default setting.

Use	То
Honor DSR	Determine whether the printer uses the DSR Signal.
On	Notes:
Off	 Off is the factory default setting. DSR is a handshaking signal used by most serial cables. The serial port uses DSR to distinguish data sent by the computer from data created by electrical noise in the serial cable. The electrical noise can cause stray characters to print. Set this to On to prevent stray characters from printing.

SMTP Setup menu

Use	То
Primary SMTP Gateway	Specify SMTP server gateway and port information.
Primary SMTP Gateway Port	Note: 25 is the default SMTP gateway port.
Secondary SMTP Gateway	
Secondary SMTP Gateway Port	
SMTP Timeout 5–30	Specify the amount of time in seconds before the server stops trying to send an e-mail.
	Note: 30 seconds is the factory default setting.
Reply Address	Specify a reply address of up to 128 characters in the e-mail sent by the printer.
Use SSL Disabled	Set the printer to use SSL for increased security when connecting to the SMTP server.
Negotiate	Notes:
Required	Disabled is the factory default setting.
	 When the Negotiate setting is used, the SMTP server determines if SSL will be used.
SMTP Server Authentication No authentication required	Specify the type of user authentication required for scan-to e-mail privileges.
Login/Plain	Note: "No authentication required" is the factory default setting.
CRAM-MD5	
Digest-MD5	
NTLM	
Kerberos 5	

Use	То
Device-Initiated E-mail None Use Device SMTP Credentials	Specify what credentials will be used when communicating to the SMTP server. Some SMTP servers require credentials to send an email.
User-Initiated E-mail*	Notes:
None Use Device SMTP Credentials Use Session User ID & Password Use Session E-mail address & Password Prompt User	 None is the factory default setting for Device-Initiated E-mail and User-Initiated E-mail. Device Userid and Device Password are used to log in to the SMTP server when Use Device SMTP Credentials is selected.
Device Userid	
Device Password	
Kerberos 5 Realm	
NTLM Domain	

Security menu

Edit Security Setups menu

Use	То
Edit Backup Password	Create a backup password.
Use Backup Password	Notes:
Off	Off is the factory default setting for Use Backup Password.
On	This menu item appears only if a backup password exists.
Password	This menu item appears only if a backup password exists.
Edit Building Blocks	Edit settings for Internal Accounts, NTLM, Simple Kerberos Setup, Kerberos
Internal Accounts	Setup, Active Directory, LDAP, Password, and PIN.
NTLM	
Simple Kerberos Setup	
Kerberos Setup	
Active Directory	
LDAP	
LDAP+GSSAPI	
Password	
PIN	
Edit Security Templates	Add or edit a security template.
[list of available templates]	

Use	То
Edit Access Controls Administrative Menus	Control access to printer menus, firmware updates, held jobs, and other access points.
Function Access	points.
Apps Configuration	
Management	
Solutions	
Cancel jobs at the Device	

Miscellaneous Security Settings menu

Use	То
Login Restrictions Login failures	Limit the number and time frames of failed login attempts from the printer control panel before <i>all</i> users are locked out.
Failure time frame Lockout time Panel Login Timeout Remote Login Timeout	 **Login failures" specifies the number of failed login attempts before users are locked out. Settings range from 1 to 10 attempts. "3 attempts" is the factory default setting. **Failure time frame" specifies the time frame during which failed login attempts can be made before users are locked out. Settings range from 1 to 60 minutes. "5 minutes" is the factory default setting. **Lockout time" specifies how long users are locked out after exceeding the login failures limit. Settings range from 1 to 60 minutes. "5 minutes" is the factory default setting. 1 indicates that the printer does not impose a lockout time. Panel Login Timeout specifies how long the printer remains idle on the home screen before automatically logging off the user. Settings range from 1 to 900 seconds. "30 seconds" is the factory default setting. Remote Login Timeout specifies how long a remote interface remains idle before automatically logging off the user. Settings range from 1 to 120 minutes. "10 minutes" is the factory default setting.
Security Reset Jumper No Effect	Adjust the security settings.
Access controls="No Security" Reset factory security defaults	 No Effect means the reset has no effect on the printer security configuration. Access controls='No Security' retains all the security information that the user has defined. No Security is the factory default setting. "Reset factory security defaults" deletes all security information that the user has defined, and restores the factory default settings in the Miscellaneous Security menu.

Use	То
LDAP Certificate Verification	Allow the user to request a server certificate.
Demand	Notes:
Try Allow Never	"Demand" is the factory default setting. This means a server certificate is requested. If a bad certificate is provided or if no certificate is provided, then the session is terminated immediately.
	"Try " means a server certificate is requested. If no certificate is provided, then the session proceeds normally. If a bad certificate is provided, then the session is terminated immediately.
	"Allow" means a server certificate is requested. If no certificate is provided, then the session proceeds normally. If a bad certificate is provided, then it will be ignored and the session proceeds normally.
	"Never" means no server certificate is requested.
Minimum PIN Length	Limit the digit length of the personal identification number (PIN).
1–16	Note: 4 is the factory default setting.

Confidential Print menu

Use	То
Max Invalid PIN	Set a limit on the number of times an invalid PIN can be entered.
Off 2–10	Notes:
2-10	 This menu item appears only when a formatted, working printer hard disk is installed.
	When the limit is reached, the print jobs for that user name and PIN are deleted.
Confidential Job Expiration	Set a limit on how long the printer stores confidential print jobs.
Off	Notes:
1 hour	If the "Confidential Job Expiration" setting is changed while confidential print
4 hours 24 hours	jobs reside in the printer memory or printer hard disk, then the expiration time
1 week	for those print jobs does not change to the new default value.
i week	 If the printer is turned off, then all confidential jobs held in the printer memory are deleted.
Repeat Job Expiration	Set a limit on how long the printer stores print jobs.
Off	
1 hour	
4 hours	
24 hours	
1 week	
Note: Off is the factory defau	ılt setting.

Use	То	
Verify Job Expiration	Set a limit on how long the printer stores print jobs needing verification.	
Off		
1 hour		
4 hours		
24 hours		
1 week		
Reserve Job Expiration	Set a limit on how long the printer stores print jobs for printing at a later time.	
Off		
1 hour		
4 hours		
24 hours		
1 week		
Note: Off is the factory default setting.		

Erase Temporary Data Files menu

Erase Temporary Data Files deletes *only* print job data on the printer hard disk that *are not* currently in use by the file system. All permanent data on the printer hard disk are preserved, such as downloaded fonts, macros, and held jobs.

Note: This menu appears only when a formatted, working printer hard disk is installed.

Use	То
Wiping Mode Auto	Specify the mode for erasing temporary data files.
Automatic Method Single pass Multiple pass	Mark all disk space used by a previous print job. This method does not permit the file system to reuse this space until it has been cleared. Notes:
	 "Single pass" is the factory default setting. Only automatic wiping enables users to erase temporary data files without having to turn off the printer for an extended amount of time. Highly confidential information should be erased using <i>only</i> the Multiple pass method.

Security Audit Log menu

Use	То
Export Log	Enable an authorized user to export the security log.
	Notes:
	To export the log from the printer control panel, attach a flash drive to the printer.
	 To export the log from the Embedded Web Server, download the log to a computer.

Use	T-
Ose	То
Delete Log	Specify whether audit logs are deleted.
Yes	
No	
Configure Log	Specify how audit logs are configured.
Enable Audit	Notes:
Yes No	 Enable Audit determines if events are recorded in the secure audit log and remote syslog. No is the factory default setting.
Enable Remote Syslog No Yes	 Enable Remote Syslog determines if logs are sent to a remote server. No is the factory default setting.
Remote Syslog Server	 Remote Syslog Server determines the value used to send logs to the remote syslog server.
[256 character string] Remote Syslog Port	 Remote Syslog Port identifies the port over which the printer transmits logged events to a remote server.
1–65535 Remote Syslog Method Normal UDP	 Remote Syslog Method identifies the protocol used by the printer to transmit logged events to a remote server. Normal UDP is the factory default setting.
Stunnel Remote Syslog Facility 0–23	 Remote Syslog Facility determines the Facility value that the printer uses when sending events to the remote syslog server. 4 is the factory default setting.
Log full behavior Wrap over oldest entries E-mail log then delete all entries	 "Log full behavior" determines how the printer resolves if the log entirely fills its allotted memory. "Wrap over oldest entries" is the factory default setting.

Use	То
Configure Log (continued)	Specify how audit logs are configured.
Admin's e-mail address	Notes:
[256 character string] Digitally sign exports Off	"Admin's e-mail address" determines if administrators are automatically notified of certain log events. This setting can have one or more e-mail addresses (separated by commas).
On Severity of events to log	"Digitally sign exports" determines if the printer automatically signs each exported security log. Off is the factory default setting.
0–7 Remote Syslog non-logged events	• "Severity of events to log" records the severity value of each event. 4 is the factory default setting.
No Yes E-mail log cleared alert No	 "Remote Syslog non-logged events" determines if the printer sends events to the remote server that have a severity level greater than the value of the "Severity of events to log" setting. No is the factory default setting.
Yes E-mail log wrapped alert No	"E-mail log cleared alert" determines if the printer sends an e-mail to the administrator every time a log is deleted through the printer control panel or EWS. No is the factory default setting.
Yes E-mail % full alert	"E-mail log wrapped alert" determines if the printer sends the administrator an e-mail when log entries are wrapping. No is the factory default setting.
No Yes % full alert level	"E-mail % full alert" determines if the printer sends the administrator an e-mail when the log fills a certain amount of its allotted space. No is the factory default setting.
1–99 E-mail log exported alert No	"% full alert level" determines if the space occupied by log equals or exceeds the value of the full alert level. 90 is the factory default setting.
Yes E-mail log settings changed alert No	 "E-mail log exported alert" determines if the printer sends the administrator an e-mail when there is a log exported. No is the factory default setting.
Yes Log line endings LF (\n)	"E-mail log settings changed alert" determines if the printer sends the administrator an e-mail when the value of the Enable Audit Log setting is toggled. No is the factory default setting.
CR (\r) CRLF (\r\n)	"Log line endings" specifies how line endings will be handled in the log file, depending on the operating system in which the file will be parsed or viewed. "LF (\n)" is the factory default setting.

Set Date and Time menu

Use	То	
Current Date and Time	View the current date and time settings for the scanner.	
Manually Set Date and Time	Enter the date and time.	
	Note: Date/Time is set in YYYY-MM-DD HH:MM:SS format.	
Time Zone	Select the time zone.	
	Note: GMT is the factory default setting.	

Use	То
Automatically Observe DST On	Set the scanner to use the applicable daylight saving time (DST) start and end times associated with the scanner Time Zone setting.
Off	Note: On is the factory default setting and uses the applicable Daylight Saving Time associated with the Time Zone setting.
Custom Time Zone Setup	Enable the user to set up the time zone.
DST Start Week	
DST Start Day	
DST Start Month	
DST Start Time	
DST End Week	
DST End Day	
DST End Month	
DST End Time	
DST Offset	
Enable NTP	Enable Network Time Protocol, which synchronizes the clocks of devices on a
On	network.
Off	Note: On is the factory default setting.
NTP Server	View the NTP server address.
Enable Authentication	Enable the authentication setting.
On	Note: Off is the factory default setting.
Off	

Settings menu

General Settings menu

Use	То
Display Language	Set the language of the text appearing on the printer display.
English	Note: Not all languages are available for all printers, and you
Francais	may need to install special hardware for those languages to
Deutsch	appear.
Italiano	
Espanol	
Dansk	
Norsk	
Nederlands	
Svenska	
Portuguese	
Suomi	
Russian	
Polski	
Greek	
Magyar	
Turkce	
Cesky	
Simplified Chinese	
Traditional Chinese	
Korean	
Japanese	
Eco-Mode	Minimize the use of energy, paper, or specialty media.
Off	Notes:
Energy Energy/Paper	Off is the factory default setting. This resets the printer to its factory default settings.
Paper	 Energy minimizes the power used by the printer. Performance may be affected, but print quality is not.
	 Energy/Paper minimizes the use of power and paper specialty media.
	 Paper minimizes the amount of paper and specialty media needed for a print job. Performance may be affected, but print quality is not.
ADF Loaded Beep	Specify whether the ADF sounds a beep when paper is loaded.
Enabled	Note: Enabled is the factory default setting.
Disabled	, , , , , , , , , , , , , , , , , , ,

То
Reduce the amount of noise produced by the printer.
Notes:
 Off is the factory default setting. This supports the performance specifications for your printer. On configures the printer to produce as little noise as possible. This is best suited for printing text and line art. For optimal printing of color-rich documents, set Quiet Mode to Off.
 Selecting Photo from the print driver may disable Quiet Mode and provide better print quality and full speed printing.
Set the printer to run the setup wizard.
Note: Yes is the factory default setting. After completing the setup wizard, the default becomes No.
Specify a language and custom key information for the printer keyboard. The additional tabs enable access to accent marks and symbols from the keyboard.

Use	То
Paper Sizes	Specify the default paper measurement.
US	Notes:
Metric	US is the factory default setting.
	 The initial setting is determined by your country or region selection in the initial setup wizard.
	 Changing this setting also changes the default setting for each input source in the Paper Size/Type menu.
Scan to PC Port Range [port range]	Specify a valid port range for printers behind a port blocking firewall.
	Note: 9751:12000 is the factory default setting.
Displayed Information Left side	Specify what is displayed on the upper left and right corners of the home screen.
Right side Custom Text [x]	For the Left side and Right side menus, select from the following options:
	None
	IP Address
	Hostname
	Contact Name
	Location
	Date/Time
	mDNS/DDNS Service Name
	Zero Configuration Name
	Custom Text [x]
	Model Name
	Notes:
	IP Address is the factory default setting for Left side.
	Date/Time is the factory default setting for Right side.

Use	То
Displayed Information (continued)	Customize the displayed information for Black Toner.
Black Toner	Select from the following options:
	When to display
	Do not display
	Display
	Message to Display
	Default
	Alternate
	Default
	[text entry]
	Alternate
	[text entry]
	Notes:
	 Do not display is the factory default setting for When to display.
	 Default is the factory default setting for Message to Display.
Displayed Information (continued) Waste Toner Bottle	Customize the displayed information for Waste Toner Bottle, Paper Jam, Load Paper, and Service Errors.
Paper Jam	Select from the following options:
Load Paper	Display
Service Errors	Yes
	No
	Message to display
	Default
	Alternate
	Default
	[text entry]
	Alternate
	[text entry]
	Notes:
	No is the factory default setting for Display.
	 Default is the factory default setting for Message to Display.

Use	То
Home screen customization Change Language Copy Copy Shortcuts Fax Fax Shortcuts E-mail E-mail Shortcuts FTP FTP Shortcuts Search Held Jobs Held Jobs USB Drive Profiles and Apps Bookmarks Jobs by user Forms and Favorites Card Copy Scan to Network MyShortcut Multi Send	Change the icons that appear on the home screen. For each icon, select from the following options: Display Do Not display Notes: Display is the factory default setting for Copy, Fax, E-mail, FTP, Search Held Jobs, Held Jobs, USB Drive, Forms and Favorites, Card Copy, Scan to Network, MyShortcut, and Multisend. Do not display is the factory default setting for Change Language, Copy Shortcuts, Fax Shortcuts, E-mail Shortcuts, FTP Shortcuts, Profiles and Apps, Bookmarks, and Jobs by user.
Date Format MM-DD-YYYY DD-MM-YYYY YYYY-MM-DD Time Format	Format the printer date. Notes: MM-DD-YYYY is the U.S. factory default setting. DD-MM-YYYY is the international factory default setting. Format the printer time.
12 hour A.M./P.M. 24 hour clock Screen Brightness 20–100	Note: 12 hour A.M./P.M. is the factory default setting. Specify the brightness of the control panel screen. Note: 100 is the factory default setting.
One Page Copy Off On	Set copies from the scanner glass to only one page at a time. Note: Off is the factory default setting.
Output Lighting Normal/Standby Mode Off Dim Bright	Set the amount of light from the standard bin. Notes: Dim is the factory default setting if Eco-Mode is set to Energy or Energy/Paper. Bright is the factory default setting if Eco-Mode is set to Paper or Off.

Use	То
Audio Feedback	Set the audio volume for the buttons.
Button Feedback	Notes:
On	On is the factory default setting for Button Feedback.
Off	
Volume	 5 is the factory default setting for Volume.
1–10	
Show Bookmarks	Specify whether bookmarks are displayed from the Held Jobs
Yes	area.
No	Note: Yes is the factory default setting.
Allow Background Removal On	Specify whether image background removal is allowed in copy, fax, e-mail, FTP, or scan-to-USB jobs.
Off	Note: On is the factory default setting. The background of the image is removed.
Allow Custom Job Scans	Scan multiple jobs to one file.
On Off	Note: On is the factory default setting. If On is selected, then the Allow Custom Job Scans setting can be enabled for specific jobs.
Scanner Jam Recovery Job level	Specify how a scanned job should be reloaded if a paper jam occurs in the ADF.
Page level	Notes:
	 Job level is the factory default setting. If selected, then the entire job must be rescanned if any pages jam.
	 If Page level is selected, then rescan from the jammed page forward.
Web Page Refresh Rate 30-300	Specify the number of seconds between Embedded Web Server refreshes.
	Note: 120 is the factory default setting.
Contact Name	Specify a contact name for the printer.
	Note: The contact name is stored on the Embedded Web Server.
Location	Specify the location of the printer.
	Note: The location is stored on the Embedded Web Server.

Use	То
Alarms Alarm Control Cartridge Alarm Staple Alarm Hole Punch Alarm	Set an alarm when the printer requires user intervention. For each alarm type, select from the following options: Off Single Continuous Notes:
	 Single is the factory default setting for Alarm Control. Single sounds three quick beeps. Off is the factory default setting for Cartridge Alarm, Staple Alarm, and Hole Punch Alarm. Continuous repeats three beeps every 10 seconds.
Timeouts Standby Mode Disabled 1–240	Specify the number of minutes of inactivity before the printer enters a lower power state. Note: 15 is the factory default setting.
Timeouts Sleep Mode Disabled 1–120	 Set the amount of time in minutes the printer waits after a job is printed before it goes into a reduced power state. Notes: 20 is the factory default setting. Disabled appears only when Energy Conserve is set to Off. Lower settings conserve more energy, but may require longer warm-up times. Select a high setting if the printer is in constant use. Under most circumstances, this keeps the printer ready to print with minimum warm-up time.
Timeouts Print with Display off Allow printing with display off Display on when printing	Allow the printer to print even when the display is off. Note: Allow printing with display off is the factory default setting.
Timeouts Hibernate Timeout Disabled 1 hour 2 hours 3 hours 6 hours 1 day 2 days 3 days 1 week 2 weeks 1 month	Set the amount of time before the printer enters Hibernate mode. Note: 3 days is the factory default setting.

Use	То
Timeouts Hibernate Timeout on Connection	Set the printer to Hibernate Timeout even when there is an active Ethernet connection.
Do Not Hibernate Hibernate	Note: Hibernate is the factory default setting.
Timeouts Screen Timeout	Set the amount of time in seconds the printer waits before returning to Ready state.
15–300	Note: 30 is the factory default setting.
Timeouts Prolong Screen Timeout	Set the printer to continue a specified job without returning to the home screen when the screen timeout timer expires.
On Off	Note: Off is the factory default setting.
Timeouts Print Timeout Disabled	Set the amount of time in seconds the printer waits to receive an end-of-job message before canceling the rest of the print job.
1–255	Notes:
	• 90 is the factory default setting.
	 When the timer expires, any partially printed page still in the printer is printed, and then the printer checks to see if any new print jobs are waiting.
	 Print Timeout is available only when using PCL emulation. This has no effect on PostScript emulation print jobs.
Timeouts Wait Timeout	Set the amount of time in seconds the printer waits for additional data before canceling a print job.
Disabled 15–65535	Notes:
15-05555	 40 is the factory default setting.
	 Wait Timeout is available only when the printer is using PostScript emulation. This has no effect on PCL emulation print jobs.
Timeouts Job Hold Timeout 5–255	Set the amount of time the printer waits for user intervention before it holds jobs that require unavailable resources and continues to print other jobs in the print queue.
	Notes:
	• 30 is the factory default setting.
	 This menu appears only when a formatted printer hard disk is installed.
Error Recovery	Set the printer to restart when an error is encountered.
Auto Reboot	Note: Reboot always is the factory default setting.
Reboot when idle	
Reboot always Reboot never	
VENOOF HEAGI	

Use	То
Error Recovery Max Auto Reboots	Determine the number of automatic reboots the printer can perform.
1–20	Note: 2 is the factory default setting.
Print Recovery Auto Continue Disabled 5–255	Let the printer automatically continue printing from certain offline situations when not resolved within the specified time period. Note: Disabled is the factory default setting.
Print Recovery	Specify whether the printer reprints jammed pages.
Jam Recovery	Notes:
On Off Auto	 Auto is the factory default setting. The printer reprints jammed pages unless the memory required to hold the pages is needed for other printer tasks. On sets the printer to always reprint jammed pages.
	Off sets the printer to never reprint jammed pages.
Print Recovery	Set the printer to automatically check for jammed paper.
Jam Assist On	Note: On is the factory default setting.
Off	
Print Recovery	Let the printer successfully print a page that may not have
Page Protect	printed otherwise.
Off	Notes:
On	 Off is the factory default setting. This prints a partial page when there is not enough memory to print the whole page. On sets the printer to process the whole page so that
	the entire page prints.
Press Sleep Button Do Nothing	Determine how the printer responds when pressing the Sleep button while the printer is idle.
Sleep	Notes:
Hibernate	Sleep is the factory default setting.
	 Sleep or Hibernate sets the printer to operate at a lower power configuration.
	 If the printer is in Sleep mode, then the display appears off and the Sleep button turns amber. Touch anywhere on the display or press a button on the control panel to wake the printer from Sleep mode.
	 If the printer is in Hibernate mode, then the display is completely off and the Sleep button turns amber and is blinking.

Use	То
Press and Hold Sleep Button Do Nothing	Determine how the printer responds when pressing the Sleep button for 3 seconds or longer while the printer is idle.
Sleep	Notes:
Hibernate	Do Nothing is the factory default setting.
	Sleep or Hibernate sets the printer to operate at a lower power configuration.
	If the printer is in Sleep mode, then the display appears off and the Sleep button turns amber. Touch anywhere on the display or press a button on the control panel to wake the printer from Sleep mode.
Factory Defaults	Restore the printer settings to the factory default settings.
Do Not Restore	Notes:
Restore Now	Do Not Restore is the factory default setting. This keeps the user-defined settings.
	 Restore Now returns all printer settings to the factory default settings except Network/Ports menu settings. All downloads stored in RAM are deleted. Downloads stored in flash memory or on a printer hard disk are not affected.
Export Configuration Package Export	Export the printer configuration file to a flash drive.

Copy Settings menu

Use	То
Content Type	Specify the content of the original document.
Text	Note: Text/Photo is the factory default setting.
Graphics	
Text/Photo	
Photo	
Content Source	Specify how the original document was produced.
Black/White Laser	Note: Black/White Laser is the factory default setting.
Color Laser	, , , , , , , , , , , , , , , , , , ,
Inkjet	
Photo/Film	
Magazine	
Newspaper	
Press	
Other	

Use	То
Sides (Duplex) 1 sided to 1 sided 1 sided to 2 sided 2 sided to 1 sided	Specify whether an original document is two-sided or one-sided, and then to specify whether the copy should be two-sided or one-sided. Notes: 1 sided to 1 sided—The original document has print on one side and the
2 sided to 2 sided	 copy will also have print on one side. 1 sided to 2 sided—The original document has print on one side, while the copy will have print on both sides.
	• 2 sided to 1 sided—The original document has print on both sides, while the copy will have print on just one side.
	 2 sided to 2 sided—The original document has print on both sides, and the copy will also have print on both sides.
Paper Saver	Copy two or four sheets of a document on one page.
Off 2-up Portrait 2-up Landscape 4-up Portrait 4-up Landscape	Note: Off is the factory default setting.
Print Page Borders	Specify whether a border is printed.
On Off	Note: Off is the factory default setting.
Collate (1,1,1) (2,2,2) (1,2,3) (1,2,3)	Keep the pages of a print job stacked in sequence when printing multiple copies. Note: (1,2,3) (1,2,3) is the factory default setting.
Punch Off 2 holes 3 holes 4 holes	 Specify the type of hole punch finishing to be used in a print or copy job. Notes: Off is the factory default setting. This menu item appears only when a staple, hole punch finisher is installed.
Staple Off 1 staple 2 staples	Enable or disable the staple finisher. Notes: Off is the factory default setting. This menu item appears only when a staple finisher is installed.

Use	То
Original Size Letter Legal Executive Tabloid Folio Statement Oficio (Mexico) Universal Auto Size Sense Mixed Sizes A3 A4 A5 A6 JIS B4 JIS B5 Custom Scan Size [x] Book Original Business Card 3 x 5 in. 4 x 6 in. ID Card	Specify the paper size of the original document. Note: Letter is the U.S. factory default setting. A4 is the international factory default setting.
Copy To Source Tray [x] Auto Size Match Multipurpose Feeder	Specify the paper source for copy jobs. Note: Tray 1 is the factory default setting.
Transparency Separators On Off	Place a sheet of paper between transparencies. Notes: On is the factory default setting. When set to On, a blank page is placed between transparencies.
Separator Sheets Off Between Copies Between Jobs Between Pages	Place a sheet of paper between pages, copies, or jobs. Note: Off is the factory default setting.
Separator Sheet Source Tray [x] Multipurpose Feeder	Specify the paper source for the separator sheet. Note: Tray 1 is the factory default setting.
Darkness 1–9	Lighten or darken the print for the copy job. Note: 5 is the factory default setting.

Use	То
Output Bin Standard Bin Bin [x]	Specify the bin to be used for the copy job. Notes: Standard Bin is the factory default setting. Bin [x] appears only when at least one optional bin is installed.
Number of Copies 1–9999	Specify the number of copies for the copy job. Note: 1 is the factory default setting.
Header/Footer [Location] Off Date/Time Page number Custom text Print on All pages First page only All but first page Custom text Overlay Confidential Copy Draft Urgent Custom Off	Specify header and footer information and its location on the page. For the location, select from the following options: Top left Top middle Top right Bottom left Bottom middle Bottom right Notes: Off is the factory default setting for the location. All pages is the factory default setting for "Print on." Specify the overlay text printed on each page of the copy job. Note: Off is the factory default setting.
Custom Overlay	Specify the custom overlay text. Note: A maximum of 64 characters is allowed.
Allow priority copies On Off	Allow interruption of a print job to copy a page or document. Note: On is the factory default setting.
Custom Job scanning On Off	Copy a document that contains mixed paper sizes into a single copy job. Notes: Off is the factory default setting. This menu item appears only when a formatted, working printer hard disk is installed.
Allow Save as Shortcut On Off	Save custom copy settings as shortcuts. Note: On is the factory default setting.
Background Removal -4 to 4	Adjust the amount of background visible on a copy. Note: 0 is the factory default setting.

Use	То
Auto Center	Automatically center the content on the page.
Off	Note: Off is the factory default setting.
On	
Color Dropout	Specify which color to drop during scanning and to adjust the dropout setting for each color threshold.
Color Dropout None	
Red	Notes:
Green	None is the factory default setting for Color Dropout.
Blue	128 is the factory default setting for each color threshold.
Default Red Threshold	
0–255	
Default Green Threshold	
0–255	
Default Blue Threshold	
0–255	
Contrast	Specify the contrast used for the copy job.
0–5	Note: Best for content is the factory default setting.
Best for content	
Mirror Image	Create a mirror image of the original document.
Off	Note: Off is the factory default setting.
On	
Negative Image	Create a negative image of the original document.
Off	Note: Off is the factory default setting.
On	
Shadow Detail	Adjust the amount of shadow detail visible on a copy.
-4 to 4	Note: 0 is the factory default setting.
Scan edge to edge	Allow edge-to-edge scanning of the original document.
Off	Note: Off is the factory default setting.
On	
Sharpness	Adjust the amount of sharpness of a copy.
1–5	Note: 3 is the factory default setting.
Sample Copy	Create a sample copy of the original document.
Off	Notes:
On	
	 Off is the factory default setting. This menu item appears only when a formatted, working printer hard disk
	is installed.

Fax Settings menu

Fax Mode (Analog Fax Setup) menu

Analog Fax Setup mode sends the fax job through a telephone line.

General Fax Settings

Use	То
Fax Name	Specify the name of the fax in the printer.
Fax Number	Specify the number assigned to the fax.
Fax ID Fax Name Fax Number	Specify how the fax is identified. Note: Fax Number is the factory default setting.
Enable Manual Fax On Off	Set the printer to fax manually, which requires a line splitter and a telephone handset. Notes: Use a regular telephone to answer an incoming fax job and to dial a fax number. Touch # 0 on the numeric keypad to go directly to the Manual Fax function. Off is the factory default setting.
Memory Use All receive Mostly receive Equal Mostly send All send	Define the allocation of non-volatile memory between sending and receiving fax jobs. Notes: Equal is the factory default setting. Equal splits the memory for sending and receiving fax jobs into equal amounts. Mostly send specifies that most of the memory is set to send fax jobs. All send specifies that all the memory is set to receive fax jobs. All receive specifies that all the memory is set to receive fax jobs. Mostly receive specifies that most of the memory is set to receive fax jobs.
Cancel Faxes Allow Don't Allow Caller ID Off Primary Alternate	Specify whether the printer cancels fax jobs. Note: Allow is the factory default setting. Specify the type of caller ID being used.

Use	То
Fax number masking	Specify the direction from where digits are masked in an outgoing fax number.
Off	Notes:
From left From right	 The number of characters masked is determined by the Digits to Mask setting. Off is the factory default setting.
Digits to Mask	Specify the number of digits to mask in an outgoing fax number.
0–58	Note: 0 is the factory default setting.
Fax Cover Page	Configure the fax cover page.
Fax Cover Page	Notes:
Off by default	Off by default is the factory default setting for Fay Cover Page
On by default	Off by default is the factory default setting for Fax Cover Page. Off is the factory default setting for Fax Cover Page.
Never use	Off is the factory default setting for all other menu items.
Always use	
Include to Field	
On	
Off	
Include from Field	
On	
Off	
From	
Include Message Field	
On	
Off	
Message	
Include Logo	
On	
Off	
Include Footer [x]	
On	
Off	
Footer [x]	

Fax Send Settings

Use	То
Resolution	Specify quality in dots per inch (dpi). A higher resolution gives better print quality,
Standard	but increases the fax transmission time for outgoing faxes.
Fine 200 dpi	Note: Standard is the factory default setting.
Super Fine 300 dpi	
Ultra Fine 600 dpi	

Use	То
Original Size Letter Legal Executive Tabloid Folio Statement Oficio (Mexico) Universal Auto Size Sense Mixed Sizes A3 A4 A5 A6 JIS B4 JIS B5 Custom Scan Size [x] Book Original Business Card 3 x 5 in. 4 x 6 in.	Specify the size of the original document. Note: Mixed Sizes is the U.S. factory default setting. A4 is the international factory default setting.
Sides (Duplex) Off Long edge Short edge	 Specify how text and graphics are oriented on a page. Notes: Off is the factory default setting. Long edge assumes binding along the long edge of the page (left edge for portrait and top edge for landscape). Short edge assumes binding along the short edge of the page (top edge for portrait and left edge for landscape).
Content Type Text Graphics Text/Photo Photo	Specify the content of the original document. Note: Text is the factory default setting.
Content Source Black/White Laser Color Laser Inkjet Photo/Film Magazine Newspaper Press Other	Specify how the original document was produced. Note: Black/White Laser is the factory default setting.

Use	То
Darkness	Lighten or darken the output.
1–9	Note: 5 is the factory default setting.
Dial Prefix	Enter a dialing prefix, such as 99. A numeric entry field is provided.
Dialing Prefix Rules Prefix Rule [x]	Establish a dialing prefix rule.
Automatic Redial 0-9	Specify the number of times the printer tries to send the fax to a specified number.
	Note: 5 is the factory default setting.
Redial frequency 1–200	Specify the number of minutes between redials. Note: 3 is the factory default setting.
Behind a PABX Yes No	Enable or disable switchboard blind dialing without a dial tone. Note: No is the factory default setting.
Enable ECM Yes No	Enable or disable Error Correction Mode for fax jobs. Note: Yes is the factory default setting.
Enable Fax Scans On Off	Fax files that are scanned at the printer. Note: On is the factory default setting.
Driver to fax Yes No	Allow the print driver to send fax jobs. Note: Yes is the factory default setting.
Allow Save as Shortcut On Off	Save fax numbers as shortcuts in the printer. Note: On is the factory default setting.
Dial Mode Tone Pulse	Specify a dialing sound. Note: Tone is the factory default setting.
Max Speed 2400 4800 9600 14400 33600	Specify the maximum speed in baud at which faxes are sent. Note: 33600 is the factory default setting.
Custom Job scanning On Off	Scan a document that contains mixed paper sizes into a single file. Notes: Off is the factory default setting. This menu item appears only when a formatted, working printer hard disk is installed.

Use	То
Scan Preview On Off Background Removal -4 to 4 Color Balance Cyan - Red Magenta - Green Yellow - Blue	 Specify whether a preview appears on the display for scan jobs. Notes: Off is the factory default setting. This menu item appears only when a formatted, working printer hard disk is installed. Adjust the amount of background visible on a scanned image. Note: 0 is the factory default setting. Enable an equal balance of colors in the scanned image.
Color Dropout Color Dropout None Red Green Blue Default Red Threshold 0-255 Default Green Threshold 0-255 Default Blue Threshold 0-255	Specify which color to drop during scanning and to adjust the dropout setting for each color threshold. Notes: None is the factory default setting for Color Dropout. 128 is the factory default setting for each color threshold.
Contrast 0-5 Best for content	Specify the contrast in the scanned image. Note: Best for content is the factory default setting.
Mirror Image Off On	Create a mirror image of the original document. Note: Off is the factory default setting.
Negative Image Off On	Create a negative image of the original document. Note: Off is the factory default setting.
Shadow Detail -4 to 4	Adjust the amount of shadow detail visible. Note: 0 is the factory default setting.
Off On	Specify if the original document is scanned edge-to-edge prior to faxing. Note: Off is the factory default setting.
Sharpness 1–5	Adjust the sharpness of a fax. Note: 3 is the factory default setting.

Use	То
Temperature -4 to 4	Specify warm or cool outputs. Cool values generate a bluer output than the default while warm values generate a redder output than the default.
	Note: 0 is the factory default setting.
Enable Color Fax Scans	Enable color faxing.
Off by default	Note: Off by default is the factory default setting.
On by default	
Never use	
Always use	
Auto Convert Color Faxes to	Convert all outgoing faxes to black and white.
Mono Faxes	Note: On is the factory default setting.
On	, s
Off	

Fax Receive Settings

Use	То
Enable Fax Receive	Allow the printer to receive fax jobs.
On	Note: On is the factory default setting.
Off	
Fax Job Waiting	Remove fax jobs from the print queue when the job requires specific unavailable
None	resources.
Toner	Note: None is the factory default setting.
Toner and Supplies	
Rings to Answer	Specify the number of rings before answering an incoming fax job.
1–25	Note: 3 is the factory default setting.
Auto Answer	Allow the printer to answer an incoming fax job.
Yes	Note: Yes is the factory default setting.
No	
Manual Answer Code	Enter a code on the telephone number pad to begin receiving a fax.
0–9	Notes:
	• *9* is the factory default setting.
	This menu item is used when the printer shares a line with a telephone.
Auto Reduction On	Scale an incoming fax job so that it fits the size of the paper loaded in the designated fax source.
Off	Note: On is the factory default setting.
Paper Source	Specify the paper source for printing incoming fax jobs.
Auto	Note: Auto is the factory default setting.
Tray [x]	
Multipurpose Feeder	
Sides (Duplex)	Enable two-sided printing for incoming fax jobs.
Off	Note: Off is the factory default setting.
On	

Use	То
Separator Sheets Off Before Job After Job	Enable the printer to include separator sheets for incoming fax jobs. Note: Off is the factory default setting.
Separator Sheet Source Tray [x] Multipurpose Feeder	Specify the paper source for the separator sheet. Note: Tray 1 is the factory default setting.
Output Bin Standard Bin Bin [x]	Specify a bin for received faxes. Note: Standard Bin is the factory default setting.
Fax Footer On Off	Print the transmission information at the bottom of each page from a received fax. Note: Off is the factory default setting.
Max Speed 2400 4800 9600 14400 33600	Specify the maximum speed in baud at which faxes are received. Note: 33600 is the factory default setting.
Fax Forwarding Print Print and Forward Forward	Enable forwarding of received faxes to another recipient. Note: Print is the factory default setting.
Forward to Fax E-mail FTP LDSS eSF	Specify the type of recipient to which faxes are forwarded. Notes: Fax is the factory default setting. This menu is available only from the printer Embedded Web Server.
Forward to Shortcut	Enter the shortcut number which matches the recipient type (Fax, E-mail, FTP, LDSS, or eSF).
Block No Name Fax Off On	Enable blocking of incoming faxes sent from devices with no station ID or fax ID specified. Note: Off is the factory default setting.
Banned Fax List Holding Faxes Held Fax Mode Off Always On Manual Scheduled Fax Holding Schedule	Enable the list of blocked fax numbers stored in the printer. Enable fax holding all of the time or according to set schedule. Note: Off is the factory default setting.

Use	То
Punch Off On	 Specify whether prints are punched. Notes: Off is the factory default setting. This menu item appears only when a staple, hole punch finisher is installed.
Staple Off 1 staple 2 staples 4 staples	Specify whether prints are stapled. Notes: Off is the factory default setting. This menu item appears only when a staple finisher is installed.
Enable Color Fax Receive On Off	Enable the printer to receive fax in color and print it in grayscale. Note: On is the factory default setting.

Fax Log Settings

Use	То
Transmission Log	Enable printing of a transmission log after each fax job.
Print log	Note: Print log is the factory default setting.
Do not print log	
Print only for error	
Receive Error Log	Enable printing of a receive error log following a receive error.
Print Never	Note: Print Never is the factory default setting.
Print on Error	
Auto Print Logs	Enable automatic printing of fax logs.
On	Notes:
Off	On is the factory default setting.
	Logs print after every 200 fax jobs.
Log Paper Source	Specify the source of the paper used for printing logs.
Tray [x]	Note: Tray 1 is the factory default setting.
Multipurpose Feeder	
Logs Display Remote Station Name	Specify whether printed logs display the dialed number or the station name or fax name returned.
Dialed Number	Note: Remote Station Name is the factory default setting.
Enable Job Log	Enable access to the Fax Job log.
On	Note: On is the factory default setting.
Off	
Enable Call Log	Enable access to the Fax Call log.
On	Note: On is the factory default setting.
Off	

Use	То
Log Output Bin	Specify the bin for the printed fax logs.
Standard Bin	Note: Standard Bin is the factory default setting.
Bin [x]	

Speaker Settings

Use	То
Speaker Mode	Specify the mode of the speaker.
Always Off	Note: On until Connected is the factory default setting. A sound is issued until
On until Connected	the fax connection is made.
Always On	
Speaker Volume	Control the volume setting.
High	Note: High is the factory default setting.
Low	
Ringer Volume	Control the fax speaker ringer volume.
Off	Note: On is the factory default setting.
On	

Answer On

Use	То
All Rings	Specify ring patterns when the printer is answering calls.
Single Ring Only	Note: All Rings is the factory default setting.
Double Ring Only	
Triple Ring Only	
Single or Double Rings Only	
Single or Triple Rings Only	
Double or Triple Rings Only	

E-mail Settings menu

Use	То
E-mail Server Setup	Specify e-mail server information.
Subject	
Message	
File Name	
Send me a copy	
Max e-mail size	
Size Error Message	
Limit destinations	
Web Link Setup	

Use	То
Format PDF (.pdf) Secure PDF TIFF (.tif) JPEG (.jpg)	Specify the format of the scanned file. Note: PDF (.pdf) is the factory default setting.
XPS (.xps) PDF Version 1.2–1.7 A–1a	Set the version of the PDF file that is scanned for e-mailing. Note: 1.5 is the factory default setting.
Content Type Text Graphics Text/Photo Photo	Specify the content of the original document. Note: Text/Photo is the factory default setting.
Content Source Black/White Laser Color Laser Inkjet Photo/Film Magazine Newspaper Press Other	Specify how the original document was produced. Note: Black/White Laser is the factory default setting.
Color Off On	Specify whether the printer captures and transmits content in color or in black and white. Note: On is the factory default setting.
Resolution 75 dpi 150 dpi 200 dpi 300 dpi 400 dpi 600 dpi	Specify the resolution of the scan in dots per inch. Note: 150 dpi is the factory default setting.
Darkness 1–9	Lighten or darken the output. Note: 5 is the factory default setting.
Orientation Portrait Landscape	Specify the orientation of the scanned image. Note: Portrait is the factory default setting.

Use	То
Original Size Letter Legal Executive Tabloid Folio Statement Oficio (Mexico) Universal Auto Size Sense Mixed Sizes A3 A4 A5 A6 JIS B4 JIS B5 Custom Scan Size [x] Book Original Business Card 3 x 5 in. 4 x 6 in.	Specify the size of the document being scanned. Note: Letter is the U.S. factory default setting. A4 is the international factory default setting.
Sides (Duplex) Off Long edge Short edge	 Specify how text and graphics are oriented on the page. Notes: Off is the factory default setting. Long edge assumes binding along the long edge of the page (left edge for portrait and top edge for landscape). Short edge assumes binding along the short edge of the page (top edge for portrait and left edge for landscape).
JPEG Quality Best for content 5–90	Set the quality of a JPEG photo image in relation to file size and quality of the image. Notes: Best for content is the factory default setting. 5 reduces the file size and quality of the image. 90 provides the best image quality, but the file size is very large. This menu setting applies to all scan functions.
Text Default 5–90	Set the quality of a text image in relation to file size and quality of the image. Note: 75 is the factory default setting.
Text/Photo Default 5–90	Set the quality of a text or photo image in relation to file size and the quality of the image. Note: 75 is the factory default setting.

Use	То
Photo Default 5–90	Set the quality of a photo image in relation to file size and the quality of the image.
	Note: 50 is the factory default setting.
E-mail images sent as	Specify how the images are sent.
Attachment Web Link	Note: Attachment is the factory default setting.
Use Multi-Page Tiff On Off	Choose between single-page TIFF files and multiple-page TIFF files. For a multiple-page scan-to-e-mail job, either one TIFF file is created containing all the pages, or multiple TIFF files are created with one file for each page of the job.
	Notes:
	On is the factory default setting.
	This menu setting applies to all scan functions.
Transmission Log	Specify whether to print the transmission log.
Print log Do not print log Print only for error	Note: Print log is the factory default setting.
Log Paper Source	Specify the paper source for printing e-mail logs.
Tray [x] Multipurpose Feeder	Note: Tray 1 is the factory default setting.
Log Output Bin	Specify the bin for FTP logs.
Standard Bin	Notes:
Bin [x]	Standard Bin is the factory default setting.
	Bin [x] appears only when at least one optional bin is installed.
E-mail Bit Depth 1 bit	Enable the Text/Photo mode to produce smaller file sizes by using 1-bit images when Color is set to Off.
8 bit	Note: 8 bit is the factory default setting.
Custom Job scanning On Off	Copy a document that contains mixed paper sizes.
	Notes:
	Off is the factory default setting.
	This menu item appears only when a formatted, working printer hard disk is installed.
Scan Preview	Specify whether a preview appears on the display for scan jobs.
On Off	Notes:
	Off is the factory default setting.
	This menu item appears only when a formatted, working printer hard disk is installed.

Use	То
Allow Save as Shortcut	Save e-mail addresses as shortcuts.
Off	 Notes: On is the factory default setting. When set to Off, the Save As Shortcut button does not appear on the email Destination screen.
Background Removal -4 to 4	Adjust the amount of background visible on a scanned image. Note: 0 is the factory default setting.
Color Balance Cyan - Red Magenta - Green Yellow - Blue	Enable an equal balance of colors in the scanned image.
Color Dropout Color Dropout None Red Green Blue Default Red Threshold 0-255 Default Green Threshold 0-255 Default Blue Threshold 0-255	Specify which color to drop during scanning and to adjust the dropout setting for each color threshold. Notes: None is the factory default setting for Color Dropout. 128 is the factory default setting for each color threshold.
Contrast 0-5 Best for content	Specify the contrast of the output. Note: Best for content is the factory default setting.
Mirror Image Off On	Create a mirror image of the original document. Note: Off is the factory default setting.
Negative Image Off On	Create a negative image of the original document. Note: Off is the factory default setting.
Shadow Detail -4 to 4	Adjust the amount of shadow detail visible on a scanned image. Note: 0 is the factory default setting.
Scan edge to edge Off On	Specify whether the original document is scanned edge-to-edge. Note: Off is the factory default setting.
Sharpness 1–5	Adjust the amount of sharpness on a scanned image. Note: 3 is the factory default setting.

Use	То
Temperature -4 to 4	Specify warm or cool outputs. Cool values generate a bluer output than the default while warm values generate a redder output than the default. Note: 0 is the factory default setting.
Use cc:/bcc: Off On	Enable the use of the "cc:" and "bcc:" fields. Note: Off is the factory default setting.

FTP Settings menu

Use	То
Format PDF (.pdf) Secure PDF (.pdf) TIFF (.tif) JPEG (.jpg) XPS (.xps)	Specify the format of the file for FTP sending. Note: PDF (.pdf) is the factory default setting.
PDF Version 1.2–1.7 A–1a	Set the version level of the PDF file for FTP sending. Note: 1.5 is the factory default setting.
Content Type Text Graphics Text/Photo Photo	Specify the content of the original document. Note: Text/Photo is the factory default setting.
Content Source Black/White Laser Color Laser Inkjet Photo/Film Magazine Newspaper Press Other	Specify how the original document was produced. Note: Black/White Laser is the factory default setting.
Color Off On	Specify whether the printer captures and transmits content in color or in black and white. Note: On is the factory default setting.
Resolution 75 dpi 150 dpi 200 dpi 300 dpi 400 dpi 600 dpi	Specify the quality of the scan in dots per inch (dpi). Note: 150 dpi is the factory default setting.

Use	То
Darkness	Lighten or darken the output.
1–9	Note: 5 is the factory default setting.
Orientation	Specify the page orientation of the scanned image.
Portrait	Note: Portrait is the factory default setting.
Landscape	
Original Size	Specify the size of the original document.
Letter	Note: Letter is the U.S. factory default setting. A4 is the international factory
Legal	default setting.
Executive	
Folio	
Statement	
Oficio (Mexico)	
Universal	
Auto Size Sense	
Mixed Sizes	
A3	
A4	
A5	
A6	
JIS B4	
JIS B5 Custom Scan Size [x]	
Book Original	
Business Card	
3 x 5 in.	
4 x 6 in.	
Sides (Duplex)	Specify the page orientation of text and graphics.
Off	
Long edge	Notes:
Short edge	Off is the factory default setting.
Short edge	 Long edge assumes binding along the long edge of the page (left edge for portrait and top edge for landscape).
	 Short edge assumes binding along the short edge of the page (top edge for portrait and left edge for landscape).
JPEG Quality	Set the quality of a JPEG photo image in relation to the file size and quality of
Best for content	the image.
5–90	Notes:
	Best for content is the factory default setting.
	 5 reduces the file size, but the quality of the image is lessened.
	 90 provides the best image quality, but the file size is very large.
	 This menu setting applies to all scan functions.
T D. C. II	
Text Default	Set the quality of the text in relation to the file size and quality of the image.
5–90	Note: 75 is the factory default setting.

Use	То
Text/Photo Default 5-90	Set the quality of a text/photo image in relation to the file size and quality of the image. Note: 75 is the factory default setting.
Photo Default 5–90	Set the quality of a photo image in relation to the file size and quality of the image. Note: 50 is the factory default setting.
Use Multi-Page TIFF On Off	Provide a choice between single-page TIFF files and multiple-page TIFF files. For a multiple-page scan-to-FTP job, either one TIFF file is created containing all the pages, or multiple TIFF files are created with one file for each page of the job.
	Notes:
	On is the factory default setting.This menu setting applies to all scan functions.
Transmission Log Print log Do not print log Print only for error	Specify whether to print the transmission log. Note: Print log is the factory default setting.
Log Paper Source Tray [x] Multipurpose Feeder	Specify a paper source when printing FTP logs. Note: Tray 1 is the factory default setting.
Log Output Bin Standard Bin Bin [x]	 Specify the bin for FTP logs. Notes: Standard Bin is the factory default setting. Bin [x] appears only when an optional bin is installed.
FTP bit Depth 1 bit	Enable the Text/Photo mode to have smaller file sizes by using 1-bit images when Color is set to Off.
8 bit	Note: 8 bit is the factory default setting.
File Name Custom Job Scanning On Off	Enter a base file name. Copy a document that contains mixed paper sizes into a single scan job. Notes: Off is the factory default setting. This menu item appears only when a formatted, working printer hard disk is installed.
Scan Preview On Off	Specify whether a preview appears on the display for scan jobs. Notes: Off is the factory default setting. This menu item appears only when a formatted, working printer hard disk is installed.

Use	То
Allow Save as Shortcut On Off	Enable shortcut creation for FTP addresses. Note: On is the factory default setting.
Background Removal -4 to 4	Adjust the amount of background visible on a copy. Note: 0 is the factory default setting.
Color Balance Cyan - Red Magenta - Green Yellow - Blue	Enable an equal balance of colors in the scanned image.
Color Dropout Color Dropout None Red Green Blue Default Red Threshold 0-255 Default Green Threshold 0-255 Default Blue Threshold 0-255	Specify which color to drop during scanning and to adjust the dropout setting for each color threshold. Notes: None is the factory default setting for Color Dropout. 128 is the factory default setting for each color threshold.
Contrast 0-5 Best for content	Specify the contrast of the output. Note: Best for content is the factory default setting.
Mirror Image Off On	Create a mirror image of the original document. Note: Off is the factory default setting.
Negative Image Off On	Create a negative image of the original document. Note: Off is the factory default setting.
Shadow Detail -4 to 4	Adjust the amount of shadow detail visible on a scanned image. Note: 0 is the factory default setting.
Scan edge to edge Off On	Specify whether the original document is scanned edge-to-edge. Note: Off is the factory default setting.
Sharpness 1–5	Adjust the amount of sharpness of a scanned image. Note: 3 is the factory default setting.
Temperature -4 to 4	Specify warm or cool outputs. Cool values generate a bluer output than the default while warm values generate a redder output than the default. Note: 0 is the factory default setting.

Flash Drive menu

Scan Settings

Use	То
Format PDF (.pdf) Secure PDF TIFF (.tif) JPEG (.jpg) XPS (.xps)	Specify the format of the file to be sent through FTP. Note: PDF (.pdf) is the factory default setting.
PDF Version	Set the version of the PDF file to be sent through FTP.
1.2–1.7 A–1a	Note: 1.5 is the factory default setting.
Content Type	Specify the content of the original document.
Text Graphics Text/Photo Photo	Note: Text/Photo is the factory default setting.
Content Source	Specify how the original document was produced.
Black/White Laser Color Laser Inkjet Photo/Film Magazine Newspaper Press Other	Note: Black/White Laser is the factory default setting.
Color On	Specify whether the printer captures and transmits content in color or in black and white.
Off	Note: On is the factory default setting.
Resolution 75 dpi 150 dpi 200 dpi 300 dpi 400 dpi 600 dpi	Specify the resolution of the scan in dots per inch (dpi). Note: 150 dpi is the factory default setting.
Darkness	Lighten or darken the output.
1–9	Note: 5 is the factory default setting.
Orientation	Specify the orientation of the scanned image.
Portrait Landscape	Note: Portrait is the factory default setting.

Use	То
Original Size Letter Legal Executive Folio Statement Oficio (Mexico) Universal Auto Size Sense Mixed Sizes A3 A4 A5 A6 JIS B4 JIS B5 Custom Scan Size [x] Book Original Business Card 3 x 5 in. 4 x 6 in.	Specify the size of the original document. Note: Letter is the U.S. factory default setting. A4 is the international factory default setting.
Sides (Duplex) Off Long edge Short edge	 Specify the page orientation of text and graphics. Notes: Off is the factory default setting. Long edge assumes binding along the long edge of the page (left edge for portrait and top edge for landscape). Short edge assumes binding along the short edge of the page (top edge for portrait and left edge for landscape).
JPEG Quality Best for content 5–90	 Set the quality of a JPEG photo image in relation to file size and quality. Notes: Best for content is the factory default setting. 5 reduces the file size, but the quality of the image is lessened. 90 provides the best image quality, but the file size is very large. This menu applies to all scan functions.
Text Default 5-90 Text/Photo Default 5-90	Set the quality of the text in relation to file size and the quality of the image. Note: 75 is the factory default setting. Set the quality of a text/photo image in relation to file size and quality. Note: 75 is the factory default setting.
Photo Default 5–90	Set the quality of a photo image in relation to file size and quality. Note: 50 is the factory default setting.

Use	То
Use Multi-Page TIFF On Off	Provide a choice between single-page TIFF files and multiple-page TIFF files. For a multiple-page scan to FTP job, either one TIFF file is created containing all the pages, or multiple TIFF files are created with one file for each page. Notes:
	On is the factory default setting.This menu applies to all scan functions.
Scan Bit Depth 1 bit	Enable the Text/Photo mode to have smaller file sizes by using 1-bit images when Color is set to Off.
8 bit	Note: 8 bit is the factory default setting.
File Name	Enter a base file name. Note: A maximum of 53 characters is allowed.
On Off	Copy a document containing mixed paper sizes in a single copy job. Notes: Off is the factory default setting. This menu item appears only when a formatted, working printer hard disk is installed.
Scan Preview On Off	 Specify whether a preview appears on the display for scan jobs. Notes: Off is the factory default setting. This menu item appears only when a formatted, working printer hard disk is installed.
Background Removal	Adjust the amount of background visible on a copy.
-4 to 4	Note: 0 is the factory default setting.
Color Balance Cyan - Red Magenta - Green Yellow - Blue	Enable an equal balance of colors in the scanned image.
Color Dropout Color Dropout None Red Green Blue Default Red Threshold 0-255 Default Green Threshold 0-255 Default Blue Threshold 0-255	Specify which color to drop during scanning and to adjust the dropout setting for each color threshold. Notes: None is the factory default setting for Color Dropout. 128 is the factory default setting for each color threshold.

Use	То
Contrast 0-5 Best for content	Specify the contrast of the scanned image. Note: Best for content is the factory default setting.
Mirror Image Off On	Create a mirror image of the original document. Note: Off is the factory default setting.
Negative Image Off On	Create a negative image of the original document. Note: Off is the factory default setting.
Shadow Detail -4 to 4	Adjust the amount of shadow detail visible on a scanned image. Note: 0 is the factory default setting.
Scan edge to edge Off On	Specify whether the original document is scanned edge-to-edge. Note: Off is the factory default setting.
Sharpness 1–5	Adjust the amount of sharpness on a scanned image. Note: 3 is the factory default setting.
Temperature -4 to 4	Specify warm or cool outputs. Cool values generate a bluer output than the default while warm values generate a redder output than the default. Note: 0 is the factory default setting.

Print Settings

Copies	Specify a default number of copies for each print job.
1–999	Note: 1 is the factory default setting.
Paper Source	Set a default paper source for all print jobs.
Tray [x] Multipurpose Feeder Manual Paper Manual Envelope	Note: Tray 1 is the factory default setting.
Collate (1,1,1) (2,2,2) (1,2,3) (1,2,3)	Stack the pages of a print job in sequence when printing multiple copies. Note: (1,2,3) (1,2,3) is the factory default setting.
Sides (Duplex) 1 sided 2 sided	Specify whether prints are on one side or on both sides of the page. Note: 1 sided is the factory default setting.
Staple Off On	Specify whether prints are stapled. Notes: Off is the factory default setting. This menu item appears only when a staple finisher is installed.

Hole Punch	Specify whether prints have punched holes.
Off	Notes:
On	Off is the factory default setting.
	 This menu item appears only when a supported staple, hole punch finisher is installed.
Hole Punch Mode	Specify the number of holes to be made on the prints.
2 holes	Notes:
3 holes 4 holes	• 3 holes is the U.S. factory default setting. 4 holes is the international factory default setting.
	This menu item appears only when a supported staple, hole punch finisher is installed.
Duplex Binding Long edge	Define binding for two-sided pages in relation to the page orientation of the printed document.
Short edge	Notes:
	 Long edge assumes binding along the long edge of the page (left edge for portrait and top edge for landscape).
	Short edge assumes binding along the short edge of the page (top edge for portrait and left edge for landscape).
Paper Saver Orientation	Specify the orientation of a multiple-page document.
Auto Landscape Portrait	Note: Auto is the factory default setting. The printer chooses between portrait and landscape.
Paper Saver	Specify that multiple-page images be printed on one side of a paper.
Off	Notes:
2-Up	Off is the factory default setting.
3-Up 4-Up	The number selected is the number of page images that are printed per side.
4-Up	
9-Up	
12-Up	
16-Up	
Paper Saver Border	Print a border on each page image.
None Solid	Note: None is the factory default setting.
Paper Saver Ordering	Specify the positioning of multiple-page images.
Horizontal	Notes:
Reverse Horizontal	Horizontal is the factory default setting.
Reverse Vertical Vertical	Positioning depends on the number of page images and whether they are in portrait or landscape orientation.

Separator Sheets	Specify whether blank separator sheets are inserted.
Off Between Copies Between Jobs Between Pages	 Notes: Off is the factory default setting. Between Copies inserts a blank sheet between each copy of a print job if Collate is set to (1,2,3) (1,2,3). If Collate is set to (1,1,1) (2,2,2), then a blank page is inserted between each set of printed pages, such as after all page 1's and after all page 2's. Between Jobs inserts a blank sheet between print jobs. Between Pages inserts a blank sheet between each page of the print job. This setting is useful when printing transparencies or when inserting blank pages in a document.
Separator Sheet Source Tray [x] Multipurpose Feeder	Specify the paper source for the separator sheet. Note: Tray 1 is the factory default setting.
Blank Pages Do Not Print Print	Specify whether blank pages are inserted in a print job. Note: Do Not Print is the factory default setting.

Print Settings

Setup menu

•		
Use	То	
Printer Language	Set the default printer language.	
PCL Emulation	Notes:	
PS Emulation	PCL Emulation is the factory default setting.	
	 PostScript emulation uses a PostScript interpreter for processing print jobs. 	
	 PCL Emulation uses a PCL interpreter for processing print jobs. 	
	 Setting a printer language default does not prevent a software program from sending print jobs that use another printer language. 	
Job Waiting	Determine if print jobs are removed from the print queue when	
On	they require unavailable printer options or custom settings.	
Off	These print jobs are stored in a separate print queue, so other jobs print normally. When the missing information or options, or both are obtained, the stored jobs print.	
	Notes:	
	Off is the factory default setting.	
	 This menu appears only if a non-read-only printer hard disk is installed. This requirement ensures that stored jobs are not deleted if the printer loses power. 	

Use	То
Print Area	Set the logical and physical printable area.
Normal Whole Page	Notes:
	 Normal is the factory default setting. When attempting to print data in the non-printable area defined by the Normal setting, the printer clips the image at the boundary. Whole Page allows the image to be moved into the non-printable area defined by the Normal setting, but the printer clips the image at the Normal setting boundary. This setting affects only pages printed using a PCL 5e interpreter and has no effect on pages printed using the PCL XL or PostScript interpreter.
Download Target	Set the storage location for downloads.
RAM	Notes:
Flash Disk	 RAM is the factory default setting. Storing downloads in the RAM is temporary.
	 Storing downloads in a flash memory or in a printer hard disk places them in permanent storage. Downloads remain in the flash memory or printer hard disk even when the printer is turned off.
	 This menu item appears only if an optional flash memory or printer hard disk is installed.
Resource Save On Off	Specify how the printer handles temporary downloads, such as fonts and macros stored in the RAM, when the printer receives a print job that requires more than the available memory.
	Notes:
	 Off is the factory default setting. Off sets the printer to retain downloads only until memory is needed. Downloads are deleted in order to process print jobs.
	 On sets the printer to retain downloads during language changes and printer resets. If the printer runs out of memory, then Memory Full [38] appears on the printer display, but downloads are not deleted.
Print All Order	Specify the order in which held and confidential jobs are
Alphabetical	printed when Print All is selected.
Oldest First Newest First	Note: Alphabetical is the factory default setting

Finishing menu

Use	То
Sides (Duplex)	Specify whether two-sided printing is set as the default for all print jobs.
1 sided 2 sided	Notes:
	1 sided is the factory default setting.
	You can set two-sided printing from the printer software.
Duplex Binding	Define the way two-sided pages are bound and printed.
Long Edge	Notes:
Short Edge	 Long Edge is the factory default setting. This assumes binding along the long edge of the page (left edge for portrait and top edge for landscape). Short Edge assumes binding along the short edge of the page (top edge for portrait and left edge for landscape).
Copies	Specify the default number of copies for each print job.
1–999	Note: 1 is the factory default setting.
Blank Pages	Specify whether blank pages are inserted in a print job.
Do Not Print	Note: Do Not Print is the factory default setting.
Print	
(111) (2.2.2)	Stack the pages of a print job in sequence when printing multiple copies.
(1,1,1) (2,2,2) (1,2,3) (1,2,3)	Note: (1,2,3) (1,2,3) is the factory default setting.
Separator Sheets	Specify whether blank separator sheets are inserted.
Off	Notes:
Between Copies Between Jobs	Off is the factory default setting.
Between Pages	 Between Copies inserts a blank sheet between each copy of a print job if Collate is set to (1,2,3) (1,2,3). If Collate is set to (1,1,1) (2,2,2), then a blank page is inserted between each set of printed pages, such as after all page 1's and after all page 2's.
	Between Jobs inserts a blank sheet between print jobs.
	 Between Pages inserts a blank sheet between each page of a print job. This setting is useful when printing transparencies or when inserting blank pages in a document.
Separator Source	Specify the paper source for the separator sheet.
Tray [x]	Notes:
Multipurpose Feeder	Tray 1 (standard tray) is the factory default setting.
	From the Paper menu, set Configure MP to "Cassette" for Multipurpose Feeder to appear as a menu setting.

Use	То
Paper Saver Off 2-Up 3-Up 4-Up 6-Up 9-Up 12-Up 16-Up	Print multiple-page images on one side of a paper. Notes: Off is the factory default setting. The number selected is the number of page images that are printed per side.
Paper Saver Ordering Horizontal Reverse Horizontal Reverse Vertical Vertical	 Specify the positioning of multiple-page images when using Paper Saver. Notes: Horizontal is the factory default setting. Positioning depends on the number of page images and whether they are in portrait or landscape orientation.
Paper Saver Orientation Auto Landscape Portrait	Specify the orientation of a multiple-page document. Note: Auto is the factory default setting. The printer chooses between portrait and landscape.
Paper Saver Border None Solid	Print a border when using Paper Saver. Note: None is the factory default setting.
Staple Job Auto Back Dual Front Off	Specify whether printed output is stapled. Notes: Off is the factory default setting. This menu appears only when a supported staple finisher is installed.
Run Stapler Test	Print a report that confirms that the staple finisher is functioning properly. Note: This menu appears only when a supported staple finisher is installed.
Hole Punch On Off	Specify whether holes are created on printed outputs for the purpose of collecting the sheets in a binder or folder. Notes: Off is the factory default setting. This menu appears only when a supported staple, hole punch finisher is installed.

Use	То
Hole Punch Mode 2 holes	Specify the number of holes to be created on printed outputs for the purpose of collecting the sheets in a binder or folder.
3 holes 4 holes	Notes: • 3 holes is the U.S. factory default setting. 4 holes is the international factory default setting.
	 This menu appears only when a supported staple, hole punch finisher is installed.
Offset Pages None Between Copies Between Jobs	 Offset pages at certain instances. Notes: None is the factory default setting. Between Copies offsets each copy of a print job if Collate is set to (1,2,3) (1,2,3). If Collate is set to (1,1,1) (2,2,2), then each set of printed pages are offset, such as all page 1's and all page 2's. Between Jobs sets the same offset position for the entire print job regardless of the number of copies printed. This menu appears only when a supported staple finisher is installed.

Quality menu

Use	То
Print Resolution	Specify the printed output resolution in dots per inch (dpi) or image quality.
300 dpi	Note: 600 dpi is the factory default setting.
600 dpi	
1200 dpi	
1200 Image Q	
2400 Image Q	
Pixel Boost	Enable more pixels to clarify and enhance images or text.
Off	Note: Off is the factory default setting.
Fonts	
Horizontally	
Vertically	
Both directions	
Toner Darkness	Determine the darkness of the printed output.
1–10	Notes:
	8 is the factory default setting.
	Selecting a smaller number can help conserve toner.

Use	То
Enhance Fine Lines On Off	Enhance the printed output to have smoother lines with sharper edges. Notes:
Oil	Off is the factory default setting.
	 You can set this option from the printer software. For Windows users, click File > Print, and then click Properties or Preferences. For Macintosh users, choose File > Print, and then adjust the settings from the Print dialog and context menus.
	 To set this option using the Embedded Web Server, type the network printer IP address in the Web browser address field.
Gray Correction	Adjust the contrast enhancement applied to images.
Auto Off	Note: Auto is the factory default setting.
Brightness	Lighten or darken the printed output.
-6 to 6	Note: 0 is the factory default setting.
Contrast	Adjust the contrast of printed objects.
0-5	Note: 0 is the factory default setting.

Job Accounting menu

Note: This menu item appears only when a formatted, working printer hard disk is installed.

Use	То	
Job Accounting Log Off On	Determine and set if the printer creates a log of the print jobs it receives. Note: Off is the factory default setting.	
Job Accounting Utilities	Print and delete log files or export them to a flash drive.	
Accounting Log Frequency Daily Weekly Monthly	Note: Monthly is the factory default setting.	
None E-mail Current Log E-mail & Delete Current Log Post Current Log Post & Delete Current Log	Determine and set how the printer responds when the frequency threshold expires. Note: None is the factory default setting.	
Log Near Full Level Off 1–99	Specify the maximum size of the log file before the printer executes the Log Action at Near Full. Note: 5 is the factory default setting.	

Use	То
Log Action at Near Full None E-mail Current Log E-mail & Delete Current Log E-mail & Delete Oldest Log Post Current Log Post & Delete Current Log Post & Delete Oldest Log Delete Current Log Delete Current Log Delete All Logs Delete All But Current Log Action at Full None E-mail & Delete Current Log E-mail & Delete Current Log Post & Delete Current Log Delete Current Log Post & Delete Current Log Post & Delete Current Log Delete All Logs Delete All Logs Delete All But Current	Determine and set how the printer responds when the hard disk is nearly full. Notes: None is the factory default setting. The value defined in Log Near Full Level determines when this action is triggered. Determine and set how the printer responds when disk usage reaches the maximum limit (100MB). Note: None is the factory default setting.
URL to Post Logs	Determine and set where the printer posts job accounting logs.
E-mail Address to Send Logs	Specify the e-mail address to which the printer sends job accounting logs.
Log File Prefix	Specify the prefix you want for the log file name. Note: The current host name defined in the TCP/IP menu is used as the default log file prefix.

Utilities menu

Use	То	
Remove Held Jobs Confidential	Delete confidential and held jobs from the printer hard disk. Notes:	
Held Not Restored All	 Selecting a setting affects only print jobs that are resident in the printer. Bookmarks, print jobs on flash drives, and other types of held jobs are not affected. 	
	 Not Restored removes all Print and Hold jobs that are not restored from the printer hard disk or memory. 	

Use	То		
Format Flash	Format the flash memory.		
Yes No	Warning—Potential Damage: Do not turn off the printer while the flash memory is being formatted.		
	Notes:		
	Yes deletes all data stored in flash memory.		
	No cancels the format request.		
	 Flash memory refers to the memory added by installing a flash memory card in the printer. 		
	The flash memory option card must not be read/write- or write-protected.		
	This menu item appears only when a non-defective flash memory card is installed.		
Delete Downloads on Disk Delete Now	Delete downloads from the printer hard disk, including all held jobs, buffered jobs, and parked jobs.		
Do Not Delete	Notes:		
	Delete Now sets the printer to delete the downloads and allows the display to return to the originating screen after the deletion.		
	Do Not Delete sets the printer to return to the originating screen after the deletion.		
Activate Hex Trace	Assist in isolating the source of a print job problem.		
	Notes:		
	When activated, all data sent to the printer is printed in hexadecimal and character representation, and control codes are not executed.		
	To exit or deactivate Hex Trace, turn off or reset the printer.		
Coverage Estimator	Provide an estimate of the percentage coverage of toner on a page. The		
Off	estimate is printed on a separate page at the end of each print job.		
On	Note: Off is the factory default setting.		

XPS menu

Use	То	
Print Error Pages	Print a page containing information on errors, including XML markup errors.	
Off	Note: Off is the factory default setting.	
On		

PDF menu

Use	То	
Scale to Fit	Scale page content to fit the selected paper size.	
Yes	Note: No is the factory default setting.	
No	-	

Use	То	
Annotations	Print annotations in a PDF.	
Do Not Print	Note: Do Not Print is the factory default setting.	
Print		

PostScript menu

Use	То	
Print PS Error	Print a page containing the PostScript error.	
On	Note: Off is the factory default setting.	
Off		
Lock PS Startup Mode	Disable the SysStart file.	
On	Note: Off is the factory default setting.	
Off		
Font Priority	Establish the font search order.	
Resident	Notes:	
Flash/Disk	Resident is the factory default setting.	
	 This menu item is available only when a formatted flash memory option card or printer hard disk is installed and operating properly. 	
	 Make sure the flash memory option or printer hard disk is not read/write-, write-, or password-protected. 	
	Job Buffer Size must not be set to 100%.	

PCL Emul menu

Use	То	
Font Source Resident Disk Download Flash All	 Specify the set of fonts used by the Font Name menu. Notes: "Resident" is the factory default setting. Resident shows the factory default set of fonts downloaded in the RAM. "Flash" and "Disk" settings show all fonts resident in that option. The flash option must be properly formatted and cannot be read/write-, write-, or password-protected. "Download" shows all the fonts downloaded in the RAM. "All" shows all fonts available to any option. 	
Font Name Courier 10	Identify a specific font and the option where it is stored. Note: Courier 10 is the factory default setting. Courier 10 shows the font name, font ID, and the storage location in the printer. The font source abbreviation is R for Resident, F for Flash, K for Disk, and D for Download.	

Use	То		
Symbol Set 10U PC-8 12U PC-850	 Specify the symbol set for each font name. Notes: 10U PC-8 is the US factory default setting. 12U PC-850 is the international factory default setting. A symbol set is a set of alphabetic and numeric characters, punctuation, and special symbols. Symbol sets support the different languages or specific programs such as math symbols for scientific text. Only the supported symbol sets are shown. 		
PCL Emulation Settings Point Size 1.00–1008.00	Change the point size for scalable typographic fonts. Notes: 12 is the factory default setting. Point size refers to the height of the characters in the font. One point equals approximately 0.014 inch. Point sizes can be increased or decreased in 0.25-point increments.		
PCL Emulation Settings Pitch 0.08–100	Specify the font pitch for scalable monospaced fonts. Notes: 10 is the factory default setting. Pitch refers to the number of fixed-space characters per inch (cpi). Pitch can be increased or decreased in 0.01-cpi increments. For nonscalable monospaced fonts, the pitch appears on the display but it cannot be changed.		
PCL Emulation Settings Orientation Portrait Landscape	Specify the orientation of text and graphics on the page. Notes: Portrait is the factory default setting. Portrait prints text and graphics parallel to the short edge of the page. Landscape prints text and graphics parallel to the long edge of the page.		
PCL Emulation Settings Lines per Page 1–255	 Specify the number of lines that print on each page. Notes: 60 is the US factory default setting. 64 is the international default setting. The printer sets the amount of space between each line based on the Lines per Page, Paper Size, and Orientation settings. Select the Paper Size and Orientation you want before setting Lines per Page. 		
PCL Emulation Settings A4 Width 198 mm 203 mm	Set the printer to print on A4-size paper. Notes: • "198 mm" is the factory default setting. • The 203-mm setting sets the width of the page to allow printing of eighty 10-pitch characters.		

Use	То	
PCL Emulation Settings Auto CR after LF	Specify whether the printer automatically performs a carriage return (CR) after a line feed (LF) control command.	
On Off	Note: Off is the factory default setting.	
PCL Emulation Settings Auto LF after CR On	Specify whether the printer automatically performs a line feed (LF) after a carriage return (CR) control command. Note: Off is the factory default setting.	
Off		
Tray Renumber Assign MP Feeder Off None 0–199 Assign Tray [x] Off None 0–199 Assign Manual Paper Off None 0–199 Assign Manual Env Off None 0–199	Configure the printer to work with printer software or programs that use different source assignments for trays and feeders. Notes: • "Off" is the factory default setting. • "None" ignores the Select Paper Feed command. This option appears only when it is selected by the PCL 5 interpreter. • "0–199" allows a custom setting to be assigned.	
Tray Renumber View Factory Defaults MPF Default = 8 T1 Default = 1 T1 Default = 4 T1 Default = 5 T1 Default = 20 T1 Default = 21 Env Default = 6 MPaper Default = 2 MEnv Default = 3	Display the factory default setting assigned to each tray or feeder.	
Tray Renumber Restore Defaults Yes No	Restore all tray and feeder assignments to the factory default settings.	

HTML menu

Use		То
Font Name	Joanna MT	Set the default font for HTML documents.
Albertus MT	Letter Gothic	Note: The Times font is used in HTML documents that do
Antique Olive	Lubalin Graph	not specify a font.
Apple Chancery	Marigold	
Arial MT	MonaLisa Recut	
Avant Garde	Monaco	
Bodoni	New CenturySbk	
Bookman	New York	
Chicago	Optima	
Clarendon	Oxford	
Cooper Black	Palatino	
Copperplate	StempelGaramond	
Coronet	Taffy	
Courier	Times	
Eurostile	TimesNewRoman	
Garamond	Univers	
Geneva	Zapf Chancery	
Gill Sans	NewSansMTJA	
Goudy	NewSansMTCS	
Helvetica	NewSansMTCT	
Hoefler Text	NewSansMTKO	
Intl CG Times		
Intl Courier		
Intl Univers		

Use	То	
Font Size	Set the default font size for HTML documents.	
1–255 pt	Notes:	
	• 12 pt is the factory default setting.	
	Font size can be increased in 1-point increments.	
Scale	Scale the default font for HTML documents.	
1–400%	Notes:	
	• 100% is the factory default setting.	
	Scaling can be increased in 1% increments.	
Orientation	Set the page orientation for HTML documents.	
Portrait Landscape	Note: Portrait is the factory default setting.	
Margin Size	Set the page margin for HTML documents.	
8–255 mm	Notes:	
	• 19 mm is the factory default setting.	
	Margin size can be increased in 1-mm increments.	

Use	То
Backgrounds	Specify whether to print backgrounds on HTML documents.
Do Not Print	Note: Print is the factory default setting.
Print	

Image menu

Use	То
Auto Fit	Select the optimal paper size, scaling, and orientation.
On Off	Note: On is the factory default setting. It overrides scaling and orientation settings for some images.
Invert	Invert bitonal monochrome images.
On Off	Notes:Off is the factory default setting.This setting does not apply to GIF or JPEG images.
Scaling Anchor Top Left Best Fit Anchor Center Fit Height/Width Fit Height Fit Width	Scale the image to fit the selected paper size. Notes: Best Fit is the factory default setting. When Auto Fit is set to On, Scaling is automatically set to Best Fit.
Orientation Portrait Landscape Reverse Portrait Reverse Landscape	Set the image orientation. Note: Portrait is the factory default setting.

Help menu

Menu item	Description
Print All Guides	Prints all the guides
Copy Guide	Provides information about making copies and configuring the settings
E-mail Guide	Provides information about sending e-mails and configuring the settings
Fax Guide	Provides information about sending faxes and configuring the settings
FTP Guide	Provides information about scanning documents and configuring the settings
Print Defects Guide	Provides a template for determining the cause of repeating print quality defects, and lists settings that can be used to adjust print quality
Information Guide	Provides help in locating additional information
Supplies Guide	Provides information about ordering supplies

Saving money and the environment

Lexmark is committed to environmental sustainability and is continually improving its printers to reduce their impact on the environment. We design with the environment in mind, engineer our packaging to reduce materials, and provide collection and recycling programs. For more information, see:

- The Notices chapter
- The Environmental Sustainability section of the Lexmark Web site at www.lexmark.com/environment
- The Lexmark recycling program at www.lexmark.com/recycle

By selecting certain printer settings or tasks, you may be able to reduce your printer's impact even further. This chapter outlines the settings and tasks that may yield a greater environmental benefit.

Saving paper and toner

Studies show that as much as eighty percent of the carbon footprint of a printer is related to paper usage. You can significantly reduce your carbon footprint by using recycled paper and the following printing suggestions, such as printing on both sides of the paper and printing multiple pages on one side of a single sheet of paper.

Using recycled paper

As an environmentally conscious company, Lexmark supports the use of recycled office paper produced specifically for use in laser printers. For more information on recycled papers that work well with your printer, see "Using recycled paper and other office papers" on page 61.

Conserving supplies

Use both sides of the paper

If your printer model supports two-sided printing, then you can control whether print appears on one or two sides of the paper.

Notes:

- Two-sided printing is the default setting in the print driver.
- For a complete list of supported products and countries, go to http://support.lexmark.com.

Place multiple pages on one sheet of paper

You can print up to 16 consecutive pages of a multiple-page document onto one side of a single sheet of paper by setting multiple page printing (N-Up) for the print job.

Check your first draft for accuracy

Before printing or making multiple copies of a document:

- Use the preview feature to see how the document looks like before you print it.
- Print one copy of the document to check its content and format for accuracy.

Avoid paper jams

Correctly set the paper type and size to avoid paper jams. For more information, see <u>"Avoiding jams" on page 241</u>.

Saving energy

Using Hibernate mode

Hibernate is an ultra-low-power operating mode.

Notes:

- Three days is the default amount of time before the printer enters Hibernate mode.
- Make sure to wake the printer from Hibernate mode before sending a print job. A hard reset or a long press of the Sleep button wakes the printer from Hibernate mode.
- If the printer is in Hibernate mode, then the Embedded Web Server is disabled.
- **1** From the home screen, navigate to:
 - > Settings > General Settings
- **2** From the "Press Sleep Button" or "Press and Hold Sleep Button" menu, select **Hibernate**, and then touch **Submit**.

Using Eco-Mode

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > General Settings > Eco-Mode > select a setting

Use	То	
Off	Use the factory default settings for all settings associated with Eco-Mode. Off supports the performance specifications of the printer.	
Energy	Reduce energy use, especially when the printer is idle.	
	• Printer engine motors do not start until it is ready to print. You may notice a short delay before the first page is printed.	
	The printer enters Sleep mode after one minute of inactivity.	
Energy/Paper	Use all the settings associated with Energy and Paper modes.	
Plain Paper	Enable the automatic two-sided (duplex) feature.	
	Turn off print log features.	

3 Click Submit.

Adjusting Sleep mode

1 From the home screen, navigate to:



> Settings > General Settings > Timeouts > Sleep Mode

- 2 In the Sleep Mode field, select the number of minutes the printer is idle before it enters Sleep mode.
- 3 Apply the changes.

Adjusting the brightness of the printer display

To save energy, or if you have trouble reading the display, adjust its brightness settings.

Using the Embedded Web Server

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address in the TCP/IP section in the Network/Ports menu. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings > General Settings.
- 3 In the Screen Brightness field, enter the brightness percentage you want for the display.
- 4 Click Submit.

Recycling

Lexmark provides collection programs and environmentally progressive approaches to recycling. For more information, see:

- The Notices chapter
- The Environmental Sustainability section of the Lexmark Web site at www.lexmark.com/environment
- The Lexmark recycling program at www.lexmark.com/recycle

Recycling Lexmark products

To return Lexmark products for recycling:

- 1 Go to www.lexmark.com/recycle.
- 2 Find the product type you want to recycle, and then select your country or region from the list.
- **3** Follow the instructions on the computer screen.

Note: Printer supplies and hardware not listed in the Lexmark collection program may be recycled through your local recycling center. Contact your local recycling center to determine the items they accept.

Recycling Lexmark packaging

Lexmark continually strives to minimize packaging. Less packaging helps to ensure that Lexmark printers are transported in the most efficient and environmentally sensitive manner and that there is less packaging to dispose of. These efficiencies result in fewer greenhouse emissions, energy savings, and natural resource savings.

Lexmark cartons are 100% recyclable where corrugated recycling facilities exist. Facilities may not exist in your area

The foam used in Lexmark packaging is recyclable where foam recycling facilities exist. Facilities may not exist in your area.

When you return a cartridge to Lexmark, you can reuse the box that the cartridge came in. Lexmark will recycle the box.

Returning Lexmark cartridges for reuse or recycling

Lexmark Cartridge Collection Program diverts millions of Lexmark cartridges from landfills annually by making it both easy and free for Lexmark customers to return used cartridges to Lexmark for reuse or recycling. One hundred percent of the empty cartridges returned to Lexmark are either reused or demanufactured for recycling. Boxes used to return the cartridges are also recycled.

To return Lexmark cartridges for reuse or recycling, follow the instructions that came with your printer or cartridge and use the prepaid shipping label. You can also do the following:


- 1 Go to www.lexmark.com/recycle.
- **2** From the Toner Cartridges section, select your country or region.
- **3** Follow the instructions on the computer screen.

Securing the printer 201

Securing the printer

Using the security lock feature

The printer is equipped with a security lock feature. When a lock compatible with most laptop computers is attached, the printer is locked. When locked, the controller board shield and the controller board cannot be removed. Attach a security lock to the printer in the location shown.



Statement of Volatility

Your printer contains various types of memory that can store device and network settings, and user data.

Type of memory	Description
Volatile memory	Your printer uses standard <i>random access memory</i> (RAM) to temporarily buffer user data during simple print jobs.
Non-volatile memory	Your printer may use two forms of non-volatile memory: EEPROM and NAND (flash memory). Both types are used to store the operating system, device settings, network information, bookmark settings, and embedded solutions.
Hard disk memory	Some printers have a hard disk drive installed. The printer hard disk is designed for device-specific functionality. This lets the device retain buffered user data from complex print jobs, as well as form data, and font data.

Erase the content of any installed printer memory in the following circumstances:

- The printer is being decommissioned.
- The printer hard disk is being replaced.
- The printer is being moved to a different department or location.
- The printer is being serviced by someone from outside your organization.
- The printer is being removed from your premises for service.
- The printer is being sold to another organization.

Disposing of a printer hard disk

Note: Some printer models may not have a printer hard disk installed.

Securing the printer 202

In high-security environments, it may be necessary to take additional steps to make sure that confidential data stored in the printer hard disk cannot be accessed when the printer—or its hard disk—is removed from your premises.

- Degaussing—Flushes the hard disk with a magnetic field that erases stored data
- Crushing—Physically compresses the hard disk to break component parts and render them unreadable
- Milling—Physically shreds the hard disk into small metal bits

Note: Most data can be erased electronically, but the only way to guarantee that all data is completely erased is to physically destroy each hard disk where data is stored.

Erasing volatile memory

The volatile memory (RAM) installed in your printer requires a power source to retain information. To erase the buffered data, simply turn off the printer.

Erasing non-volatile memory

Erase individual settings, device and network settings, security settings, and embedded solutions by following these steps:

- 1 Turn off the printer.
- **2** From the control panel, hold down **2** and **6** while turning the printer on. Release the buttons when the screen with the progress bar appears.
- **3** From the Configuration menu, navigate to:

Restore Factory Defaults > Erase Printer Memory > Yes

The printer restarts several times during this process.

4 Touch **Back**, and then exit the Configuration menu.

Note: The printer performs a power-on reset, and then returns to normal operating mode.

Erasing printer hard disk memory

- **1** Turn off the printer.
- **2** From the control panel, hold down **2** and **6** while turning the printer on. Release the buttons when the screen with the progress bar appears.
- **3** From the Configuration menu, navigate to:

Restore Factory Defaults > Erase Hard Disk > select the method to erase the hard disk memory > **Yes**

Note: This process can take from several minutes to more than an hour, during which the printer is unavailable for other user tasks.

4 Touch **Back**, and then exit the Configuration menu.

Note: The printer performs a power-on reset, and then returns to normal operating mode.

Securing the printer 203

Configuring printer hard disk encryption

Enable hard disk encryption to prevent loss of sensitive data in the event the printer or its hard disk is stolen.

Note: Some printer models may not have a hard disk installed.

- **1** Turn off the printer.
- **2** From the control panel, hold down **2** and **6** while turning the printer on. Release the buttons only when the screen with the progress bar appears.
- 3 Touch Disk Encryption > Enable.

Note: Enabling disk encryption erases the contents of the hard disk.

4 Touch **Yes** to proceed with disk wiping.

Notes:

- Do not turn off the printer during the encryption process. Doing so may result in loss of data.
- Disk encryption can take from several minutes to more than an hour, during which the printer is unavailable for other user tasks.
- A status bar indicates the progress of the disk wiping task. After the disk is encrypted, the printer returns to the Enable/Disable screen.
- **5** Touch **Back**, and then exit the Configuration menu.

Note: The printer performs a power-on reset, and then returns to normal operating mode.

Finding the printer security information

In high-security environments, it may be necessary to take additional steps to make sure that confidential data stored in the printer cannot be accessed by unauthorized persons. For more information, go to the Lexmark security Web page or see the Embedded Web Server—Security: Administrator's Guide at http://support.lexmark.com.

Maintaining the printer

Warning—Potential Damage: Failure to maintain optimum printer performance, or to replace parts and supplies, may cause damage to your printer.

Cleaning printer parts

Cleaning the printer

Note: You may need to perform this task after every few months.

Warning—Potential Damage: Damage to the printer caused by improper handling is not covered by the printer warranty.

1 Make sure that the printer is turned off and unplugged from the electrical outlet.



CAUTION—SHOCK HAZARD: To avoid the risk of electrical shock when cleaning the exterior of the printer, unplug the power cord from the electrical outlet and disconnect all cables from the printer before proceeding.

- **2** Remove paper from the standard bin and multipurpose feeder.
- **3** Remove any dust, lint, and pieces of paper around the printer using a soft brush or vacuum.
- **4** Dampen a clean, lint-free cloth with water, and use it to wipe the outside of the printer.

Warning—Potential Damage: Do not use household cleaners or detergents to prevent damage to the exterior of the printer.

5 Make sure all areas of the printer are dry before sending a new print job.

Cleaning the scanner glass

Clean the scanner glass if you encounter print quality problems, such as streaks on copied or scanned images.

1 Open the scanner cover.



2 Wipe the areas shown with a soft or lint-free cloth.



1	White underside of the scanner cover
2	Scanner glass
3	ADF glass
4	White underside of the ADF cover


3 Close the scanner cover.

Cleaning the charger and the printhead lens


1 Open the bottom front door.




2 Remove the waste toner bottle.



3 Locate the white tab.




4 Gently pull the tab until it stops, and then slowly slide it back into place. Repeat three times.




Remove the printhead wiper.



Insert the wiper into the hole until it stops, and then slide it out. Repeat three times.



- 7 Put the wiper back to its holder.
- Reinstall the waste toner bottle.



Close the bottom front door.

Emptying the hole punch box


1 Open door H.



2 Remove and empty the hole punch box.



3 Reinstall the hole punch box.



4 Close door H.

Checking the status of parts and supplies

A message appears on the display when a replacement supply item is needed or when maintenance is required.

Checking the status of parts and supplies on the printer control panel

From the home screen, touch **Status/Supplies** > **View Supplies**.

Checking the status of parts and supplies from the Embedded Web Server

Note: Make sure the computer and the printer are connected to the same network.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Device Status > More Details.

Estimated number of remaining pages

The estimated number of remaining pages is based on the recent printing history of the printer. Its accuracy may vary significantly and is dependent on many factors, such as actual document content, print quality settings, and other printer settings.

The accuracy of the estimated number of remaining pages may decrease when the actual printing consumption is different from the historical printing consumption. Consider the variable level of accuracy before purchasing or replacing supplies based on the estimate. Until an adequate print history is obtained on the printer, initial estimates assume future supplies consumption based on the International Organization for Standardization* test methods and page content.

* Average continuous black declared cartridge yield in accordance with ISO/IEC 19752.

Ordering supplies

To order parts and supplies in the U.S., contact Lexmark at 1-800-539-6275 for information about Lexmark Authorized Supplies Dealers in your area. In other countries or regions, go to the Lexmark Web site at www.lexmark.com or contact the place where you purchased the printer.

Note: All life estimates for printer supplies assume printing on letter- or A4-size plain paper.

Using genuine Lexmark parts and supplies

Your Lexmark printer is designed to function best with genuine Lexmark supplies and parts. Use of third-party supplies or parts may affect the performance, reliability, or life of the printer and its imaging components. Use of third-party supplies or parts can affect warranty coverage. Damage caused by the use of third-party supplies or parts is not covered by the warranty. All life indicators are designed to function with Lexmark supplies and parts, and may deliver unpredictable results if third-party supplies or parts are used. Imaging component usage beyond the intended life may damage your Lexmark printer or its associated components.

Ordering a toner cartridge

Notes:

- The estimated cartridge yield is based on the ISO/IEC 19752 standard.
- Extremely low print coverage for extended periods of time may negatively affect actual yield.

Part name	Part number
High Yield Toner Cartridge	64G0H00

Ordering a photoconductor unit

Extremely low print coverage for extended periods of time may cause photoconductor unit parts to fail prior to exhaustion of toner.

Item	Part number
Photoconductor unit	54G0P00

Ordering a waste toner bottle

Item	Part number
Waste toner bottle	54G0W00

Ordering staple cartridges

Item	Part number
Staple cartridges	25A0013

Ordering a 300K maintenance kit

Note: To replace the parts included in the maintenance kit, see the instruction sheet that came with each part.

Item	Part number
Maintenance kit	40X9669

Storing parts and supplies

Storing supplies


Choose a cool, clean storage area for the printer supplies. Store supplies right side up in their original packing until you are ready to use them.

Do not expose supplies to:

- Direct sunlight
- Temperatures above 35°C (95°F)
- High humidity above 80%
- Salty air
- Corrosive gases
- Heavy dust

Storing the rollers

Your printer comes with replacement rollers stored in the compartment inside the standard trays. After you purchase new rollers, make sure to store them in the compartments inside the trays.



Note: For proper disposal of parts and supplies, see "Recycling" on page 199.


Replacing supplies

Replacing a photoconductor unit

1 Open the bottom front door.




2 Remove the waste toner bottle.



3 Unlock the photoconductor unit.



4 Remove the photoconductor unit.




5 Unpack the new photoconductor unit.

Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems.

Warning—Potential Damage: Do not touch the photoconductor drum. Doing so may affect the print quality of future print jobs.


6 Install the photoconductor unit.



7 Lock the photoconductor unit.



8 Reinstall the waste toner bottle.



9 Close the bottom front door.

Replacing the staple cartridge


Replacing the staple cartridge in the staple finisher

Note: The staple finisher is supported only in select printer models.


1 Press the latch on the staple finisher, and then slide the finisher to the left.



Remove the staple cartridge holder.



Remove the empty staple cartridge from the cartridge holder.




Insert the new cartridge into the cartridge holder.






Push the cartridge holder into the finisher until the holder *clicks* into place.



Slide the finisher back into place.




Replacing the staple cartridge in the booklet finisher


1 Open door H, and then pull out the booklet maker.




2 Remove the staple cartridge holder.




Remove the empty staple cartridge from the cartridge holder.



Insert the new cartridge into the cartridge holder.



Push the cartridge holder into the booklet maker until the holder *clicks* into place.



Push the booklet maker back into place, and then close the door.

Replacing the staple cartridge in the staple, hole punch finisher

1 Open door H.




2 Remove the staple cartridge holder.






3 Remove the empty staple cartridge from the cartridge holder.





4 Insert the new cartridge into the cartridge holder.





5 Push the cartridge holder into the finisher until the holder *clicks* into place.



6 Close door H.

Replacing the toner cartridge

1 Open the top front door.



2 Rotate the toner cartridge counterclockwise, and then pull it out.






3 Unpack the new toner cartridge, remove the packing material, and then shake the cartridge to redistribute the toner.



4 Insert the toner cartridge into the printer.



5 Rotate the cartridge clockwise to lock it into place.



6 Close the top front door.



7 Clean the charger and the printhead lens. For more information, see <u>"Cleaning the charger and the printhead lens"</u> on page 205.

Replacing the waste toner bottle


1 Open the bottom front door.



Remove the waste toner bottle.



- **3** Clean the charger and the printhead lens. For more information, see steps 3–7 of <u>"Cleaning the charger and the printhead lens" on page 205</u>.
- Unpack the new waste toner bottle.
- Insert the new waste toner bottle into the printer until it *clicks* into place.



Close the bottom front door.

Replacing the 300K maintenance kit


Replacing the exhaust and ozone filters



1	Exhaust filter	
2	Ozone filter	

Replacing the exhaust filter

1 Pull out the exhaust filter.



2 Unpack the new exhaust filter.




3 Insert the new filter.



Replacing the ozone filter


1 Pull out the ozone filter.




2 Unpack the new ozone filter.



3 Insert the new filter.




Replacing the pick, feed, and separator rollers




1	Pick roller	
2	Feed roller	
3	3 Separator roller	

Note: You can use the rollers stored in the compartment inside the standard trays. For more information, see <u>"Storing the rollers" on page 211</u>.

1 Turn off the printer.




- 2 Remove all trays.
 - Standard tray




• Optional 2 x 500- or 2500-sheet tray

Note: To remove the optional 2 x 500-sheet tray, follow the procedure in removing the standard tray.



3 Open door C. Make sure that it does not hit any cable attached to the printer.

Note: If the 3000-sheet tray is installed, slide the tray to open the door.




4 Open door D.

Notes:


- You can only open door D if the optional 2 x 500- or 2500-sheet tray is installed.
- If the 3000-sheet tray is installed, slide the tray to open the door.



5 Locate the rollers.




6 Remove the rollers.





7 Insert the new rollers until they *click* into place.



Note: Make sure to insert the rollers to their right places.


- 8 Close doors C and D.
- **9** Insert the trays.

Replacing the transfer module


Note: Use the screwdriver located inside the bottom front door of the printer.



1 Turn off the printer.



2 Open door C. Make sure that it does not hit any cable attached to the printer.






Note: If the 3000-sheet tray is installed, then slide the tray to the right to open the door.

3 Remove the door stopper.







Loosen the screws of the transfer module lock.



Remove the paper guide.



Lift the transfer module using the handles, and then pull it out completely.



Unpack the new transfer module.

Warning—Potential Damage: Do not expose the transfer belt to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems.

Warning—Potential Damage: Do not touch the transfer belt. Doing so may affect the print quality of future print jobs.



8 Insert the new transfer module until it *clicks* into place.






- **9** Place the paper guide back into place.
- **10** Tighten the screws of the transfer module lock.
- **11** Reinstall the door stopper.
- 12 Close door C.

Replacing the transfer roller


1 Open door C. Make sure that it does not hit any cable attached to the printer.

Note: If the 3000-sheet tray is installed, then slide the tray to the right to open the door.






2 Pull out the transfer roller.



- **3** Unpack the new transfer roller.
- 4 Insert the new transfer roller until it *clicks* into place.



5 Close door C.

Resetting the maintenance counter

- **1** Turn off the printer.
- **2** From the control panel, hold down **2** and **6** while turning the printer on. Release the buttons when the screen with the progress bar appears.
- **3** From the Configuration menu, navigate to:


Reset Maintenance Counter > Reset 300K Maintenance Kit

4 Touch **Back**, and then exit the Configuration menu.


Note: The printer performs a power-on reset, and then returns to normal operating mode.

Replacing the ADF scan pad


1 Open the scanner cover.



2 Remove the ADF scan pad.



3 Unpack the new ADF scan pad, and then remove the packing materials.




4 Lay the ADF scan pad flat on the scanner glass with the white area facedown.



5 Close the scanner cover to stick the ADF scan pad to the cover, and then open the cover.



6 Push the corners of the ADF scan pad to secure it into place.



7 Close the scanner cover.

Moving the printer



CAUTION—POTENTIAL INJURY: The printer weight is greater than 18 kg (40 lb) and requires two or more trained personnel to lift it safely.

Before moving the printer


CAUTION—POTENTIAL INJURY: Before moving the printer, follow these guidelines to avoid personal injury or printer damage:

- Turn off the printer, and then unplug the power cord from the electrical outlet.
- Disconnect all cords and cables from the printer.
- If the printer does not have a caster base but is configured with optional trays, then remove the trays.
- Use the handholds located on both sides of the printer to lift it.
- Make sure your fingers are not under the printer when you set it down.
- Make sure there is adequate clearance around the printer.
- Use only the power cord provided with this product or the manufacturer's authorized replacement.


Warning—Potential Damage: Damage to the printer caused by improper moving is not covered by the printer warranty.

Moving the printer to another location

• Using a flat-head screwdriver, reinstall the screws to lock the scanner bed in place.



Note: Remove the screws after setting up the printer in another location.



- If necessary, use a cart with a surface large enough to support the full dimensions of the printer.
- Keep the printer in an upright position.
- Avoid jarring movements.

Shipping the printer

When shipping the printer, use the original packaging.

Managing the printer 238

Managing the printer

Checking the virtual display

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- **2** Check the virtual display that appears in the top left corner of the screen.

The virtual display works as an actual display would work on a printer control panel.

Setting up e-mail alerts

Configure the printer to send you e-mail alerts when the supplies are getting low or when the paper needs to be changed or added, or when there is a paper jam.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click Settings.
- **3** From the Other Settings menu, click **E-mail Alert Setup**.
- **4** Select the items you want to be notified on, and then type the e-mail addresses.
- 5 Click Submit.

Note: For information on setting up the e-mail server, contact your system support person.

Viewing reports

You can view some reports from the Embedded Web Server. These reports are useful for assessing the status of the printer, network, and supplies.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- **2** Click **Reports**, and then click the type of report you want to view.

Managing the printer 239

Copying printer settings to other printers

Note: This feature is available only in network printers.

1 Open a Web browser, and then type the printer IP address in the address field.

Notes:

- View the printer IP address in the TCP/IP section in the Network/Ports menu. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 2 Click the Copy Printer Settings.
- **3** To change the language, select a language from the drop-down menu, and then click **Click here to submit language**.
- 4 Click Printer Settings.
- **5** Type the IP addresses of the source and target printers in their appropriate fields.

Note: If you want to add or remove a target printer, then click Add Target IP or Remove Target IP.

6 Click Copy Printer Settings.

Configuring supply notifications from the Embedded Web Server

You can determine how you would like to be notified when supplies run nearly low, low, near end-of-life, or reach their end-of-life by setting the selectable alerts.

Note: The percentage of estimated remaining supply that prompts the alert can be set on some supplies for some supply conditions.

- **1** Open a Web browser, and then type the printer IP address.
- 2 Click Settings > Print Settings > Supply Notifications.
- **3** From the drop-down menu, select one of the following notification options:

Notification	Description	
Off	The normal printer behavior for all supplies occurs.	
SNMP Only	The printer generates a Simple Network Management Protocol (SNMP) alert when the supply condition is reached. The status of the supply appears on the menus page and status page.	
E-mail	The printer generates an e-mail when the supply condition is reached. The status of the supply appears on the menus page and status page.	
Warning	The printer displays the warning message and generates an e-mail about the status of the supply. The printer does not stop when the supply condition is reached.	
Continuable Stop ¹	The printer stops processing jobs when the supply condition is reached, and the user needs to press a button to continue printing.	

¹ The printer generates an e-mail about the status of the supply when supply notification is enabled.

² The printer stops when some supplies become empty to prevent damage.

Managing the printer 240

Notification	Description	
Non Continuable Stop ^{1,2}	The printer stops processing jobs when the supply condition is reached. The supply must be replaced to continue printing.	
¹ The printer generates an e-mail about the status of the supply when supply notification is enabled.		
² The printer stops when some supplies become empty to prevent damage.		

4 Click Submit.

Restoring factory default settings

If you want to keep a list of the current menu settings for reference, then print a menu settings page before restoring the factory default settings. For more information, see "Printing a menu settings page" on page 50.

For a more comprehensive method of restoring the printer factory default settings, see <u>"Erasing non-volatile memory" on page 202</u>.

Warning—Potential Damage: Restoring factory defaults returns most printer settings to the original factory default settings. Exceptions include the display language, custom sizes and messages, and network/port menu settings. All downloads stored in the RAM are deleted. Downloads stored in the flash memory or in a printer hard disk are not affected.

1 From the home screen, navigate to:



2 Apply the changes.


Clearing jams

Note: Jam Recovery is set to Auto by default. The printer reprints jammed pages unless the memory required to hold the pages is needed for other printer tasks.

Avoiding jams

Load paper properly

Make sure paper lies flat in the tray.



- Do not remove a tray while the printer is printing.
- Do not load a tray while the printer is printing. Load it before printing, or wait for a prompt to load it.
- Do not load too much paper. Make sure the stack height is below the maximum paper fill indicator.
- Do not slide the paper into the tray. Load paper as shown in the illustration.



- Make sure the guides in the tray or the multipurpose feeder are properly positioned and are not pressing tightly against the paper or envelopes.
- Push the tray firmly into the printer after loading paper.

Use recommended paper

- Use only recommended paper or specialty media.
- Do not load wrinkled, creased, damp, bent, or curled paper.

• Flex, fan, and straighten paper before loading it.




- Do not use paper that has been cut or trimmed by hand.
- Do not mix paper sizes, weights, or types in the same tray.
- Make sure the paper size and type are set correctly on the computer or printer control panel.
- Store paper according to manufacturer recommendations.

Understanding jam messages and locations

When a jam occurs, a message indicating the jam location and information to clear the jam appears on the printer display. Open the doors, covers, and trays indicated on the display to remove the jam.

Notes:

- When Jam Assist is set to On, the printer flushes blank pages or pages with partial prints after a jammed page has been cleared. Check your printed output for blank pages.
- When Jam Recovery is set to On or Auto, the printer reprints jammed pages. However, the Auto setting reprints jammed pages only if adequate printer memory is available.



	Area name
1	Automatic document feeder (ADF)
2	Door C
3	Door D
4	Door F
5	Trays
6	Door H

	Area name
7	Finisher bins
8	Door J
9	Area G

Area name	Control panel message	What to do
ADF	[x]-page jam, press latch at area E to open ADF's top cover. [28y.xx]	Open the ADF top door, and then remove the jammed paper.
Multipurpose feeder	[x]-page jam, clear jammed paper from the multipurpose feeder. [200.xx]	Remove the jammed paper from the feeder.
Door C, trays	[x]-page jam, open door C and clear all jammed paper. [2yy.xx]	Open door C, and then remove the jammed paper.
	[x]-page jam, slide the 3000-sheet tray and open door C. [2yy.xx]	Pull out the tray, and then remove the jammed paper.
Door D, trays	[x]-page jam, open door D and clear all jammed paper. [24y.xx]	Open door D, and then remove the jammed paper.
	[x]-page jam, slide the 3000-sheet tray and open door D. [24y.xx]	Pull out the tray, and then remove the jammed paper.
Doors C and F	[x]-page jam, slide the 3000-sheet tray and open door F. [24y.xx]	Pull the 3000-sheet tray, and then remove the jammed paper from the side of the tray.
		Open door F, and then remove the jammed paper.
Area G, doors C, J, and H, finisher bin	[x] page jam, open doors G, H, and J and clear jammed paper. [4yy.xx]	Open door G, and then remove the jammed paper.
		Open door H, and then remove the jammed paper.
Doors C and G, finisher bin	[x]-page jam, press latch beside door G and slide finisher to the left. Leave paper in bin. [40y.xx]	· · · · · · · · · · · · · · · · · · ·
Area G, doors C, J, and H, finisher bin	[x]-page jam, open door H and rotate knob SD3 clockwise. Leave paper in bin. [426.xx–428.xx]	Open door H, and then remove the jammed paper.

[x]-page jam, clear jammed paper from multipurpose feeder. [200.xx]


- **1** Remove all paper from the multipurpose feeder.
- 2 Remove the jammed paper.



3 Open door C to remove any paper fragments.

Note: Make sure that door C does not hit any cable attached to the printer.


- 4 Close door C.
- **5** Flex the sheets back and forth to loosen them, and then fan them. Do not fold or crease the paper. Straighten the edges on a level surface.



6 Reload the paper.

[x]-page jam, open door C and clear all jammed paper. [2yy.xx]

1 Open door C. Make sure that it does not hit any cable attached to the printer.




2 Remove the jammed paper from any of the following locations:


Note: Make sure that all paper fragments are removed.

CAUTION—HOT SURFACE: The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.

• Fuser area



• Below the fuser area



• Duplex area





• Above the duplex area



3 Open the standard trays, and then locate the jammed paper.



4 Remove the jammed paper.


Note: Make sure that all paper fragments are removed.



5 Close the trays and door C.

[x]-page jam, slide the 3000-sheet tray and open door C. [2yy.xx]

1 Slide the 3000-sheet tray.



2 Open door C. Make sure that it does not hit any cable attached to the printer.




3 Remove the jammed paper from any of the following locations:


Note: Make sure that all paper fragments are removed.

CAUTION—HOT SURFACE: The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.

• Fuser area



• Below the fuser area



• Duplex area



• Above the duplex area



4 Open the standard trays, and then locate the jammed paper.



5 Remove the jammed paper.

Note: Make sure that all paper fragments are removed.



- **6** Close the trays and door C.
- **7** Slide the 3000-sheet tray back into place.

[x]-page jam, open door D and clear all jammed paper. [24y.xx]

1 Open door D, and then remove the jammed paper.

Note: Make sure that all paper fragments are removed.






2 Open the optional tray, and then locate the jammed paper.



3 Remove the jammed paper.


Note: Make sure that all paper fragments are removed.



4 Close the tray and door D.


[x]-page jam, slide the 3000-sheet tray and open door D. [24y.xx]

1 Slide the 3000-sheet tray.



2 Open door D, and then remove the jammed paper.

Note: Make sure that all paper fragments are removed.



3 Open the optional tray, and then locate the jammed paper.



4 Remove the jammed paper.


Note: Make sure that all paper fragments are removed.



- **5** Close the tray and door D.
- **6** Slide the 3000-sheet tray back into place.


[x]-page jam, slide the 3000-sheet tray and open door F. [24y.xx]

1 Slide the 3000-sheet tray.



2 Remove the jammed paper.

Note: Make sure that all paper fragments are removed.




3 Open door F, and then remove the jammed paper.

Note: Make sure that all paper fragments are removed.



- 4 Close door F.
- **5** Open door C. Make sure that it does not hit any cable attached to the printer.




6 Remove the jammed paper from any of the following locations:


Note: Make sure that all paper fragments are removed.

CAUTION—HOT SURFACE: The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.

• Fuser area




• Below the fuser area




• Duplex area





• Above the duplex area



7 Close door C, and then slide the 3000-sheet tray back into place.


[x]-page jam, open doors G, H, and J and clear jammed paper. Leave paper in bin. [4yy.xx]

1 Open door G, and then remove the jammed paper.

Note: Make sure that all paper fragments are removed.



2 Open door J, and then lift handle J1 to its upright position.




3 Open door H.




4 Remove the jammed paper from any of the following locations:

Note: Make sure that all paper fragments are removed.

• Door J



Note: If there is a jammed paper between the finisher bins, then remove the paper.




• Areas H1 and H2





• Areas H3 and H4






• Area H6



- **5** Close Door H.
- **6** Open door C, and then remove the jammed paper.

Note: Make sure that door C does not hit any cable attached to the printer.



Notes:


- Make sure that all paper fragments are removed.
- If the 3000-sheet tray is installed, then slide the tray to the right to open the door.
- **7** Close door C.

[x]-page jam, press latch to access area G. Leave paper in bin. [40y.xx]

1 Remove all paper from the staple finisher bin.



2 Press the latch and slide the staple finisher to the left, and then remove the jammed paper.




Notes:

- Make sure that all paper fragments are removed.
- If necessary, turn spinner wheel G1 downward to feed jammed paper into the finisher bin, and then remove the paper.




3 Slide the finisher back into place.



4 Open door C, and then remove the jammed paper.



CAUTION—HOT SURFACE: The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.



Notes:

- Make sure that door C does not hit any cable attached to the printer.
- Make sure that all paper fragments are removed.
- If the 3000-sheet tray is installed, then slide the tray to the right to open the door.
- **5** Close door C.

[x]-page jam, press latch to access area G and clear jammed staples. Leave paper in bin. [402.93]


1 Remove all paper from the staple finisher bin.




2 Press the latch on the staple finisher, and then slide the finisher to the left.



3 Remove the staple cartridge holder.



4 Use the metal tab to lift the staple guard, and then remove any loose staples.




5 Press the staple guard down until it *clicks* into place.




6 Press the staples against the metal bracket.




Note: If the staples are at the rear of the cartridge, then shake the cartridge downward to bring the staples near the metal bracket.



7 Push the cartridge holder into the finisher until the holder *clicks* into place.



8 Slide the finisher back into place.




[x]-page jam, open door H and rotate knob H6 clockwise. Leave paper in bin. [426.xx-428.xx]

If the jammed paper is located under door G, then open the door and remove the paper.



1 Open door J, and then lift handle J1.




2 Open door H.




3 Remove the jammed paper from any of the following locations:

Note: Make sure that all paper fragments are removed.

• Door J



Note: If there is a jammed paper between the finisher bins, then remove the paper.



• Areas H1 and H2






• Areas H3 and H4





• Area H6



4 Using handle H5, pull out the booklet maker.



5 Remove the jammed paper from any of the following locations:

Note: Make sure that all paper fragments are removed.


• Area H8



• Area H9



• Area H10



- **6** Push the booklet maker back into place.
- **7** Close door H.
- **8** Open door C, and then remove the jammed paper.



CAUTION—HOT SURFACE: The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.



Notes:

- Make sure that door C does not hit any cable attached to the printer.
- Make sure that all paper fragments are removed.
- If the 3000-sheet tray is installed, then slide the tray to the right to open the door.
- **9** Close door C.

[x]-page jam, press latch at area E to open ADF's top cover. [28y.xx]

1 Remove all original documents from the ADF tray.

2 Open the top ADF top cover.




3 Remove jammed paper.

Note: Make sure that all paper fragments are removed.



- 4 Close the cover.
- **5** Open the scanner cover, and then open the bottom ADF door.



6 Remove jammed paper.

Note: Make sure that all paper fragments are removed.



7 Close the door.



8 Close the scanner cover.

Troubleshooting

Understanding the printer messages

Cartridge low [88.xy]

You may need to order a replacement toner cartridge. If necessary, touch **Continue** on the printer control panel to clear the message and continue printing.

Cartridge nearly low [88.xy]

If necessary, touch **Continue** on the printer control panel to clear the message and continue printing.

Cartridge very low [88.xy]

You may need to replace the toner cartridge very soon. For more information, see <u>"Replacing the toner cartridge"</u> on page 220.

If necessary, touch Continue on the control panel to clear the message and continue printing.

Change [paper source] to [custom string] load [orientation]

Try one or more of the following:

- Load the correct size and type of paper in the tray, specify the paper size and type in the Paper menu on the control panel, and then touch **Finished changing paper**.
- Touch Use current [paper source] to use the available paper size and type in the tray.
- Touch Reset active bin to reset the active bin for a linked set of bins.
- Cancel the print job.

Change [paper source] to [custom type name] load [orientation]

Try one or more of the following:

- Load the correct size and type of paper in the tray or feeder, specify the paper size and type in the Paper menu on the printer control panel, and then touch **Finished changing paper**.
- Touch **Reset active bin** to reset the active bin for a linked set of bins.
- Cancel the print job.

Change [paper source] to [paper size] load [orientation]

- Load the correct size and type of paper in the tray or feeder, specify the size and type of paper in the Paper menu on the control panel, and then touch **Finished changing paper**.
- Touch Use current [paper source] to use the available size and type of paper in the current tray or feeder.

- Touch Reset active bin to reset the active bin for a linked set of bins.
- Cancel the print job.

Change [paper source] to [paper type] [paper size] load [orientation]

Try one or more of the following:

- Load the correct size and type of paper in the tray or feeder, specify the paper size and type in the Paper menu on the control panel, and then touch **Finished changing paper**.
- Touch Use current [paper source] to use the available paper size and type in the tray.
- Touch **Reset active bin** to reset the active bin for a linked set of bins.
- Cancel the print job.

Close door [x]

Close the specified door.

Complex page, some data may not have printed [39]

Try one or more of the following:

- From the control panel, touch Continue to clear the message and continue printing.
- Touch Reset active bin to reset the active bin for a linked set of bins.
- Cancel the print job.
- Install additional printer memory.

Configuration change, some held jobs were not restored [57]

Held jobs are invalidated because of the following possible changes in the printer:

- The printer firmware has been updated.
- The tray for the print job has been removed.
- The print job is sent from a flash drive that is no longer attached to the USB port.
- The printer hard disk contains print jobs that were stored when the hard disk was installed in a different printer model.

From the printer control panel, touch **Continue** to clear the message.

Defective flash detected [51]

- Replace the defective flash memory card.
- From the printer control panel, touch Continue to ignore the message and continue printing.
- Cancel the current print job.

Disk full [62]

Try one or more of the following:

- From the control panel, touch Continue to clear the message and continue printing.
- Touch Reset active bin to reset the active bin for a linked set of bins.
- Delete fonts, macros, and other data stored in the printer hard disk.
- · Install a hard disk with larger capacity.

Disk full, scan job canceled

Try one or more of the following:

- Touch Continue to clear the message and continue scanning.
- Delete fonts, macros, and other data stored in the printer hard disk.
- Install a hard disk with higher capacity.

Disk must be formatted for use in this device

From the printer control panel, touch Format disk to format the printer hard disk and clear the message.

Note: Formatting deletes all the files stored in the printer hard disk.

Disk near full. Securely clearing disk space.

Try one or more of the following:

- Touch **Continue** to clear the message and continue printing.
- Delete fonts, macros, and other data stored on the printer hard disk.
- Install a hard disk with higher capacity.

Empty the hole punch box

Try one or more of the following:

- Empty the hole punch box.
- Select **Continue** on the printer control panel to clear the message and continue printing.
- Cancel the print job.

Error reading USB drive. Remove USB.

An unsupported USB device is inserted. Remove the USB device, and then insert a supported one.

Error reading USB hub. Remove hub.

An unsupported USB hub has been inserted. Remove the USB hub, and then install a supported one.

Fax memory full

From the printer control panel, touch **Continue** to clear the message.

Fax partition inoperative. Contact system administrator.

Try one or more of the following:

- From the printer control panel, touch **Continue** to clear the message.
- Turn off the printer, and then turn it back on. If the message appears again, then contact your system support person.

Fax server 'To Format' not set up. Contact system administrator.

Try one or more of the following:

- From the printer control panel, touch **Continue** to clear the message.
- Complete the Fax Server setup. If the message appears again, then contact your system support person.

Fax Station Name not set up. Contact system administrator.

Try either of the following:

- From the printer control panel, touch **Continue** to clear the message.
- Complete the Analog Fax setup. If the message appears again after completing the setup, then contact
 your system support person.

Fax Station Number not set up. Contact system administrator.

Try one or more of the following:

- From the printer control panel, touch **Continue** to clear the message.
- Complete the Analog Fax setup. If the message appears again after completing the setup, then contact your system support person.

Incorrect paper size, open [paper source] [34]

- Load the correct paper size and type in the tray or feeder, and then specify the paper size and type in the Paper menu on the control panel.
- Make sure that the correct paper size and type are specified in Print Properties or the Print dialog settings.
- Check the length and width guides and make sure that the paper is loaded properly in the tray or feeder.
- From the control panel, touch **Continue** to clear the message and then print using a different tray.
- Touch **Reset active bin** to reset the active bin for a linked set of bins.
- Cancel the print job.

Insert hole punch box

Insert the hole punch box into the finisher, and then touch **Continue** to clear the message.

Insert Tray [x]

Try one or more of the following:

- Insert the specified tray into the printer.
- Cancel the print job.
- Reset the active bin for a linked set of bins by selecting Reset active bin on the printer control panel.

Insufficient memory for Flash Memory Defragment operation [37]

Try one or more of the following:

- From the printer control panel, touch Continue to stop the defragmentation and continue printing.
- Delete fonts, macros, and other data in the printer memory.
- Install additional printer memory.

Insufficient memory to collate job [37]

Try one or more of the following:

- From the printer control panel, touch **Continue** to print the part of the job already stored and begin collating the rest of the print job.
- Cancel the current print job.

Insufficient memory to support Resource Save feature [35]

Install additional printer memory or touch **Continue** to disable Resource Save, clear the message, and continue printing.

Insufficient memory, some Held Jobs were deleted [37]

From the printer control panel, touch **Continue** to clear the message.

Insufficient memory, some held jobs will not be restored [37]

Try one or more of the following:

- From the printer control panel, touch Continue to clear the message.
- Delete other held jobs to free up additional printer memory.

Insufficient space between paper stacks in Tray 3

Move the paper stacks apart, and then touch **Continue** on the control panel to clear the message and continue printing.

Load [paper source] with [custom string] [paper orientation]

Try one or more of the following:

Load the tray or feeder with the correct size and type of paper, and then touch Finished loading paper
on the control panel.

- Touch **Reset active bin** to reset the active bin for a linked set of bins.
- Cancel the current job.

Load [paper source] with [custom type name] [paper orientation]

Try one or more of the following:

- Load the tray or feeder with the correct size and type of paper, and then touch **Finished loading paper** on the control panel.
- Touch **Reset active bin** to reset the active bin for a linked set of bins.
- Cancel the print job.

Load [paper source] with [paper size] [paper orientation]

Try one or more of the following:

- Load the tray or feeder with the correct size of paper, and then touch **Finished loading paper** on the control panel.
- Touch Reset active bin to reset the active bin for a linked set of bins.
- Cancel the current job.

Load [paper source] with [paper type] [paper size] [paper orientation]

Try one or more of the following:

- Load the specified tray or feeder with the correct size and type of paper, and then touch Finished loading paper on the control panel.
- Touch Reset active bin to reset the active bin for a linked set of bins.
- Cancel the current job.

Load Multipurpose Feeder with [custom string] [paper orientation]

- Load the feeder with the correct size and type of paper.
- From the control panel, touch one of the following:
 - Prompt each page, paper loaded or Do not prompt, paper loaded—To clear the message and continue printing.
 - **Automatically select paper**—To use the paper loaded in the tray.
 - Reset active bin—To reset the active bin for a linked set of bins.
- Cancel the print job.

Load Multipurpose Feeder with [custom type name] [paper orientation]

Try one or more of the following:

- Load the feeder with the correct size and type of paper.
- From the control panel, touch one of the following:
 - Prompt each page, paper loaded or Do not prompt, paper loaded—To clear the message and continue printing.
 - **Automatically select paper**—To use the paper loaded in the tray.
 - Reset active bin—To reset the active bin for a linked set of bins.
- Cancel the print job.

Load Multipurpose Feeder with [paper size] [paper orientation]

Try one or more of the following:

- Load the feeder with the correct size of paper.
- From the control panel, touch one of the following:
 - Prompt each page, paper loaded or Do not prompt, paper loaded—To clear the message and continue printing.
 - **Automatically select paper**—To use the paper loaded in the tray.
 - Reset active bin—To reset the active bin for a linked set of bins.
- Cancel the print job.

Load Multipurpose Feeder with [paper type] [paper size] [paper orientation]

Try one or more of the following:

- Load the feeder with the correct size and type of paper.
- From the control panel, touch one of the following:
 - Prompt each page, paper loaded or Do not prompt, paper loaded—To clear the message and continue printing.
 - **Automatically select paper**—To use the paper loaded in the tray.
 - Reset active bin—To reset the active bin for a linked set of bins.
- Cancel the print job.

Load staples

- Replace or insert the staple cartridge in the finisher.
 - For instructions on inserting or replacing a staple cartridge in the finisher, touch **More information** on the printer control panel.
- From the printer control panel, touch **Continue** to clear the message and continue printing.
- From the printer control panel, touch **Cancel job** to cancel the print job.

Load staples [G11, G12]

Try one or more of the following:

• Replace or insert the staple cartridge into the finisher.

For instructions on replacing or inserting the staple cartridge into the finisher, touch **More information** on the control panel.

- From the control panel, touch Continue to clear the message and continue printing.
- Cancel the print job.

[x] maintenance kit very low [80.xy]

You may need to replace the maintenance kit very soon. For more information, go to the Lexmark support Web site at http://support.lexmark.com or contact customer support, and then report the message.

If necessary, touch Continue to clear the message and continue printing.

Memory full [38]

Try one or more of the following:

- From the control panel, touch **Cancel job** to clear the message.
- Touch Reset active bin to reset the active bin for a linked set of bins.
- Install additional printer memory.

Memory full, cannot print faxes

From the printer control panel, touch **Continue** to clear the message without printing. Held faxes attempt to print after the printer is restarted.

Memory full, cannot send faxes

- 1 From the printer control panel, touch Continue to clear the message and cancel the fax job.
- **2** Try one or more of the following:
 - Reduce the fax resolution, and then resend the fax job.
 - Reduce the number of pages in the fax, and then resend the fax job.

No analog phone line connected to modem, fax is disabled.

Connect the printer to an analog phone line.

Network [x] software error [54]

- From the printer control panel, touch Continue to continue printing.
- Turn off the printer, wait for about 10 seconds, and then turn the printer back on.

 Update the network firmware in the printer or print server. For more information, visit the Lexmark support Web site at http://support.lexmark.com.

Not enough free space in flash memory for resources [52]

Try one or more of the following:

- From the control panel, touch **Continue** to clear the message and continue printing.
- Touch Reset active bin to reset the active bin for a linked set of bins.
- Delete fonts, macros, and other data stored in the flash memory.
- Install a flash memory card with larger capacity.

Note: Downloaded fonts and macros not previously stored in the flash memory are deleted.

Open door H and remove paper from beneath area H10

Remove the paper from the specified area.

Paper changes needed

Try one or more of the following:

- Touch **Use current supplies** to clear the message and continue printing.
- Cancel the current print job.

Parallel port [x] disabled [56]

Try one or more of the following:

- From the printer control panel, touch Continue to clear the message.
- Enable the parallel port. From the printer control panel, navigate to:

Network/Ports > Parallel [x] > Parallel Buffer > Auto

Note: The printer discards any data received through the parallel port.

Photoconductor low [84.xy]

You may need to order a replacement photoconductor. If necessary, select **Continue** on the control panel to clear the message and continue printing.

Photoconductor very low [84.xy]

You may need to replace the photoconductor unit very soon. For more information, see <u>"Replacing a photoconductor unit" on page 212.</u>

If necessary, touch Continue on the control panel to clear the message and continue printing.

Printer had to restart. Last job may be incomplete.

From the printer control panel, touch Continue to clear the message and continue printing.

For more information, visit http://support.lexmark.com or contact customer support.

Reinstall missing or unresponsive cartridge [31.xy]

Try one or more of the following:

- Check if the toner cartridge is missing. If missing, install the toner cartridge.

 For information on installing the cartridge, see the "Replacing supplies" section of the *User's Guide*.
- If the toner cartridge is installed, then remove the unresponsive toner cartridge, and then reinstall it.

Note: If the message appears after reinstalling the supply, then the cartridge is defective. Replace the toner cartridge.

Reinstall missing or unresponsive photoconductor [31.xy]

Try one or more of the following:

- If the photoconductor unit is missing, then install it. For more information, see <u>"Replacing a photoconductor unit" on page 212</u>.
- If the photoconductor unit is installed, then remove and then reinstall it.

Note: If the message appears after reinstalling the supply, then replace the defective photoconductor unit.

Remove defective disk [61]

Remove and replace the defective printer hard disk.

Remove packaging material, [area name]

Remove any remaining packaging material from the specified location.

Remove packaging material, open door C, remove metal clips, remove all screws from scanner carriage

Open door C and the scanner cover, and then remove any remaining packaging material.

Note: Make sure door C does not hit any cable attached to the printer.

Remove paper from all bins

Remove the paper from all of the bins. The printer automatically senses paper removal and resumes printing. If removing the paper does not clear the message, then touch **Continue**.

Remove paper from bin [x]

Remove the paper from the specified bin. The printer automatically senses paper removal and resumes printing.

If removing the paper does not clear the message, then touch Continue.

Remove paper from [linked set bin name]

Remove paper from the specified bin. The printer automatically detects paper removal and resumes printing. If removing the paper does not clear the message, then touch **Continue**.

Remove paper from standard output bin

Remove the paper stack from the standard bin.

Replace all originals if restarting job.

Try one or more of the following:

- Touch Cancel job to clear the message and cancel the scan job.
- Touch **Scan from automatic feeder** to continue scanning from the ADF immediately after the last successful scan job.
- Touch Scan from flatbed to continue scanning from the scanner immediately after the last successful scan job.
- Touch Finish job without further scanning to end the last successful scan job.
- Touch Restart job to restart the scan job with the same settings from the previous scan job.

Replace cartridge, 0 estimated pages remain [88.xy]

Replace the toner cartridge to clear the message and continue printing. For more information, see the instruction sheet that came with the supply or see the "Replacing supplies" section of the *User's Guide*.

Note: If you do not have a replacement cartridge, then see the "Ordering supplies" section of the *User's Guide* or visit **www.lexmark.com**.

Replace cartridge, printer region mismatch [42.xy]

Install a toner cartridge that matches the region number of the printer. *x* indicates the value of the printer region. *y* indicates the value of the cartridge region. *x* and *y* can have the following values:

Printer and toner cartridge regions

Region number	Region
0	Global
1	United States, Canada
2	European Economic Area (EEA), Switzerland
3	Asia Pacific, Australia, New Zealand
4	Latin America
5	Africa, Middle East, rest of Europe

Region number	Region
9	Invalid

Notes:

- The x and y values represent .xy in the code that appears on the printer control panel.
- The x and y values must match for printing to continue.

Replace jammed originals if restarting job.

Try one or more of the following:

- Touch Cancel job to clear the message and cancel the scan job.
- Touch Scan from automatic feeder to continue scanning from the ADF immediately after the last successful scan job.
- Touch Scan from flatbed to continue scanning from the scanner immediately after the last successful scan job.
- Touch **Finish job without further scanning** to end the last successful scan job.
- Touch **Restart job** to restart the scan job with the same settings from the previous scan job.

Replace [x] maintenance kit, 0 estimated pages remain [80.xy]

The printer is scheduled for maintenance. For more information, go to the Lexmark support Web site at http://support.lexmark.com or contact your service representative, and then report the message.

Replace missing photoconductor [31.xy]

Install the missing photoconductor unit to clear the message. For more information, see <u>"Replacing a photoconductor unit"</u> on page 212.

Replace missing waste toner bottle [82.xy]

Install the missing waste toner bottle to clear the message. For more information, see the instruction sheet that came with the supply.

Replace missing cartridge [31.xy]

Install the missing cartridge to clear the message. For more information, see <u>"Replacing the toner cartridge"</u> on page 220.

Replace paper pick rollers in [paper source], use parts and instructions in tray 1 or tray 2 compartment [80]

Try one or more of the following:

- Replace the pick rollers, and then touch **Rollers replaced** on the control panel to clear the message and continue printing.
- Touch **Continue and replace later (Jams may continue to occur)** to ignore the message and continue printing.

Replace photoconductor, 0 pages remain [84.xy]

Replace the photoconductor unit to clear the message and continue printing. For more information, see the instruction sheet that came with the supply or see <u>"Replacing a photoconductor unit" on page 212</u>.

Note: If you do not have a replacement photoconductor unit, then see <u>"Ordering supplies" on page 210</u> or go to **www.lexmark.com**.

Replace unsupported cartridge [32.xy]

Remove the toner cartridge, and then install a supported one to clear the message and continue printing. For more information, see the instruction sheet that came with the supply or see the "Replacing supplies" section of the *User's Guide*.

Note: If you do not have a replacement cartridge, then see the "Ordering supplies" section of the *User's Guide* or visit **www.lexmark.com**.

Replace unsupported photoconductor [32.xy]

Remove the photoconductor unit, and then install a supported one to clear the message and continue printing. For more information, see the instruction sheet that came with the supply or see <u>"Replacing a photoconductor unit" on page 212</u>.

Note: If you do not have a replacement photoconductor unit, then see <u>"Ordering supplies" on page 210</u> or go to <u>www.lexmark.com</u>.

Replace waste toner bottle [82.xy]

Replace the waste toner bottle to clear the message.

Restore held jobs?

Try one or more of the following:

- From the printer control panel, touch Restore to restore all held jobs stored in the printer hard disk.
- From the printer control panel, touch Do not restore if you do not want to restore any of the print jobs.

Scanner disabled by admin [840.01]

Print without the scanner, or contact your system support person.

Scanner disabled. Contact system administrator if problem persists. [840.02]

Try one or more of the following:

- Touch **Continue with scanner disabled** to return to the home screen, and then contact your system support person.
- Touch Reboot and automatically enable scanner to cancel the job.

Note: This attempts to enable the scanner.

Scanner jam, remove jammed originals from the scanner [2yy.xx]

Remove the jammed paper from the scanner.

Scanner maintenance required, use ADF Kit [80]

The printer is scheduled for maintenance. For more information, go to the Lexmark support Web site at http://support.lexmark.com or contact your service representative, and then report the message.

Scanner maintenance required soon, use ADF Kit [80]

Contact customer support, and then report the message. The printer is scheduled for maintenance.

Serial port [x] disabled [56]

Try one or more of the following:

- From the printer control panel, touch **Continue** to clear the message.
 - The printer discards any data received through the specified serial port.
- Make sure Serial Buffer is not set to Disabled.
- From the printer control panel, set Serial Buffer to Auto in the Serial [x] menu.

Some held jobs were not restored

From the printer control panel, touch **Continue** to delete the indicated job.

Note: Held jobs that are not restored remain in the printer hard disk and are inaccessible.

SMTP server not set up. Contact system administrator.

From the printer control panel, touch **Continue** to clear the message.

Note: If the message appears again, then contact your system support person.

Standard network software error [54]

Try one or more of the following:

- From the printer control panel, touch Continue to continue printing.
- Turn off the printer, and then turn it back on.
- Update the network firmware in the printer or print server. For more information, visit the Lexmark support Web site at http://support.lexmark.com or contact customer support, and then report the message.

Standard USB port disabled [56]

Try one or more of the following:

- From the printer control panel, touch **Continue** to clear the message.
- Enable the USB port. From the printer control panel, navigate to:

Network/Ports > USB Buffer > Auto

Note: The printer discards any data received through the USB port.

Supply needed to complete job

Do either of the following:

- Install the missing supply to complete the job.
- Cancel the current job.

The device is operating in Safe Mode. Some print options may be disabled or provide unexpected results.

Touch **Continue** on the control panel to clear the message and continue printing.

Too many flash options installed [58]

Try one or more of the following:

- Touch **Continue** on the control panel to continue printing.
- Remove the extra flash memory:
 - **1** Turn off the printer.
 - **2** Unplug the power cord from the electrical outlet.
 - **3** Remove the extra flash memory.
 - 4 Connect the power cord to a properly grounded electrical outlet.
 - **5** Turn the printer back on.

Too many trays attached [58]

- **1** Turn off the printer.
- **2** Unplug the power cord from the electrical outlet.

- **3** Remove the extra trays.
- 4 Connect the power cord to a properly grounded electrical outlet.
- **5** Turn the printer back on.

Tray [x] paper size unsupported

Replace with a supported paper size.

Unformatted flash detected [53]

Try one or more of the following:

- From the printer control panel, touch **Continue** to stop the defragmentation and continue printing.
- Format the flash memory.

Note: If the error message remains, then the flash memory may be defective and needs to be replaced.

Unsupported disk

Remove the unsupported printer hard disk, and then insert a supported one.

Unsupported option in slot [x] [55]

- 1 Turn off the printer.
- **2** Unplug the power cord from the electrical outlet.
- **3** Remove the unsupported option card from the printer controller board, and then replace it with a supported card.
- **4** Connect the power cord to a properly grounded electrical outlet.
- **5** Turn the printer back on.

Waste toner bottle nearly full [82.xy]

You may need to order a waste toner bottle. If necessary, touch **Continue** on the printer control panel to clear the message and continue printing.

Weblink server not set up. Contact system administrator.

From the printer control panel, touch **Continue** to clear the message.

Note: If the message appears again, then contact your system support person.

Solving printer problems

Basic printer problems

The printer is not responding

Action	Yes	No
Step 1 Make sure the printer is turned on. Is the printer turned on?	Go to step 2.	Turn on the printer.
Step 2 Check if the printer is in Sleep mode or Hibernate mode. Is the printer in Sleep mode or Hibernate mode?	Press the Sleep button to wake the printer from Sleep mode or Hibernate mode.	Go to step 3.
Step 3 Check if one end of the power cord is plugged into the printer and the other to a properly grounded electrical outlet. Is the power cord plugged into the printer and a properly grounded electrical outlet?	Go to step 4.	Plug one end of the power cord into the printer and the other to a properly grounded electrical outlet.
Step 4 Check other electrical equipment plugged into the electrical outlet. Does other electrical equipment work?	Unplug the other electrical equipment, and then turn on the printer. If the printer does not work, then reconnect the other electrical equipment.	Go to step 5.
Step 5 Check if the cables connecting the printer and the computer are inserted in the correct ports. Are the cables inserted in the correct ports?	Go to step 6.	Make sure to match the following: • The USB symbol on the cable with the USB symbol on the printer • The appropriate Ethernet cable with the Ethernet port
Step 6 Make sure the electrical outlet is not turned off by a switch or breaker. Is the electrical outlet turned off by a switch or breaker?	Turn on the switch or reset the breaker.	Go to step 7.

Action	Yes	No
Step 7 Check if the printer is plugged into any surge protectors, uninterruptible power supplies, or extension cords. Is the printer plugged into any surge protectors, uninterruptible power supplies, or extension cords?	Connect the printer power cord directly to a properly grounded electrical outlet.	Go to step 8.
Step 8 Check if one end of the printer cable is plugged into a port on the printer and the other to the computer, print server, option, or other network device. Is the printer cable securely attached to the printer and the computer, print server, option, or other network device?	Go to step 9.	Connect the printer cable securely to the printer and the computer, print server, option, or other network device.
Step 9 Make sure to install all hardware options properly and remove any packing material. Are all hardware options properly installed and all packing material removed?	Go to step 10.	Turn off the printer, remove all packing materials, then reinstall the hardware options, and then turn on the printer.
Step 10 Check if you have selected the correct port settings in the printer driver. Are the port settings correct?	Go to step 11.	Use correct printer driver settings.
Step 11 Check the installed printer driver. Is the correct printer driver installed?	Go to step 12.	Install the correct printer driver.
Step 12 Turn off the printer, then wait for about 10 seconds, and then turn the printer back on. Is the printer working?	The problem is solved.	Contact <u>customer</u> <u>support</u> .

Printer display is blank

Action	Yes	No
Step 1 Press the Sleep button on the printer control panel.	The problem is solved.	Go to step 2.
Does Ready appear on the printer display?		
Step 2 Turn off the printer, then wait for about 10 seconds, and then turn the printer back on.	The problem is solved.	Turn off the printer, and then contact customer support.
Do Please wait and Ready appear on the printer display?		

Hardware and internal option problems

Cannot detect internal option

Action	Yes	No
Step 1 Turn off the printer, then wait for about 10 seconds, and then turn on the printer.	The problem is solved.	Go to step 2.
Does the internal option operate correctly?		
 Step 2 Check if the internal option is properly installed in the controller board. a Turn off the printer using the power switch, and then unplug the power cord from the electrical outlet. b Make sure the internal option is installed in the appropriate connector in the controller board. c Connect the power cord to the printer, then to a properly grounded electrical outlet, and then turn on the printer. 	Go to step 3.	Connect the internal option to the controller board.
Is the internal option properly installed in the controller board? Step 3	Go to step 4.	Reinstall the internal
Print a menu settings page, and then check to see if the internal option is listed in the Installed Features list.	ου το στερ 4.	option.
Is the internal option listed in the menu settings page?		

Action	Yes	No
Step 4 a Check if the internal option is selected.	The problem is solved.	Contact <u>customer</u> <u>support</u> .
It may be necessary to manually add the internal option in the printer driver to make it available for print jobs. For more information, see <u>"Adding available options in the print driver" on page 45</u> .		
b Resend the print job. Does the internal option operate correctly?		

Internal print server does not operate correctly

Action	Yes	No
 Step 1 Reinstall the internal print server. a Remove, and then install the internal print server. For more information, see "Installing an Internal Solutions Port" on page 32. b Print a menu settings page, and then check if the internal print server is listed in the Installed Features list. Is the internal print server listed in the Installed Features list? 	Go to step 2.	Check if the internal print server is supported by the printer. Note: An internal print server from another printer may not work with this printer.
Step 2 Check the cable and the internal print server connection. Use the correct cable, and then check if it is securely connected to the internal print server. Does the internal print server operate correctly?	The problem is solved.	Contact <u>customer</u> <u>support</u> .

Internal Solutions Port does not operate correctly

Action	Yes	No
Step 1 Make sure the Internal Solutions Port (ISP) is installed.	Go to step 2.	Check if you have a supported ISP.
a Install the ISP. For more information, see <u>"Installing an Internal Solutions Port" on page 32</u> .		Note: An ISP from another printer may
b Print a menu settings page, and then check if the ISP is listed in the Installed Features list.		not work on this printer.
Is the ISP listed in the Installed Features list?		

Action	Yes	No
Step 2 Check the cable and the ISP connection.	The problem is solved.	Contact <u>customer</u> <u>support</u> .
a Use the correct cable, and then make sure it is securely connected to the ISP.		
b Check if the ISP solution interface cable is securely connected into the receptacle of the controller board.		
Note: The ISP solution interface cable and the receptacle on the controller board are color-coded.		
Does the Internal Solutions Port operate correctly?		

Tray problems

Action	Yes	No
 Step 1 a Pull out the tray, and then do one or more of the following: Check for paper jams or misfeeds. Check if the paper size indicators on the paper guides are aligned with the paper size indicators on the tray. If you are printing on custom-size paper, then make sure that the paper guides rest against the edges of the paper. Make sure the paper is below the maximum paper fill indicator. Make sure paper lies flat in the tray. b Check if the tray closes properly. 	The problem is solved.	Go to step 2.
 Step 2 a Turn off the printer, then wait about 10 seconds, and then turn the printer back on. b Resend the print job. Is the tray working? 	The problem is solved.	Go to step 3.
Step 3 Check if the tray is installed and recognized by the printer. Print a menu settings page, and then check if the tray is listed in the Installed Features list. Is the tray listed in the menu settings page?	Go to step 4.	Reinstall the tray. For more information, see the setup documentation that came with the tray.

Action	Yes	No
Step 4 Check if the tray is available in the printer driver.	The problem is solved.	Contact <u>customer</u> <u>support</u> .
Note: If necessary, manually add the tray in the printer driver to make it available for print jobs. For more information, see "Adding available options in the print driver" on page 45. Is the tray available in the printer driver?		

USB/parallel interface card does not operate correctly

Action	Yes	No
Step 1 Make sure the USB or parallel interface card is installed. a Install the USB or parallel interface card. For more information,	Go to step 2.	Check if you have a supported USB or parallel interface
see "Installing an Internal Solutions Port" on page 32.		card. Note: A USB or
b Print a menu settings page, and then check if the USB or parallel interface card is listed in the Installed Features list.		parallel interface card from another printer may not work
Is the USB or parallel interface card listed in the Installed Features list?		on this printer.
Step 2	The problem is	Contact <u>customer</u>
Check the cable and the USB or parallel interface card connection. Use the correct cable, and then make sure it is securely connected to the USB or parallel interface card.	solved.	support.
Does the USB or parallel interface card operate correctly?		

Paper feed problems

Jammed pages are not reprinted

Action	Yes	No
Turn on Jam Recovery. a From the home screen, navigate to:	The problem is solved.	Contact <u>customer</u> <u>support</u> .
> Settings > General Settings > Print Recovery		
b From the Jam Recovery menu, select On or Auto .		
c Save your changes.		
Do pages reprint after a jam?		

Paper frequently jams

Action	Yes	No
 Step 1 a Pull out the tray, and then do one or more of the following: Make sure paper lies flat in the tray. Check if the paper size indicators on the paper guides are aligned with the paper size indicators on the tray. Check if the paper guides are aligned against the edges of the paper. Make sure the paper is below the maximum paper fill indicator. Check if you are printing on a recommended paper size and type. b Insert the tray properly. If jam recovery is enabled, then the print jobs will reprint automatically. 	Go to step 2.	The problem is solved.
Do paper jams still occur frequently?		
 Step 2 a Load paper from a fresh package. Note: Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you use it. b Resend the print job. Do paper jams still occur frequently?	Go to step 3.	The problem is solved.
Step 3 a Review the tips on avoiding jams. For more information, see "Avoiding jams" on page 241. b Follow the recommendations, and then resend the print job. Do paper jams still occur frequently?	Contact <u>customer</u> <u>support</u> .	The problem is solved.

Paper jam message remains after jam is cleared

Action	Yes	No
 Check the entire paper path for jammed paper. a Remove any jammed paper. b From the printer control panel, touch Continue to clear the message. 	Contact <u>customer</u> <u>support</u> .	The problem is solved.
Does the paper jam message remain?		

Solving print problems

Printing problems

Confidential and other held jobs do not print

Note: Confidential, Verify, Reserve, and Repeat print jobs may be deleted if the printer requires extra memory to process additional held jobs.

Action	Yes	No
Step 1 Open the held jobs folder on the printer display, and then verify that your print job is listed. Is your print job listed in the held jobs folder?	Go to step 2.	Select one of the Print and Hold options, and then resend the print job. For more information, see "Printing held jobs" on page 73.
 Step 2 The print job may contain a formatting error or invalid data. Delete the print job, and then send it again. For PDF files, generate a new PDF, and then print it again. If you are printing from the Internet, then the printer may be reading multiple job titles as duplicates and deleting all jobs except the first one. For Windows users a Open the Print Properties folder. b From the Print and Hold dialog, select the "Keep duplicate documents" check box. c Enter a PIN number. For Macintosh users Save each print job, name each job differently, and then send the individual jobs to the printer. Does the job print? 	The problem is solved.	Go to step 3.
Step 3 Free up additional printer memory by deleting some of the held jobs. Does the job print?	The problem is solved.	Add additional printer memory.

Envelope seals when printing

A	ction	Yes	No
а	Use envelopes that have been stored in a dry environment.	Contact <u>customer</u> support.	The problem is solved.
	Note: Printing on envelopes with high moisture content can seal the flaps.		
b	Resend the print job.		
D	pes the envelope seal when printing?		

Error message about reading the flash drive appears

Action	Yes	No
Step 1 Check if the flash drive is inserted into the front USB port. Note: The flash drive will not work if it is inserted into the rear USB port. Is the flash drive inserted into the front USB port?	Go to step 2.	Insert the flash drive into the front USB port.
Step 2 Check if the indicator light on the printer control panel is blinking green. Note: A green blinking light indicates that the printer is busy. Is the indicator light blinking green?	Wait until the printer is ready, then view the held jobs list, and then print the documents.	Go to step 3.
Step 3 a Check for an error message on the display. b Clear the message. Does the error message still appear?	Go to step 4.	The problem is solved.
Step 4 Check if the flash drive is supported. For more information on tested and approved USB flash drives, see "Supported flash drives and file types" on page 72. Does the error message still appear?	Go to step 5.	The problem is solved.
Step 5 Check if the USB port is disabled by the system support person. Does the error message still appear?	Contact <u>customer</u> <u>support</u> .	The problem is solved.

Incorrect characters print

Action	Yes	No
Step 1 Make sure that the printer is not in Hex Trace mode. Note: If Ready Hex appears on the display, then turn off the printer, and then turn it back on to deactivate Hex Trace mode. Is the printer in Hex Trace mode?	Deactivate Hex Trace mode.	Go to step 2.
Step 2 a From the control panel, select Standard Network or Network [x], and then set PCL SmartSwitch or PS SmartSwitch to On. b Resend the print job. Do incorrect characters print?	Contact <u>customer</u> <u>support</u> .	The problem is solved.

Job prints from the wrong tray or on the wrong paper

Action	Yes	No
Step 1 a Check if you are printing on paper that is supported by the tray. b Resend the print job.	The problem is solved.	Go to step 2.
Did the job print from the correct tray or on the correct paper?		
 Step 2 a From the Paper menu on the printer control panel, set the paper size and type to match the paper loaded in the tray. b Resend the print job. 	The problem is solved.	Go to step 3.
Did the job print from the correct tray or on the correct paper?		
 Step 3 a Depending on your operating system, open Printing Preferences or the Print dialog, and then specify the paper type. b Resend the print job. 	The problem is solved.	Go to step 4.
Did the job print from the correct tray or on the correct paper?		
Step 4 a Check if the trays are not linked. b Resend the print job.	The problem is solved.	Contact <u>customer</u> <u>support</u> .
Did the job print from the correct tray or on the correct paper?		

Large jobs do not collate

Action	Yes	No
 Step 1 a From the Finishing menu on the printer control panel, set Collate to (1,2,3) (1,2,3). b Resend the print job. 	The problem is solved.	Go to step 2.
Did the job print and collate correctly?		
 Step 2 a From the printer software, set Collate to (1,2,3) (1,2,3). Note: Setting Collate to (1,1,1) (2,2,2) in the software overrides the setting in the Finishing menu. b Resend the print job. Did the job print and collate correctly? 	The problem is solved.	Go to step 3.
Step 3 Reduce the complexity of the print job by eliminating the number and size of fonts, the number and complexity of images, and the number of pages in the job. Did the job print and collate correctly?	The problem is solved.	Contact <u>customer</u> <u>support</u> .

Multiple-language PDF files do not print

Action	Yes	No
Step 1	The problem is solved.	Go to step 2.
a Check if the print options for the PDF output are set to emberall fonts.	d solved.	
For more information, see the documentation that came with Adobe Acrobat.	1	
b Generate a new PDF file, and then resend the print job.		
Do the files print?		
Step 2	The problem is	Contact <u>customer</u>
a Open the document you want to print in Adobe Acrobat.	solved.	support.
b Click File > Print > Advanced > Print As Image > OK > OK .		
Do the files print?		

Print job takes longer than expected

Action	Yes	No
Step 1 a Disable Eco-Mode. From the control panel, navigate to: Settings > General Settings > Eco-Mode > Off Note: Disabling Eco-Mode may increase the consumption of energy or paper, or both. b Resend the print job.	The problem is solved.	Go to step 2.
Did the job print?		
Step 2 Reduce the number and size of fonts, the number and complexity of images, and the number of pages in the print job, and then resend the job.	The problem is solved.	Go to step 3.
Did the job print?		
Step 3a Remove held jobs stored in the printer memory.b Resend the print job.	The problem is solved.	Go to step 4.
Did the job print?		
 a Disable the Page Protect feature. From the control panel, navigate to: Settings > General Settings > Print Recovery > Page Protect Off b Resend the print job. Did the job print?	The problem is solved.	Go to step 5.
 Step 5 a Check if the cable connections to the printer and print server are secure. For more information, see the setup documentation that came with the printer. b Resend the print job. Did the job print? 	The problem is solved.	Go to step 6.
Step 6 Install additional printer memory, and then resend the print job. Did the job print?	The problem is solved.	Contact <u>customer</u> <u>support</u> .

Print jobs do not print

Action	Yes	No
Step 1	The problem is	Go to step 2.
a From the document you are trying to print, open the Print dialog and check if you have selected the correct printer.	solved.	
Note: If the printer is not the default printer, then you must select the printer for each document that you want to print.		
b Resend the print job.		
Do the jobs print?		
Step 2	The problem is	Go to step 3.
a Check if the printer is plugged in and turned on, and if Ready appears on the printer display.	solved.	
b Resend the print job.		
Do the jobs print?		
Step 3	The problem is	Go to step 4.
If an error message appears on the printer display, then clear the message.	solved.	
Note: The printer continues to print after clearing the message.		
Do the jobs print?		
Step 4	The problem is	Go to step 5.
a Check if the ports (USB, serial, or Ethernet) are working and if the cables are securely connected to the computer and the printer.	solved.	
Note: For more information, see the setup documentation that came with the printer.		
b Resend the print job.		
Do the jobs print?		
Step 5	The problem is	Go to step 6.
a Turn off the printer, then wait for about 10 seconds, and then turn the printer back on.	solved.	
b Resend the print job.		
Do the jobs print?		
Step 6	The problem is	Contact <u>customer</u>
a Remove, and then reinstall the printer software. For more information, see <u>"Installing the printer" on page 45</u> .	solved.	support.
Note: The printer software is available at http://support.lexmark.com .		
b Resend the print job.		
Do the jobs print?		

Tray linking does not work

Notes:

- The trays can detect paper length.
- The multipurpose feeder does not automatically detect the paper size. You must set the size from the Paper Size/Type menu.

Action	Yes	No
Step 1	The problem is	Go to step 2.
a Open the trays, and then check if they contain paper of the same size and type.	solved.	
 Check if the paper guides are in the correct positions for the size of the paper loaded in each tray. 		
 Check if the paper size indicators on the paper guides are aligned with the paper size indicators on the tray. 		
b Resend the print job.		
Do the trays link correctly?		
Step 2	The problem is	Contact <u>customer</u>
a From the printer control panel, set the paper size and type in the Paper menu to match the paper loaded in the trays to be linked.	solved.	<u>support</u> .
Note: The paper size and type must match for trays to be linked.		
b Resend the print job.		
Do the trays link correctly?		

Unexpected page breaks occur

Action	Yes	No
Increase the printing timeout. a From the home screen, navigate to: > Settings > General Settings > Timeouts b Increase the Print Timeout setting, and then touch Submit. c Resend the print job.	The problem is solved.	Check the original file for manual page breaks.
Did the file print correctly?		


Print quality problems

Characters have jagged or uneven edges



Action	Yes	No
 Step 1 a Print a font sample list to check if the fonts you are using are supported by the printer. 1 From the printer control panel, navigate to: > Reports > Print Fonts 2 Touch PCL Fonts or PostScript Fonts. 	Go to step 2.	The problem is solved.
 b Use a font that is supported by the printer or install the font that you want to use. For more information, contact your system support person. c Resend the print job. Do prints still contain characters that have jagged or uneven edges? 		
 Step 2 a Use a font that is supported by the printer or install the font that you want to use on your computer. For more information, contact your system support person. b Resend the print job. Do prints still contain characters that have jagged or uneven 	Contact <u>customer</u> <u>support</u> .	The problem is solved.


Clipped pages or images





Action	Yes	No
 Step 1 a Move the paper guides in the tray to the correct positions for the paper loaded. b Resend the print job. Is the page or image clipped? 	Go to step 2.	The problem is solved.
Step 2	Go to step 3.	Do one or more of
From the control panel, set the paper size and type in the Paper menu to match the paper loaded in the tray. Do the paper size and type match the paper loaded in the tray?	Go to step 3.	the following: • Specify the paper size from the tray settings to match the paper loaded in the tray.
		 Change the paper loaded in the tray to match the paper size specified in the tray settings.
 Step 3 a Depending on your operating system, specify the paper size from Printing Preferences or from the Print dialog. b Resend the print job. 	Go to step 4.	The problem is solved.
Is the page or image clipped?		
 Step 4 a Clean the charger and the printhead lens. b Resend the print job. Is the page or image clipped?	Go to step 5.	The problem is solved.
Step 5	Contact customer	The problem is
 a Remove, and then reinstall the photoconductor unit. Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. b Resend the print job. Is the page or image clipped? 	support.	solved.
la the page of fillage clipped:		

Gray background on prints






Action	Yes	No
 Step 1 a From the Quality menu on the control panel, decrease the toner darkness. b Resend the print job. 	The problem is solved.	Go to step 2.
Did the gray background disappear from the prints?		
Remove, and then reinstall the photoconductor unit and the toner cartridge.	The problem is solved.	Go to step 3.
Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems.		
b Resend the print job.		
Did the gray background disappear from the prints?		
Step 3a Clean the charger and the printhead lens.b Resend the print job.	The problem is solved.	Go to step 4.
Did the gray background disappear from the prints?		
Step 4 Replace the photoconductor unit, and then resend the print job.	The problem is solved.	Contact <u>customer</u> <u>support</u> .
Did the gray background disappear from the prints?		

Horizontal voids appear on prints



Action	Yes	No
 Step 1 a Make sure that your software program is using a correct fill pattern. b Resend the print job. Do horizontal voids appear on prints? 	Go to step 2.	The problem is solved.
 Step 2 a Load the specified tray or feeder with a recommended type of paper. b Resend the print job. Do horizontal voids appear on prints? 	Go to step 3.	The problem is solved.
Step 3 a Remove, and then reinstall the photoconductor unit. Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems. b Resend the print job. Do horizontal voids appear on prints?	Go to step 4.	The problem is solved.
Step 4 a Clean the charger and the printhead lens. b Resend the print job. Do horizontal voids appear on prints?	Go to step 5.	The problem is solved.
Step 5 Replace the photoconductor unit, and then resend the print job. Do horizontal voids appear on prints?	Contact <u>customer</u> <u>support</u> .	The problem is solved.

Incorrect margins on prints



Action	Yes	No
Step 1 a Move the width and length guides in the tray to the correct positions for the paper size loaded. b Resend the print job. Are the margins correct?	The problem is solved.	Go to step 2.
Step 2 From the printer control panel, set the paper size in the Paper menu to match the paper loaded in the tray. Does the paper size match the paper loaded in the tray?	Go to step 3.	Do one or more of the following: • Specify the paper size from the tray settings to match the paper loaded in the tray. • Change the paper loaded in the tray to match the paper size specified in the tray settings.
 Step 3 a Depending on your operating system, specify the paper size from Printing Preferences or from the Print dialog. b Resend the print job. Are the margins correct?	The problem is solved.	Contact <u>customer</u> <u>support</u> .

Paper curl

Action	Yes	No
Step 1 Move the width and length guides in the tray to the correct positions for the size of the paper loaded.	Go to step 2.	Adjust the width and length guides.
Are the width and length guides positioned correctly?		
Step 2 From the printer control panel, set the paper type and weight in the Paper menu to match the paper loaded in the tray.	Go to step 3.	Specify the paper type and weight from the tray settings to match the paper
Do the paper type and weight match the type and weight of the paper in the tray?		loaded in the tray.

Action	Yes	No
 Step 3 a Depending on your operating system, specify the paper type and weight from Printing Preferences or from the Print dialog. b Resend the print job. Is the paper still curled? 	Go to step 4.	The problem is solved.
Step 4 a Remove the paper from the tray, and then turn it over. b Resend the print job. Is the paper still curled?	Go to step 5.	The problem is solved.
Step 5 a Load paper from a fresh package. Note: Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you use it. b Resend the print job. Is the paper still curled?	Contact <u>customer</u> <u>support</u> .	The problem is solved.

Printer is printing blank pages

Ad	tior	1	Yes	No
St	ep 1		Go to step 2.	The problem is
а	Ch un	eck if there is a packing material left on the photoconductor it.		solved.
	1	Remove the photoconductor unit.		
	2	Check if the packing material is properly removed from the photoconductor unit.		
		Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems.		
	3	Reinstall the photoconductor unit.		
b	Re	send the print job.		
ls	the	printer still printing blank pages?		

Action	Yes	No
Step 2a Clean the charger and the printhead lens.b Resend the print job.	Go to step 3.	The problem is solved.
Is the printer still printing blank pages?		
Step 3 Replace the photoconductor unit, and then resend the print job.	Contact <u>customer</u> <u>support</u> .	The problem is solved.
Is the printer still printing blank pages?		

Printer is printing solid black pages



Action	Yes	No
Step 1 a Reinstall the photoconductor unit. Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. b Resend the print job.	Go to step 2.	The problem is solved.
Step 2 a Clean the charger and the printhead lens. b Resend the print job. Is the printer printing solid black pages?	Go to step 3.	The problem is solved.
Step 3 Replace the photoconductor unit, and then resend the print job. Is the printer printing solid black pages?	Contact <u>customer</u> <u>support</u> .	The problem is solved.

Print irregularities





Action	Yes	No
 Step 1 a Move the paper guides in the tray to the correct positions for the paper size loaded in the tray. b Resend the print job. Do print irregularities still appear? 	Go to step 2.	The problem is solved.
	Co to stop 3	Specific the namer
Step 2 From the control panel, set the paper size and type in the Paper menu to match the paper loaded in the tray.	Go to step 3.	Specify the paper size and type in the tray settings to match the paper
Do the printer settings match the size and type of the paper loaded in the tray?		loaded in the tray.
 Step 3 a Depending on your operating system, specify the paper type and weight in Printing Preferences or in the Print dialog. b Resend the print job. Do print irregularities still appear?	Go to step 4.	The problem is solved.
Step 4 Check if the paper loaded in the tray has texture or rough finishes. Are you printing on textured or rough paper?	From the control panel, set the paper texture in the Paper menu to match the paper loaded in the tray.	Go to step 5.
Step 5 a Load paper from a fresh package. Note: Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you use it. b Resend the print job. Do print irregularities still appear?	Go to step 6.	The problem is solved.
Step 6 a Clean the charger and the printhead lens. b Resend the print job. Do print irregularities still appear?	Go to step 7.	The problem is solved.

Action	Yes	No
Step 7 Replace the photoconductor unit, and then resend the print job. Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems.	Contact <u>customer</u> <u>support</u> or your service representative.	The problem is solved.
Do print irregularities still appear?		

Print is too dark



Action	Yes	No
Step 1 a From the Quality menu on the control panel, reduce the toner darkness. Note: 8 is the factory default setting. b Resend the print job. Is the print still too dark?	Go to step 2.	The problem is solved.
 Step 2 a From the control panel, set the paper type, texture, and weight in the Paper menu to match the paper loaded in the tray. b Resend the print job. Is the tray set to the type, texture, and weight of the paper loaded? 	Go to step 3.	Do one or more of the following: • Specify the paper type, texture, and weight from the tray settings to match the paper loaded in the tray. • Change the paper loaded in the tray to match the paper ype, texture, and weight specified in the tray settings.

Action	Yes	No
 Step 3 a Depending on your operating system, specify the paper type, texture, and weight from Printing Preferences or from the Print dialog. b Resend the print job. Is the print still too dark? 	Go to step 4.	The problem is solved.
Step 4 Check if the paper loaded in the tray has texture or rough finishes. Are you printing on textured or rough paper?	From the control panel, change the texture settings in the Paper Texture menu to match the paper you are printing on.	Go to step 5.
 Step 5 a Load paper from a fresh package. Note: Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you use it. b Resend the print job. 	Go to step 6.	The problem is solved.
Step 6 a Clean the charger and the printhead lens. b Resend the print job. Is the print still too dark?	Go to step 7.	The problem is solved.
Step 7 Replace the photoconductor unit, and then resend the print job. Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems. Is the print still too dark?	Contact <u>customer</u> <u>support</u> .	The problem is solved.


Print is too light



Action	Yes	No
 Step 1 a From the Quality menu on the control panel, increase the toner darkness. Note: 8 is the factory default setting. b Resend the print job. 	Go to step 2.	The problem is solved.
Step 2	Go to step 3.	Change the paper
From the control panel, set the paper type, texture, and weight in the Paper menu to match the paper loaded in the tray. Is the tray set to the type, texture, and weight of the paper loaded?		type, texture, and weight to match the paper loaded in the tray.
Step 3	Go to step 4.	The problem is
a Depending on your operating system, specify the paper type, texture, and weight from Printing Preferences or from the Print dialog.		solved.
b Resend the print job.		
Is the print still too light?		
Step 4 Make sure that the paper has no texture or rough finishes. Are you printing on textured or rough paper?	From the control panel, change the texture settings in the Paper Texture menu to match the	Go to step 5.
	paper you are printing on.	
Step 5	Go to step 6.	The problem is
 a Load paper from a fresh package. Note: Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you use it. b Resend the print job. 		solved.
Is the print still too light?		
Step 6 a Clean the charger and the printhead lens. b Resend the print job.	Go to step 7.	The problem is solved.
Is the print still too light?		


Action	Yes	No
	Contact <u>customer</u> <u>support</u> .	The problem is solved.
Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems. Is the print still too light?		

Repeating defects appear on prints



Action	Yes	No
Step 1	Go to step 2.	The problem is
a Clean the charger and the printhead lens.		solved.
b Resend the print job.		
Do repeating defects still appear on prints?		
Step 2	Go to step 3.	The problem is
a Replace the photoconductor unit if the distance between the defects is equal to 95.8 mm (3.77 in.).		solved.
b Resend the print job.		
Do repeating defects still appear on prints?		
Step 3	Contact <u>customer</u>	The problem is
a Replace the 300K maintenance kit if the distance between the defects is equal to either of the following:	support.	solved.
• 62.65 mm (2.47 in.)		
• 75.85 mm (2.99 in.)		
b Resend the print job.		
Do repeating defects still appear on prints?		


Shadow images appear on prints





Action	Yes	No
Step 1 Load paper with the correct paper type and weight in the tray. Is paper with the correct paper type and weight loaded in the tray?	Go to step 2.	Load paper with the correct paper type and weight in the tray.
Step 2 From the control panel, set the paper type and weight in the Paper menu to match the paper loaded in the tray. Is the tray set to the type and weight of the paper loaded?	Go to step 3.	Change the paper loaded in the tray to match the paper type and weight specified in the tray settings.
 Step 3 a Depending on your operating system, specify the paper type and weight from Printing Preferences or from the Print dialog. b Resend the print job. Do shadow images still appear on prints? 	Go to step 4.	The problem is solved.
Step 4 a Clean the charger and the printhead lens. b Resend the print job. Do shadow images still appear on prints?	Go to step 5.	The problem is solved.
Step 5 Replace the photoconductor unit, and then resend the print job. Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems. Do shadow images still appear on prints?	Contact <u>customer</u> <u>support</u> .	The problem is solved.

Skewed print



Action	Yes	No
 Step 1 a Move the width and length guides in the tray to the correct positions for the size of the paper loaded. b Resend the print job. 	Go to step 2.	The problem is solved.
Is the print still skewed?		
Step 2	Contact <u>customer</u>	The problem is
a Check if you are printing on a paper that is supported by the tray.	support.	solved.
b Resend the print job.		
Is the print still skewed?		

Streaked horizontal lines appear on prints



Action	Yes	No
Step 1 a Depending on your operating system, specify the tray or feeder from Printing Preferences or the Print dialog.	Go to step 2.	The problem is solved.
b Resend the print job.		
Do streaked horizontal lines appear on prints?		
Step 2 From the control panel, set the paper type and weight in the Paper menu to match the paper loaded in the tray.	Go to step 3.	Change the paper type and weight to match the paper loaded in the tray.
Do the paper type and weight match the type and weight of the paper in the tray?		

Action	Yes	No
 Step 3 a Load paper from a fresh package. Note: Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you use it. b Resend the print job. 	Go to step 4.	The problem is solved.
Do streaked horizontal lines appear on prints?		
a Remove, and then reinstall the photoconductor unit. Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. b Resend the print job. Do streaked horizontal lines appear on prints?	Go to step 5.	The problem is solved.
Step 5 a Clean the charger and the printhead lens. b Resend the print job. Do streaked horizontal lines appear on prints?	Go to step 6.	The problem is solved.
Step 6 Replace the photoconductor unit, and then resend the print job. Do streaked horizontal lines appear on prints?	Contact <u>customer</u> <u>support</u> .	The problem is solved.

Streaked vertical lines appear on prints






Action	Yes	No
Step 1 a Depending on your operating system, specify the paper type, texture, and weight from Printing Preferences or from the Print dialog.	Go to step 2.	The problem is solved.
b Resend the print job. Do streaked vertical lines appear on prints?		


Action	Yes	No
Step 2 From the control panel, set the paper texture, type, and weight in the Paper menu to match the paper loaded in the tray. Do the paper texture, type, and weight match the paper in the tray?	Go to step 3.	Do one or more of the following: • Specify the paper texture, type, and weight from the tray settings to match the paper loaded in the tray. • Change the paper loaded in the tray to match the paper texture, type, and weight specified in the tray settings.
 Step 3 a Load paper from a fresh package. Note: Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you use it. b Resend the print job. Do streaked vertical lines appear on prints?	Go to step 4.	The problem is solved.
Step 4 a Remove, and then reinstall the photoconductor unit. 1 Remove the photoconductor unit. Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. 2 Install the photoconductor unit. b Resend the print job. Do streaked vertical lines appear on prints?	Go to step 5.	The problem is solved.
Step 5 a Clean the charger and the printhead lens. b Resend the print job. Do streaked vertical lines appear on prints?	Go to step 6.	The problem is solved.
Step 6 Replace the photoconductor unit, and then resend the print job. Do streaked vertical lines appear on prints?	Contact <u>customer</u> <u>support</u> .	The problem is solved.

Toner fog or background shading appears on prints



Action	Yes	No
Step 1a Clean the charger and the printhead lens.b Resend the print job.	Go to step 2.	The problem is solved.
Did the toner fog or background shading disappear from the prints?		
Step 2	The problem is	Go to step 3.
a Reinstall the photoconductor unit.	solved.	
 Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. b Resend the print job. 		
Did the toner fog or background shading disappear from the prints?		
Step 3	The problem is	Contact <u>customer</u>
Replace the photoconductor unit, and then resend the print job.	solved.	support.
Did the toner fog or background shading disappear from the prints?		

Toner rubs off



Action	Yes	No
Step 1 From the Paper menu on the printer control panel, check the paper type, texture, and weight. Do the paper type, texture, and weight match the paper loaded in the tray?	Go to step 2.	Specify the paper type, texture, and weight from the tray settings to match the paper loaded in the tray.
Step 2 Resend the print job.	Contact <u>customer</u> <u>support</u> .	The problem is solved.
Does the toner still rub off?		


Toner specks appear on prints

Action	Yes	No
Step 1a Clean the charger and the printhead lens.b Resend the print job.	Go to step 2.	The problem is solved.
Do toner specks appear on prints?		
Step 2 Replace the photoconductor unit, and then resend the print job.	Contact <u>customer</u> <u>support</u> .	The problem is solved.
Do toner specks appear on prints?		

Transparency print quality is poor

Action	Yes	No
Step 1 From the printer control panel, set the paper type in the Paper menu to match the paper loaded in the tray.	Go to step 2.	Set the paper type to Transparency.
Is the paper type for the tray set to Transparency?		
Step 2 a Check if you are using a recommended type of transparency. b Resend the print job.	Contact <u>customer</u> <u>support</u> .	The problem is solved.
Is the print quality still poor?		

Uneven print density



Action	Yes	No
Step 1a Clean the charger and the printhead lens.b Resend the print job.	Go to step 2.	The problem is solved.
Is the print density uneven?		
Step 2 Replace the photoconductor unit, and then resend the print job.	Contact <u>customer</u> <u>support</u> .	The problem is solved.
Is the print density uneven?		

Vertical voids appear on prints



Action	Yes	No
 Step 1 a Make sure your software program is using a correct fill pattern. b Resend the print job. 	Go to step 2.	The problem is solved.
Do vertical voids appear on prints?		
 Step 2 a From the control panel, set the paper type and weight in the Paper menu to match the paper loaded in the tray. b Resend the print job. 	Go to step 3.	The problem is solved.
Do vertical voids appear on prints?		

Action	Yes	No
 Step 3 Check if you are using a recommended type of paper. a Load the specified tray or feeder with a recommended type of paper. b Resend the print job. 	Go to step 4.	The problem is solved.
Do vertical voids appear on prints?		
Step 4 a Remove the photoconductor unit, and then reinstall it.	Go to step 5.	The problem is solved.
 Warning—Potential Damage: Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. b Resend the print job. 		
Do vertical voids appear on prints?		
Step 5 a Clean the charger and the printhead lens. b Resend the print job. Do vertical voids appear on prints?	Go to step 6.	The problem is solved.
Step 6	Contact <u>customer</u>	The problem is
Replace the photoconductor unit, and then resend the print job.	support.	solved.
Do vertical voids appear on prints?		

Solving copy problems

Copier does not respond

Action	Yes	No
Step 1 Check if an error or status message appears on the display.	Clear the error or status message.	Go to step 2.
Does an error or status message appear?		
Step 2 Check if the power cord is plugged into the printer and a properly grounded electrical outlet.	Go to step 3.	Connect the power cord to the printer and a properly grounded electrical
Is the power cord plugged into the printer and a properly grounded electrical outlet?		outlet.

Action	Yes	No
Step 3 Turn off the printer, then wait for about 10 seconds, and then turn it back on.	The problem is solved.	Contact <u>customer</u> <u>support</u> .
Did Performing Self Test and Ready appear?		

Partial document or photo copies

Action	Yes	No
Step 1 Check the placement of the document or photo. Make sure the document or photo is loaded facedown on the scanner glass in the upper left corner. Is the document or photo loaded correctly?	Go to step 2.	Place the document or photo facedown on the scanner glass in the upper left corner.
Step 2	Go to step 3.	Change the paper
Check if the paper size setting matches the size of the paper loaded in the tray. From the Paper menu on the printer control panel, check the Paper Size setting. Does the paper size setting match the size of the paper loaded in the tray.		size setting to match the paper loaded in the tray, or load the tray with paper that matches the paper size setting.
 Step 3 a Specify the paper size. Depending on your operating system, specify the paper size in Printing Preferences or the Print dialog. b Resend the print job. 	The problem is solved.	Contact <u>customer</u> <u>support</u> .
Do copies print properly?		

Poor copy quality

Action	Yes	No
Step 1 Check if an error or status message appears on the display.	Clear the error or status message.	Go to step 2.
Does an error or status message appear?		
Step 2 Check the quality of the original document.	Go to step 3.	Increase the scan resolution setting for a higher-quality
Is the quality of the original document satisfactory?		output.

Action	Yes	No
Step 3	Go to step 4.	See <u>"Cleaning the</u>
If dark marks appear on prints, then clean the scanner glass and		scanner glass" on
the ADF glass using a clean, lint-free cloth dampened with water.		<u>page 204</u> .
Is the scanner glass clean?		
Step 4	Go to step 5.	See <u>"Print quality</u>
Send a print job, and then check for print quality problems.		problems" on
a From the Copy menu, adjust the toner darkness.		<u>page 300</u> .
b If the print remains faded, then replace the toner cartridge.		
Is the print quality satisfactory?		
Step 5	Go to step 6.	Place the document
Check the placement of the document or photo.		or photo facedown
Make sure that the document or photo is loaded facedown on		on the scanner glass in the upper left
the scanner glass in the upper left corner.		corner.
Is the document or photo loaded correctly?		
Step 6	Go to step 7.	Change the Content
Check the copy settings.		Type and Content
From the Copy screen, check if the Content Type and Content		Source settings to match the document
Source settings are correct for the document being scanned.		being scanned.
Are the Content Type and Content Source settings correct for the		
document being scanned?		
Step 7	Go to step 8.	The problem is
Check for patterns on prints.		solved.
a From the Copy screen, navigate to:		
Advanced Options > Advanced Imaging > Sharpness > select a lower setting		
Note: Make sure that no scaling is being selected.		
b Resend the copy job.		
Do patterns appear on prints?		
Step 8	Go to step 9.	The problem is
Check for missing or faded text on prints.		solved.
a From the Copy screen, navigate to:		
Advanced Options > Advanced Imaging		
b Adjust the settings:		
Sharpness—Increase the current setting.		
Contrast—Increase the current setting.		
c Resend the copy job.		
Do prints have missing or faded text?		

Action	Yes	No
Step 9	Contact <u>customer</u>	The problem is solved.
Check for washed-out or overexposed output.	support.	solved.
a From the Copy screen, navigate to:		
Advanced Options > Advanced Imaging		
b Adjust the settings of the following:		
Background Removal—Reduce the current setting.		
Shadow Detail—Reduce the current setting.		
c Resend the copy job.		
Do pages show washed-out or overexposed prints?		

Solving fax problems

Caller ID is not shown

Action	Yes	No
Contact your telephone company to check if your telephone line is subscribed to the caller ID service.	The problem is solved.	Contact <u>customer</u> <u>support</u> .
Notes:		
 If your region supports multiple caller ID patterns, then you may have to change the default setting. There are two settings available: FSK (pattern 1) and DTMF (pattern 2). 		
 The availability of these settings in the Fax menu depends on whether your country or region supports multiple caller ID patterns. 		
 Contact your telephone company to determine which pattern or switch setting to use. 		
Does the caller ID appear?		

Cannot send or receive a fax

Action	Yes	No
Step 1 Check if an error or status message appears on the display. Is there an error or status message on the display?	Clear the error or status message.	Go to step 2.
Step 2 Check if the power cord is plugged into the printer and a properly grounded electrical outlet. Is the power cord plugged into the printer and a properly grounded electrical outlet?	Go to step 3.	Connect the power cord to the printer and a properly grounded electrical outlet.
Step 3 Check the power. Check if the printer is plugged in and turned on, and if Ready appears on the display. Is the printer turned on, and does Ready appear on the display?	Go to step 4.	Turn on the printer, and then wait until Ready appears on the display.
Step 4 Check the printer connections. If applicable, check if the cable connections for the following equipment are secure: • Telephone • Handset • Answering machine Are the cable connections secure?	Go to step 5.	Securely connect the cables.
 Step 5 a Check the telephone wall jack. 1 Plug the telephone cable into the wall jack. 2 Listen for a dial tone. 3 If you do not hear a dial tone, then plug a different telephone cable into the wall jack. 4 If you still do not hear a dial tone, then plug the telephone cable into a different wall jack. 5 If you hear a dial tone, then connect the printer to that wall jack. b Try sending or receiving a fax. Can you send or receive a fax? 	The problem is solved.	Go to step 6.

Action	Yes	No
 Step 6 Check if the printer is connected to an analog phone service or the correct digital connector. The fax modem is an analog device. Certain devices can be connected to the printer so that digital telephone services can be used. If you are using an ISDN telephone service, then connect the printer to an analog telephone port (an R-interface port) on an ISDN terminal adapter. For more information and to request an R-interface port, contact your ISDN provider. If you are using DSL, then connect to a DSL filter or router that will support analog use. For more information, contact your DSL provider. If you are using a PBX telephone service, then make sure you are connecting to an analog connection on the PBX. If none exists, then consider installing an analog telephone line for the fax machine. Is the printer connected to an analog phone service or the correct digital connector? 	Go to step 7.	Connect the printer to an analog phone service or the correct digital connector.
Step 7 Check for a dial tone. Did you hear a dial tone?	Go to step 8.	 Try calling the fax number to make sure that it is working properly. If the telephone line is being used by another device, then wait until the other device is finished before sending a fax. If you are using the On Hook Dial feature, then turn up the volume to check if you hear a dial tone.
Step 8 Temporarily disconnect other equipment (such as answering machines, computers with modems, or telephone line splitters) between the printer and the telephone line, and then try sending or receiving a fax. Can you send or receive a fax?	The problem is solved.	Go to step 9.

Action	Yes	No
 Step 9 a Temporarily disable call waiting. Contact your telephone company to obtain the keypad sequence for temporarily disabling call waiting. b Try sending or receiving a fax. 	The problem is solved.	Go to step 10.
Can you send or receive a fax?		
 Step 10 a Temporarily disable voice mail service. For more information, contact your telephone company. Note: If you want to use both voice mail and the printer, then consider adding a second telephone line for the printer. b Try sending or receiving a fax. Can you send or receive a fax? 	The problem is solved.	Go to step 11.
Step 11 Scan the original document one page at a time. a Dial the fax number. b Scan the document one page at a time. Can you send or receive a fax?	The problem is solved.	Contact <u>customer</u> <u>support</u> .

Can receive but not send faxes

Action	Yes	No
Step 1 Check if the printer is in Fax mode. From the home screen, touch Fax to put the printer in Fax mode, and then send the fax.	The problem is solved.	Go to step 2.
Can you send faxes?		
Step 2 Load the original document properly into the ADF tray or on the scanner glass.	The problem is solved.	Go to step 3.
Can you send faxes?	The problem is	Contact quaternar
 Step 3 Set up the shortcut number properly. Check if the shortcut number has been set for the telephone number that you want to dial. Dial the telephone number manually. 	The problem is solved.	Contact <u>customer</u> <u>support</u> .
Can you send faxes?		

Can send but not receive faxes

Action	Yes	No
Step 1 Check the tray or feeder. If empty, then load paper in the tray or feeder. Can you receive faxes?	The problem is solved.	Go to step 2.
 Step 2 Check the ring count delay settings. a Open a Web browser, and then type the printer IP address in the address field. Notes: View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123. If you are using a proxy server, then temporarily disable it to load the Web page correctly. b Click Settings > Fax Settings > Analog Fax Setup. c In the "Rings to Answer" field, enter the number of times you want the phone to ring before the printer answers. d Click Submit. Can you receive faxes?	The problem is solved.	Go to step 3.
Step 3 Replace the toner cartridge. For more information, see the instruction sheet that came with the supply. Can you receive faxes?	The problem is solved.	Contact <u>customer</u> <u>support</u> .

Fax and e-mail functions are not set up

Notes:

- Before you troubleshoot, check if the fax cables are connected.
- The indicator light is blinking red until you set up fax and e-mail.

	Action	Yes	No
	a From the home screen, navigate to:	The problem is	Contact <u>customer</u>
	> Settings > General Settings > Run initial setup > Yes > Submit	solved.	support.
	b Turn off the printer, and then turn it back on.		
	The "Select your language" screen appears on the printer display.		
	c Select a language, and then touch ✓.		
	d Select a country or region, and then touch Next .		
	e Select a time zone, and then touch Next .		
	f Select Fax and E-mail , and then touch Next .		
4	Are fax and e-mail functions set up?		

Solving scanner problems

Cannot scan from a computer

Action	Yes	No
Step 1 Make sure the printer is turned on and that Ready appears on the printer display before scanning a job.	Go to step 3.	Go to step 2.
Does Ready appear before scanning the job?		
Step 2 Turn off the printer, then wait for about 10 seconds, and then turn the printer back on.	Clear the error message.	Go to step 3.
Is there an error message on the printer display?		
Step 3 Check the cable connections between the printer and the print server to make sure they are secure. For more information, see the setup documentation that came with the printer.	Contact <u>customer</u> <u>support</u> .	Tighten the cable connections.
Are the cable connections between the printer and the print server secure?		

Partial document or photo scans

Action	Yes	No
Check the placement of the document or photo. Make sure the document or photo is loaded facedown on the scanner glass in the upper left corner.	Contact <u>customer</u> <u>support</u> .	Load the document or photo facedown on the scanner glass in the upper left
Is the document or photo loaded correctly?		corner.

Poor scanned image quality

Action	Yes	No
Step 1 Check if an error message appears on the display. Is there an error message on the printer display?	Clear the error message.	Go to step 2.
Step 2 Check the quality of the original document. Is the quality of the original document satisfactory?	Go to step 3.	Increase the scan resolution settings for a higher-quality output.
Step 3 Clean the scanner glass and the ADF glass using a clean, lint-free cloth dampened with water. Is the scanner glass clean?	Go to step 4.	See "Cleaning the scanner glass" on page 204.
Step 4 Check the placement of the document or photo. Make sure that the document or photo is loaded facedown on the scanner glass in the upper left corner. Is the document or photo loaded correctly?	Go to step 5.	Place the document or photo facedown on the scanner glass in the upper left corner.
 Step 5 Send a print job, and then check for print quality problems. From the Copy menu, adjust the toner darkness. When the print becomes faded, replace the toner cartridge. Is the print quality satisfactory? 	Go to step 6.	See "Print quality problems" on page 300.
Step 6 Check the scan settings. From the Scan screen, make sure that the Content Type and Content Source settings are correct for the document being scanned. Are the Content Type and Content Source settings correct for the document being scanned?	Go to step 7.	Change the Content Type and Content Source settings to match the document being scanned.

Action	Yes	No
Step 7 Increase the scan resolution settings for a higher-quality output.	Problem solved.	Contact <u>customer</u> <u>support</u> .
Did the increased resolution produce a higher-quality output?		

Scan job was not successful

Action	Yes	No
Step 1 Check the cable connections. Make sure the Ethernet or USB cable is securely connected to the computer and the printer. Are the cables securely connected?	Go to step 2.	Connect the cables properly.
Step 2 Check if the file name is already in use. Is the file name already in use?	Change the file name.	Go to step 3.
Step 3 Check if the document or photo you want to scan is open in another application or being used by another user. Is the file you want to scan open by another application or user?	Close the file you are scanning.	Go to step 4.
Step 4 Check if either the Append time stamp or the Overwrite existing file check box is selected in the destination configuration settings. Is the Append time stamp or Overwrite existing file check box selected in the destination configuration settings?	Contact <u>customer</u> <u>support</u> .	Select the Append time stamp or Overwrite existing file check box in the destination configuration settings.

Scanner unit does not close

Action	Yes	No
Check if there are obstructions in the scanner unit.	The problem is	Contact <u>customer</u>
a Lift the scanner unit.	solved.	support.
b Remove any obstruction keeping the scanner unit open.		
c Lower the scanner unit.		
Did the scanner unit close correctly?		

Scanning takes very long or freezes the computer

Action	Yes	No
Step 1 Check if other applications are interfering with the scan. Close all applications that are not being used.	Go to step 2.	The problem is solved.
Does scanning still take too long or freeze the computer?		
Step 2	Contact <u>customer</u> support.	The problem is solved.
Select a lower scan resolution.	support.	Solved.
Does scanning still take too long or freeze the computer?		

The scanner does not respond

Action	Yes	No
Step 1	Go to step 2.	Turn on the printer.
Check if the printer is turned on.		
Is the printer turned on?		
Step 2 Check if the printer cable is securely attached to the printer and the computer, print server, option, or other network device. Is the printer cable securely attached to the printer and the computer, print server, option, or other network device?	Go to step 3.	Connect the printer cable securely to the printer and the computer, print server, option, or other network device.
Step 3 Check if the power cord is plugged into the printer and a properly grounded electrical outlet. Is the power cord plugged into the printer and a properly grounded electrical outlet?	Go to step 4.	Connect the power cord to the printer and a properly grounded electrical outlet.
Step 4 Check if the electrical outlet is turned off by a switch or breaker. Is the electrical outlet turned off by a switch or breaker?	Turn on the switch or reset the breaker.	Go to step 5.
Step 5	Connect the printer	Go to step 6.
Check if the printer is plugged into any surge protectors, uninterruptible power supplies, or extension cords.	power cord directly to a properly grounded electrical	3 13 Stop 5.
Is the printer plugged into any surge protectors, uninterruptible power supplies, or extension cords?	outlet.	

Action	Yes	No
Step 6 Check other electrical equipment plugged into the outlet. Are the other electrical equipment working?	Unplug the other electrical equipment and turn on the printer. If the printer does not work, then reconnect the other electrical equipment and then go to step 6.	Go to step 7.
Step 7 Turn off the printer, then wait for about 10 seconds, and then turn the printer back on. Are the printer and scanner working?	The problem is solved.	Contact <u>customer</u> <u>support</u> .

Solving home screen application problems

An application error has occurred

Action	Yes	No
Step 1	Go to step 2.	Contact <u>customer</u>
Check the system log for relevant details.		support.
a Open a Web browser, and then type the printer IP address in the address field.		
If you do not know the IP address of the printer, then you can:		
 View the IP address on the printer home screen. 		
 Print a network setup page or the menu settings pages, and then locate the IP address in the TCP/IP section. 		
Note: An IP address appears as four sets of numbers separated by periods, such as 123.123.123.23.		
b Click Settings > Apps > Apps Management > System tab > Log .		
c From the Filter menu, select an application status.		
d From the Application menu, select an application, and then click Submit .		
Does an error message appear in the log?		
Step 2	The problem is	Contact <u>customer</u>
Resolve the error.	solved.	support.
Is the application working now?		

Embedded Web Server does not open

Action	Yes	No
Step 1 Make sure the printer IP address is correct. View the printer IP address: • From the printer home screen • From the TCP/IP section in the Network/Ports menu • By printing a network setup page or menu settings page, and then finding the TCP/IP section Note: An IP address appears as four sets of numbers separated by periods, such as 123.123.123.123. Is the printer IP address correct?	Go to step 2.	Type the correct printer IP address in the address field of your Web browser. Note: Depending on the network settings, you may need to type "https://" instead of "http://" before the printer IP address to access the Embedded Web Server.
Step 2 Check if the printer is turned on. Is the printer turned on?	Go to step 3.	Turn on the printer.
Step 3 Check if the network connection is working. Is the network connection working?	Go to step 4.	Contact your system support person.
Step 4 Make sure the cable connections to the printer and print server are secure. For more information, see the setup documentation that came with the printer. Are the cable connections to the printer and print server secure?	Go to step 5.	Tighten the cable connection.
Step 5 Temporarily disable the Web proxy servers. Note: Proxy servers may block or restrict you from accessing certain Web sites including the Embedded Web Server. Are the Web proxy servers disabled?	Go to step 6.	Contact your system support person.
Step 6 Access the Embedded Web Server again by typing the correct IP address in the address field. Did the Embedded Web Server open?	The problem is solved.	Contact <u>customer</u> <u>support</u> .

Contacting customer support

When you contact customer support, you will need to be able to describe the problem you are experiencing, the message on the printer display, and the troubleshooting steps you have already taken to find a solution.

You need to know your printer model type and serial number. For more information, see the label at the back of the printer. The serial number is also listed on the menu settings page.

Lexmark has various ways to help you solve your printing problem. Visit the Lexmark Web site at http://support.lexmark.com, and then select one of the following:

Tech Library	You can browse our library of manuals, support documentation, drivers, and other downloads to help you solve common problems.
E-mail	You can send an e-mail to the Lexmark team, describing your problem. A service representative will respond and provide you with information to solve your problem.
Live chat	You can chat directly with a service representative. They can work with you to solve your printer problem or provide assistance through Assisted Service where the service representative can remotely connect to your computer through the Internet to troubleshoot problems, install updates, or complete other tasks to help you successfully use your Lexmark product.

Telephone support is also available. In the U.S. or Canada, call 1-800-539-6275. For other countries or regions, visit http://support.lexmark.com.

Notices

Product information

Product name:

Lexmark MX910de, MX911dte, MX912dxe

Machine type:

7421

Model(s):

036, 236, 436

Edition notice

September 2022

The following paragraph does not apply to any country where such provisions are inconsistent with local law: LEXMARK INTERNATIONAL, INC., PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions; therefore, this statement may not apply to you.

This publication could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in later editions. Improvements or changes in the products or the programs described may be made at any time.

References in this publication to products, programs, or services do not imply that the manufacturer intends to make these available in all countries in which it operates. Any reference to a product, program, or service is not intended to state or imply that only that product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any existing intellectual property right may be used instead. Evaluation and verification of operation in conjunction with other products, programs, or services, except those expressly designated by the manufacturer, are the user's responsibility.

For Lexmark technical support, visit http://support.lexmark.com.

For information on supplies and downloads, visit www.lexmark.com.

© 2014 Lexmark International, Inc.

All rights reserved.

GOVERNMENT END USERS

The Software Program and any related documentation are "Commercial Items," as that term is defined in 48 C.F.R. 2.101, "Computer Software" and "Commercial Computer Software Documentation," as such terms are used in 48 C.F.R. 12.212 or 48 C.F.R. 227.7202, as applicable. Consistent with 48 C.F.R. 12.212 or 48 C.F.R. 227.7202-1 through 227.7207-4, as applicable, the Commercial Computer Software and Commercial Software Documentation are licensed to the U.S. Government end users (a) only as Commercial Items and (b) with only those rights as are granted to all other end users pursuant to the terms and conditions herein.

Trademarks

Lexmark, Lexmark with diamond design, MarkNet, and MarkVision are trademarks of Lexmark International, Inc., registered in the United States and/or other countries.

ScanBack is a trademark of Lexmark International, Inc.

Mac and the Mac logo are trademarks of Apple Inc., registered in the U.S. and other countries.

PCL® is a registered trademark of the Hewlett-Packard Company. PCL is Hewlett-Packard Company's designation of a set of printer commands (language) and functions included in its printer products. This printer is intended to be compatible with the PCL language. This means the printer recognizes PCL commands used in various application programs, and that the printer emulates the functions corresponding to the commands.

The following terms are trademarks or registered trademarks of these companies:

Albertus	The Monotype Corporation plc
Antique Olive	Monsieur Marcel OLIVE
Apple-Chancery	Apple Computer, Inc.
Arial	The Monotype Corporation plc
CG Times	Based on Times New Roman under license from The Monotype Corporation plc, is a product of Agfa Corporation
Chicago	Apple Computer, Inc.
Clarendon	Linotype-Hell AG and/or its subsidiaries
Eurostile	Nebiolo
Geneva	Apple Computer, Inc.
GillSans	The Monotype Corporation plc
Helvetica	Linotype-Hell AG and/or its subsidiaries
Hoefler	Jonathan Hoefler Type Foundry
ITC Avant Garde Gothic	International Typeface Corporation
ITC Bookman	International Typeface Corporation
ITC Mona Lisa	International Typeface Corporation
ITC Zapf Chancery	International Typeface Corporation
Joanna	The Monotype Corporation plc
Marigold	Arthur Baker
Monaco	Apple Computer, Inc.
New York	Apple Computer, Inc.
Oxford	Arthur Baker
Palatino	Linotype-Hell AG and/or its subsidiaries
Stempel Garamond	Linotype-Hell AG and/or its subsidiaries
Taffy	Agfa Corporation
Times New Roman	The Monotype Corporation plc

Univers	Linotype-Hell AG and/or its subsidiaries
---------	--

All other trademarks are the property of their respective owners.

AirPrint and the AirPrint logo are trademarks of Apple, Inc.

Federal Communications Commission (FCC) compliance information statement

This product has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

The FCC Class A limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference, in which case the user will be required to correct the interference at his own expense.

The manufacturer is not responsible for any radio or television interference caused by using other than recommended cables or by unauthorized changes or modifications to this equipment. Unauthorized changes or modifications could void the user's authority to operate this equipment.

Note: To assure compliance with FCC regulations on electromagnetic interference for a Class A computing device, use a properly shielded and grounded cable such as Lexmark part number 1021231 for parallel attach or 1021294 for USB attach. Use of a substitute cable not properly shielded and grounded may result in a violation of FCC regulations.

Licensing notices

All licensing notices associated with this product can be viewed from the CD:\NOTICES directory of the installation software CD.

Noise emission levels

The following measurements were made in accordance with ISO 7779 and reported in conformance with ISO 9296.

Note: Some modes may not apply to your product.

1-meter average sound pressure, dBA		
Printing	One-sided: 52 (MX910de), 53 (MX911de, MX911dte), 55 (MX912de, MX912dxe); Two-sided: 55 (MX910de, MX911de, MX911dte), 56 (MX912de, MX912dxe)	
Scanning	57 (MX910de); 56 (MX911de, MX911dte, MX912de, MX912dxe)	

1-meter average sound pressure, dBA		
Copying	53 (MX910de); 54 (MX911de, MX911dte); 55 (MX911de, MX911dte)	
Ready	29 (MX910de); 31 (MX911de, MX911dte, MX912de, MX912dxe)	

Values are subject to change. See www.lexmark.com for current values.

Waste from Electrical and Electronic Equipment (WEEE) directive



The WEEE logo signifies specific recycling programs and procedures for electronic products in countries of the European Union. We encourage the recycling of our products.

If you have further questions about recycling options, visit the Lexmark Web site at <u>www.lexmark.com</u> for your local sales office phone number.

Taiwan RoHS information 限用物質含有情況標示

設備名稱:雷射印表機或多功能印表機 Equipment name: Laser Printer or Multifunction Printer			型號(型式):請參閱注意事項章節 Type designation (Type): Please see the Notices section.			
單元		限用物質及其化學符號				
Unit	Restricted s	ubstances a	nd their chem	ical symbols		
	鉛	汞	鎘	六價鉻	多溴聯苯	多溴二苯醚
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent chromium (Cr VI)	Polybrominated biphenyl (PBB)	Polybrominated diphenylether (PBDE)
電路板	超出	0	0	0	0	0
Circuit boards	(exceeding)					
	0.1 wt %					
電源供應器	超出	0	0	0	0	0
Power supply	(exceeding)					
	0.1 wt %					
電源線	超出	0	0	0	0	0
Power cords	(exceeding)					
	0.1 wt %					

設備名稱:雷射印表機或多功能印表機 型號(型式):請參閱注意事項章節 **Equipment name: Laser Printer or** Type designation (Type): Please see the Notices section. **Multifunction Printer** 單元 限用物質及其化學符號 Unit Restricted substances and their chemical symbols 鉛 汞 鎘 六價鉻 多溴聯苯 多溴二苯醚 Lead (Pb) Cadmium **Polybrominated** Mercury Hexavalent Polybrominated (Hg) (Cd) chromium (Cr biphenyl (PBB) diphenylether VI) (PBDE) 連接器 \bigcirc \bigcirc 超出 \bigcirc \bigcirc \bigcirc (exceeding) Connectors 0.1 wt % 機械組件-軸. 超出 \bigcirc \bigcirc \bigcirc \bigcirc \bigcirc 滾軸 (exceeding) Mechanical 0.1 wt % assembliesshafts, rollers 機械組件-馬達 \bigcirc 超出 \bigcirc \bigcirc \bigcirc \bigcirc Mechanical (exceeding) assemblies-0.1 wt % motors 機械組件-其他 超出 \bigcirc \bigcirc \bigcirc \bigcirc \bigcirc Mechanical (exceeding) assemblies-0.1 wt % other 掃描器組件,僅適 超出 \bigcirc \bigcirc \bigcirc \bigcirc 用於多功能印表 (exceeding) 機產品 0.1 wt % Scanner assembly, for multifunction printer only \bigcirc \bigcirc \bigcirc 液晶顯示面板 超出 \bigcirc \bigcirc LCD display (exceeding) 0.1 wt %

備考 1. "超出 0.1 wt %"及 "超出 0.01 wt %"係指限用物質之百分比含量超出百分比含量基準值。

Note 1: "Exceeding 0.1 wt %" and "exceeding 0.01 wt %" indicate that the percentage content of the restricted substance exceeds the reference percentage value of presence condition.

備考 2. "○" 係指該項限用物質之百分比含量未超出百分比含量基準值。

Note 2: "O" indicates that the percentage content of the restricted substance does not exceed the percentage of reference value of presence condition.

備考 3. "一" 係指該項限用物質為排除項目。

Note 3: "—" indicates that the restricted substance corresponds to the exemption.

India E-Waste notice

This product complies with the India E-Waste (Management and Handling) Rules, 2011, which prohibit use of lead, mercury, hexavalent chromium, polybrominated biphenyls, or polybrominated diphenyl ethers in concentrations exceeding 0.1% by weight and 0.01% by weight for cadmium, except for the exemption set in Schedule II of the Rules.

Product disposal

Do not dispose of the printer or supplies in the same manner as normal household waste. Consult your local authorities for disposal and recycling options.

Static sensitivity notice



This symbol identifies static-sensitive parts. Do not touch in the areas near these symbols without first touching the metal frame of the printer.

ENERGY STAR

Any Lexmark product bearing the ENERGY STAR® emblem on the product or on a start-up screen is certified to comply with Environmental Protection Agency (EPA) ENERGY STAR requirements as configured when shipped by Lexmark.



Temperature information

Ambient operating temperature	10 to 30°C (50 to 86°F)
Shipping temperature	-10 to 40°C (14 to 104°F)
Storage temperature and relative humidity	-10 to 40°C (14 to 104°F)
	15 to 85% RH

Laser notice

The printer is certified in the U.S. to conform to the requirements of DHHS 21 CFR Chapter I, Subchapter J for Class I (1) laser products, and elsewhere is certified as a Class I laser product conforming to the requirements of IEC 60825-1: 2014.

Class I laser products are not considered to be hazardous. The printer contains internally a Class IIIb (3b) laser that is nominally a 15-milliwatt gallium arsenide laser operating in the wavelength of 787–800 nanometers. The laser system and printer are designed so there is never any human access to laser radiation above a Class I level during normal operation, user maintenance, or prescribed service condition.

Laser advisory label

A laser notice label may be affixed to this printer as shown:

DANGER - Invisible laser radiation when cartridges are removed and interlock defeated. Avoid exposure to laser beam.

PERIGO - Radiação a laser invisível será liberada se os cartuchos forem removidos e o lacre rompido. Evite a exposição aos feixes de laser.

Opasnost - Nevidlijvo lasersko zračenie kada su kasete ukloniene i poništena sigurnosna veza, Izbiegavati izlaganie zracima.

NEBEZPEČÍ - Když jsou vyjmuty kazety a je odblokována pojistka, ze zařízení je vysíláno neviditelné laserové záření. Nevystavujte se působení laserového paprsku. FARE - Usynlig laserstråling, når patroner fjernes, og spærreanordningen er slået fra. Undgå at blive udsat for laserstrålen.

GEVAAR - Onzichtbare laserstraling wanneer cartridges worden verwijderd en een vergrendeling wordt genegeerd. Voorkom blootstelling aan de laser.

DANGER - Rayonnements laser invisibles lors du retrait des cartouches et du déverrouillage des loquets. Eviter toute exposition au rayon laser.

VAARA - Näkymätöntä lasersäteilyä on varottava, kun värikasetit on poistettu ja lukitus on auki. Vältä lasersäteelle altistumista.

GEFAHR - Unsichtbare Laserstrahlung beim Herausnehmen von Druckkassetten und offener Sicherheitssperre. Laserstrahl meiden.

ΚΙΝΔΥΝΟΣ - Έκλυση αόρατης ακτινοβολίας laser κατά την αφαίρεση των κασετών και την απασφάλιση της μανδάλωσης. Αποφεύγετε την έκθεση στην ακτινοβολία laser.

VESZÉLY – Nem látható lézersugárzás fordulhat elő a patronok eltávolításakor és a zárószerkezet felbontásakor. Kerülje a lézersugárnak való kitettséget.

PERICOLO - Emissione di radiazioni laser invisibili durante la rimozione delle cartucce e del blocco. Evitare l'esposizione al raggio laser.

FARE – Usynlig laserstråling når kassettene tas ut og sperren er satt ut av spill. Unngå eksponering for laserstrålen.

NIEBEZPIECZEŃSTWO - niewidzialne promieniowanie laserowe podczas usuwania kaset i blokady. Należy unikać naświetlenia promieniem lasera.

ОПАСНО! Невидимое лазерное излучение при извлеченных картриджах и снятии блокировки. Избегайте воздействия лазерных лучей.

Pozor – Nebezpečenstvo neviditeľného laserového žiarenia pri odobratých kazetách a odblokovanej poistke. Nevystavujte sa lúčom.

PELIGRO: Se producen radiaciones láser invisibles al extraer los cartuchos con el interbloqueo desactivado. Evite la exposición al haz de láser.

FARA – Osynlig laserstrålning när patroner tas ur och spärrmekanismen är upphävd. Undvik exponering för laserstrålen.

危**险** - 当移除碳粉盒及互**锁**失效时会产生看不见的激光辐射,请避免暴露在激光光束下。

危險 - 移除碳粉匣與安全連續開關失效時會產生看不見的雷射輻射。請避免曝露在雷射光束下。

危険 - カートリッジが取り外され、内部ロックが無効になると、見えないレーザー光が放射されます。 このレーザー光に当たらないようにしてください。

Power consumption

Product power consumption

The following table documents the power consumption characteristics of the product.

Note: Some modes may not apply to your product.

Mode	Description	Power consumption (Watts)
Printing	The product is generating hard-copy output from electronic inputs.	One-sided: 865 (MX910de), 925 (MX911de, MX911dte), 985 (MX912de, MX912dxe); Two-sided: 790 (MX910de), 850 (MX911de, MX911dte), 890 (MX912de, MX912dxe)

Mode	Description	Power consumption (Watts)
Сору	The product is generating hard-copy output from hard-copy original documents.	880 (MX910de); 950 (MX911de, MX911dte); 1000 (MX912de, MX912dxe)
Scan	The product is scanning hard-copy documents.	230
Ready	The product is waiting for a print job.	220
Sleep Mode	The product is in a high-level energy-saving mode.	3.6
Hibernate	The product is in a low-level energy-saving mode.	0.6
Off	The product is plugged into an electrical outlet, but the power switch is turned off.	0

The power consumption levels listed in the previous table represent time-averaged measurements. Instantaneous power draws may be substantially higher than the average.

Values are subject to change. See www.lexmark.com for current values.

Sleep Mode

This product is designed with an energy-saving mode called *Sleep Mode*. The Sleep Mode saves energy by lowering power consumption during extended periods of inactivity. The Sleep Mode is automatically engaged after this product is not used for a specified period of time, called the *Sleep Mode Timeout*.

actory default Sleep Mode Timeout for this product (in minutes):	20	$\Big]$
--	----	---------

By using the configuration menus, the Sleep Mode Timeout can be modified between 1 minute and 120 minutes. Setting the Sleep Mode Timeout to a low value reduces energy consumption, but may increase the response time of the product. Setting the Sleep Mode Timeout to a high value maintains a fast response, but uses more energy.

Hibernate Mode

This product is designed with an ultra-low power operating mode called *Hibernate mode*. When operating in Hibernate Mode, all other systems and devices are powered down safely.

The Hibernate mode can be entered in any of the following methods:

- Using the Hibernate Timeout
- Using the Schedule Power modes
- Using the Sleep/Hibernate button

Factory default Hibernate Timeout for this product in all countries or regions	3 days
Tractory deliant insernate innecation this product in an equilibria	C days

The amount of time the printer waits after a job is printed before it enters Hibernate mode can be modified between one hour and one month.

Off mode

If this product has an off mode which still consumes a small amount of power, then to completely stop product power consumption, disconnect the power supply cord from the electrical outlet.

Total energy usage

It is sometimes helpful to calculate the total product energy usage. Since power consumption claims are provided in power units of Watts, the power consumption should be multiplied by the time the product spends in each mode in order to calculate energy usage. The total product energy usage is the sum of each mode's energy usage.

Applicability of Regulation (EU) 2019/2015 and (EU) 2019/2020

Per Commission Regulation (EU) 2019/2015 and (EU) 2019/2020, the light source contained within this product or its component is intended to be used for Image Capture or Image Projection only, and is not intended for use in other applications.

Industry Canada compliance statement

This Class A digital apparatus meets all requirements of the Canadian Interference-Causing Equipment Standard ICES-003.

Avis de conformité aux normes de l'industrie du Canada

Cet appareil numérique de classe A est conforme aux exigences de la norme canadienne relative aux équipements pouvant causer des interférences NMB-003.

Japanese VCCI notice

製品にこのラベルが表示されている場合、 次の要件を満たしています。

この装置は、クラス A 情報技術装置です。この装置を家庭環境で使用する と電波妨害を引き起こすことがあります。この場合には使用者が適切な対策 を講ずるよう要求されることがあります。 VCCI-A

この装置は、クラスA情報技術装置です。この装置を家庭環境で使用すると電波妨害を引き起こすことがあります。この場合には使用者が適切な対策を講ずるよう要求されることがあります。 VCCI-A

European Community (EC) directives conformity

This product is in conformity with the protection requirements of EC Council directives 2004/108/EC, 2006/95/EC, and 2011/65/EU on the approximation and harmonization of the laws of the Member States relating to electromagnetic compatibility, safety of electrical equipment designed for use within certain voltage limits, and on the restrictions of use of certain hazardous substances in electrical and electronic equipment.

The manufacturer of this product is: Lexmark International, Inc., 740 West New Circle Road, Lexington, KY, 40550 USA. The authorized representative is: Lexmark International Technology Hungária Kft., 8 Lechner Ödön fasor, Millennium Tower III, 1095 Budapest HUNGARY, A declaration of conformity to the requirements of the Directives is available upon request from the Authorized Representative.

This product satisfies the Class A limits of EN 55022 and safety requirements of EN 60950-1.

Radio interference notice

Warning

This is a product that complies with the emission requirements of EN55022 Class A limits and immunity requirements of EN55024. This product is not intended to be used in residential/domestic environments.

This is a Class A product. In a domestic environment, this product may cause radio interference, in which case the user may be required to take adequate measures.

Regulatory notices for telecommunication terminal equipment

This section contains regulatory information pertaining to products that contain telecommunication terminal equipment such as facsimile.

Notice to users of the US telephone network: FCC requirements

This equipment complies with Part 68 of the FCC rules and the requirements adopted by the Administrative Council for Terminal Attachments (ACTA). On the back of this equipment is a label that contains, among other information, a product identifier in the format US:AAAEQ##TXXXX. If requested, this number must be provided to your telephone company.

This equipment uses the RJ-11C Universal Service Order Code (USOC) jack.

A plug and jack used to connect this equipment to the premises' wiring and telephone network must comply with the applicable FCC Part 68 rules and requirements adopted by the ACTA. A compliant telephone cord and modular plug is provided with this product. It is designed to be connected to a compatible modular jack that is also compliant. See your setup documentation for more information.

The Ringer Equivalence Number (REN) is used to determine the number of devices that may be connected to a telephone line. Excessive RENs on a telephone line may result in the devices not ringing in response to an incoming call. In most but not all areas, the sum of RENs should not exceed five (5.0). To be certain of the number of devices that may be connected to a line, as determined by the total RENs, contact your local telephone company. For products approved after July 23, 2001, the REN for this product is part of the product identifier that has the format US:AAAEQ##TXXXX. The digits represented by ## are the REN without a decimal point (for example, 03 is a REN of 0.3). For earlier products, the REN is shown separately on the label.

If this equipment causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. If advance notice is not practical, the telephone company will notify the customer as soon as possible. You will also be advised of your right to file a complaint with the FCC.

The telephone company may make changes in its facilities, equipment, operations or procedures that could affect the operation of this equipment. If this happens, the telephone company will provide advance notice in order for you to make necessary modifications to maintain uninterrupted service.

If you experience trouble with this equipment, for repair or warranty information, contact Lexmark International, Inc. at www.lexmark.com or your Lexmark representative. If the equipment is causing harm to the telephone network, the telephone company may request that you disconnect the equipment until the problem is resolved.

This equipment contains no user serviceable parts. For repair and warranty information, contact Lexmark International, Inc. See the previous paragraph for contact information.

Connection to party line service is subject to state tariffs. Contact the state public utility commission, public service commission, or corporation commission for information.

If your home has specially wired alarm equipment connected to the telephone line, ensure the installation of this equipment does not disable your alarm equipment. If you have questions about what will disable alarm equipment, consult your telephone company or a qualified installer.

Telephone companies report that electrical surges, typically lightning transients, are very destructive to customer terminal equipment connected to AC power sources. This has been identified as a major nationwide problem. It is recommended that the customer install an appropriate AC surge arrestor in the AC outlet to which this device is connected. An appropriate AC surge arrestor is defined as one that is suitably rated, and certified by UL (Underwriter's Laboratories), another NRTL (Nationally Recognized Testing Laboratory), or a recognized safety certification body in the country/region of use. This is to avoid damage to the equipment caused by local lightning strikes and other electrical surges.

The Telephone Consumer Protection Act of 1991 makes it unlawful for any person to use a computer or other electronic device, including fax machines, to send any message unless said message clearly contains in a margin at the top or bottom of each transmitted page or on the first page of the transmission, the date and time it is sent and an identification of the business or other entity, or other individual sending the message, and the telephone number of the sending machine or such business, other entity, or individual. (The telephone number provided may not be a 900 number or any other number for which charges exceed local or long-distance transmission charges.)

See your user documentation in order to program this information into your fax machine.

Notice to users of the Canadian telephone network

This product meets the applicable Industry Canada technical specifications. The Ringer Equivalence Number (REN) is an indication of the maximum number of terminals allowed to be connected to a telephone interface. The terminus of an interface may consist of any combination of devices, subject only to the requirement that the sum of the RENs of all the devices does not exceed five. The modem REN is located on the rear of the equipment on the product labeling.

Telephone companies report that electrical surges, typically lightning transients, are very destructive to customer terminal equipment connected to AC power sources. This has been identified as a major nationwide problem. It is recommended that the customer install an appropriate AC surge arrestor in the AC outlet to which this device is connected. An appropriate AC surge arrestor is defined as one that is suitably rated, and certified by UL (Underwriter's Laboratories), another NRTL (Nationally Recognized Testing Laboratory), or a recognized safety certification body in the country/region of use. This is to avoid damage to the equipment caused by local lightning strikes and other electrical surges.

This equipment uses CA11A telephone jacks.

Avis réservé aux utilisateurs du réseau téléphonique du Canada

Ce produit est conforme aux spécifications techniques d'Industrie Canada. Le numéro REN (ringer equivalence number : numéro d'équivalence de sonnerie) fournit une indication du nombre maximum de terminaux pouvant être connectés à l'interface téléphonique. En bout de ligne, le nombre d'appareils qui peuvent être connectés n'est pas directement limité, mais la somme des REN de ces appareils ne doit pas dépasser cinq. Le numéro REN du modem est indiqué sur l'étiquette produit située à l'arrière de l'équipement.

Les compagnies de téléphone constatent que les surtensions électriques, en particulier celles dues à la foudre, entraînent d'importants dégâts sur les terminaux privés connectés à des sources d'alimentation CA. Il s'agit-là d'un problème majeur d'échelle nationale. En conséquence, il vous est recommandé de brancher un parasurtenseur dans la prise de courant à laquelle l'équipement est connecté. Utilisez un parasurtenseur répondant à des caractéristiques nominales satisfaisantes et certifié par le laboratoire d'assureurs UL (Underwriter's Laboratories), un autre laboratoire agréé de type NRTL (Nationally Recognized Testing

Laboratory) ou un organisme de certification agréé dans votre région ou pays. Ceci prévient tout endommagement de l'équipement causé par les orages et autres surtensions électriques.

Cet équipement utilise des prises de téléphone CA11A.

Notice to users of the New Zealand telephone network

The following are special conditions for the Facsimile User Instructions. The grant of a telepermit for any item of terminal equipment indicates only that Telecom has accepted that the item complies with minimum conditions for connection to its network. It indicates no endorsement of the product by Telecom, nor does it provide any sort of warranty. Above all, it provides no assurance that any item will work correctly in all respects with another item of telepermitted equipment of a different make or model, nor does it imply that any product is compatible with all of Telecom's network services.

This equipment shall not be set up to make automatic calls to the Telecom's 111 Emergency Service.

This equipment may not provide for the effective hand-over of a call to another device connected to the same line.

This equipment should not be used under any circumstances that may constitute a nuisance to other Telecom customers.

Some parameters required for compliance with Telecom's telepermit requirements are dependent on the equipment associated with this device. The associated equipment shall be set to operate within the following limits for compliance to Telecom's specifications:

- There shall be no more than 10 call attempts to the same number within any 30 minute period for any single manual call initiation, and
- The equipment shall go on-hook for a period of not less than 30 seconds between the end of one attempt and the beginning of the next call attempt.
- The equipment shall be set to ensure that automatic calls to different numbers are spaced such that there is not less than 5 seconds between the end of one call attempt and the beginning of another.

Japanese telecom notice

The installed optional modem is in compliance with Japanese Telecommunication Law and has been Certified by JATE, with Certification Number A11-0160001.



Using this product in Switzerland

This product requires a Swiss billing tone filter (Lexmark part number 80D1877) to be installed on any line which receives metering pulses in Switzerland. The filter must be used, as metering pulses are present on all analog telephone lines in Switzerland.

Utilisation de ce produit en Suisse

Cet appareil nécessite l'utilisation d'un filtre de tonalité de facturation suisse (n° de référence Lexmark : 80D1877) devant être installé sur toute ligne recevant des impulsions de comptage en Suisse. Ce filtre doit être utilisé pour toute installation car ces impulsions existent sur toutes les lignes téléphoniques suisses.

Verwendung dieses Produkts in der Schweiz

Für dieses Produkt muss ein schweizerischer Billing Tone Filter zur Zählzeichenübertragung (Lexmark Teilenummer 80D1877) für jede Leitung installiert werden, über die in der Schweiz Zeitsteuertakte übertragen werden. Die Verwendung des Filters ist obligatorisch, da in allen analogen Telefonleitungen in der Schweiz Zeitsteuertakte vorhanden sind.

Uso del prodotto in Svizzera

Questo prodotto richiede un filtro toni Billing svizzero, (codice Lexmark 80D1877) da installare su tutte le linee che ricevono impulsi remoti in Svizzera. È necessario utilizzare il filtro poiché gli impulsi remoti sono presenti su tutte le linee analogiche in Svizzera.

Notice to Users in the European Union

Products bearing the CE mark are in conformity with the protection requirements of EC Council directives 2004/108/EC, 2006/95/EC, 1999/5/EC, and 2011/65/EU on the approximation and harmonization of the laws of the Member States relating to electromagnetic compatibility, safety of electrical equipment designed for use within certain voltage limits, radio equipment and telecommunications terminal equipment, and on the restrictions of use of certain hazardous substances in electrical and electronic equipment.

Compliance is indicated by the CE marking.



The manufacturer of this product is: Lexmark International, Inc., 740 West New Circle Road, Lexington, KY, 40550 USA. The authorized representative is: Lexmark International Technology Hungária Kft., 8 Lechner Ödön fasor, Millennium Tower III, 1095 Budapest HUNGARY. A declaration of conformity to the requirements of the Directives is available upon request from the Authorized Representative.

This product satisfies the Class A limits of EN 55022 and safety requirements of EN 60950-1.

Refer to the table at the end of the Notices section for further compliance information.

Regulatory notices for wireless products

This section contains the following regulatory information pertaining to wireless products that contain transmitters, for example, but not limited to, wireless network cards or proximity card readers.

Modular component notice

This product may contain the following modular component(s):

Lexmark Regulatory Type/Model LEX-M01-005; FCC ID:IYLLEXM01005; IC:2376A-M01005

Exposure to radio frequency radiation

The radiated output power of this device is far below the radio frequency exposure limits of the FCC and other regulatory agencies. A minimum separation of 20 cm (8 inches) must be maintained between the antenna and any persons for this device to satisfy the RF exposure requirements of the FCC and other regulatory agencies.

Industry Canada (Canada)

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (EIRP) is not more than that necessary for successful communication.

This device complies with Industry Canada license-exempt RSS standards. Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

To prevent radio interference to the licensed service, this device is intended to be operated indoors and away from windows to provide maximum shielding.

Industrie Canada (Canada)

Selon la règlementation d'Industrie Canada, l'émetteur radio ne fonctionner qu'avec une antenne dont le type et le gain maximal (ou inférieur) ont été approuvés par Industrie Canada. Pour réduire les interférences radio potentielles auprès d'autres utilisateurs, le type d'antenne et son gain doivent être choisis de telle sorte que la puissance isotrope rayonnée équivalente (PIRE) ne soit pas supérieure à ce qui est nécessaire pour assurer la réussite de la communication.

Cet appareil est conforme aux normes RSS exemptes de licence d'Industrie Canada. Son fonctionnement est soumis aux deux conditions suivantes : (1) cet appareil ne doit pas causer d'interférences et (2) il doit accepter toutes les interférences, y compris les interférences pouvant entraîner un fonctionnement indésirable.

Pour éviter toute interférence radio au service sous licence, cet appareil est destiné à être utilisé à l'intérieur et à l'écart des fenêtres afin d'assurer une protection maximale.

Notice to users in the European Union

Products bearing the CE mark are in conformity with the protection requirements of EC Council directives 2004/108/EC, 2006/95/EC, 1999/5/EC, and 2011/65/EU on the approximation and harmonization of the laws of the Member States relating to electromagnetic compatibility, safety of electrical equipment designed for use within certain voltage limits, radio equipment and telecommunications terminal equipment, and on the restrictions of use of certain hazardous substances in electrical and electronic equipment.

Compliance is indicated by the CE marking.



The manufacturer of this product is: Lexmark International, Inc., 740 West New Circle Road, Lexington, KY, 40550 USA. The authorized representative is: Lexmark International Technology Hungária Kft., 8 Lechner Ödön fasor, Millennium Tower III, 1095 Budapest HUNGARY, A declaration of conformity to the requirements of the Directives is available upon request from the Authorized Representative.

This product satisfies the Class A limits of EN 55022 and safety requirements of EN 60950-1.

Products equipped with 2.4GHz Wireless LAN option are in conformity with the protection requirements of EC Council directives 2004/108/EC, 2006/95/EC, and 1999/5/EC on the approximation and harmonization of the laws of the Member States relating to electromagnetic compatibility, safety of electrical equipment designed for use within certain voltage limits and on radio equipment and telecommunications terminal equipment.

Compliance is indicated by the CE marking.



Operation is allowed in all EU and EFTA countries, but is restricted to indoor use only.

The manufacturer of this product is: Lexmark International, Inc., 740 West New Circle Road, Lexington, KY, 40550 USA. The authorized representative is: Lexmark International Technology Hungária Kft., 8 Lechner Ödön fasor, Millennium Tower III, 1095 Budapest HUNGARY, A declaration of conformity to the requirements of the Directives is available upon request from the Authorized Representative.

This product may be used in the countries indicated in the table below.

AT	BE	BG	СН	CY	CZ	DE	DK	EE
EL	ES	FI	FR	HR	HU	IE	IS	IT
LI	LT	LU	LV	МТ	NL	NO	PL	PT
RO	SE	SI	SK	TR	UK			

Česky	Společnost Lexmark International, Inc. tímto prohlašuje, že výrobek tento výrobek je ve shodě se základními požadavky a dalšími příslušnými ustanoveními směrnice 1999/5/ES.
Dansk	Lexmark International, Inc. erklærer herved, at dette produkt overholder de væsentlige krav og øvrige relevante krav i direktiv 1999/5/EF.
Deutsch	Hiermit erklärt Lexmark International, Inc., dass sich das Gerät dieses Gerät in Übereinstimmung mit den grundlegenden Anforderungen und den übrigen einschlägigen Bestimmungen der Richtlinie 1999/5/EG befindet.
Ελληνική	ΜΕ ΤΗΝ ΠΑΡΟΥΣΑ Η LEXMARK INTERNATIONAL, INC. ΔΗΛΩΝΕΙ ΟΤΙ ΑΥΤΌ ΤΟ ΠΡΟΪ́ΟΝ ΣΥΜΜΟΡΦΩΝΕΤΑΙ ΠΡΟΣ ΤΙΣ ΟΥΣΙΩΔΕΙΣ ΑΠΑΙΤΗΣΕΙΣ ΚΑΙ ΤΙΣ ΛΟΙΠΕΣ ΣΧΕΤΙΚΕΣ ΔΙΑΤΑΞΕΙΣ ΤΗΣ ΟΔΗΓΙΑΣ 1999/5/ΕΚ.
English	Hereby, Lexmark International, Inc., declares that this type of equipment is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC.

Español	Por medio de la presente, Lexmark International, Inc. declara que este producto cumple con los requisitos esenciales y cualesquiera otras disposiciones aplicables o exigibles de la Directiva 1999/5/CE.
Eesti	Käesolevaga kinnitab Lexmark International, Inc., et seade see toode vastab direktiivi 1999/5/EÜ põhinõuetele ja nimetatud direktiivist tulenevatele muudele asjakohastele sätetele.
Suomi	Lexmark International, Inc. vakuuttaa täten, että tämä tuote on direktiivin 1999/5/EY oleellisten vaatimusten ja muiden sitä koskevien direktiivin ehtojen mukainen.
Français	Par la présente, Lexmark International, Inc. déclare que l'appareil ce produit est conforme aux exigences fondamentales et autres dispositions pertinentes de la directive 1999/5/CE.
Magyar	Alulírott, Lexmark International, Inc. nyilatkozom, hogy a termék megfelel a vonatkozó alapvető követelményeknek és az 1999/5/EC irányelv egyéb előírásainak.
Íslenska	Hér með lýsir Lexmark International, Inc. yfir því að þessi vara er í samræmi við grunnkröfur og aðrar kröfur, sem gerðar eru í tilskipun 1999/5/EC.
Italiano	Con la presente Lexmark International, Inc. dichiara che questo questo prodotto è conforme ai requisiti essenziali ed alle altre disposizioni pertinenti stabilite dalla direttiva 1999/5/CE.
Latviski	Ar šo Lexmark International, Inc. deklarē, ka šis izstrādājums atbilst Direktīvas 1999/5/EK būtiskajām prasībām un citiem ar to saistītajiem noteikumiem.
Lietuvių	Šiuo Lexmark International, Inc. deklaruoja, kad šis produktas atitinka esminius reikalavimus ir kitas 1999/5/EB direktyvos nuostatas.
Malti	Bil-preżenti, Lexmark International, Inc., jiddikjara li dan il-prodott huwa konformi mal-ħtiġijiet essenzjali u ma dispożizzjonijiet oħrajn relevanti li jinsabu fid-Direttiva 1999/5/KE.
Nederlands	Hierbij verklaart Lexmark International, Inc. dat het toestel dit product in overeenstemming is met de essentiële eisen en de andere relevante bepalingen van richtlijn 1999/5/EG.
Norsk	Lexmark International, Inc. erklærer herved at dette produktet er i samsvar med de grunnleggende krav og øvrige relevante krav i direktiv 1999/5/EF.
Polski	Niniejszym Lexmark International, Inc. oświadcza, że niniejszy produkt jest zgodny z zasadniczymi wymogami oraz pozostałymi stosownymi postanowieniami Dyrektywy 1999/5/EC.
Português	A Lexmark International Inc. declara que este este produto está conforme com os requisitos essenciais e outras disposições da Diretiva 1999/5/CE.
Slovensky	Lexmark International, Inc. týmto vyhlasuje, že tento produkt spĺňa základné požiadavky a všetky príslušné ustanovenia smernice 1999/5/ES.
Slovensko	Lexmark International, Inc. izjavlja, da je ta izdelek v skladu z bistvenimi zahtevami in ostalimi relevantnimi določili direktive 1999/5/ES.
Svenska	Härmed intygar Lexmark International, Inc. att denna produkt står i överensstämmelse med de väsentliga egenskapskrav och övriga relevanta bestämmelser som framgår av direktiv 1999/5/EG.

STATEMENT OF LIMITED WARRANTY FOR LEXMARK LASER PRINTERS, LEXMARK LED PRINTERS, AND LEXMARK MULTIFUNCTION LASER PRINTERS

Lexmark International, Inc., Lexington, KY

This limited warranty applies to the United States and Canada. For customers outside the U.S., refer to the country-specific warranty information that came with your product.

This limited warranty applies to this product only if it was originally purchased for your use, and not for resale, from Lexmark or a Lexmark Remarketer, referred to in this statement as "Remarketer."

Limited warranty

Lexmark warrants that this product:

- —Is manufactured from new parts, or new and serviceable used parts, which perform like new parts
- —Is, during normal use, free from defects in material and workmanship

If this product does not function as warranted during the warranty period, contact a Remarketer or Lexmark for repair or replacement (at Lexmark's option).

If this product is a feature or option, this statement applies only when that feature or option is used with the product for which it was intended. To obtain warranty service, you may be required to present the feature or option with the product.

If you transfer this product to another user, warranty service under the terms of this statement is available to that user for the remainder of the warranty period. You should transfer proof of original purchase and this statement to that user.

Limited warranty service

The warranty period starts on the date of original purchase as shown on the purchase receipt and ends 12 months later provided that the warranty period for any supplies and for any maintenance items included with the printer shall end earlier if it, or its original contents, are substantially used up, depleted, or consumed. Fuser Units, Transfer/Transport Units, Paper Feed items, if any, and any other items for which a Maintenance Kit is available are substantially consumed when the printer displays a "Life Warning" or "Scheduled Maintenance" message for such item.

To obtain warranty service you may be required to present proof of original purchase. You may be required to deliver your product to the Remarketer or Lexmark, or ship it prepaid and suitably packaged to a Lexmark designated location. You are responsible for loss of, or damage to, a product in transit to the Remarketer or the Lexmark designated location.

When warranty service involves the exchange of a product or part, the item replaced becomes the property of the Remarketer or Lexmark. The replacement may be a new or repaired item.

The replacement item assumes the remaining warranty period of the original product.

Replacement is not available to you if the product you present for exchange is defaced, altered, in need of a repair not included in warranty service, damaged beyond repair, or if the product is not free of all legal obligations, restrictions, liens, and encumbrances.

As part of your warranty service and/or replacement, Lexmark may update the firmware in your printer to the latest version. Firmware updates may modify printer settings and cause counterfeit and/or unauthorized products, supplies, parts, materials (such as toners and inks), software, or interfaces to stop working. Authorized use of genuine Lexmark products will not be impacted.

Before you present this product for warranty service, remove all print cartridges, programs, data, and removable storage media (unless directed otherwise by Lexmark).

For further explanation of your warranty alternatives and the nearest Lexmark authorized servicer in your area contact Lexmark on the World Wide Web.

Remote technical support is provided for this product throughout its warranty period. For products no longer covered by a Lexmark warranty, technical support may not be available or only be available for a fee.

Extent of limited warranty

Lexmark does not warrant uninterrupted or error-free operation of any product or the durability or longevity of prints produced by any product.

Warranty service does not include repair of failures caused by:

- -Modification or unauthorized attachments
- —Accidents, misuse, abuse or use inconsistent with Lexmark user's guides, manuals, instructions or guidance
- -Unsuitable physical or operating environment
- -Maintenance by anyone other than Lexmark or a Lexmark authorized servicer
- —Operation of a product beyond the limit of its duty cycle
- —Use of printing media outside of Lexmark specifications
- -Refurbishment, repair, refilling or remanufacture by a third party of products, supplies or parts
- -Products, supplies, parts, materials (such as toners and inks), software, or interfaces not furnished by Lexmark

TO THE EXTENT PERMITTED BY APPLICABLE LAW, NEITHER LEXMARK NOR ITS THIRD PARTY SUPPLIERS OR REMARKETERS MAKE ANY OTHER WARRANTY OR CONDITION OF ANY KIND, WHETHER EXPRESS OR IMPLIED, WITH RESPECT TO THIS PRODUCT, AND SPECIFICALLY DISCLAIM THE IMPLIED WARRANTIES OR CONDITIONS OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND SATISFACTORY QUALITY. ANY WARRANTIES THAT MAY NOT BE DISCLAIMED UNDER APPLICABLE LAW ARE LIMITED IN DURATION TO THE WARRANTY PERIOD. NO WARRANTIES, EXPRESS OR IMPLIED, WILL APPLY AFTER THIS PERIOD. ALL INFORMATION, SPECIFICATIONS, PRICES, AND SERVICES ARE SUBJECT TO CHANGE AT ANY TIME WITHOUT NOTICE.

Limitation of liability

Your sole remedy under this limited warranty is set forth in this document. For any claim concerning performance or nonperformance of Lexmark or a Remarketer for this product under this limited warranty, you may recover actual damages up to the limit set forth in the following paragraph.

Lexmark's liability for actual damages from any cause whatsoever will be limited to the amount you paid for the product that caused the damages. This limitation of liability will not apply to claims by you for bodily injury or damage to real property or tangible personal property for which Lexmark is legally liable. **IN NO EVENT WILL LEXMARK BE LIABLE FOR ANY LOST PROFITS, LOST SAVINGS, INCIDENTAL DAMAGE, OR OTHER ECONOMIC OR CONSEQUENTIAL DAMAGES.** This is true even if you advise Lexmark or a Remarketer of the possibility of such damages. Lexmark is not liable for any claim by you based on a third party claim.

This limitation of remedies also applies to claims against any Suppliers and Remarketers of Lexmark. Lexmark's and its Suppliers' and Remarketers' limitations of remedies are not cumulative. Such Suppliers and Remarketers are intended beneficiaries of this limitation.

Additional rights

Some states do not allow limitations on how long an implied warranty lasts, or do not allow the exclusion or limitation of incidental or consequential damages, so the limitations or exclusions contained above may not apply to you.

This limited warranty gives you specific legal rights. You may also have other rights that vary from state to state.

Patent acknowledgment

The use of this product or service is subject to the reasonable, non-discriminatory terms in the Intellectual Property Rights (IPR) Disclosure of Certicom Corp. at the IETF for Elliptic Curve Cryptography (ECC) Cipher Suites for Transport Layer Security (TLS) implemented in the product or service.

The use of this product or service is subject to the reasonable, non-discriminatory terms in the Intellectual Property Rights (IPR) Disclosure of Certicom Corp. at the IETF for TLS Elliptic Curve Cipher Suites with SHA-256/382 and AES Galois Counter Mode (GCM) implemented in the product or service.

The use of this product or service is subject to the reasonable, non-discriminatory terms in the Intellectual Property Rights (IPR) Disclosure of Certicom Corp. at the IETF for TLS Suite B Profile for Transport Layer Security (TLS) implemented in the product or service.

The use of this product or service is subject to the reasonable, non-discriminatory terms in the Intellectual Property Rights (IPR) Disclosure of Certicom Corp. at the IETF for Addition of the Camellia Cipher Suites to Transport Layer Security (TLS) implemented in the product or service.

The use of certain patents in this product or service is subject to the reasonable, non-discriminatory terms in the Intellectual Property Rights (IPR) Disclosure of Certicom Corp. at the IETF for AES-CCM ECC Cipher Suites for TLS implemented in the product or service.

The use of this product or service is subject to the reasonable, non-discriminatory terms in the Intellectual Property Rights (IPR) Disclosure of Certicom Corp. at the IETF for IKE and IKEv2 Authentication Using the Eliptic Curve Digital Signature Algorithm (ECDSA) implemented in the product or service.

The use of this product or service is subject to the reasonable, non-discriminatory terms in the Intellectual Property Rights (IPR) Disclosure of Certicom Corp. at the IETF for Suite B Cryptographic Suites for IPSec implemented in the product or service.

The use of this product or service is subject to the reasonable, non-discriminatory terms in the Intellectual Property Rights (IPR) Disclosure of Certicom Corp. at the IETF for Algorithms for Internet Key Exchange version 1 (IKEv1) implemented in the product or service.

Index

Numerics

300K maintenance kit ordering 211

Symbols

[x] maintenance kit very low [80.xy] 277 [x]-page jam, clear manual feeder. [200.xx] 244 [x]-page jam, detach the 3000-sheet tray and open door F. [24y.xx] 251 [x]-page jam, open door C and clear all jammed media. [2yy.xx] 244 [x]-page jam, open door D and clear all jammed media. [24y.xx] 249 [x]-page jam, open door H and rotate knob H6 clockwise. Leave paper in bin. [426.xx-428.xx] 263 [x]-page jam, open doors G, H, and J and clear jammed paper. Leave paper in bin. [400– 402] 254 [x]-page jam, press latch at area E to open ADF's top cover. [28v.xx] printer messages 268 [x]-page jam, press latch to access area G and clear jammed staples. Leave paper in bin. [402.93] 260 [x]-page jam, press latch to access area G. Leave paper in bin. [40y.xx] 257 [x]-page jam, slide the 3000-sheet tray and open door C. [2yy.xx] 246 [x]-page jam, slide the 3000-sheet tray and open door

Α

accessing the controller board 27

D. [24y.xx] 250

accessing the Embedded Web Server 20 Active NIC menu 128 adapter plug 99 adding hardware options print driver 45 adding internal options print driver 45 ADF scan pad replacing 234 adjusting copy quality 79 adjusting printer display brightness 199 adjusting Sleep mode 199 adjusting toner darkness 70 advanced options, touch-screen copy 83 e-mail 88 fax 110 FTP 115 answering machine setting up 90 AppleTalk menu 133 applications home screen 22 understanding 21 attaching cables 44 automatic document feeder (ADF) using 14 available internal options 27 avoiding jams 63 avoiding paper jams 241

В

Bin Setup menu 125 blocking junk faxes 107 buttons, control panel 15 buttons, touch screen using 18

C

cables
Ethernet 44
USB 44
canceling a fax job 108
canceling a print job
from the computer 75

from the printer control panel 75 canceling an e-mail 86 cannot open Embedded Web Server 332 Card Copy setting up 23 card stock tips 58 Cartridge low [88.xy] 270 Cartridge nearly low [88.xy] 270 Cartridge very low [88.xy] 270 Change [paper source] to [custom string] load [orientation] 270 Change [paper source] to [custom type name] load [orientation] 270 Change [paper source] to [paper size] load [orientation] 270 Change [paper source] to [paper type] [paper size] load [orientation] 271 changing output file type e-mailing 86 changing port settings internal solutions port 49 charger cleaning 205 checking an unresponsive printer 286 checking status of parts and supplies 209 checking the status of parts and supplies 209 checking the virtual display using the Embedded Web Server 238 checking virtual display using the Embedded Web Server 238 cleaning exterior of the printer 204 scanner glass 204 cleaning the charger 205 cleaning the printer 204 cleaning the printhead lens 205

Close door [x] 271

collate control panel 15 creating a fax destination copy options 82 factory defaults, restoring 240 shortcut collating copies control panel, printer using the Embedded Web copying 79 indicator light 15 Server 105 creating an e-mail shortcut Complex page, some data may Sleep button light 15 not have printed [39] 271 controller board using the control panel 85 confidential data accessing 27 creating an FTP shortcut using the Embedded Web information on securing 203 copies copy options 82 Server 111 confidential jobs Custom Bin Names menu 124 modifying print settings 74 copy options confidential print jobs 73 collate 82 custom job Confidential Print menu 143 copies 82 copying 80 darkness 82 Configuration change, some held Custom Names menu 124 Save As Shortcut 82 jobs were not restored [57] 271 custom paper type configuration information sides (duplex) 82 assigning 57 wireless network 46 custom paper type name copy quality Configure MP menu 120 adjusting 79 creating 56 configuring Custom Scan Sizes menu 124 copy screen multiple printers 239 Custom Types menu 124 advanced options 83 customer support configuring e-mail settings 84 content source 82 configuring port settings 49 content type 82 contacting 333 configuring supply options 81, 82 notifications 239 Copy Settings menu 157 D connecting printer to distinctive copy troubleshooting darkness ring service 103 copier does not respond 319 copy options 82 connecting the printer to an partial document or photo e-mail options 87 outlet 10 copies 320 fax options 109 connecting to a wireless network poor copy quality 320 scan options 114 using PIN (Personal poor scanned image date and time, fax Identification Number) quality 328 setting 103 scanner unit does not method 48 daylight saving time, faxing 104 using Push Button Configuration close 329 Default Source menu 117 method 48 copying Defective flash detected [51] 271 using the Embedded Web canceling a copy job 81 delayed send Server 49 creating shortcuts using the fax options 109 using wireless setup wizard 47 printer control panel 77 device and network settings on both sides of the paper conservation settings information brightness, adjusting 199 (two-sided) 79 erasing 202 conserving supplies 197 copying different paper sizes 78 different paper sizes, copying 78 Eco-Mode 198 copying from different size Hibernate mode 198 selected tray 78 copying to 78 Sleep Mode 199 copying multiple pages on one digital subscriber line (DSL) conserving supplies 197 sheet 80 fax setup 95 contacting customer support 333 copying on both sides of the digital telephone service paper (two-sided) 79 content fax setup 98 e-mail settings 87 copying on letterhead 77 directory list copying on transparencies 77 content source printing 74 e-mail settings 87 copying photos 76 Disk full [62] 272 fax options 109 copying to a different size 78 Disk full, scan job canceled 272 content type Disk must be formatted for use in e-mail settings 87 this device 272

fax options 109

display troubleshooting E-mail Settings menu 170 envelopes printer display is blank 288 tips on using 58 e-mail shortcut, creating display, control panel 15 environmental settings using the control panel 85 conserving supplies 197 e-mail shortcuts, creating display, printer control panel adjusting brightness 199 Eco-Mode 198 using the Embedded Web disposing of printer hard Hibernate mode 198 Server 85 disk 201 printer display brightness, e-mail, sending using a shortcut number 86 distinctive ring service, fax adjusting 199 connecting to 103 Sleep Mode 199 e-mailing documents, printing Erase Temporary Data Files configuring e-mail settings 84 from a computer 70 menu 144 creating shortcuts using the door C erasing hard disk memory 202 Embedded Web Server 85 paper jams, clearing 244, 246 erasing non-volatile using a shortcut number 86 door D memory 202 using the address book 86 paper jams, clearing 249, 250 erasing volatile memory 202 e-mailing a document DSL filter 95 Error reading USB drive. Remove using the control panel 85 USB. 272 Error reading USB hub. Remove F Ε hub. 272 factory defaults Eco-Mode setting 198 Ethernet network Edit Security Setups menu 141 restoring 240 preparing to set up for Ethernet embedded solutions information printing 46 erasing 202 sending at a scheduled Ethernet port 44 **Embedded Web Server** time 105 Ethernet setup accessing 20 fax and e-mail functions preparing for an 46 adjusting brightness 199 setting up 326 exhaust filter checking the status of fax and e-mail functions are not replacing 224 parts 209 set up 326 exporting a configuration checking the status of fax job using the Embedded Web supplies 209 canceling 108 Server 26 copying settings to other Fax memory full 273 EXT port 44 printers 239 Fax Mode (Analog Fax Setup) exterior of the printer creating a fax destination menu 162 cleaning 204 shortcut 105 fax name, setting 103 e-mail creating an FTP shortcut 111 fax number, setting 103 canceling 86 creating e-mail shortcuts 85 fax options e-mail alerts initial fax setup 90 content source 109 low supply levels 238 modifying confidential print content type 109 paper jam 238 settings 74 darkness 109 setting up 238 problem accessing 332 delayed send 109 e-mail options setting up e-mail alerts 238 page setup 109 darkness 87 Embedded Web Server resolution 109 message 87 Security: Administrator's Guide scan preview 110 original size 87 where to find 203 Fax partition inoperative. Contact page setup 88 emission system administrator. 273 recipient(s) 86 notices 336, 342, 343, 347 fax port 44 resolution 87 Empty the hole punch box 272 fax screen Save As Shortcut 87 emptying the hole punch advanced options 110 Send As 87 box 208 options 110 subject 86 encrypting the printer hard Fax server 'To Format' not set up. e-mail screen disk 203 Contact system advanced options 88 enlarging a copy 79 administrator. 273

options 87, 88

fax setup country- or region-specific 99 digital telephone service 98 DSL connection 95 standard telephone line connection 90 VoIP 96 Fax Station Name not set up. Contact system administrator. 273 Fax Station Number not set up. Contact system administrator. 273 fax troubleshooting caller ID is not shown 322 can receive but not send faxes 325 can send but not receive faxes 326 cannot send or receive a fax 323 faxing blocking junk faxes 107 changing resolution 106 configuring the printer to observe daylight saving time 104 creating shortcuts using the Embedded Web Server 105 creating shortcuts using the printer control panel 106 distinctive ring service 103 fax setup 90 forwarding faxes 108 holding faxes 108 holding faxes 108 making a fax lighter or darker 107 sending a fax at a scheduled time 105 setting the date and time 103 setting the fax number 103 setting the fax number 103 setting the outgoing fax name 103 viewing a fax log 107 FCC notices 336, 343, 347 feet stabilizing 38 file name scan options 114 finding more information about	finding the IP address of the computer 20 finisher supported paper sizes 67 supported paper types 67 supported paper weights 67 Finishing menu 186 firmware card 27 flash drive printing from 71 scanning 113 Flash Drive menu 179 flash drives supported file types 72 font sample list printing 74 Forms and Favorites setting up 22 forwarding faxes 108 FTP FTP options 114 FTP address creating shortcuts using the printer control panel 112 FTP address, scanning to using the control panel 112 FTP options FTP 114 FTP screen advanced options 115 FTP Settings menu 175 G General Settings menu 148 green settings Eco-Mode 198 Hibernate mode 198 H hardware options, adding print driver 45 held jobs 73 printing from a Macintosh computer 73 printing from a Macintosh computer 73 printing from Windows 73 Holp manu 196	Hibernate mode using 198 hiding icons on the home screen 21 holding faxes 108 hole punch 82 hole punch box emptying 208 home screen customizing 21 hiding icons 21 showing icons 21 showing icons 21 home screen applications configuring 22 finding information 22 home screen buttons and icons description 16 HTML menu 195 I icons on the home screen hiding 21 showing 21 Image menu 196 importing a configuration using the Embedded Web Server 26 Incorrect paper size, open [paper source] [34] 273 indicator light 15 individual settings information erasing 202 initial fax setup 90 using the Embedded Web Server 90 Insert hole punch box 274 Insert Tray [x] 274 inserting a header or footer copying 81 installing a memory card 30 installing an optional card 31 installing hardware options order of installation 38 installing the optional trays 38 Insufficient memory for Flash Memory Defragment operation [37] 274 Insufficient memory to collate job [37] 274
the printer 9	Help menu 196	Insufficient memory to support
finding printer IP address 20		Resource Save feature [35] 274

Insufficient memory, some Held Load [paper source] with [paper Custom Bin Names 124 Custom Names 124 Jobs were deleted [37] 274 size][paper orientation] 275 Insufficient memory, some held Load [paper source] with [paper Custom Scan Sizes 124 jobs will not be restored [37] 274 type][paper size][paper Custom Types 124 Insufficient space between paper orientation] 275 Default Source 117 stacks in Tray 3 274 Load Multipurpose Feeder with diagram of 116 internal options 27 [custom string][paper Edit Security Setups 141 internal options, adding orientation 275 Erase Temporary Data Files 144 print driver 45 Load Multipurpose Feeder with E-mail Settings 170 internal print server [custom type name] [paper Fax Mode (Analog Fax troubleshooting 289 orientation] 276 Setup) 162 Internal Solutions Port Load Multipurpose Feeder with Finishing 186 troubleshooting 289 [paper size] [paper Flash Drive 179 Internal Solutions Port (ISP) orientation] 276 FTP Settings 175 Load Multipurpose Feeder with installing 32 General Settings 148 IP address of computer [paper type] [paper size] [paper Help 196 HTML 195 finding 20 orientation] 276 IP address, printer Load staples 276 Image 196 Load staples [G11, G12] 277 IPv6 132 finding 20 IPv6 menu 132 loading letterhead Job Accounting 189 paper orientation 59 Miscellaneous Security loading the multipurpose Settings 142 J feeder 53 Network [x] 128 iams loading trays 51 Network Card 130 avoiding 241 lock, security 201 Network Reports 130 locating jam areas 242 Paper Loading 122 locations 242 Paper Size/Type 117 М numbers 242 Paper Texture 121 maintenance counter, jams, clearing Parallel [x] 135 in 3000-sheet tray 251 resetting 233 PCL Emul 192 in door C 251 making copies using paper from PDF 191 in door F 251 selected tray 78 PostScript 192 in multipurpose feeder 244 memory Quality 188 in top ADF door 268 types installed on printer 201 Reports 127 Job Accounting menu 189 memory card 27 Security Audit Log 144 installing 30 Serial [x] 137 Memory full [38] 277 L Set Date and Time 146 Memory full, cannot print labels, paper Setup 184 faxes 277 tips 59 SMTP Setup 140 Memory full, cannot send letterhead Standard Network 128 faxes 277 copying on 77 Standard USB 134 menu settings loading, multipurpose Substitute Size 121 loading on multiple feeder 59 TCP/IP 130 printers 239 loading, trays 59 Universal Setup 125 menu settings page line filter 95 Utilities 190 printing 50 LINE port 44 Wireless 132 menus linking trays 56, 57 XPS 191 Active NIC 128 Load [paper source] with [custom menus diagram 116 AppleTalk 133 string] [paper orientation] 275 message Bin Setup 125 Load [paper source] with [custom e-mail options 87 Confidential Print 143 type name] [paper Miscellaneous Security Settings

Configure MP 120

Copy Settings 157

menu 142

orientation] 275

mobile device	options, touch-screen	Paper Loading menu 122
printing from 73	copy 81	paper size
moving the printer 10, 236	e-mail 87, 88	setting 51
Multi Send	fax 110	Paper Size/Type menu 117
adding a profile 24	ordering	paper sizes
setting up 24	300K maintenance kit 211	supported 63
multipurpose feeder	photoconductor unit 210	Paper Texture menu 121
loading 53	staple cartridges 211	paper type
MyShortcut	ordering supplies	setting 51
about 24	toner cartridge 210	paper types
	waste toner bottle 210	supported by printer 66
N	organizing cables 44	paper weights
Network [x] menu 128	original size	supported by printer 66
Network [x] software error	e-mail options 87	Parallel [x] menu 135
[54] 277	scan options 114	Parallel port [x] disabled [56] 278
Network Card menu 130	output file type	parts
Network Reports menu 130	changing 86	checking status 209
network setup page	scan image 114	checking, from printer control
printing 50	ozone filter	panel 209
No analog phone line connected	replacing 224	checking, using the Embedded
to modem, fax is disabled. 277		Web Server 209
noise emission levels 336	P	storing 211
non-volatile memory 201	page setup	using genuine Lexmark 210
erasing 202	e-mail options 88	parts, ordering
Not enough free space in flash	fax options 109	300K maintenance kit 211
memory for resources [52] 278	scan options 115	PCL Emul menu 192
notices 335, 336, 339, 340, 341,	paper	PDF menu 191
342, 343, 344, 345, 347, 348	characteristics 60	Personal Identification Number
number of remaining pages	different sizes, copying 78	method
estimate 209	letterhead 61	using 48
estimate 203	preprinted forms 61	phone splitter 96
•	recycled 61	Photoconductor low [84.xy] 278
0	saving 80	photoconductor unit
Open door H and remove paper	selecting 61	ordering 210
from beneath area H10 278	storing 60, 63	replacing 212
optional 2 x 500-sheet tray	unacceptable 61	Photoconductor very low
installing 38	using recycled 197	[84.xy] 278
optional 2500-sheet tray	Paper changes needed 278	photos
installing 38	paper characteristics 60	copying 76
optional card	paper feed troubleshooting	placing separator sheets
installing 31	message remains after jam is	between copies
optional trays	cleared 292	copying 80
installing 38	paper jams	port settings
options	avoiding 241	configuring 49
firmware cards 27	paper jams, clearing	PostScript menu 192
Internal Solutions Port (ISP) 32	door C 244, 246	power cord socket 44
memory card 27, 30	door D 249, 250	preparing to set up the printer on
printer hard disk, removing 36	in 3000-sheet tray 251	an Ethernet network 46
options, copy screen	in bottom ADF door 268	print driver
copy from 81	in door C 251	hardware options, adding 45
scale 82	in door F 251	print irregularities 307

in door F 251

in multipurpose feeder 244

print job canceling from the computer 75 print quality cleaning the scanner glass 204 replacing a photoconductor unit 212 print quality troubleshooting blank pages 305 characters have jagged edges 300 clipped pages or images 300 gray background on prints 302 horizontal voids appear on prints 302 print irregularities 307 print is too dark 308 print is too light 309 printer is printing solid black pages 306 repeating defects appear on prints 311 shadow images appear on prints 312 skewed print 313 streaked horizontal lines appear on prints 313 streaked vertical lines 314 toner fog or background shading appears on prints 316 toner rubs off 316 toner specks appear on prints 317 transparency print quality is poor 317 uneven print density 318 white streaks 318 print quality, troubleshooting cleaning the charger 205 cleaning the printhead lens 205 print troubleshooting envelope seals when printing 294 error reading flash drive 294 held jobs do not print 293 incorrect characters print 295 incorrect margins on prints 303 jammed pages are not reprinted 291 job prints from wrong tray 295 job prints on wrong paper 295

jobs do not print 298 Large jobs do not collate 296 multiple-language PDF files do not print 296 paper curl 304 paper frequently jams 292 print job takes longer than expected 297 tray linking does not work 299 unexpected page breaks occur 299 printer 45 basic model 11 connecting to an outlet 10 fully configured 11 minimum clearances 10 moving 10, 236 selecting a location 10 shipping 237 printer configurations 11 printer control panel adjusting brightness 199 indicator light 15 Sleep button light 15 Printer had to restart. Last job may be incomplete. 278 printer hard disk disposing of 201 encrypting 203 removing 36 printer hard disk encryption 203 printer hard disk memory erasing 202 printer information where to find 9 printer IP address finding 20 printer is printing blank pages 305 printer messages [x] maintenance kit very low [80.xy] 277 [x]-page jam, clear manual feeder. [200.xx] 244 [x]-page jam, detach the 3000-sheet tray and open door F. [24y.xx] 251 [x]-page jam, open door C and clear all jammed media.

[2yy.xx] 244

clear all jammed media. [24y.xx] 249 [x]-page jam, open door H and rotate knob H6 clockwise. Leave paper in bin. [426.xx-428.xx] 263 [x]-page jam, open doors G, H, and J and clear jammed paper. Leave paper in bin. [400-402] 254 [x]-page jam, press latch at area E to open ADF's top cover. [28y.xx] 268 [x]-page jam, press latch to access area G and clear jammed staples. Leave paper in bin. [402.93] 260 [x]-page jam, press latch to access area G. Leave paper in bin. [40y.xx] 257 [x]-page jam, slide the 3000-sheet tray and open door C. [2yy.xx] 246 [x]-page jam, slide the 3000-sheet tray and open door D. [24y.xx] 250 Cartridge low [88.xy] 270 Cartridge nearly low [88.xy] 270 Cartridge very low [88.xy] 270 Change [paper source] to [custom string] load [orientation] 270 Change [paper source] to [custom type name] load [orientation] 270 Change [paper source] to [paper size] load [orientation] 270 Change [paper source] to [paper type] [paper size] load [orientation] 271 Close door [x] 271 Complex page, some data may not have printed [39] 271 Configuration change, some held jobs were not restored [57] 271 Defective flash detected [51] 271 Disk full [62] 272

[x]-page jam, open door D and

Disk full, scan job canceled 272 Disk must be formatted for use in this device 272 Disk near full. Securely clearing disk space. 272 Empty the hole punch box 272 Error reading USB drive. Remove USB. 272 Error reading USB hub. Remove hub. 272 Fax memory full 273 Fax partition inoperative. Contact system administrator. 273 Fax server 'To Format' not set up. Contact system administrator. 273 Fax Station Name not set up. Contact system administrator. 273 Fax Station Number not set up. Contact system administrator. 273 Incorrect paper size, open [paper source] [34] 273 Insert hole punch box 274 Insert Tray [x] 274 Insufficient memory for Flash Memory Defragment operation [37] 274 Insufficient memory to collate job [37] 274 Insufficient memory to support Resource Save feature [35] 274 Insufficient memory, some Held Jobs were deleted [37] 274 Insufficient memory, some held jobs will not be restored [37] 274 Insufficient space between paper stacks in Tray 3 274 Load [paper source] with [custom string] [paper orientation] 275 Load [paper source] with [custom type name [paper orientation 275 Load [paper source] with [paper size][paper orientation] 275

Load [paper source] with [paper type] [paper size] [paper orientation] 275 Load Multipurpose Feeder with [custom string] [paper orientation 275 Load Multipurpose Feeder with [custom type name] [paper orientation] 276 Load Multipurpose Feeder with [paper size] [paper orientation] 276 Load Multipurpose Feeder with [paper type] [paper size] [paper orientation] 276 Load staples 276 Load staples [G11, G12] 277 Memory full [38] 277 Memory full, cannot print faxes 277 Memory full, cannot send faxes 277 Network [x] software error [54] 277 No analog phone line connected to modem, fax is disabled. 277 Not enough free space in flash memory for resources [52] 278 Open door H and remove paper from beneath area H10 278 Paper changes needed 278 Parallel port [x] disabled [56] 278 Photoconductor low [84.xy] 278 Photoconductor very low [84.xy] 278 Printer had to restart. Last job may be incomplete. 278 Reinstall missing or unresponsive cartridge [31.xy] 279 Reinstall missing or unresponsive photoconductor [31.xy] 279 Remove defective disk [61] 279 Remove packaging material, [area name] 279 Remove packaging material, open door C, remove metal

scanner carriage 279 Remove paper from [linked set bin name] 280 Remove paper from all bins 279 Remove paper from bin [x] 279 Remove paper from standard output bin 280 Replace [x] maintenance kit, 0 estimated pages remain [80.xy] 281 Replace all originals if restarting job. 280 Replace cartridge, 0 estimated pages remain [88.xy] 280 Replace cartridge, printer region mismatch [42.xy] 280 Replace jammed originals if restarting job. 281 Replace missing cartridge [31.xy] 281 Replace missing photoconductor [31.xy] 281 Replace missing waste toner bottle [82.xy] 281 Replace paper pick rollers in [paper source], use parts and instructions in tray 1 or tray 2 compartment [80] 282 Replace photoconductor, 0 pages remain [84.xy] 282 Replace unsupported cartridge [32.xy] 282 Replace unsupported photoconductor [32.xy] 282 Replace waste toner bottle [82.xy] 282 Restore held jobs? 282 Scanner disabled by admin [840.01] 282 Scanner disabled. Contact system administrator if problem persists. [840.02] 283 Scanner jam, remove jammed originals from the scanner [2yy.xx] 283 Scanner maintenance required soon, use ADF Kit [80] 283 Scanner maintenance required,

use ADF Kit [80] 283

clips, remove all screws from

Serial port [x] disabled [56] 283 from a computer 70 Remove paper from all bins 279 from a mobile device 73 SMTP server not set up. Contact Remove paper from bin [x] 279 system administrator. 283 from flash drive 71 Remove paper from standard Some held jobs were not menu settings page 50 output bin 280 restored 283 network setup page 50 removing printer hard disk 36 Standard network software printing a directory list 74 repeat print jobs 73 error [54] 284 printing a font sample list 74 printing from a Macintosh Standard USB port disabled printing a menu settings computer 73 [56] 284 page 50 printing from Windows 73 Supply needed to complete printing a network setup repeating defects appear on job 284 page 50 prints 311 The device is operating in safe printing forms 70 Replace [x] maintenance kit, 0 estimated pages remain mode. Some print options may printing from a flash drive 71 be disabled or provide printing from a mobile device 73 [80.xy] 281 unexpected results. 284 printing held jobs Replace all originals if restarting Too many flash options installed from a Macintosh computer 73 job. 280 from Windows 73 [58] 284 Replace cartridge, 0 estimated Too many trays attached publications pages remain [88.xy] 280 [58] 284 where to find 9 Replace cartridge, printer region **Push Button Configuration** Tray [x] paper size mismatch [42.xy] 280 Replace jammed originals if unsupported 285 method Unformatted flash detected using 48 restarting job. 281 [53] 285 Replace missing cartridge Unsupported disk 285 [31.xy] 281 Q Unsupported option in slot [x] Replace missing photoconductor Quality menu 188 [55] 285 [31.xy] 281 Unsupported USB hub, please Replace missing waste toner R remove 272 bottle [82.xy] 281 recipient(s) Waste toner bottle nearly full Replace paper pick rollers in e-mail options 86 [82.xy] 285 [paper source], use parts and recycled paper Weblink server not set up. instructions in tray 1 or tray 2 using 61, 197 compartment [80] 282 Contact system recycling administrator. 285 Replace photoconductor, 0 Lexmark packaging 200 printer options troubleshooting pages remain [84.xy] 282 Lexmark products 199 internal option is not Replace unsupported cartridge toner cartridges 200 detected 288 [32.xy] 282 reducing a copy 79 internal print server 289 Replace unsupported Reinstall missing or unresponsive Internal Solutions Port 289 photoconductor [32.xy] 282 cartridge [31.xy] 279 tray problems 290 Replace waste toner bottle Reinstall missing or unresponsive USB/parallel interface card 291 [82.xy] 282 photoconductor [31.xy] 279 printer problems, solving replacing parts Remote Operator Panel basic 286 pick, feed, separator setting up 25 rollers 226 printer security Remove defective disk [61] 279 information on 203 transfer module 229 Remove packaging material, printhead lens transfer roller 232 [area name] 279 cleaning 205 replacing supplies Remove packaging material, printing staple cartridge in booklet open door C, remove metal clips, canceling, from the printer finisher 217 remove all screws from scanner control panel 75 staple cartridge in staple carriage 279 directory list 74 finisher 214 Remove paper from [linked set font sample list 74 staple cartridge in staple, hole bin name] 280 forms 70 punch finisher 219

toner cartridge 220	scan options	scanning to a flash drive 113
waste toner bottle 222	darkness 114	scanning to an FTP address
replacing the ADF scan pad 234	file name 114	creating shortcuts using the
replacing the exhaust filter 224	original size 114	computer 111
replacing the ozone filter 224	page setup 115	using the control panel 112
replacing the pick, feed, and	resolution 114	scanning to network
separator rollers 226	Save As Shortcut 114	destinations 111
replacing the staple cartridge in	Scan Preview 115	security
the booklet finisher 217	Send As 114	modifying confidential print
replacing the staple cartridge in	Scan Preview	settings 74
the staple finisher 214		Security Audit Log menu 144
•	scan options 115	,
replacing the staple cartridge in	scan preview	security lock 201
the staple, hole punch	fax options 110	security settings information
finisher 219	scan screen	erasing 202
replacing the toner	content source 114	security Web page
cartridge 220	content type 114	printer security information 203
replacing the transfer	Scan to Computer	selecting a location for the
module 229	setting up 113	printer 10
replacing the transfer roller 232	Scan to Network	selecting paper 61
replacing the waste toner	setting up 25	Send As
bottle 222	using 111	e-mail options 87
reports	scan troubleshooting	scan options 114
viewing 238	cannot scan from a	sending a fax
Reports menu 127	computer 327	using the computer 104
reserve print jobs 73	partial document or photo	using the control panel 104
printing from a Macintosh	scans 328	sending an e-mail using the
computer 73	scan job was not	control panel 85
printing from Windows 73	successful 329	sending fax at a scheduled
resetting the maintenance	scanner unit does not	time 105
counter 233	close 329	Serial [x] menu 137
resolution	scanning takes too long or	Serial port [x] disabled [56] 283
e-mail options 87	freezes the computer 330	serial printing
fax options 109	scanner	setting up 50
scan options 114	functions 13	Set Date and Time menu 146
resolution, fax	Scanner disabled by admin	setting
changing 106	[840.01] 282	paper size 51
Restore held jobs? 282	Scanner disabled. Contact	paper type 51
restoring factory default	system administrator if problem	TCP/IP address 130
settings 240	persists. [840.02] 283	setting the fax number 103
RJ11 adapter 99	scanner glass	setting the lax number 103
rollers	cleaning 204	name 103
	_	
replacing 226	using 14	setting the Universal paper size 51
•	Scanner jam, remove jammed	
S	originals from the scanner	setting up e-mail alerts 238
safety information 7, 8	[2yy.xx] 283	setting up fax
Save As Shortcut	Scanner maintenance required	country- or region-specific 99
copy options 82	soon, use ADF Kit [80] 283	digital telephone service 98
e-mail options 87	Scanner maintenance required,	DSL connection 95
scan options 114	use ADF Kit [80] 283	standard telephone line
saving paper 80	scanning	connection 90
scan image	to an FTP address 112	VoIP connection 96
autaut fila tuna 111	scanning to a computer 113	

scanning to a computer 113

output file type 114

setting up fax and e-mail streaked vertical lines appear on functions 326 prints 314 recycling 200 setting up serial printing 50 streaks appear 318 toner darkness Setup menu 184 Substitute Size menu 121 adjusting 70 shortcuts, creating checking status 209 [58] 284
setting up serial printing 50 streaks appear 318 toner darkness Setup menu 184 Substitute Size menu 121 adjusting 70 shipping the printer 237 supplies Too many flash options installed
Setup menu 184 Substitute Size menu 121 adjusting 70 shipping the printer 237 supplies Too many flash options installed
shipping the printer 237 supplies Too many flash options installed
copy screen 77 checking, from printer control Too many trays attached
e-mail 85 panel 209 [58] 284
fax destination 105, 106 checking, using the Embedded touch screen
FTP address 112 Web Server 209 buttons 18
FTP destination 111 conserving 197 transfer module
showing icons on the home storing 211 replacing 229
screen 21 using genuine Lexmark 210 transfer roller
sides (duplex) using recycled paper 197 replacing 232
copy options 82 supplies, ordering transparencies
Sleep Mode photoconductor unit 210 copying on 77
adjusting 199 staple cartridges 211 tips 60
SMTP server not set up. Contact toner cartridge 210 Tray [x] paper size
system administrator. 283 waste toner bottle 210 unsupported 285
SMTP Setup menu 140 Supply needed to complete trays
Some held jobs were not job 284 linking 56, 57
restored 283 supply notifications loading 51
stabilizing feet 38 configuring 239 unlinking 56, 57
Standard Network menu 128 supported flash drives 72 troubleshooting
Standard network menu 128 supported hash drives 72 troubleshooting Standard network software error supported paper sizes 63 an application error has
54] 284 finisher 67 occurred 331
Standard USB menu 134 supported paper types 66 cannot open Embedded Web
Standard USB port disabled finisher 67 Server 332
•
[56] 284 supported paper weights 66 checking an unresponsive staple 82 finisher 67 printer 286
staple 62 printer 280 staple cartridge in booklet contacting customer
replacing 247
stanle cartridge in stanle finisher
telecommunication
stable cartridge in stable halo
nunch finisher the scanner does not
roplacing 210
otable cottidaes
unexpected results. 204
statement of volatility 201
status of parts
chocking 200
status of supplies
chocking 200
storing storing
nanor 62
note 211
cumpling 211
supplies 211 toner cartridge printer display is blank 288 storing print jobs 73 troubleshooting, fax
ordering 210
streaked horizontal lines appear replacing 220 caller ID is not shown 322 on prints 313

on prints 313

can receive but not send faxes 325 can send but not receive faxes 326 cannot send or receive a fax 323 troubleshooting, paper feed message remains after jam is cleared 292 troubleshooting, print envelope seals when printing 294 error reading flash drive 294 held jobs do not print 293 incorrect characters print 295 incorrect margins on prints 303 jammed pages are not reprinted 291 job prints from wrong tray 295 job prints on wrong paper 295 jobs do not print 298 Large jobs do not collate 296 multiple-language PDF files do not print 296 paper curl 304 paper frequently jams 292 print job takes longer than expected 297 tray linking does not work 299 unexpected page breaks occur 299 troubleshooting, print quality blank pages 305 characters have jagged edges 300 clipped pages or images 300 gray background on prints 302 horizontal voids appear on prints 302 print irregularities 307 print is too dark 308 print is too light 309 printer is printing solid black pages 306 repeating defects appear on prints 311 shadow images appear on prints 312 skewed print 313 streaked horizontal lines appear on prints 313 streaked vertical lines 314

toner fog or background shading appears on prints 316 toner rubs off 316 toner specks appear on prints 317 transparency print quality is poor 317 uneven print density 318 white streaks on a page 318 troubleshooting, printer options internal option is not detected 288 internal print server 289 Internal Solutions Port 289 tray problems 290 USB/parallel interface card 291 troubleshooting, scan cannot scan from a computer 327 partial document or photo scans 328 scan job was not successful 329 scanner unit does not close 329 scanning takes too long or freezes the computer 330 two-sided copying 79

U

understanding the home screen buttons and icons 16 uneven print density 318 Unformatted flash detected [53] 285 Universal paper size setting 51 Universal Setup menu 125 unlinking trays 56, 57 Unsupported option in slot [x] [55] 285 Unsupported USB hub, please remove 272 USB port 44 USB/parallel interface card troubleshooting 291 using Forms and Favorites 70 using Hibernate mode 198 using recycled paper 197 using the address book e-mailing 86

using the ADF
copying 76
using the automatic document
feeder (ADF) 14
using the scanner glass 14
copying 76
using the touch-screen
buttons 18
Utilities menu 190

V

verify print jobs 73 printing from a Macintosh computer 73 printing from Windows 73 vertical voids appear 318 viewing reports 238 virtual display checking, using Embedded Web Server 238 voice mail setting up 90 voice over Internet Protocol (VoIP) fax setup 96 voids appear 318 VoIP adapter 96 volatile memory 201 erasing 202 volatility statement of 201

W

waste toner bottle ordering 210 replacing 222 Waste toner bottle nearly full [82.xy] 285 Weblink server not set up. Contact system administrator. 285 Wireless menu 132 wireless network configuration information 46 wireless network setup using the Embedded Web Server 49 wireless setup wizard using 47



XPS menu 191