

## 2.4G DIGITAL WIRELESS MICROPHONE



User Manual  
 3 Legged Thing

## STREAMCASE TRANSMITTER (TX)



## STREAMCASE TRANSMITTER (TX)

Number	Function	Instructions	Status & Light
1	Power Button	Press and hold 2 seconds to turn on/off	Solid blue light: Paired
	Mute	Short press power button to mute or unmute	Flashing red light: Mute active
2	Type C charging port	Use Type C charging cable to charge transmitter (in case)	Solid red light: Charging
3	Noise reduction	Short press to turn on/off noise reduction	Solid green light: Noise Reduction On Solid blue light when switched off
	Pair key	Short press "+" key and "-" key simultaneously to pair with receiver	Flashing blue light: Pairing Solid blue light: Paired and Connected
4	Pair key		
5	Mic input	Connect to TRS microphone	Connecting external microphones disables the internal microphone
6	Built-in Mic	Built-in Microphone	
7	Indicator light	Indicator light for different status	Slow flashing red light: Low battery (will power down in 3 minutes)
			Solid red light: Charging No lights: System charged fully

## STREAMCASE RECEIVER (RX)



## STREAMCASE RECEIVER (RX)

Number	Function	Instructions	Status & Light
1	Power Button	Press and hold 2 seconds to turn on/off	Solid blue light: Paired
	Built-in Mic	Short press power button twice to turn on/off built-in microphone	Solid green light: Microphone on Solid blue light: Microphone off (default)
2	Type C charging port	Use Type C charging cable to charge receiver (in case)	Solid red light: Charging No light: Fully charged
	Audio output	Use the supplied cables to connect with different devices	Type C to Type C cable for Android devices; Type C to Lightning cable for iOS devices Type C to 3.5mm cable for camera, camcorder or sound recorder devices
3	Volume control	Short press + for volume up Short press - for volume down	Volume control levels: High, Mid and low.
			High: Blue light flashes twice Low: Green light flashes twice
4	Pair key	Short press both keys simultaneously to pair with transmitter	Pairing Status: Flash blue light Paired Status: Solid blue light
5	Monitor Jack	Connect to headphones	Real-time audio monitoring

## STREAMCASE RECEIVER (RX)

6	Built-in Microphone	Keep clean	N/A
7	Indicator light	Indicator light for different status	Slow flashing red light: Low battery (will power down in 3 minutes) Solid red light: Charging No lights: System charged fully

## OPERATION GUIDE:

- Long press power button to turn on the transmitter and receiver.
- The transmitter and receiver will pair automatically, if not, please pair the TX and RX manually (see Transmitter & Receiver instructions).
- Select your transmitter(r) and attach using the clip.
- Connect the receiver to your camera, smartphone or cameras etc with supplied cables:  
 Type C to Type C cable for your Android devices  
 Type C to Lightning cable for your iOS devices  
 Type C to 3.5mm cable for your camera, camcorder or audio recorder etc devices.
- Ready to use.

## HOW TO PAIR

- Short press transmitter "+" and "-" key simultaneously  
The indicator light will flash every second.
- Short press receiver "+" "-" key at the same time  
The indicator light will flash every second.
- The transmitter and receiver will pair automatically.
- The indicator will be solid blue. If not, please repeat step 1 and 2.

## SPECIFICATIONS:

Transmission Type: 2.4GHz Frequency  
 RF power: 10dBm  
 RF Modulation: GFSK  
 Signal to Noise: 80dB  
 Operation Range: 50m (Without Obstacle)  
 Battery Life: 5 hours  
 Working Temperature: 0°C to 50°C  
 Power Requirements: Built-in Li-ion Battery or USB-C DC 5V  
 Dimensions: 45x22x13mm

## PACKING LIST:

- 1x Receiver
- 2 x Transmitters
- 1x Charging Case
- 1x Carry Case
- 3x Furry dead hamsters (like dead kittens, but smaller. And cuter)
- 1x Type C to Type C with Charging cable
- 1x Type C to Lightning with Charging cable
- 1x Type C to 3.5mm cable
- 1x USB-C to USB-A Charging Cable

3 LEGGED THING®

3 Legged Thing LTD  
 Unit 2A Kinsbourne Farm, Bury End, Stagsden MK43 8TS. UK  
 Email: support@3leggedthing.com