

Vibe P108 RGB Video Light

User Manual

In order to ensure user's safety and prevent the product damages caused by any improper use, please carefully read the "Warnings" below and properly keep this User Manual for future reference.

Foreword

Thank you for purchasing SmallRig's product.

Warnings

- Please read this User Manual carefully.
- Do not use the product in water because it is not dust or water proof.
- Do not let the product fall to the ground, be hit or suffer violent impact.
- Do not use the product in the completely closed environment, or it may lead to rise of internal temperature, which causes product failure, ignition or other accident.
- Do not look straight at the LED bead in use from close range, or it may cause visual impairment.
- Do not place the product nearby any combustible or volatile solution, or it may cause a fire disaster or smog.
- Be sure to power the product off when it is not in use.
- Never remove the non-detachable lithium battery without permission.
- Do not pick up the camera by grabbing the holder of the filling light.
- When the battery is not in use for a long time, please charge and discharge the battery every 6 months, and provide it with about 60% of the electric quantity to prolong its use life.
- Since there are some hazardous substances in the battery, please do not discard it. Instead, dispose of the product that is damaged or will never be used according to the waste management measures.



Please do not disassemble the product or change its battery. If you have any question, please contact the seller to apply after-sales service.

Intended Use

- Please read this User Manual carefully, especially the "Warnings".
- Please use or store the product in the environment mentioned herein.
- It will be regarded as an improper use when the users are not correctly follow the user manual or use the product under the specific working condition.

In the Box



Vibe P108 RGB Video Light × 1




USB-C Charging Cable × 1





User Manual × 1

Specifications

Product Model	P108
Color Temperature	2700K ~ 6500K
100% Light Flux / Lm Cold Light	≥250Lm (Max)
Color Rendering Index	≥95
Maximum Power Consumption	5W
Battery Specification	2500mAh / 3.7V / 9.25Wh
Compensatory Range	≤5m
Lamp Beads	108
Product Dimensions	72.0 × 89.0 × 31.6mm
Operating Temperature	-10°C ~ 50°C
Input	5V  1A

Product Details



① On / Off Button

② The Indicator Light

③ Adjust / Press the Knob Button



④ Charging Port

⑤ 1/4"-20 Threaded Hole

⑥ Cold Shoe Mount

Note: the brightness and color temperature of the light can be adjusted when the non-polar knob is clockwise / counterclockwise. When the key is pressed toggle the color temperature or brightness adjustment

Installation Instructions for LED Video Light



When the fill-up light is installed on the camera, SLR, and tripod

1. Insert the cold shoe adapter of the LED video light directly into the camera mount and tighten it clockwise.
2. Tighten the screw hole at the joint of the cold shoe connection at the bottom of the light and the screws on the tripod, then adjust the proper Angle of the light for light filling operation.

Product Introduction

This product Vibe P108 LED video light adopts 2700K ~ 6500K LED light source. Click to adjust the color temperature, knob switch can adjust the brightness.

Product Function Description and Characteristics

1. This product is composed of 3 kinds of lamp beads, including 40 LEDs with a color temperature of 2700K ~ 3000K, 40 LEDs with a color temperature of 6000K ~ 6500K, and 28 LEDs in RGB.
2. Two-color temperature lamp beads in cold and warm light mode can be infinitely adjusted, and different atmosphere effects can be set, such as sunrise and sunset.
3. RGB mode color gamut 0° ~ 360° stepless adjustment to meet various color needs.
4. 12 kinds of scene atmosphere special effects to simulate various scene lighting.
5. Built-in high-capacity 2500mAh lithium battery, allowing you to use one-day long .

Directions for Use

1. Switch / Lighting button

press the power button with 1.5S to switch the light On / Off

2. Mode switch

A total of 14 light effects to switch the modes, the police light mode is light effect: cold and warm light effect, save light effect, fire special effect, RGB slow speed, RGB fast effect, short-time lightning 2, lightning 2 special effect, screen special effect mode, candle special effect, fireworks special effects, pulse effects, disco, RGB effects.

3. Color temperature / gamut adjustment

Cold and warm light mode and RGB mode, rotate the knob to adjust color temperature/color gamut, color temperature adjustable range: 2700K ~ 6500K; color gamut adjustable range 0° ~ 360°.

4. Brightness adjustment

Cold and warm light mode and RGB mode, short button to adjust the brightness, a total of four levels of brightness adjustment, four white LED indicators represent the brightness level respectively: 1 represents the current brightness level 1, 2 represents the current brightness level 2, 3 LEDs Represents the current brightness of 3 levels, and 4 means the current brightness of 4 levels; in the special effect mode, turn the knob to adjust the brightness.

5. Indicator light

- **Working indicator:** green LED indicator*1, the green indicator flashes after booting.
- **Battery indicator:** White LED indicator*4, 1 light on means 25% power, 2 lights on means 50% power, 3 lights on means 75% power, 4 lights on means 100% power.
- **Charging indicator:** White LED indicator*4 flashes in sequence when charging, and 4 white LED indicators are always on when fully charged.

Service Warranty

Please keep your original receipt and guarantee card. Be sure the dealer has written on it the date of purchase and SN of the product. These are required for warranty service.

After-sale warranty terms:

1. 7 Days DOA Return Policy: Within 7 days from the date of the package receipt, return or replacement can be done if the item received is malfunctioning or physical damaged (not caused by human abused), returnshipping cost will be on SmallRig's charge.

2. SmallRig products are entitled to warranty services as of the date of payment.

- Electronic products: 1-year warranty, 1-year free warranty service.

- Non-electronic products: 2-year warranty, 2-year free warranty service.

Note: In case of any conflict between our warranty period policy and applicable laws and regulations of the country/region where the products are sold, the latter shall prevail.

This warranty does not cover:

1. Defect caused by users' violation of the "Warnings" and "Intended Use".

2. The product identification or SN label is removed or defaced in any way.

3. Product damage caused by problems not attributable to the quality of the products such as improper use of the products.

4. Product damage caused by unauthorized modification, disassembly, repair and other acts.

5. Product damage caused by fires, floods, lightning and other force majeure factors.

Warranty Mode:

- For the products within the scope of warranty, SmallRig will repair or replace them on the basis of specific failures; the repaired/replaced products/parts are entitled to the remaining part of the original warranty period.

Contact Information:

- You're advised to contact the online customer service personnel of corresponding shopping platform and submit a repair service application.

- You may also apply for repair service through SmallRig's service email.

Service Email: support@smallrig.com

For more support information: www.smallrig.com/support

Guarantee Card

ID No.	
Item Name	
Purchase Date	
User Name	
Mobile	
Address	
Receipt	

EC	REP
----	-----

Prolinx GmbH
Brehmstr.56,40239 Duesseldorf Germany
eu@eulinx.eu

UK	REP
----	-----

Prolinx Global LTD
27 Old Gloucester Street London, WC1N3AX, UK
eu@eulinx.eu

Manufacturer: Shenzhen Leqi Network Technology Co., Ltd.

Add: Rooms 103, 501 and 601, Building 5, Fenghe Industrial Park, Nos. 1301-50 Guangguang Road,
Longhua District, Shenzhen, Guangdong, China.

Consignor: Shenzhen LC Co., Ltd.

Add: Rooms 602, Building 5, Fenghe Industrial Park, No. 1301-50 Guangguang Road, Xinlan Community,
Guanlan Street, Longhua District, Shenzhen, Guangdong, China.



www.smallrig.com

Made in China