



LED Video Light



Instruction manual | 说明手册
Chinese English Bilingual | 中英文双语

Model: LED 64

Foreword:

Thank you for purchasing this Godox Product!

LED64 video light is excellent for macrophotography, product shooting, and video recording, etc. This lightweight and portable light provides high brightness and accurate color temperature. You can flexibly control the light brightness by using the dimmer and by interlocking multiple lights.

For your safety:

- ⚠ Do not place in high temperature or high humidity conditions.
- ⚠ If this product overheats, it will cease operation and resume working after cooling down. This is due to the built-in overtemperature protection.
- ⚠ Do not handle with wet hands, immerse in water, or expose to rain.
- ⚠ Observe precautions when handling batteries:
 - * Do not mix new and used batteries or batteries of different types.
 - * Do not put batteries into a fire or apply direct heat to it.
 - * Batteries are prone to leakage when fully discharged. To avoid damage to the product, be sure to remove batteries out when the product will not be used for a long time or when batteries run out of charge.
 - * Should liquid from batteries come into contact with skin or clothing, rinse immediately with fresh water.

Parts:

- 01. 64 LED Beads
- 02. Power Switch
- 03. Brightness Controller
- 04. Battery Compartment Lock
- 05. Light Hotshoe Connection
- 06. Locking Ring
- 07. Camera Hotshoe Connection
- 08. DC Power Jack
- 09. 1/4" Bracket Mounting Hole



Installation and Operation

1.Installing the Video Light

- Screw the Locking Ring (06) to the highest point and insert the Camera Hotshoe Connection horizontally into the hotshoe of a camera or a camcorder.
- Tighten the Locking Ring (06).




Note: If your camcorder has no hotshoe connection, you are advised to purchase a connecting bracket for camcorder. The video light has a 1/4" Bracket Mounting Hole as your camcorder does. Therefore, you can easily connect both the light and the camcorder to the bracket.


2.Using the Video Light



- Slide the Battery Compartment Lock (04) to the right and open the compartment.



- Install batteries (4*AA) according to indications in the compartment and then lock it.



- Switch the power on, the video light giving out light.



- Turn the Brightness Controller (03) to adjust the brightness.

Instead of AA batteries, the light can use AC power by using the DC Power Jack. Connect the video light to AC power using a 5V charger (purchased separately). Then switch the light on to start working.

3.Interlocking Multiple Video Lights

Through the Light Hotshoe Connection (05) and Camera Hotshoe Connection (07), multiple video lights can be interlocked together to strengthen the lighting brightness and get a better control of the lighting effects.



Technical Data:

Battery	Four AA batteries
DC Power Supply	5V
Power (Max.)	<4.5W
Color Temperature	5500~6500K
Brightness	>1000Lux (0.5m)
Brightness Control	Stepless
LED Beads Quantity	64
Operation Temperature	-10~40°C
Dimension	85mm*85mm*35mm
Net weight	130g

* Product design and specifications are subject to change without notice.