

### **INSTALLATION MANUAL**

# **VOLUME CONTROL ATTENUATOR**


AT-025 AT-100 AT-100EMG AT-10K

### 1. GENERAL DESCRIPTION


TOA's volume control attenuators provide precise level adjustment to single or multiple speaker lines. They are available in 25W or 100W models with a Decora-style wall plate. AT-100EMG is equipped with a 24VDC@15mA relay for applications that require emergency and paging signals to bypass/override the attenuator. AT-10K is a 10k ohm linear taper control for single-point remote level adjustment of voltage controlled amplifiers such as TOA's M-900MK2, A-9000MK2, M-9000MZ, A-9000MZ, A-700, BG-2000, BA-200, AV-20D series mixers/amplifiers.

#### 2. WIRING DIAGRAMS


### AT-025 / AT-100



### AT-100EMG




#### **AT-10K**



# 3. SPECIFICATIONS

Model	AT-025	AT-100	AT-100EMG	AT-10K
Input Capacity	25W	100W	100W	-
Attenuation	13 steps (0dB, -3dB, -6dB, -9dB, -12dB, -15dB, -18dB,			Continuous
	-21dB, -24dB, -27dB, -30dB, -33dB, OFF)			10kΩ
Wire Capacity	14-gauge			
Priority Relay	-	-	24VDC@15mA	-
Finish	White plate & sub-plate / Decora-style			
Dimensions	Plate Width 2.75"	Plate Width 2.75"	Plate Width 2.75"	Plate Width 2.75"
	Plate Height 4.5"	Plate Height 4.5"	Plate Height 4.5"	Plate Height 4.5"
	A: 1.75"	A: 1.812"	A: 2.125"	
	B: 2.5"	B: 2.5"	B: 2.5"	(see below drawing)
	C: 1.875"	C: 1.875"	C: 1.875"	

## AT-025 / AT-100 / AT-100EMG



# AT-10K

